

Adjustment Program (Version 1.0) for DFX-8500 Operating Instructions

1. Operating Environment:

- MS-DOS version 6.2 or higher.
(The operation is also checked with Windows 95, both on the emulation mode (rebooting the system in MS-DOS mode) and on the DOS box.)
- Use any **LPT1:** as printer port
- Use **only COM1:** as serial port.
- CONFIG.SYS
Check the contents of your CONFIG.SYS file, and add the following command line if not exist ;

For MS-DOS version 6.1 or older :

device=c:¥<current directory>¥ansi.sys or
deviceheigh=c:¥<current directory>¥ansi.sys

Turn the PC on after finishing procedures above to enable the new settings.

2. Cautions

- 1) When operating this program on the Windows 95, you cannot operate it with EPW(Epson Printer Window)is running. Close EPW before executing the adjustment program.
- 2) When you can not get a Printer Model Name correctly, press the **Alt** and **E** key simultaneously. Then enter the corresponding Printer Model Name correctly as below.
Example : Correct input >>> DFX-8500
Wrong input >>> dfx-8500, or DFX8500 etc.
- 3) When five minutes or more has passed without any printing operation, the carriage will locked in the Energy Star mode. In this case, turn the printer off once and back on again, then re-execute the adjustment program.

- Over -