

7 Electrical Parts List

※ You can search for updated part codes through ITSELF web site.

URL : <http://itself.sec.samsung.co.kr/>

7-1 Main PCB Parts

Level	Loc. No.	Code No.	Description	Specification	Remarks
0	MH17WS				
1	S4-MH17WS	-	1	LTM170W1-L01 ZPD	-
3	BN94-00572A	-	ASSY PCB MAIN	MH17WS	SNA
4	0204-002420	CIS3	SOLVENT	1M-1000,C3H7OH,96,-,-	SNA
4	0204-002426	CIS2	FLUX	DF-201TVS,MIX,0.820,FLUX 13%, 14KG,-	SNA
4	1203-000165	IC608	IC-POSI.ADJUST REG.	78R12,TO-220,4P,-,PLASTIC,11.7/12.3V,1.5W,-20TO+80C,1A,-,ST	SA
4	2904-001179	FT700	FILTER-SAW	36.125MHz,-,32.65-39.6MHz/0.5dB,SIP5K,+0MHz/21.8dB,31.25MHz/37dB	SA
4	3701-001224	CN102	CONNECTOR-DVI	24P,3R,FEMALE,STRAIGHT,AU10U	SA
4	3701-001302	CN101	CONNECTOR-DSUB	15P,3R,FEMALE,STRAIGHT,AUF	SA
4	3705-001331	CN709	CONNECTOR-COAXIAL	PAL,ADAPTOR(J/J),-,75ohm,-	SA
4	3711-004183	CN200	CONNECTOR-HEADER	BOX,10P,1R,-,ANGLE,SN	SA
4	3711-004712	CN600	CONNECTOR-HEADER	BOX,9P,1R,2mm,STRAIGHT,SN	SA
4	3711-005505	CN700	CONNECTOR-HEADER	NOWALL,11P,1R,2.54mm,ANGLE,SN,WHT	SA
4	3722-000498	CN506	JACK-SCART	21P,-,SN,BLK,NO	SA
4	3722-001061	CN505	JACK-PHONE	1P,3.6PI,AG,BLK,N	SA
4	3722-001734	CN701	JACK-VHS	4P,-,SN,BLK,-	SA
4	3722-001844	CN507	JACK-PIN	3P,8.3MM,AU,YEL/WHT/RED,-	SA
4	3722-001845	CN300	JACK-PIN	3P,8.3MM,AU,GRN/BLU/RED,-	SA
4	3722-001846	CN503	JACK-PIN	2P,8.3MM,AU,WHT/RED,-	SA
4	3722-001931	CN702	JACK-PIN	1P,-,AU,BLK,-	SA
4	3722-002176	CN504	JACK-PHONE	7P/4C,-,SN,L-BLU,-	SA
4	AA63-00864A	CIS7	GASKET	MH17FS,CONDUCTIVE FAB,3mm,5mm,30mm,GRAY,45K,71TSVK-5-3-30-13	SNA
4	BN40-00052A	TUNER	TUNER	TECC0849FL40B(S)NTSC,181CH,38.9MHz,33V,75 OHM,PHONE-JACK,ASYMM,5V,TR,4V	SA
4	BN41-00392A	TUNER_PCB	PCB SUB	KD17AS,FR4,2L,MP1.0,1.6T,54*13	SNA
4	BN63-00896A	CIS	GASKET	NB21BS,CONDUCTIVE FAB,5MM,15MM,25MM,GRAY,32K,71TSSK-15-5-25-13	SNA
4	BN63-01384A	CIS6	SHIELD-JACK IN	730MP,SPTTE,T0.5	SNA
4	BN97-00362X	MICOM	ASSY MICOM	MH17WS	SNA
5	1102-001129	IC202	IC-EPROM	M27W401,512K8BIT,PLCC,32P,11.35X13.89MM,80NS,3.3V,10%,PLASTIC,40TO+85C,-,CMOS,	SA
4	BN97-00384J	-	ASSY SMD	MH17WS	SNA
5	0401-001056	D100	DIODE-SWITCHING	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D101	DIODE-SWITCHING	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D103	DIODE-SWITCHING	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D104	DIODE-SWITCHING	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D105	DIODE-SWITCHING	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D111	DIODE-SWITCHING	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D112	DIODE-SWITCHING	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D113	DIODE-SWITCHING	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D114	DIODE-SWITCHING	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D115	DIODE-SWITCHING	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D116	DIODE-SWITCHING	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D117	DIODE-SWITCHING	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D118	DIODE-SWITCHING	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D119	DIODE-SWITCHING	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D706	DIODE-SWITCHING	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D707	DIODE-SWITCHING	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D708	DIODE-SWITCHING	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0402-000553	D600	DIODE-RECTIFIER	SS24,40V,2.0A,DO-214AA	SA
5	0403-000579	D102	DIODE-ZENER	BZX84C5V1,4.8-5.4V,200MW,SOT-23,TP	SA
5	0403-000579	D106	DIODE-ZENER	BZX84C5V1,4.8-5.4V,200MW,SOT-23,TP	SA
5	0403-000579	D107	DIODE-ZENER	BZX84C5V1,4.8-5.4V,200MW,SOT-23,TP	SA
5	0403-000579	D108	DIODE-ZENER	BZX84C5V1,4.8-5.4V,200MW,SOT-23,TP	SA
5	0403-000579	D109	DIODE-ZENER	BZX84C5V1,4.8-5.4V,200MW,SOT-23,TP	SA
5	0403-000579	D110	DIODE-ZENER	BZX84C5V1,4.8-5.4V,200MW,SOT-23,TP	SA
5	0403-000579	D122	DIODE-ZENER	BZX84C5V1,4.8-5.4V,200MW,SOT-23,TP	SA
5	0403-000579	D123	DIODE-ZENER	BZX84C5V1,4.8-5.4V,200MW,SOT-23,TP	SA
5	0403-000579	D124	DIODE-ZENER	BZX84C5V1,4.8-5.4V,200MW,SOT-23,TP	SA
5	0403-001048	D700	DIODE-ZENER	BZX84C16,15.3-17.1V,225mW,SOT-23,TP	SA
5	0403-001048	D701	DIODE-ZENER	BZX84C16,15.3-17.1V,225mW,SOT-23,TP	SA
5	0403-001382	ZD700	DIODE-ZENER	UDZ33B,32.15-33.79V,200MW,SOD-323,TP	SA
5	0403-001435	D121	DIODE-ZENER	QZX363C5V6,5.32-5.88V,200MW,SOT-363,TP	SA
5	0403-001435	D514	DIODE-ZENER	QZX363C5V6,5.32-5.88V,200MW,SOT-363,TP	SA
5	0403-001435	ZD200	DIODE-ZENER	QZX363C5V6,5.32-5.88V,200MW,SOT-363,TP	SA
5	0403-001435	ZD201	DIODE-ZENER	QZX363C5V6,5.32-5.88V,200MW,SOT-363,TP	SA
5	0406-001163	D301	DIODE-TVS	CDS3C05GTA,6.4V/-,-,SMD	SA
5	0406-001163	D302	DIODE-TVS	CDS3C05GTA,6.4V/-,-,SMD	SA

7 Electrical Parts List

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	0406-001163	D303	DIODE-TVS	CDS3C05GTA,6.4V/-/-,-,SMD	SA
5	0406-001163	D500	DIODE-TVS	CDS3C05GTA,6.4V/-/-,-,SMD	SA
5	0406-001163	D501	DIODE-TVS	CDS3C05GTA,6.4V/-/-,-,SMD	SA
5	0406-001163	D502	DIODE-TVS	CDS3C05GTA,6.4V/-/-,-,SMD	SA
5	0406-001163	D503	DIODE-TVS	CDS3C05GTA,6.4V/-/-,-,SMD	SA
5	0406-001163	D504	DIODE-TVS	CDS3C05GTA,6.4V/-/-,-,SMD	SA
5	0406-001163	D505	DIODE-TVS	CDS3C05GTA,6.4V/-/-,-,SMD	SA
5	0406-001163	D506	DIODE-TVS	CDS3C05GTA,6.4V/-/-,-,SMD	SA
5	0406-001163	D507	DIODE-TVS	CDS3C05GTA,6.4V/-/-,-,SMD	SA
5	0406-001163	D508	DIODE-TVS	CDS3C05GTA,6.4V/-/-,-,SMD	SA
5	0406-001163	D509	DIODE-TVS	CDS3C05GTA,6.4V/-/-,-,SMD	SA
5	0406-001163	D510	DIODE-TVS	CDS3C05GTA,6.4V/-/-,-,SMD	SA
5	0406-001163	D511	DIODE-TVS	CDS3C05GTA,6.4V/-/-,-,SMD	SA
5	0406-001163	D512	DIODE-TVS	CDS3C05GTA,6.4V/-/-,-,SMD	SA
5	0406-001163	D513	DIODE-TVS	CDS3C05GTA,6.4V/-/-,-,SMD	SA
5	0406-001163	D515	DIODE-TVS	CDS3C05GTA,6.4V/-/-,-,SMD	SA
5	0406-001163	D516	DIODE-TVS	CDS3C05GTA,6.4V/-/-,-,SMD	SA
5	0406-001163	D517	DIODE-TVS	CDS3C05GTA,6.4V/-/-,-,SMD	SA
5	0406-001163	D518	DIODE-TVS	CDS3C05GTA,6.4V/-/-,-,SMD	SA
5	0406-001163	D703	DIODE-TVS	CDS3C05GTA,6.4V/-/-,-,SMD	SA
5	0406-001163	D704	DIODE-TVS	CDS3C05GTA,6.4V/-/-,-,SMD	SA
5	0406-001163	D705	DIODE-TVS	CDS3C05GTA,6.4V/-/-,-,SMD	SA
5	0501-000280	Q512	TR-SMALL SIGNAL	KSA1182,P,NP,150mW,SOT-23,TP,70	SA
5	0501-000342	Q509	TR-SMALL SIGNAL	KSC1623-Y,NPN,200mW,SOT-23,TP,135-270	SA
5	0501-002080	Q100	TR-SMALL SIGNAL	2SC2412K,NPN,200mW,SC-59,TP,120-270	SA
5	0501-002080	Q101	TR-SMALL SIGNAL	2SC2412K,NPN,200mW,SC-59,TP,120-270	SA
5	0501-002080	Q300	TR-SMALL SIGNAL	2SC2412K,NPN,200mW,SC-59,TP,120-270	SA
5	0501-002080	Q305	TR-SMALL SIGNAL	2SC2412K,NPN,200mW,SC-59,TP,120-270	SA
5	0501-002080	Q501	TR-SMALL SIGNAL	2SC2412K,NPN,200mW,SC-59,TP,120-270	SA
5	0501-002080	Q502	TR-SMALL SIGNAL	2SC2412K,NPN,200mW,SC-59,TP,120-270	SA
5	0501-002080	Q503	TR-SMALL SIGNAL	2SC2412K,NPN,200mW,SC-59,TP,120-270	SA
5	0501-002080	Q505	TR-SMALL SIGNAL	2SC2412K,NPN,200mW,SC-59,TP,120-270	SA
5	0501-002080	Q507	TR-SMALL SIGNAL	2SC2412K,NPN,200mW,SC-59,TP,120-270	SA
5	0501-002080	Q508	TR-SMALL SIGNAL	2SC2412K,NPN,200mW,SC-59,TP,120-270	SA
5	0501-002080	Q510	TR-SMALL SIGNAL	2SC2412K,NPN,200mW,SC-59,TP,120-270	SA
5	0501-002080	Q511	TR-SMALL SIGNAL	2SC2412K,NPN,200mW,SC-59,TP,120-270	SA
5	0501-002080	Q600	TR-SMALL SIGNAL	2SC2412K,NPN,200mW,SC-59,TP,120-270	SA
5	0501-002080	Q601	TR-SMALL SIGNAL	2SC2412K,NPN,200mW,SC-59,TP,120-270	SA
5	0501-002080	Q602	TR-SMALL SIGNAL	2SC2412K,NPN,200mW,SC-59,TP,120-270	SA
5	0501-002080	Q603	TR-SMALL SIGNAL	2SC2412K,NPN,200mW,SC-59,TP,120-270	SA
5	0501-002080	Q700	TR-SMALL SIGNAL	2SC2412K,NPN,200mW,SC-59,TP,120-270	SA
5	0801-002404	IC503	IC-CMOS LOGIC	74VHC4066,ANALOG SWITCH,SOP,14	SA
5	0801-002709	IC702	IC-CMOS LOGIC	74HC373,D FLIP-FLOP,TSSOP,20P,173MIL,OC,TP,PLASTIC,3-STATE,-0V,-40TO+85C,600	SA
5	0801-002899	IC703	IC-CMOS LOGIC	CD4069UBC,INVERTER,SOIC,14P,8.74x3.99mm,HEX,TP,-,-,-,0.05V,-	SA
55to+	25C,500mW,4V,-	SA			
5	1103-000129	IC100	IC-EEPROM	24C02,256x8,SOP,8P,5x4mm,4.5/5.5V,0to+70C	SA
5	1103-000129	IC101	IC-EEPROM	24C02,256x8,SOP,8P,5x4mm,4.5/5.5V,0to+70C	SA
5	1103-001279	IC201	IC-EEPROM	24C32,4Kx8,SOP,8P,5x4mm,2.5/5.5V,-40to+85C	SA
5	1105-001165	IC302	IC-DRAM	416S1020,512Kx16BITx2,TSOP,50P	SA
5	1201-001983	IC500	IC-AUDIO AMP	TPA3002D2PHP,HTQFP,48P,7X7MM,-,-,PLASTIC,20V,2.7W,-40TO+85C,-,1V/US,-,10MV,TR	SA
5	1201-002136	IC504	IC-AUDIO AMP	LM4810,MSOP,8P,3x3mm,DUAL,-,PLASTIC,5.5V,-,40 to 85C,-,-,-,-,-,TP	SA
5	1203-001212	IC701	IC-VOL. DETECTOR	7029,SOT-89,3P,-,PLASTIC,-,500	SA
5	1203-001488	IC604	IC-POSI.FIXED REG.	7805,T0-252,3P,-,PLASTIC,4.8/5	SA
5	1203-001816	IC605	IC-POSI.FIXED REG.	78M08,T0-252,3P,-,PLASTIC,7.7/8.3V,1.0W,-40TO+85C,0.5A,-,TP	SA
5	1203-002844	IC607	IC-POSI.FIXED REG.	AP1117D-18A,T0-252-3L,3P,6.7X5.6MM,PLASTIC,1.764/1.836V,-,0TO+150C,1A,-,TP	SA
5	1203-002898	IC606	IC-POSI.FIXED REG.	G950T45R,T0-252,3P,6.54x6.46mm,PLASTIC,2.475/2.575V,0to+125C,1A,-,TP	SA
5	1203-003059	IC600	IC-SWITCH VOL. REG.	MP1583,SOIC,8P,4.9x3.9mm,PLASTIC,1.22/21V,-,40to+85CC,3A,1.194/1.25V,TP	SA
5	1205-002518	IC300	IC-LCD CONTROLLER	MST51510,LQFP,256P,-,PLASTIC,3.3V,-,0to+70C,TR,IC-LCD CONTROLLER	SA
5	2007-000043	R110	R-CHIP	1Kohm,1%,1/10W,TP,1608	SA
5	2007-000043	R114	R-CHIP	1Kohm,1%,1/10W,TP,1608	SA
5	2007-000043	R240	R-CHIP	1Kohm,1%,1/10W,TP,1608	SA
5	2007-000043	R241	R-CHIP	1Kohm,1%,1/10W,TP,1608	SA
5	2007-000043	R628	R-CHIP	1Kohm,1%,1/10W,TP,1608	SA
5	2007-000052	R600	R-CHIP	10Kohm,1%,1/10W,TP,1608	SA
5	2007-000052	R602	R-CHIP	10Kohm,1%,1/10W,TP,1608	SA
5	2007-000067	R565	R-CHIP	15Kohm,1%,1/10W,TP,1608	SA
5	2007-000070	R222	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R366	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R530	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000072	R132	R-CHIP	47ohm,5%,1/10W,TP,1608	SA
5	2007-000072	R133	R-CHIP	47ohm,5%,1/10W,TP,1608	SA
5	2007-000072	R134	R-CHIP	47ohm,5%,1/10W,TP,1608	SA
5	2007-000072	R135	R-CHIP	47ohm,5%,1/10W,TP,1608	SA
5	2007-000072	R136	R-CHIP	47ohm,5%,1/10W,TP,1608	SA
5	2007-000072	R137	R-CHIP	47ohm,5%,1/10W,TP,1608	SA
5	2007-000072	R138	R-CHIP	47ohm,5%,1/10W,TP,1608	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	2007-000072	R139	R-CHIP	47ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R101	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R102	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R117	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R118	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R119	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R120	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R123	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R124	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R125	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R142	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R147	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R148	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R151	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R153	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R211	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R212	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R226	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R228	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R335	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R340	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R341	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R342	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R343	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R505	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R506	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R518	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R520	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R524	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R526	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R528	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R533	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R581	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R586	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R700	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R7103	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R7109	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R7110	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R7135	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R7136	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R7137	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R7138	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R7139	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R7140	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R7141	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R723	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000076	R542	R-CHIP	330ohm,5%,1/10W,TP,1608	SA
5	2007-000076	R544	R-CHIP	330ohm,5%,1/10W,TP,1608	SA
5	2007-000076	R571	R-CHIP	330ohm,5%,1/10W,TP,1608	SA
5	2007-000077	R521	R-CHIP	470ohm,5%,1/10W,TP,1608	SA
5	2007-000078	R155	R-CHIP	1Kohm,5%,1/10W,TP,1608	SA
5	2007-000078	R336	R-CHIP	1Kohm,5%,1/10W,TP,1608	SA
5	2007-000078	R392	R-CHIP	1Kohm,5%,1/10W,TP,1608	SA
5	2007-000078	R502	R-CHIP	1Kohm,5%,1/10W,TP,1608	SA
5	2007-000078	R517	R-CHIP	1Kohm,5%,1/10W,TP,1608	SA
5	2007-000078	R519	R-CHIP	1Kohm,5%,1/10W,TP,1608	SA
5	2007-000078	R523	R-CHIP	1Kohm,5%,1/10W,TP,1608	SA
5	2007-000078	R525	R-CHIP	1Kohm,5%,1/10W,TP,1608	SA
5	2007-000078	R527	R-CHIP	1Kohm,5%,1/10W,TP,1608	SA
5	2007-000078	R532	R-CHIP	1Kohm,5%,1/10W,TP,1608	SA
5	2007-000078	R572	R-CHIP	1Kohm,5%,1/10W,TP,1608	SA
5	2007-000078	R580	R-CHIP	1Kohm,5%,1/10W,TP,1608	SA
5	2007-000078	R584	R-CHIP	1Kohm,5%,1/10W,TP,1608	SA
5	2007-000078	R585	R-CHIP	1Kohm,5%,1/10W,TP,1608	SA
5	2007-000078	R701	R-CHIP	1Kohm,5%,1/10W,TP,1608	SA
5	2007-000078	R708	R-CHIP	1Kohm,5%,1/10W,TP,1608	SA
5	2007-000078	R7132	R-CHIP	1Kohm,5%,1/10W,TP,1608	SA
5	2007-000078	R7133	R-CHIP	1Kohm,5%,1/10W,TP,1608	SA
5	2007-000078	R757	R-CHIP	1Kohm,5%,1/10W,TP,1608	SA
5	2007-000081	R111	R-CHIP	2.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000082	R765	R-CHIP	3.3Kohm,5%,1/10W,TP,1608	SA
5	2007-000084	R129	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000084	R130	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000084	R131	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000084	R348	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000084	R371	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	SA

7 Electrical Parts List

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	2007-000084	R391	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000084	R393	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000084	R507	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000084	R508	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000084	R509	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000084	R543	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000084	R702	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000084	R7142	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000084	R781	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000087	R743	R-CHIP	6.8Kohm,5%,1/10W,TP,1608	SA
5	2007-000087	R744	R-CHIP	6.8Kohm,5%,1/10W,TP,1608	SA
5	2007-000087	R745	R-CHIP	6.8Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R103	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R104	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R116	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R121	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R141	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R144	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R145	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R306	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R307	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R358	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R378	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R379	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R381	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R535	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R536	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R545	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R553	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R556	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R560	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R563	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R564	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R566	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R567	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R582	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R583	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R615	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R616	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R617	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R623	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R624	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R625	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R626	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R7130	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R7143	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000097	R541	R-CHIP	47Kohm,5%,1/10W,TP,1608	SA
5	2007-000097	R557	R-CHIP	47Kohm,5%,1/10W,TP,1608	SA
5	2007-000097	R559	R-CHIP	47Kohm,5%,1/10W,TP,1608	SA
5	2007-000097	R562	R-CHIP	47Kohm,5%,1/10W,TP,1608	SA
5	2007-000097	R574	R-CHIP	47Kohm,5%,1/10W,TP,1608	SA
5	2007-000098	R548	R-CHIP	56Kohm,5%,1/10W,TP,1608	SA
5	2007-000098	R549	R-CHIP	56Kohm,5%,1/10W,TP,1608	SA
5	2007-000102	C706	R-CHIP	100Kohm,5%,1/10W,TP,1608	SA
5	2007-000102	R612	R-CHIP	100Kohm,5%,1/10W,TP,1608	SA
5	2007-000102	R613	R-CHIP	100Kohm,5%,1/10W,TP,1608	SA
5	2007-000102	R614	R-CHIP	100Kohm,5%,1/10W,TP,1608	SA
5	2007-000102	R620	R-CHIP	100Kohm,5%,1/10W,TP,1608	SA
5	2007-000102	R627	R-CHIP	100Kohm,5%,1/10W,TP,1608	SA
5	2007-000102	R7131	R-CHIP	100Kohm,5%,1/10W,TP,1608	SA
5	2007-000103	R569	R-CHIP	120Kohm,5%,1/10W,TP,1608	SA
5	2007-000118	R301	R-CHIP	390ohm,5%,1/10W,TP,1608	SA
5	2007-000402	R531	R-CHIP	150ohm,5%,1/10W,TP,1608	SA
5	2007-000458	R522	R-CHIP	18Kohm,5%,1/10W,TP,1608	SA
5	2007-000539	R621	R-CHIP	200ohm,5%,1/10W,TP,1608	SA
5	2007-000616	R568	R-CHIP	24Kohm,5%,1/10W,TP,1608	SA
5	2007-000869	R550	R-CHIP	4.7Kohm,1%,1/10W,TP,1608	SA
5	2007-000869	R551	R-CHIP	4.7Kohm,1%,1/10W,TP,1608	SA
5	2007-000869	R7107	R-CHIP	4.7Kohm,1%,1/10W,TP,1608	SA
5	2007-000869	R7108	R-CHIP	4.7Kohm,1%,1/10W,TP,1608	SA
5	2007-000913	R577	R-CHIP	43Kohm,5%,1/10W,TP,1608	SA
5	2007-000965	R576	R-CHIP	5.1Kohm,5%,1/10W,TP,1608	SA
5	2007-000979	R601	R-CHIP	5.6Kohm,1%,1/10W,TP,1608	SA
5	2007-001002	R149	R-CHIP	510ohm,5%,1/10W,TP,1608	SA
5	2007-001164	R108	R-CHIP	75ohm,1%,1/10W,TP,1608	SA
5	2007-001164	R109	R-CHIP	75ohm,1%,1/10W,TP,1608	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	2007-001164	R122	R-CHIP	75ohm,1%,1/10W,TP,1608	SA
5	2007-001167	R345	R-CHIP	75ohm,5%,1/10W,TP,1608	SA
5	2007-001167	R346	R-CHIP	75ohm,5%,1/10W,TP,1608	SA
5	2007-001167	R347	R-CHIP	75ohm,5%,1/10W,TP,1608	SA
5	2007-001167	R529	R-CHIP	75ohm,5%,1/10W,TP,1608	SA
5	2007-001167	R768	R-CHIP	75ohm,5%,1/10W,TP,1608	SA
5	2007-001167	R769	R-CHIP	75ohm,5%,1/10W,TP,1608	SA
5	2007-001167	R770	R-CHIP	75ohm,5%,1/10W,TP,1608	SA
5	2007-001167	R771	R-CHIP	75ohm,5%,1/10W,TP,1608	SA
5	2007-001167	R772	R-CHIP	75ohm,5%,1/10W,TP,1608	SA
5	2007-001167	R773	R-CHIP	75ohm,5%,1/10W,TP,1608	SA
5	2007-001167	R774	R-CHIP	75ohm,5%,1/10W,TP,1608	SA
5	2007-001167	R775	R-CHIP	75ohm,5%,1/10W,TP,1608	SA
5	2007-001179	R575	R-CHIP	8.2Kohm,5%,1/10W,TP,1608	SA
5	2007-001179	R703	R-CHIP	8.2Kohm,5%,1/10W,TP,1608	SA
5	2007-007852	R534	R-CHIP	140ohm,1%,1/10W,TP,1608	SA
5	2011-000881	RA301	R-NET	33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.6x0.5mm	SA
5	2011-000881	RA302	R-NET	33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.6x0.5mm	SA
5	2011-000881	RA303	R-NET	33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.6x0.5mm	SA
5	2203-000140	C505	C-CER,CHIP	1.5nF,10%,50V,X7R,TP,1608,-	SA
5	2203-000140	C506	C-CER,CHIP	1.5nF,10%,50V,X7R,TP,1608,-	SA
5	2203-000140	C507	C-CER,CHIP	1.5nF,10%,50V,X7R,TP,1608,-	SA
5	2203-000140	C508	C-CER,CHIP	1.5nF,10%,50V,X7R,TP,1608,-	SA
5	2203-000140	C517	C-CER,CHIP	1.5nF,10%,50V,X7R,TP,1608,-	SA
5	2203-000140	C518	C-CER,CHIP	1.5nF,10%,50V,X7R,TP,1608,-	SA
5	2203-000140	C521	C-CER,CHIP	1.5nF,10%,50V,X7R,TP,1608,-	SA
5	2203-000140	C522	C-CER,CHIP	1.5nF,10%,50V,X7R,TP,1608,-	SA
5	2203-000140	C528	C-CER,CHIP	1.5nF,10%,50V,X7R,TP,1608,-	SA
5	2203-000140	C529	C-CER,CHIP	1.5nF,10%,50V,X7R,TP,1608,-	SA
5	2203-000189	C105	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C106	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C107	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C110	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C111	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C112	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C208	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C209	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C504	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C540	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C541	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C542	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C543	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C545	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C547	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C557	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C567	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C568	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C569	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C603	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C606	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C628	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C629	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C632	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C633	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C723	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C730	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C731	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C733	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C740	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C741	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C742	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C743	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C744	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C745	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C746	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C758	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C759	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C760	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C763	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C765	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C766	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C767	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000236	C102	C-CER,CHIP	0.1nF,5%,50V,C0G,TP,1608	SA
5	2203-000236	C114	C-CER,CHIP	0.1nF,5%,50V,C0G,TP,1608	SA
5	2203-000236	C608	C-CER,CHIP	0.1nF,5%,50V,C0G,TP,1608	SA
5	2203-000257	C527	C-CER,CHIP	10nF,10%,50V,X7R,TP,1608	SA

7 Electrical Parts List

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	2203-000257	C534	C-CER,CHIP	10nF,10%,50V,X7R,TP,1608	SA
5	2203-000257	C570	C-CER,CHIP	10nF,10%,50V,X7R,TP,1608	SA
5	2203-000257	C576	C-CER,CHIP	10nF,10%,50V,X7R,TP,1608	SA
5	2203-000257	C600	C-CER,CHIP	10nF,10%,50V,X7R,TP,1608	SA
5	2203-000257	C642	C-CER,CHIP	10nF,10%,50V,X7R,TP,1608	SA
5	2203-000257	C700	C-CER,CHIP	10nF,10%,50V,X7R,TP,1608	SA
5	2203-000257	C705	C-CER,CHIP	10nF,10%,50V,X7R,TP,1608	SA
5	2203-000440	C352	C-CER,CHIP	1nF,10%,50V,X7R,TP,1608,-	SA
5	2203-000440	C536	C-CER,CHIP	1nF,10%,50V,X7R,TP,1608,-	SA
5	2203-000440	C537	C-CER,CHIP	1nF,10%,50V,X7R,TP,1608,-	SA
5	2203-000440	C571	C-CER,CHIP	1nF,10%,50V,X7R,TP,1608,-	SA
5	2203-000440	C572	C-CER,CHIP	1nF,10%,50V,X7R,TP,1608,-	SA
5	2203-000440	C728	C-CER,CHIP	1nF,10%,50V,X7R,TP,1608,-	SA
5	2203-000440	C729	C-CER,CHIP	1nF,10%,50V,X7R,TP,1608,-	SA
5	2203-000440	C737	C-CER,CHIP	1nF,10%,50V,X7R,TP,1608,-	SA
5	2203-000440	C739	C-CER,CHIP	1nF,10%,50V,X7R,TP,1608,-	SA
5	2203-000440	C761	C-CER,CHIP	1nF,10%,50V,X7R,TP,1608,-	SA
5	2203-000440	C768	C-CER,CHIP	1nF,10%,50V,X7R,TP,1608,-	SA
5	2203-000552	C707	C-CER,CHIP	0.02nF,5%,50V,C0G,TP,1608	SA
5	2203-000552	C708	C-CER,CHIP	0.02nF,5%,50V,C0G,TP,1608	SA
5	2203-000626	C101	C-CER,CHIP	0.022nF,5%,50V,C0G,TP,1608	SA
5	2203-000626	C367	C-CER,CHIP	0.022nF,5%,50V,C0G,TP,1608	SA
5	2203-000626	C368	C-CER,CHIP	0.022nF,5%,50V,C0G,TP,1608	SA
5	2203-000626	C735	C-CER,CHIP	0.022nF,5%,50V,C0G,TP,1608	SA
5	2203-000626	C736	C-CER,CHIP	0.022nF,5%,50V,C0G,TP,1608	SA
5	2203-000903	C103	C-CER,CHIP	0.0047nF,0.25PF,50V,C0G,TP,1608	SA
5	2203-000903	C104	C-CER,CHIP	0.0047nF,0.25PF,50V,C0G,TP,1608	SA
5	2203-000903	C115	C-CER,CHIP	0.0047nF,0.25PF,50V,C0G,TP,1608	SA
5	2203-000903	C378	C-CER,CHIP	0.0047nF,0.25PF,50V,C0G,TP,1608	SA
5	2203-000972	C350	C-CER,CHIP	47nF,10%,16V,X7R,TP,1608	SA
5	2203-000972	C351	C-CER,CHIP	47nF,10%,16V,X7R,TP,1608	SA
5	2203-000972	C353	C-CER,CHIP	47nF,10%,16V,X7R,TP,1608	SA
5	2203-000972	C749	C-CER,CHIP	47nF,10%,16V,X7R,TP,1608	SA
5	2203-000972	C750	C-CER,CHIP	47nF,10%,16V,X7R,TP,1608	SA
5	2203-000972	C751	C-CER,CHIP	47nF,10%,16V,X7R,TP,1608	SA
5	2203-001071	C204	C-CER,CHIP	0.056nF,5%,50V,C0G,TP,1608	SA
5	2203-001222	C601	C-CER,CHIP	0.82nF,10%,50V,X7R,TP,1608	SA
5	2203-001607	C559	C-CER,CHIP	0.22nF,5%,50V,NP0,-,1608	SA
5	2203-005005	C100	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C341	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C344	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C355	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C356	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C381	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005065	C108	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C109	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C113	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C201	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C202	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C203	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C205	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C206	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C300	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C301	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C302	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C303	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C304	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C305	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C306	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C307	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C308	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C309	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C311	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C312	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C313	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C314	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C315	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C316	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C317	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C318	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C319	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C320	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C321	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C322	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C323	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C370	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	2203-005065	C371	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C372	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C373	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C374	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C375	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C376	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C377	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C379	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C380	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C502	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C503	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C509	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C551	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C560	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C562	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C564	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C577	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C578	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C605	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C610	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C611	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C623	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C625	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C701	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C702	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C703	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C704	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C709	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C710	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C711	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C712	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C713	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C714	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C715	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C716	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C717	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C732	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005261	C549	C-CER,CHIP	1000nF,10%,25V,X7R,-,3216	SA
5	2203-005261	C566	C-CER,CHIP	1000nF,10%,25V,X7R,-,3216	SA
5	2203-005437	C546	C-CER,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	SA
5	2203-006170	C531	C-CER,CHIP	220NF,10%,16V,X7R,TP,1608	SA
5	2203-006170	C574	C-CER,CHIP	220NF,10%,16V,X7R,TP,1608	SA
5	2402-001080	C762	C-AL,SMD	47uF,20%,50V,WT,TP,8x10mm	SNA
5	2402-001080	C764	C-AL,SMD	47uF,20%,50V,WT,TP,8x10mm	SNA
5	2402-001081	C631	C-AL,SMD	100uF,20%,25V,WT,TP,8.3x8.3x10	SA
5	2402-001081	C638	C-AL,SMD	100uF,20%,25V,WT,TP,8.3x8.3x10	SA
5	2402-001081	C640	C-AL,SMD	100uF,20%,25V,WT,TP,8.3x8.3x10	SA
5	2402-001081	C641	C-AL,SMD	100uF,20%,25V,WT,TP,8.3x8.3x10	SA
5	2402-001086	C604	C-AL,SMD	100UF,20%,16V,WT,TP,6.6X6.6X5.3	SA
5	2402-001086	C607	C-AL,SMD	100UF,20%,16V,WT,TP,6.6X6.6X5.3	SA
5	2402-001086	C624	C-AL,SMD	100UF,20%,16V,WT,TP,6.6X6.6X5.3	SA
5	2402-001086	C627	C-AL,SMD	100UF,20%,16V,WT,TP,6.6X6.6X5.3	SA
5	2402-001086	C634	C-AL,SMD	100UF,20%,16V,WT,TP,6.6X6.6X5.3	SA
5	2402-001086	C635	C-AL,SMD	100UF,20%,16V,WT,TP,6.6X6.6X5.3	SA
5	2402-001128	C513	C-AL,SMD	100UF,20%,16V,WT,TP,6.3X5.7MM	SA
5	2402-001128	C555	C-AL,SMD	100UF,20%,16V,WT,TP,6.3X5.7MM	SA
5	2402-001128	C558	C-AL,SMD	100UF,20%,16V,WT,TP,6.3X5.7MM	SA
5	2402-001158	C554	C-AL,SMD	1UF,20%,50V,WT,TP,4X5.2MM	SA
5	2402-001158	C556	C-AL,SMD	1UF,20%,50V,WT,TP,4X5.2MM	SA
5	2402-001158	C561	C-AL,SMD	1UF,20%,50V,WT,TP,4X5.2MM	SA
5	2402-001158	C563	C-AL,SMD	1UF,20%,50V,WT,TP,4X5.2MM	SA
5	2402-001160	C51	C-AL,SMD	330UF,20%,16V,WT,TP,1008	SA
5	2402-001176	C510	C-AL,SMD	4.7UF,20%,25V,WT,TP,4X5.4MM	SA
5	2402-001176	C511	C-AL,SMD	4.7UF,20%,25V,WT,TP,4X5.4MM	SA
5	2402-001176	C512	C-AL,SMD	4.7UF,20%,25V,WT,TP,4X5.4MM	SA
5	2402-001176	C514	C-AL,SMD	4.7UF,20%,25V,WT,TP,4X5.4MM	SA
5	2402-001176	C515	C-AL,SMD	4.7UF,20%,25V,WT,TP,4X5.4MM	SA
5	2402-001176	C516	C-AL,SMD	4.7UF,20%,25V,WT,TP,4X5.4MM	SA
5	2402-001176	C590	C-AL,SMD	4.7UF,20%,25V,WT,TP,4X5.4MM	SA
5	2402-001176	C591	C-AL,SMD	4.7UF,20%,25V,WT,TP,4X5.4MM	SA
5	2402-001176	C592	C-AL,SMD	4.7UF,20%,25V,WT,TP,4X5.4MM	SA
5	2402-001176	C593	C-AL,SMD	4.7UF,20%,25V,WT,TP,4X5.4MM	SA
5	2402-001176	C734	C-AL,SMD	4.7UF,20%,25V,WT,TP,4X5.4MM	SA
5	2402-001183	C523	C-AL,SMD	22UF,20%,16V,WT,TP,5.3X5.3X6MM	SA
5	2402-001183	C524	C-AL,SMD	22UF,20%,16V,WT,TP,5.3X5.3X6MM	SA
5	2402-001216	C602	C-AL,SMD	470uF,20%,16V,WT,TP,10.3x10.3x10mm	SA

7 Electrical Parts List

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	2402-001222	C721	C-AL,SMD	3.3UF,20%,50V,HR,TP,4.3X4.3X5.8MM	SNA
5	2402-001226	C565	C-AL,SMD	4.7UF,20%,35V,HR,TP,4.3X4.3X5.8MM	SNA
5	2703-000222	L701	INDUCTOR-SMD	560nH,10%,2012	SA
5	2703-000398	L702	INDUCTOR-SMD	10uH,10%,3225	SA
5	2703-000398	L703	INDUCTOR-SMD	10uH,10%,3225	SA
5	2703-001334	L200	INDUCTOR-SMD	1.5uH,10%,2012	SA
5	2703-001778	L504	INDUCTOR-SMD	3.3uH,20%,3225	SA
5	2703-001778	L505	INDUCTOR-SMD	3.3uH,20%,3225	SA
5	2703-001778	L506	INDUCTOR-SMD	3.3uH,20%,3225	SA
5	2703-001778	L507	INDUCTOR-SMD	3.3uH,20%,3225	SA
5	2801-003667	X300	CRYSTAL-SMD	14.31818MHz,30ppm,28-AAN,16,50ohm,TP	SA
5	2801-004004	X700	CRYSTAL-SMD	20.25MHz,20ppm,28-AAN,13pF,25ohm,TP	SA
5	3301-001145	FT520	BEAD-SMD	60ohm,4516,6000mA,TP,70ohm/45MHz,82ohm/760MHz,0.01ohm	SNA
5	3301-001145	FT521	BEAD-SMD	60ohm,4516,6000mA,TP,70ohm/45MHz,82ohm/760MHz,0.01ohm	SNA
5	3301-001145	FT522	BEAD-SMD	60ohm,4516,6000mA,TP,70ohm/45MHz,82ohm/760MHz,0.01ohm	SNA
5	3301-001145	FT523	BEAD-SMD	60ohm,4516,6000mA,TP,70ohm/45MHz,82ohm/760MHz,0.01ohm	SNA
5	3301-001145	FT600	BEAD-SMD	60ohm,4516,6000mA,TP,70ohm/45MHz,82ohm/760MHz,0.01ohm	SNA
5	3301-001145	FT601	BEAD-SMD	60ohm,4516,6000mA,TP,70ohm/45MHz,82ohm/760MHz,0.01ohm	SNA
5	3301-001145	FT701	BEAD-SMD	60ohm,4516,6000mA,TP,70ohm/45MHz,82ohm/760MHz,0.01ohm	SNA
5	3301-001288	BD700	BEAD-SMD	30ohm,1608,400mA,TP,,,0.3ohm	SA
5	3704-000249	IC202 SOCK	SOCKET-IC	32P,PLCC,SN,1.27mm	SA
5	3711-002049	CN201	CONNECTOR-HEADER	BOX,6P,1R,1.25mm,SMD-A,SN	SA
5	3711-005292	CN203	CONNECTOR-HEADER	BOX,3P,1R,2MM,SMD-A,SN,WHT	SA
5	3711-005292	CN502	CONNECTOR-HEADER	BOX,3P,1R,2MM,SMD-A,SN,WHT	SA
5	3711-005472	CN301	CONNECTOR-HEADER	BOX,20P,1R,1.25mm,SMD-A,Sn+Pb,IVR	SA
5	3711-005477	CN501	CONNECTOR-HEADER	BOX,4P,1R,2mm,SMD-A,Sn+Pb,WHT	SA
5	BN09-00008A	IC700	IC MICOM	VCTX1Y1-D2,MH17WS,144,8.7,20.25,20,8,MQFP,TR,8,0 to +65	SA
5	BN27-00001A	L500	COIL CHOKE	68UH,68UH,10%,5845,0.5OHM,7.3X7.3X3.3MM,REEL	SA
5	BN27-00001A	L501	COIL CHOKE	68UH,68UH,10%,5845,0.5OHM,7.3X7.3X3.3MM,REEL	SA
5	BN27-00001A	L502	COIL CHOKE	68UH,68UH,10%,5845,0.5OHM,7.3X7.3X3.3MM,REEL	SA
5	BN27-00001A	L503	COIL CHOKE	68UH,68UH,10%,5845,0.5OHM,7.3X7.3X3.3MM,REEL	SA
5	BN27-00009A	L600	COIL CHOKE	SMD 12X12X6,EOS,33UH,15%,-0.12 g MAX,2ADR10X5.0MM,18.5TS,12X12X6,1.8MM,1UEW 0.	SA
5	BN27-00017A	L700	COIL CHOKE-SMD	PO5845-330,LT17N2,33uH,10%,0.3ohm,1A,DR5845,35.5Ts,6"5.2"4.5,1.5mm,TP	SA
5	BN41-00513A	MP1.0	PCB MAIN	730MW,FR4,1.0,1.6,234*142*1.6,730MW	SNA
2	BN91-00807J	-	ASSY SHIELD	MH17WS	SNA
3	6003-000117	SH/PAN+M/PCB	SCREW-TAPTITE	BH,+,B,M3,L6,ZPC(YEL),SWRCH18A	SNA
3	6003-000117	SH/PAN+POW/PCB	SCREW-TAPTITE	BH,+,B,M3,L6,ZPC(YEL),SWRCH18A	SNA
3	6003-000117	SH/PAN+SH/PCB	SCREW-TAPTITE	BH,+,B,M3,L6,ZPC(YEL),SWRCH18A	SNA
3	6003-000276	C/F+SH/PAN	SCREW-TAPTITE	BH,+,B,M3,L10,ZPC(YEL),SWCH10	SNA
3	BN39-00519A	CIS	LEAD CONNECTOR	MONTE,UL1061#28,ULCSA,20P,100MM,#26,12507HS-20,12507HS-20L,BK,1061#28,SJ03-01-6	SA
3	BN44-00116A	CIS	IP BOARD	IP-48135T,MH17WS,3.2mA,8.6mA,48KHZ,4.90V/264VAC,+13V/+5.1V,0 to +60, -20 to -70,	SNA
3	BN61-01234A	CIS	HOLDER-INVERTER	MATISSE,ABS V0,BK07	SNA
3	BN63-01420A	CIS	SHIELD-PANEL	730MW,SECC,T1.0	SNA

7-2 MH17WS Others

Level	Loc. No.	Code No.	Description	Specification	Remarks
2	BN90-00659K	-	ASSY COVER FRONT	MH17WS	SNA
3	6003-001003	C/F+C/R	SCREW-TAPTITE	BH,+B,M4,L12,ZPC(BLK),SWRCH18	SNA
3	BN96-01295A	C/F	ASSY COVER P-FRONT	730MW,ABS HB GR70	SNA
2	BN90-00663A	-	ASSY COVER REAR	MH17WS	SNA
3	BN96-01435A	C/R	ASSY STAND P-SET	MH17WS,ABS+BI	SNA
2	BN91-00567J	-	ASSY LCD	NK17,S4	SNA
3	BN07-00112A	CIS	LCD	LTM170W1-L01,LSA,8BIT,404*258*16.2,16.7M,30,-,-,AMLCD/2 LVDS,-	SA
2	BN91-00801U	-	ASSY CHASSIS	MH17WS	SNA
2	BN92-01071K	-	ASSY P/MATERIAL	MH17WS	SNA
3	6902-000520	P/M	BAG PE	HDPE/NITRON(DOUBLE),T0.015/T0.5(DOUBLE),W700,L700,TRP,28 LANGUAGE,2-	SNA
3	BH69-00457B	P/M	PACKING-PAD BOTTOM	GH15,FOAM,T3.0,930,1000	SNA
3	BH69-40321A	P/M	PACKING-PAD	SW-4,W2155*L140,-,DEC,-,-,-,-,	SNA
3	BH69-40383J	P/M	PACKING-PAD/TOP	CB-SW4,960*760,-,CGE7507	SNA
3	BN68-00129A	P/M	LABEL SHIPPING-00	-,LABEL SHIPPING,ART-PAPER,100G,-,WHT,BLACK,-,-,-	SNA
3	BN69-00140M	P/M	PAD-PALLET COVER	IBM15,SW,800*3540,1295,-,-,-,-,-	SNA
3	BN69-00140V	P/M	PAD-PALLET COVER	RB15AS,SW4,1200,3530,-,-,-,-,-	SNA
3	BN69-00617N	P/M	PALLET-WOODEN	730MW,WOODEN,1240,830,120	SNA
3	BN69-00843A	P/M	CUSHION	730MW,EPS,M50	SNA
2	BN92-01072J	-	ASSY ACCESSORY	MH17WS	SNA
3	BN96-01490D	UNIT/ACCESSORY	ASSY ACCESSORY	MH17WS	SNA
4	3705-001191	ACCESSORY	CONNECTOR-COAXIAL	PAL,ADAPTER(J/P),30mohm,-,-	SA
4	3903-000042	ACCESSORY	CBF-POWER CORD	DT,EU,FP3YES,IEC320 C13/C14,250/250V,10-16*10A,BLK,1830MM,-,H05VV-F 3X0.75MM²2,	SA
4	4301-000121	ACCESSORY	BATTERY-MN	1.5V,-,AAA,10.5x44.5m,HOLDER	SA
4	6902-000110	ACCESSORY	BAG PE	LDPE,T0.05,L356,W240,TRP,28,2,PE MARK	SNA
4	AA39-00365A	ACCESSORY	CBF IF	CS29M6PF,1P,RCA-HOLDER,1900mm,BLK,RCA,FM-RADIO ANT	SA
4	BH68-70438A	ACCESSORY	CARD-BLOC WARRANTY-09	TFT LCD,BASIC,EU,MOJO,100G,W21	SNA
4	BH68-70448A	ACCESSORY	CARD-01	TFT LCD,SRC,RUSSIA,S/W,120,W210*L120,INSTALL CARD	SNA
4	BN39-00061B	ACCESSORY	CBF SIGNAL-STEREO	MH15NS,1P,UL2851#26,2000mm,PLUG(BLK/GRN),BLACK,STEREO,SJ03-01-418	SA
4	BN39-00244B	ACCESSORY	CBF SIGNAL	MO15PS,15P/15P,20276-N,1830MM,UL20276,BLACK,D-SUB/MALE,DET. TYPE	SA
4	BN59-00434A	ACCESSORY	REMOCON	Manet_Multi,TM79,40,SV-012P,EX,NT/PAL	SA
4	BN96-00832K	ACCESSORY	ASSY MANUAL P-IB+QSG	730MW,SyncMaster,W/W,28Lang,BN59-390K+BH68-376L	SNA
5	BH68-00376L	QUICK_SETUP	MANUAL-02	LCDQUICK SETUP GUIDE,SYNCMaster,E/F/S/G/P/L13LANGS,W/W,MOJO100G,298,420	SNA
5	BN59-00390K	IB	S/W DRIVER-00,IB	730MW,W/W,SyncMaster,28Lang	SNA

Memo