


A vertical scale with five horizontal tick marks. The marks are labeled A, B, C, D, and E from bottom to top.



SYSTEM CONTROL & SERVO ICs DC VOLTAGE CHART (SP MODE)

REF. NO.	IC6001																			
MODE	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
STOP	0	3.1	0	3.1	0	3.1	3.1	3.1	0	0	3.1	0.1	3.2	0	0	1.6	3.1	0	0	0
PLAY	0	0	3.1	0	0	3.1	3.1	0	0	3.1	3.1	0.1	3.2	0	0	1.6	0	0	0	0
F.F	0	3.2	3.2	0	3.2	2.7	3.1	3.2	0	0	3.2	0.1	3.2	0	0	1.6	1.9	0	0	0

REF. NO.	IC6001																			
MODE	21	22	23	24	25	26	27	28	29	30	31	32	33	34	35	36	37	38	39	40
STOP	0	3.1	1.6	3.1	3.1	0	3.2	0.1	0	0	3.1	0	3.0	3.0	0	3.0	3.1	3.2	1.6	1.6
PLAY	0	0	1.6	3.1	3.1	0	3.1	0.1	0	0	3.0	0	3.0	3.0	0	3.0	3.0	3.1	—	—
F.F	0	3.2	1.6	3.2	3.2	0	3.2	0.1	0	0	3.0	0	3.0	3.0	0	3.0	3.0	3.2	—	—

REF. NO.	IC6001																			
MODE	41	42	43	44	45	46	47	48	49	50	51	52	53	54	55	56	57	58	59	60
STOP	1.5	1.2	0	0	0.8	2.8	0	0.1	0.2	0	0.2	2.7	2.7	2.8	3.0	3.0	2.9	0	0	0.9
PLAY	1.6	1.2	0	0	0.8	2.8	0	0.1	0	0	0	2.7	2.7	2.7	3.0	3.0	3.0	0	3.1	1.2
F.F	1.6	1.1	0	0	0.8	2.8	0	0	0.4	0	0.4	2.8	2.8	2.8	3.0	2.7	2.9	0	3.2	0.9

REF. NO.	IC6001																			
MODE	61	62	63	64	65	66	67	68	69	70	71	72	73	74	75	76	77	78	79	80
STOP	0	0	1.6	0	3.1	3.1	0	0	0.3	3.0	0	0.1	0	0.7	0	1.6	0.1	0	1.6	1.6
PLAY	0	0	1.6	0	3.1	3.1	0	0	0.3	3.0	0	2.5	1.6	0.7	1.5	1.5	0.1	0	1.6	1.6
F.F	0	0	1.6	0	3.2	3.2	0	0	0.3	3.0	0	1.3	1.5	0.7	1.5	1.6	0.1	0	1.6	1.6

REF. NO.	IC6001																			
MODE	81	82	83	84	85	86	87	88	89	90	91	92	93	94	95	96	97	98	99	100
STOP	1.4	1.7	3.1	0	0	0	1.6	1.6	0	3.0	1.6	3.1	0	1.5	3.1	0	2.7	3.1	2.0	1.7
PLAY	1.5	1.6	3.1	0	0	0	1.6	1.6	0	3.0	1.5	3.1	1.4	1.3	3.1	0	1.3	3.1	2.0	2.2
F.F	1.4	1.6	3.2	0	0	0	1.6	1.6	0	3.0	1.6	3.2	1.3	1.5	3.2	0	2.0	3.1	2.0	1.7

REF. NO.	IC6001																			
MODE	101	102	103	104	105	106	107	108	109	110	111	112	113	114	115	116	117	118	119	120
STOP	0	0	0	0	3.0	3.0	3.0	3.0	3.1	3.1	3.1	3.1	2.8	2.4	0	3.1	3.1	0	0	0
PLAY	0	0	0	0	3.0	3.0	3.0	3.0	3.1	3.1	3.1	3.1	2.9	0	3.1	3.1	0	0	0	0
F.F	0	0	0	0	3.0	3.0	3.0	3.0	3.2	3.2	3.2	3.2	2.8	2.4	0	3.2	3.2	0	0	0

REF. NO.	IC6001																			
MODE	121	122	123	124	125	126	127	128												
STOP	0	0	3.1	3.1	0	0	3.1	0												
PLAY	0	0	3.1	3.1	0	0	0	0												
F.F	0	0	3.2	3.2	0	0	3.2	0												

REF. NO.	IC6002																			
MODE	1	2	3	4	5	6	7	8												
STOP	3.1	3.1	0	3.1	3.2	7.1	3.2	3.3												
PLAY	3.1	3.1	0	3.1	3.2	7.1	3.2	3.2												
F.F	3.2	3.2	0	3.2	3.2	7.0	3.2	3.3												

REF. NO.	IC6003																			
MODE	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
STOP	2.8	2.8	2.7	3.1	3.0	0	0	1.4	0	0	0	0	0	0	0	0	0	0	2.9	2.6
PLAY	2.8	2.8	2.8	3.1	3.0	0	0	1.4	0	0	0	0	0	0	0	0	0	0	3.0	2.7
F.F	2.8	2.8	2.7	3.1	3.0	0	0	1.4	0	0	0	0	0	0	0	0	0	0	3.0	2.7

REF. NO.	IC6004										IC6005									
MODE	1	2	3	4	5	6	7	8			1	2	3	4	5	6	7	8		
STOP	3.0	3.0	3.0	2.9	3.0	2.6	0	0			0	7.0	4.9	0	0	0	0	0		
PLAY	3.0	3.0	3.0	3.0	3.0	2.7	0	0			0	7.0	4.9	0	0	3.0	0	0		
F.F	3.0	3.0	3.0	2.9	3.0	2.7	0	0			0	7.0	4.9	0	0	3.0	0	0		

REF. NO.	IC6006										IC6008									
MODE	1	2	3	4	5	6	7	8			1	2	3	4	5	6	7	8		
STOP	3.0	0.6	0.7	0	2.8	0.4	4.6	4.9			0	2.8	2.8	0	0	0.3	3.0	3.1		
PLAY	1.5	0.7	0.7	0	2.8	0.4	4.6	4.9			0	2.8	2.8	0	0	0.3	3.0	3.1		
F.F	1.4	0.6	0.6	0	2.8	0.4	4.6	4.9			0	2.8	2.8	0	0	0.3	3.0	3.0		

REF. NO.	IC6009										IC6012									
MODE	1	2	3	4	5						1	2	3	4	5	6	7	8		
STOP	1.5	1.5	0	1.3	3.1						2.7	0	0	0	2.7	2.7	2.8	3.0		
PLAY	1.5	1.5	0	1.4	3.0						2.8	0	0	0	0	0.5	2.6	3.0		
F.F	1.5	1.5	0	1.4	3.0						2.7	0	0	0	0	2.7	2.8	3.0		

SYSTEM CONTROL & SERVO TRs DC VOLTAGE CHART (SP MODE)

REF. NO.	Q6002			Q6006			Q6201											
MODE	E	C	B	E	C	B	E	C	B									
STOP	0.1	7.1	0	7.1	7.0	6.5	0	0.3	0									
PLAY	0.1	7.1	0	7.0	7.0	6.4	3.2	3.1	2.6									
F.F	0.6	7.0	0.5	7.0	6.9	6.4	3.2	3.1	2.6									

REF. NO.	QR6001			QR6003			QR6004						QR6006			QR6007		
MODE	E	C	B	E	C	B	1	2	3	4	5	6	E	C	B	E	C	B
STOP	3.0	0	3.2	3.1	0	3.1	3.1	0	0	3.1	3.1	3.0	0	2.7	0.7	0	0	3.1
PLAY	3.0	0	3.2	3.0	0	3.1	3.0	3.1	0	3.0	0	0	0	0	0.7	0	0	3.1
F.F	3.0	0	3.2	3.0	0.5	2.6	3.0	3.2	0	3.0	0	0	0	2.7	0.7	0	0	3.1

REF. NO.	QR6008			QR6012			QR6014			QR6015			QR6050				
MODE	E	C	B	E	C	B	E	C	B	E	C	B	1	2	3	4	5
STOP	0	0	0	0	2.7	0	0	3.2	0	0	6.3	0	0	0	0	0	0
PLAY	0	0	0	0	2.8	0	0	3.2	0	0	6.8	0	0	0	0	0	0
F.F	0	0	0	0	2.8	0	0	3.2	0	0	6.5	0	0	0	0	0	0