

## 4-2. ELECTRICAL REPLACEMENT PARTS LIST

- Note: 1. Be sure to make your orders of replacement parts according to this list.  
 2. IMPORTANT SAFETY NOTICE: Components identified with the mark < I > have the special characteristics for safety. When replacing any of these components, use only the same type.  
 3. Unless otherwise specified,  
 All resistors are in OHMS, K-1,000 OHMS. All capacitors are in MICROFARADS (uf), P-uuf.  
 4. The P.C. Board units marked with "■" show below the main assembled parts.  
 5. The marking (RTL) indicates the retention time is limited for this item.  
 After the discontinuation of this assembly in production, it will no longer be available.

Ref.No.	Part No.	Part Name & Description	Pcs	Remarks
■	VEP23432B	CAMERA/MAIN C.B.A.	1	(RTL)
		NV-RX9B		
		NV-RX10EG/A/EN/ENH/EU		
■	VEP23432A	CAMERA/MAIN C.B.A.	1	(RTL)
		NV-RX19B		
		NV-RX20EG/EN/ENH/EU		
■	VEP28229M	E.V.F. C.B.A.	1	(RTL)
		NV-RX9B		
		NV-RX10EG/A/EN/ENH/EU		
■	VEP28229L	E.V.F. C.B.A.	1	(RTL)
		NV-RX19B		
		NV-RX20EG/EN/ENH/EU		
■	VEP22248A	CGD FLEX. CARD C.B.A.	1	(RTL)
■	VEK8063	LENS FLEX. CARD C.B.A.	1	(RTL)
■	VEK8058	MIC UNIT	1	(RTL)
		NV-RX9B		
		NV-RX10EG/A/EN/ENH/EU		
■	VEK7707	MIC UNIT	1	(RTL)
		NV-RX19B		
		NV-RX20EG/EN/ENH/EU		
■	VEP00X56A	FRONT C.B.A.	1	(RTL)
		NV-RX19B		
		NV-RX20EG/EN/ENH/EU		
■	VEP00X57C	AV JACK C.B.A.	1	(RTL)
		NV-RX19B		
		NV-RX20EG/EN/ENH/EU		
■	VEP23432B	CAMERA/MAIN C.B.A.	1	(RTL)
		NV-RX9B		
		NV-RX10EG/A/EN/ENH/EU		
C201	EGST0JY106Z	T. CAPACITOR CH 6.3V 10U	1	
C202	ECUX1C104ZV	G. CAPACITOR CH 16V 0.1U	1	
C203	EGST0JY156Z	T. CAPACITOR CH 6.3V 15U	1	
C204	ECUX1C104ZV	G. CAPACITOR CH 16V 0.1U	1	
C205	ECUM1C105ZFN	G. CAPACITOR CH 16V 1U	1	
C206-12	ECUX1C104ZV	G. CAPACITOR CH 16V 0.1U	7	
C213	ECUX1H180JCV	G. CAPACITOR CH 50V 18P	1	
C214	ECUX1C104ZV	G. CAPACITOR CH 16V 0.1U	1	
C216	ECUX1H101JCV	G. CAPACITOR CH 50V 100P	1	
C218	EGST0JY106Z	T. CAPACITOR CH 6.3V 10U	1	
C219	ECUX1C104ZV	G. CAPACITOR CH 16V 0.1U	1	
C220	ECUX1H120JCV	G. CAPACITOR CH 50V 12P	1	
C221	ECUM1C105ZFN	G. CAPACITOR CH 16V 1U	1	
C222	EGST0JY106Z	T. CAPACITOR CH 6.3V 10U	1	
C223	ECUX1C104ZV	G. CAPACITOR CH 16V 0.1U	1	
C224	EGST0JY106Z	T. CAPACITOR CH 6.3V 10U	1	
C225	ECUX1C104ZV	G. CAPACITOR CH 16V 0.1U	1	
C226	EGST1GY475Z	T. CAPACITOR CH 16V 4.7U	1	
C227	ECUX1H330JCV	G. CAPACITOR CH 50V 33P	1	
C228	ECUX1C104ZV	G. CAPACITOR CH 16V 0.1U	1	
C229	EGST1GX155Z	T. CAPACITOR CH 4V 2.2U	1	
C230	ECUM1H104ZFN	G. CAPACITOR CH 50V 0.1U	1	
C231, 32	ECUM1C105ZFN	G. CAPACITOR CH 16V 1U	2	
C235, 36	ECUX1C104ZV	G. CAPACITOR CH 16V 0.1U	2	

Ref.No.	Part No.	Part Name & Description	Pcs	Remarks
C238	ECUX1C104ZV	G. CAPACITOR CH 16V 0.1U	1	
C243	EGEVOJA101	E. CAPACITOR CH 6.3V 100U	1	
C244	ECUX1H330JCV	G. CAPACITOR CH 50V 33P	1	
C301, 02	ECUX1H103KBV	G. CAPACITOR CH 50V 0.01U	2	
C304	ECUM1C224ZFN	G. CAPACITOR CH 16V 0.22U	1	
C306	ECUX1H120JCV	G. CAPACITOR CH 50V 12P	1	
C307	ECUX1H080CGV	G. CAPACITOR CH 50V 8P	1	
C309	EGST0JY106Z	T. CAPACITOR CH 6.3V 10U	1	
C310	ECUX1H102KBV	G. CAPACITOR CH 50V 1000P	1	
C311	EGST1AY225Z	T. CAPACITOR CH 10V 2.2U	1	
C312	ECUX1H103KBV	G. CAPACITOR CH 50V 0.01U	1	
C321	ECUX1H220JCV	G. CAPACITOR CH 50V 22P	1	
C322	ECUX1H103KBV	G. CAPACITOR CH 50V 0.01U	1	
C403	EGST0JY106Z	T. CAPACITOR CH 6.3V 10U	1	
C405	ECUX1C104ZV	G. CAPACITOR CH 16V 0.1U	1	
C406	ECUX1H103KBV	G. CAPACITOR CH 50V 0.01U	1	
C407, 08	ECUX1C104KBV	G. CAPACITOR CH 16V 0.1U	2	
C409	ECUM1C105KBM	G. CAPACITOR CH 16V 1U	1	
C410	ECUX1H103KBV	G. CAPACITOR CH 50V 0.01U	1	
C411	ECUM1C105KBM	G. CAPACITOR CH 16V 1U	1	
C412	ECUX1H103KBV	G. CAPACITOR CH 50V 0.01U	1	
C413	ECUX1H470JCV	G. CAPACITOR CH 50V 47P	1	
C414	EGST1GY105Z	T. CAPACITOR CH 16V 1U	1	
C415	ECUM1C105KBM	G. CAPACITOR CH 16V 1U	1	
C416	ECUX1C104ZV	G. CAPACITOR CH 16V 0.1U	1	
C417	EGST0JY106Z	T. CAPACITOR CH 6.3V 10U	1	
C418	ECUX1H220JCV	G. CAPACITOR CH 50V 22P	1	
C701	ECUX1H332KBV	G. CAPACITOR CH 50V 3300P	1	
C703	ECUX1H103KBV	G. CAPACITOR CH 50V 0.01U	1	
C704	EGST0JY106Z	T. CAPACITOR CH 6.3V 10U	1	
C705	ECUX1C104ZV	G. CAPACITOR CH 16V 0.1U	1	
C706, 07	ECUX1C104KBV	G. CAPACITOR CH 16V 0.1U	2	
C708, 09	ECUX1H102KBV	G. CAPACITOR CH 50V 1000P	2	
C711	EGEVI4A470	E. CAPACITOR CH 16V 47U	1	
C712	ECUX1H102KBV	G. CAPACITOR CH 50V 1000P	1	
C713	ECUX1H332KBV	G. CAPACITOR CH 50V 3300P	1	
C714	EGST0JY106Z	T. CAPACITOR CH 6.3V 10U	1	
C715	ECUM1C105KBM	G. CAPACITOR CH 16V 1U	1	
C716	ECUM1H104ZFN	G. CAPACITOR CH 50V 0.1U	1	
C718	ECUX1C104KBV	G. CAPACITOR CH 16V 0.1U	1	
C719	ECUX1H102KBV	G. CAPACITOR CH 50V 1000P	1	
C720	ECUM1A105KBN	G. CAPACITOR CH 10V 1U	1	
C721	ECUX1H102KBV	G. CAPACITOR CH 50V 1000P	1	
C722	ECUM1H104ZFN	G. CAPACITOR CH 50V 0.1U	1	
C724	ECUX1C104KBV	G. CAPACITOR CH 16V 0.1U	1	
C726, 27	ECUX1C104KBV	G. CAPACITOR CH 16V 0.1U	2	
C1002	ECUM1A225KBM	G. CAPACITOR CH 10V 2.2U	1	
C1003	ECUM1A335KBM	G. CAPACITOR CH 10V 3.3U	1	
C1004	ECUX1H331JCV	G. CAPACITOR CH 50V 330P	1	
C1005	ECUM1C105KBM	G. CAPACITOR CH 16V 1U	1	
C1008	ECUM1A335KBM	G. CAPACITOR CH 10V 3.3U	1	
C1009	ECUX1H331JCV	G. CAPACITOR CH 50V 330P	1	
C1010	ECUM1C105KBM	G. CAPACITOR CH 16V 1U	1	
C1012	ECUX1H102KBV	G. CAPACITOR CH 50V 1000P	1	
C1014	ECUX1H561JCV	G. CAPACITOR CH 50V 560P	1	
C1017	ECUM1E105KB	G. CAPACITOR CH 25V 1U	1	
C1019	ECUM1E334KBM	G. CAPACITOR CH 25V 0.33U	1	
C1020	ECUM1C105ZFN	G. CAPACITOR CH 16V 1U	1	
C1022	ECUM1H104ZFN	G. CAPACITOR CH 50V 0.1U	1	
C1024	ECUM1A105KBN	G. CAPACITOR CH 10V 1U	1	
C1025	ECUX1C104KBV	G. CAPACITOR CH 16V 0.1U	1	
C1026	EGEVI4A010	E. CAPACITOR CH 50V 1U	1	
C1027	ECUX1H101JCV	G. CAPACITOR CH 50V 100P	1	
C1028	EGEVI4AR47	E. CAPACITOR CH 50V 0.47U	1	
C1029	ECUX1H471JCV	G. CAPACITOR CH 50V 470P	1	
C1030	ECUX1H822KBV	G. CAPACITOR CH 50V 8200P	1	
C1031	ECUX1H471JCV	G. CAPACITOR CH 50V 470P	1	
C1032	ECUX1H822KBV	G. CAPACITOR CH 50V 8200P	1	
C1033-35	ECUX1H102KBV	G. CAPACITOR CH 50V 1000P	3	
C1036	ECUX1H471JCV	G. CAPACITOR CH 50V 470P	1	
C1037	ECUX1H822KBV	G. CAPACITOR CH 50V 8200P	1	
C1040, 41	ECUX1H103KBV	G. CAPACITOR CH 50V 0.01U	2	
C1051	ECUM1C334KBN	G. CAPACITOR CH 16V 0.33U	1	
C1055	ECUM1C105KBM	G. CAPACITOR CH 16V 1U	1	
C1057	ECUM1C105KBM	G. CAPACITOR CH 16V 1U	1	

Ref.No.	Part No.	Part Name & Description	Pcs	Remarks	Ref.No.	Part No.	Part Name & Description	Pcs	Remarks
C1064	EGUM1C105KBM	C. CAPACITOR CH 16V 1U	1		C4048	EGUX1H103KBV	C. CAPACITOR CH 50V 0.01U	1	
C1066	EGUM1C105ZFN	C. CAPACITOR CH 16V 1U	1		C4049	EGST0JY106Z	T. CAPACITOR CH 6.3V 10U	1	
C1071	EGUM1C105KBM	C. CAPACITOR CH 16V 1U	1		C4050	ECEVO5A470	E. CAPACITOR CH 4V 47U	1	
C1073	EGUX1H103KBV	C. CAPACITOR CH 50V 0.01U	1		C4051	EGUX1H270JCV	C. CAPACITOR CH 50V 27P	1	
C1080, 81	EGUX1C473KBV	C. CAPACITOR CH 16V 0.047U	2		C5001-04	EGUX1H103ZFN	C. CAPACITOR CH 50V 0.01U	4	
C1112	EGUM1A225KBM	C. CAPACITOR CH 10V 2.2U	1		C5005-08	EGUX1H270JCV	C. CAPACITOR CH 50V 27P	4	
C2001, 02	ECEV1HA010	E. CAPACITOR CH 50V 1U	2		C5009, 10	EGUX1H103ZFN	C. CAPACITOR CH 50V 0.01U	2	
C2003	EGUX1H332KBV	C. CAPACITOR CH 50V 3300P	1		C5011	EGUM1E473KBN	C. CAPACITOR CH 25V 0.047U	1	
C2004	EGUX1H101JCV	C. CAPACITOR CH 50V 100P	1		C5012, 13	EGUX1H103KBV	C. CAPACITOR CH 50V 0.01U	2	
C2005	EGUX1H152KBV	C. CAPACITOR CH 50V 1500P	1		C5014	EGST0JY106Z	T. CAPACITOR CH 6.3V 10U	1	
C2007	ECEV1HA010	E. CAPACITOR CH 50V 1U	1		C5016	EGST0JY106Z	T. CAPACITOR CH 6.3V 10U	1	
C2009	EGUX1C104KBV	C. CAPACITOR CH 16V 0.1U	1		C5017	EGUX1H103ZFN	C. CAPACITOR CH 50V 0.01U	1	
C2010	EGUX1C104ZFN	C. CAPACITOR CH 16V 0.1U	1		C5018	EGST0JY106Z	T. CAPACITOR CH 6.3V 10U	1	
C2011	EGUX1H101JCV	C. CAPACITOR CH 50V 100P	1		C5019	EGUM1C105ZFN	C. CAPACITOR CH 16V 1U	1	
C2012, 13	EGUX1H103KBV	C. CAPACITOR CH 50V 0.01U	2		C5020, 21	EGUX1H103ZFN	C. CAPACITOR CH 50V 0.01U	2	
C2014	ECEV1CA100	E. CAPACITOR CH 16V 10U	1		C5022	EGUM1C104KBN	C. CAPACITOR CH 16V 0.1U	1	
C2015-17	EGUX1C104KBV	C. CAPACITOR CH 16V 0.1U	3		C5023	EGUX1H103ZFN	C. CAPACITOR CH 50V 0.01U	1	
C2018	ECEVOJA220	E. CAPACITOR CH 6.3V 22U	1		C5024, 25	EGUX1H103KBV	C. CAPACITOR CH 50V 0.01U	2	
C2020-22	EGUX1H103KBV	C. CAPACITOR CH 50V 0.01U	3		C5041	EGUX1H101JCV	C. CAPACITOR CH 50V 100P	1	
C2023	EGUM1C105KBM	C. CAPACITOR CH 16V 1U	1		C5501, 02	EGUX1H103KBV	C. CAPACITOR CH 50V 0.01U	2	
C2025-27	EGUX1C104ZFN	C. CAPACITOR CH 16V 0.1U	3		C5503	EGUX1C473KBV	C. CAPACITOR CH 16V 0.047U	1	
C2028	ECEVOJA220	E. CAPACITOR CH 6.3V 22U	1		C5504-06	EGUX1H103KBV	C. CAPACITOR CH 50V 0.01U	3	
C2029	EGUX1H103ZFN	C. CAPACITOR CH 50V 0.01U	1		C5507	ECEVO5A470	E. CAPACITOR CH 4V 47U	1	
C2033	EGUM1C105ZFN	C. CAPACITOR CH 16V 1U	1		C5508	EGUX1H103KBV	C. CAPACITOR CH 50V 0.01U	1	
C2040-42	EGUX1C473KBV	C. CAPACITOR CH 16V 0.047U	3		C5509	ECEVO5A470	E. CAPACITOR CH 4V 47U	1	
C2043	EGUX1C104ZFN	C. CAPACITOR CH 16V 0.1U	1		C5510	EGUM1C105KBM	C. CAPACITOR CH 16V 1U	1	
C2070	EGUX1H103KBV	C. CAPACITOR CH 50V 0.01U	1		C5511	EGUX1C104KBV	C. CAPACITOR CH 16V 0.1U	1	
C3001	EGUX1H680JCV	C. CAPACITOR CH 50V 68P	1		C5512	EGST0G226Z	T. CAPACITOR CH 4V 22U	1	
C3004	EGUX1C104KBV	C. CAPACITOR CH 16V 0.1U	1		C5513	EGUX1C473KBV	C. CAPACITOR CH 16V 0.047U	1	
C3005	ECEVO5A470	E. CAPACITOR CH 4V 47U	1		C5514	EGUM1C105KBM	C. CAPACITOR CH 16V 1U	1	
C3006	EGUX1H103KBV	C. CAPACITOR CH 50V 0.01U	1		C5515	EGUX1H181JCV	C. CAPACITOR CH 50V 180P	1	
C3008	EGUX1C104KBV	C. CAPACITOR CH 16V 0.1U	1		C5516	EGUX1H390JCV	C. CAPACITOR CH 50V 39P	1	
C3009, 10	EGUX1H103KBV	C. CAPACITOR CH 50V 0.01U	2		C5517	EGUM1C474KBM	C. CAPACITOR CH 16V 0.47U	1	
C3016	EGUX1H151JCV	C. CAPACITOR CH 50V 150P	1		C5518	EGUX1H103KBV	C. CAPACITOR CH 50V 0.01U	1	
C3017	EGUX1C104KBV	C. CAPACITOR CH 16V 0.1U	1		C5519	EGUX1C104KBV	C. CAPACITOR CH 16V 0.1U	1	
C3018	EGUX1H330JCV	C. CAPACITOR CH 50V 33P	1		C5520	EGUM1H333KBN	C. CAPACITOR CH 50V 0.033U	1	
C3019, 20	EGUX1C104KBV	C. CAPACITOR CH 16V 0.1U	2		C5523	EGUX1H180JCV	C. CAPACITOR CH 50V 18P	1	
C3022	EGUX1C104KBV	C. CAPACITOR CH 16V 0.1U	1		C5524	EGUX1H150JCV	C. CAPACITOR CH 50V 15P	1	
C3023	EGUM1C105KBM	C. CAPACITOR CH 16V 1U	1		C5526	EGUX1H040CCV	C. CAPACITOR CH 50V 4P	1	
C3024	EGUX1C104KBV	C. CAPACITOR CH 16V 0.1U	1		C5527	EGUX1C104KBV	C. CAPACITOR CH 16V 0.1U	1	
C3026	EGUX1C104KBV	C. CAPACITOR CH 16V 0.1U	1		C5530	EGUX1H331JCV	C. CAPACITOR CH 50V 330P	1	
C3027	EGUM1A225KBM	C. CAPACITOR CH 10V 2.2U	1		C5531	EGUX1H103KBV	C. CAPACITOR CH 50V 0.01U	1	
C3028	ECEVOGA471	E. CAPACITOR CH 4V 470U	1		C5533	EGUX1C273KBV	C. CAPACITOR CH 16V 0.027U	1	
C3029	ECEV1AAN100	E. CAPACITOR CH 10V 10U	1		C6001-03	EGUX1C104ZFN	C. CAPACITOR CH 16V 0.1U	3	
C3030	EGUM1C105KBM	C. CAPACITOR CH 16V 1U	1		C6004	EGUX1C104KBV	C. CAPACITOR CH 16V 0.1U	1	
C3031	EGUX1C104KBV	C. CAPACITOR CH 16V 0.1U	1		C6005	EGUX1H103KBV	C. CAPACITOR CH 50V 0.01U	1	
C3032	ECEVO5A470	E. CAPACITOR CH 4V 47U	1		C6006	EGUX1H080CCV	C. CAPACITOR CH 50V 8P	1	
C3033	EGUX1H103KBV	C. CAPACITOR CH 50V 0.01U	1		C6007	EGUX1H150JCV	C. CAPACITOR CH 50V 15P	1	
C3035	EGST0JY106Z	T. CAPACITOR CH 6.3V 10U	1		C6008, 09	EGUX1C104ZFN	C. CAPACITOR CH 16V 0.1U	2	
C4001	EGYX1H821JCV	C. CAPACITOR CH 50V 820P	1		C6011	EGUX1C104ZFN	C. CAPACITOR CH 16V 0.1U	1	
C4002	EGUM1C105ZFN	C. CAPACITOR CH 16V 1U	1		C6012	EGUX1H070DCV	C. CAPACITOR CH 50V 7P	1	
C4003	EGUX1H822KBV	C. CAPACITOR CH 50V 8200P	1		C6013	EGUX1H100CCV	C. CAPACITOR CH 50V 100P	1	
C4008	EGUM1C105ZFN	C. CAPACITOR CH 16V 1U	1		C6014, 15	EGUX1C104ZFN	C. CAPACITOR CH 16V 0.1U	2	
C4011	ECEVO5A470	E. CAPACITOR CH 4V 47U	1		C6017	EGUX1C104ZFN	C. CAPACITOR CH 16V 0.1U	1	
C4012	EGST0JX226Z	T. CAPACITOR CH 6.3V 22U	1		C6020	EGUX1C104ZFN	C. CAPACITOR CH 16V 0.1U	1	
C4014	EGUX1C223KBV	C. CAPACITOR CH 16V 0.022U	1		C6025	EGUX1C104ZFN	C. CAPACITOR CH 16V 0.1U	1	
C4015	EGUX1H682KBV	C. CAPACITOR CH 50V 6800P	1		C6027	ECEVOGA101	E. CAPACITOR CH 4V 100U	1	
C4016	EGUM2A472JCV	C. CAPACITOR CH 100V 4700P	1		C6030	EGUM1A105KBN	C. CAPACITOR CH 10V 1U	1	
C4017	EGUX1H102KBV	C. CAPACITOR CH 50V 1000P	1		C6031	EGUX1C104ZFN	C. CAPACITOR CH 16V 0.1U	1	
C4019, 20	EGUM1C474KBN	C. CAPACITOR CH 16V 0.47U	2		C6032	EGUX1C104KBV	C. CAPACITOR CH 16V 0.1U	1	
C4021, 22	EGUX1H103KBV	C. CAPACITOR CH 50V 0.01U	2		C6036	EGUX1H103KBV	C. CAPACITOR CH 50V 0.01U	1	
C4023	EGUX1H272KBV	C. CAPACITOR CH 50V 2700P	1		C6038	EGUX1H103KBV	C. CAPACITOR CH 50V 0.01U	1	
C4024	EGST1CY475Z	T. CAPACITOR CH 16V 4.7U	1		C6039	EGUM1A105KBN	C. CAPACITOR CH 10V 1U	1	
C4025	EGST0JY685Z	T. CAPACITOR CH 6.3V 6.8U	1		C6040	EGUX1C104KBV	C. CAPACITOR CH 16V 0.1U	1	
C4026	EGUX1H103KBV	C. CAPACITOR CH 50V 0.01U	1		C6046-48	EGUX1H103KBV	C. CAPACITOR CH 50V 0.01U	3	
C4027	EGST1AY225Z	T. CAPACITOR CH 10V 2.2U	1		C6049, 50	ECEV1CA100	E. CAPACITOR CH 16V 10U	2	
C4028	EGUX1H102KBV	C. CAPACITOR CH 50V 1000P	1		C6051	EGUX1C223KBV	C. CAPACITOR CH 16V 0.022U	1	
C4029	EGUX1H222KBV	C. CAPACITOR CH 50V 2200P	1		C6052	EGUX1H561JCV	C. CAPACITOR CH 50V 560P	1	
C4030	EGUX1H562KBV	C. CAPACITOR CH 50V 5600P	1		C6060	EGUM1A105KBN	C. CAPACITOR CH 10V 1U	1	
C4031	EGUX1H102KBV	C. CAPACITOR CH 50V 1000P	1		C6061	EGUX1C104KBV	C. CAPACITOR CH 16V 0.1U	1	
C4032	EGUM1C105KBM	C. CAPACITOR CH 16V 1U	1		C6201, 02	EGUX1C104KBV	C. CAPACITOR CH 16V 0.1U	2	
C4033, 34	EGUM1C105ZFN	C. CAPACITOR CH 16V 1U	2		C6203	EGST0JY106Z	T. CAPACITOR CH 6.3V 10U	1	
C4035	EGUM1C105KBM	C. CAPACITOR CH 16V 1U	1		C6204	EGUM1C105KBM	C. CAPACITOR CH 16V 1U	1	
C4036	EGST0JY335Z	T. CAPACITOR CH 6.3V 3.3U	1		C6205	EGUX1C104ZFN	C. CAPACITOR CH 16V 0.1U	1	
C4040	EGUM1C105ZFN	C. CAPACITOR CH 16V 1U	1		C6206	ECEVOGA101	E. CAPACITOR CH 4V 100U	1	

Ref.No.	Part No.	Part Name & Description	Pcs	Remarks	Ref.No.	Part No.	Part Name & Description	Pcs	Remarks
C6207	EGUX1H103KBV	C. CAPACITOR CH 50V 0.01U	1		L1001	VLQ0759	COIL	1	
C6208	EGUX1C104KBV	C. CAPACITOR CH 16V 0.1U	1		L1002	VLQ0760	COIL	1	
C6209	EGST0JX226Z	T. CAPACITOR CH 6.3V 22U	1		L1003	VLQ0763	COIL	1	
C6210	ECUM1C105KBM	C. CAPACITOR CH 16V 1U	1		L1004	VLQ0319K100	COIL 10UH	1	
					L1006	VLQ0319F150	COIL 15UH	1	
D202	1SS355	DIODE	1		L1007	VLQ0761	COIL	1	
D203	RB751V40	DIODE	1		L1008	VLQ0319M4R7	COIL 4.7UH	1	
D204	1SS355	DIODE	1		L1010	VLQ0319K100	COIL 10UH	1	
D481, 82	RB751V40	DIODE	2		L1011	VLQ0319K101	COIL 100UH	1	
D1002	EC20QS06	DIODE	1		L1014	VLQ0319K100	COIL 10UH	1	
D1006, 07	MA111	DIODE	2		L1015	VLQ0319K470	COIL 47UH	1	
D1015	EC15QS04	DIODE	1		L1062	VLQ0762	COIL	1	
D3004	1SS355	DIODE	1		L3002	VLQ0319K100	COIL 10UH	1	
D4004	1SS355	DIODE	1		L3003	VLQ0163J820	COIL 82UH	1	
D6001, 02	MA132WA	DIODE	2		L3021	VLQ0319K470	COIL 47UH	1	
D6003	1SS355	DIODE	1		L4005	VLQ0319K101	COIL 100UH	1	
D6006	RB751V40	DIODE	1		L5001-04	VLQ0319K470	COIL 47UH	4	
D6007	MA132WK	DIODE	1		L5501	VLQ0319K100	COIL 10UH	1	
D6008	1SS355	DIODE	1		L5502	ELJFA100JB	COIL 10UH	1	
D6016	MA133	DIODE	1		L5503	VLQ0426J120	COIL 12UH	1	
D6201	1SS355	DIODE	1		L5504	ELJFA390JB	COIL 39UH	1	
					L5505	ELJFA150JB	COIL 15UH	1	
FP302	VJS3654B011	CONNECTOR (FEMALE) 11P	1		L5506	VLQ0319K470	COIL 47UH	1	
FP701	VJS3319B018	CONNECTOR (FEMALE) 18P	1		L5508	VLQ0163J471	COIL 470UH	1	
FP2001	VJS3654D007	CONNECTOR (FEMALE) 7P	1		L6002	VLQ0319K101	COIL 100UH	1	
FP2002	VJS2958B018	CONNECTOR (FEMALE) 18P	1						
FP4001	VJS2958D009	CONNECTOR (FEMALE) 9P	1		LB209, 10	ERJ36EYJ330	M. RESISTOR CH 1/16W 33	2	
FP4002	VJS3320B026	CONNECTOR (FEMALE) 26P	1		LB211	VLP0154	COIL	1	
FP5001	VJS2959B013	CONNECTOR (FEMALE) 13P	1		LB213	VLP0146	COIL	1	
FP6001	VJS2959D018	CONNECTOR (FEMALE) 18P	1		LB301	VLP0323A102	COIL	1	
FP6002	VJS2959B006	CONNECTOR (FEMALE) 6P	1		LB307	VLP0323A102	COIL	1	
FP6006	VJS3319B021	CONNECTOR (FEMALE) 21P	1		LB308	VLP0140	COIL	1	
					LB309	VLP0304	COIL	1	
IC201	MN5224	IC	1		LB6001	VLP0323A102	COIL	1	
IC202	MN31121SA	IC	1						
IC203	NN2035FAQ	IC	1		PP201	VJP3358C012	CONNECTOR (MALE) 12P	1	
IC205	AN1358S	IC	1		PP401	VJP2962C024	CONNECTOR (MALE) 24P	1	
IC301	F436002APZ	IC	1		PP3001	VJP3358C016	CONNECTOR (MALE) 16P	1	
IC302	M623676P	IC	1						
IC701, 02	TB6526F	IC	2		PS1001	VJS2961C024	CONNECTOR (FEMALE) 24P	1	
IC706	NJM2115VA	IC	1						
IC710	MN1882421M9S	IC	1		Q201	2SD2216	TRANSISTOR	1	
IC711	TA75W01FU	IC	1		Q203	XP4601	TRANSISTOR-TRANSISTOR	1	
IC1001	BA9706K	IC	1		Q205	XP4601	TRANSISTOR-TRANSISTOR	1	
IC2001	TB6518F	IC	1		Q206	2SD1030	TRANSISTOR	1	
IC2002, 03	MDC05TR	IC	2		Q404	XP4501	TRANSISTOR-TRANSISTOR	1	
IC3001	HA118403F	IC	1		Q405	2SD2216	TRANSISTOR	1	
IC4001	UPC457262	IC	1		Q701-03	XN4404	TRANSISTOR	3	
IC5001	AN3355FHP	IC	1		Q704	2SD601A	TRANSISTOR	1	
IC5501	MSM7470-73MS	IC	1		Q705	2SD2216	TRANSISTOR	1	
IC6001	MN67556M9R	IC	1		Q706	XN4404	TRANSISTOR	1	
IC6002	MM1355XFE	IC	1		Q1001	2SA1731-R	TRANSISTOR	1	
IC6003	UPD6462GS618	IC	1		Q1003	MPL1	TRANSISTOR	1	
IC6004	AK6440HF	IC	1		Q1004	2SD2210	TRANSISTOR	1	
IC6005	BA6289F	IC	1		Q1062	MPL1	TRANSISTOR	1	
IC6006	TA75W393FU	IC	1		Q3001	XP4501	TRANSISTOR-TRANSISTOR	1	
IC6008	TC7W04F	IC	1		Q3002	XP4401	TRANSISTOR	1	
IC6009	TC7S08F	IC	1		Q3010, 11	2SD2216	TRANSISTOR	2	
IC6012	TC4W53F	IC	1		Q4002	2SD602-R	TRANSISTOR	1	
					Q4003	2SB1219	TRANSISTOR	1	
L201	ELJFA330JB	COIL 33UH	1		Q4004	XP4501	TRANSISTOR-TRANSISTOR	1	
L202	VLQ0426J680	COIL 68UH	1		Q4006	2SD2216	TRANSISTOR	1	
L203	VLQ0426J820	COIL 82UH	1		Q4007	XP4501	TRANSISTOR-TRANSISTOR	1	
L204	ELJFA220JB	COIL 22UH	1		Q4009	2SD2216	TRANSISTOR	1	
L205	VLQ0426J8R2	COIL 8.2UH	1		Q4014	2SB1462	TRANSISTOR	1	
L206	ELJFA220JB	COIL 22UH	1		Q4015	2SD2216	TRANSISTOR	1	
L208	ELJFA220JB	COIL 22UH	1		Q4019	2SD2216	TRANSISTOR	1	
L212	VLQ0426J270	COIL 27UH	1		Q5001, 02	XN4504	TRANSISTOR	2	
L402	VLQ0319K220	COIL 22UH	1		Q5003	2SA812	TRANSISTOR	1	
L403	VLQ0426J470	COIL 47UH	1		Q5502	2SD2216	TRANSISTOR	1	
L404	VLQ0319K220	COIL 22UH	1		Q6002, 03	2SD2216	TRANSISTOR	2	
L701, 02	VLQ0319K220	COIL 22UH	2		Q6005	2SD2216	TRANSISTOR	1	
L703	VLQ0319F150	COIL 15UH	1		Q6006	2SB1462	TRANSISTOR	1	
L704, 05	VLQ0319K220	COIL 22UH	2		Q6008	2SD2216	TRANSISTOR	1	
L708	VLQ0319K220	COIL 22UH	1		Q6201	2SB1462	TRANSISTOR	1	

Ref.No.	Part No.	Part Name & Description	Pcs	Remarks	Ref.No.	Part No.	Part Name & Description	Pcs	Remarks
QR401	MRN1103	TRANSISTOR-RESISTOR	1		R318	ERJ6GEYOR00	M. RESISTOR CH 1/10W 0	1	
QR402	MRN1102	TRANSISTOR-RESISTOR	1		R320	ERJ3GEYOR00	M. RESISTOR CH 1/16W 0	1	
QR701	MRN1102	TRANSISTOR-RESISTOR	1		R321	ERJ3GEYJ182	M. RESISTOR CH 1/16W 1.8K	1	
QR1001	MRN2102	TRANSISTOR-RESISTOR	1		R323	ERJ3GEYOR00	M. RESISTOR CH 1/16W 0	1	
QR1061	MRN2111	TRANSISTOR-RESISTOR	1		R325	ERJ3GEYOR00	M. RESISTOR CH 1/16W 0	1	
QR2002	MRN1111	TRANSISTOR-RESISTOR	1		R327	ERJ3GEYJ821	M. RESISTOR CH 1/16W 820	1	
QR3001	MRN1104	TRANSISTOR-RESISTOR	1		R333	ERJ3GEYOR00	M. RESISTOR CH 1/16W 0	1	
QR4003	MRN2103	TRANSISTOR-RESISTOR	1		R336	ERJ3GEYJ182	M. RESISTOR CH 1/16W 1.8K	1	
QR4004	XP1215	TRANSISTOR-RESISTOR	1		R337	ERJ3GEYOR00	M. RESISTOR CH 1/16W 0	1	
QR4005	MRN1104	TRANSISTOR-RESISTOR	1		R406	ERJ3GEYOR00	M. RESISTOR CH 1/16W 0	1	
QR4008	MRN1104	TRANSISTOR-RESISTOR	1		R409	ERJ3GEYOR00	M. RESISTOR CH 1/16W 0	1	
QR5502	UN2130X	TRANSISTOR-RESISTOR	1		R411	ERJ3GEYG472	M. RESISTOR CH 1/16W 4.7K	1	
QR5503	MRN1103	TRANSISTOR-RESISTOR	1		R412	ERJ3GEYJ272	M. RESISTOR CH 1/16W 2.7K	1	
QR5504	MRN1104	TRANSISTOR-RESISTOR	1		R413	ERJ3GEYJ103	M. RESISTOR CH 1/16W 10K	1	
QR6003	MRN2103	TRANSISTOR-RESISTOR	1		R415	ERJ3GEYG152	M. RESISTOR CH 1/16W 1.5K	1	
QR6004	XP4115	TRANSISTOR-RESISTOR	1		R417, 18	ERJ3RBD123	M. RESISTOR CH 1/16W 12K	2	
QR6006	MRN1104	TRANSISTOR-RESISTOR	1		R419	ERJ3RBD223	M. RESISTOR CH 1/16W 22K	1	
QR6007	MRN1102	TRANSISTOR-RESISTOR	1		R420	ERJ3RBD473	M. RESISTOR CH 1/16W 47K	1	
QR6008	MRN1104	TRANSISTOR-RESISTOR	1		R423	ERJ3GEYJ103	M. RESISTOR CH 1/16W 10K	1	
QR6012	MRN1104	TRANSISTOR-RESISTOR	1		R424	ERJ3GEYJ132	M. RESISTOR CH 1/16W 1.3K	1	
QR6014	UN9210	TRANSISTOR-RESISTOR	1		R425	ERJ3GEYJ911	M. RESISTOR CH 1/16W 710K	1	
QR6015	MRN1111	TRANSISTOR-RESISTOR	1		R426	ERJ3GEYJ222	M. RESISTOR CH 1/16W 2.2K	1	
QR6050	XP1211	TRANSISTOR-RESISTOR	1		R428	ERJ3GEYG152	M. RESISTOR CH 1/16W 1.5K	1	
					R429	ERJ3GEYJ821	M. RESISTOR CH 1/16W 820	1	
R202	ERJ3GEYJ182	M. RESISTOR CH 1/16W 1.8K	1		R430	ERJ3GEYJ103	M. RESISTOR CH 1/16W 10K	1	
R203	ERJ3GEYJ105	M. RESISTOR CH 1/16W 1M	1		R481	ERJ3GEYJ103	M. RESISTOR CH 1/16W 10K	1	
R204	ERJ3GEYJ391	M. RESISTOR CH 1/16W 390	1		R701, 02	ERJ3GEYJ3R3	M. RESISTOR CH 1/16W 3.3	2	
R205	ERJ3GEYOR00	M. RESISTOR CH 1/16W 0	1		R703, 04	ERJ3GEYJ2R2	M. RESISTOR CH 1/16W 2.2	2	
R206	ERJ3GEYG472	M. RESISTOR CH 1/16W 4.7K	1		R705, 06	ERJ3GEYJ473	M. RESISTOR CH 1/16W 47K	2	
R207, 08	ERJ3GEYG102	M. RESISTOR CH 1/16W 1K	2		R707	ERJ3GEYJ101	M. RESISTOR CH 1/16W 100	1	
R209	ERJ3GEYG152	M. RESISTOR CH 1/16W 1.5K	1		R708, 09	ERJ3GEYJ473	M. RESISTOR CH 1/16W 47K	2	
R210	ERJ3GEYJ391	M. RESISTOR CH 1/16W 390	1		R713	ERJ3GEYG102	M. RESISTOR CH 1/16W 1K	1	
R211	ERJ3GEYG822	M. RESISTOR CH 1/16W 8.2K	1		R716	ERJ3GEYG472	M. RESISTOR CH 1/16W 4.7K	1	
R212	ERJ3GEYJ335	M. RESISTOR CH 1/16W 3.3M	1		R717	ERJ3GEYJ221	M. RESISTOR CH 1/16W 220	1	
R213	ERJ3GEYJ563	M. RESISTOR CH 1/16W 56K	1		R718	ERJ3GEYJ223	M. RESISTOR CH 1/16W 22K	1	
R214	ERJ3GEYG472	M. RESISTOR CH 1/16W 4.7K	1		R719	ERJ3GEYOR00	M. RESISTOR CH 1/16W 0	1	
R215	ERJ2RHD753	M. RESISTOR CH 2W 75K	1		R720, 21	ERJ3GEYJ103	M. RESISTOR CH 1/16W 10K	2	
R216	ERJ2RHD153	M. RESISTOR CH 2W 15K	1		R722	ERJ3GEYJ104	M. RESISTOR CH 1/16W 100K	1	
R217	ERJ3GEYG113	M. RESISTOR CH 1/16W 11K	1		R723	ERJ3GEYJ103	M. RESISTOR CH 1/16W 10K	1	
R218	ERJ3GEYG183	M. RESISTOR CH 1/16W 18K	1		R724	ERJ3GEYG102	M. RESISTOR CH 1/16W 1K	1	
R219	ERJ3GEYJ221	M. RESISTOR CH 1/16W 220	1		R725	ERJ3GEYJ101	M. RESISTOR CH 1/16W 100	1	
R220	ERJ3GEYG472	M. RESISTOR CH 1/16W 4.7K	1		R726	ERJ3GEYG102	M. RESISTOR CH 1/16W 1K	1	
R221	ERJ3GEYJ105	M. RESISTOR CH 1/16W 1M	1		R727	ERJ3GEYJ223	M. RESISTOR CH 1/16W 22K	1	
R224	ERJ3GEYG222	M. RESISTOR CH 1/16W 2.2K	1		R728	ERJ3GEYJ273	M. RESISTOR CH 1/16W 27K	1	
R225	ERJ3GEYG102	M. RESISTOR CH 1/16W 1K	1		R729	ERJ3GEYJ153	M. RESISTOR CH 1/16W 15K	1	
R226, 27	ERJ3GEYJ105	M. RESISTOR CH 1/16W 1M	2		R730	ERJ3GEYJ103	M. RESISTOR CH 1/16W 10K	1	
R228	ERJ3GEYJ683	M. RESISTOR CH 1/16W 68K	1		R732	ERJ3GEYJ333	M. RESISTOR CH 1/16W 33K	1	
R229	ERJ3GEYJ123	M. RESISTOR CH 1/16W 12K	1		R733	ERJ3GEYJ684	M. RESISTOR CH 1/16W 680K	1	
R233	ERJ6GEYOR00	M. RESISTOR CH 1/10W 0	1		R734, 35	ERJ3GEYJ123	M. RESISTOR CH 1/16W 12K	2	
R234	ERJ3GEYG131	M. RESISTOR CH 1/16W 130	1		R736	ERJ3GEYJ474	M. RESISTOR CH 1/16W 470K	1	
R235	ERJ3GEYJ561	M. RESISTOR CH 1/16W 560	1		R737	ERJ3GEYJ684	M. RESISTOR CH 1/16W 680K	1	
R236	ERJ3GEYOR00	M. RESISTOR CH 1/16W 0	1		R738	ERJ3GEYJ124	M. RESISTOR CH 1/16W 120K	1	
R239	ERJ3GEYG471	M. RESISTOR CH 1/16W 470	1		R740	ERJ3GEYJ333	M. RESISTOR CH 1/16W 33K	1	
R240, 41	ERJ3GEYJ221	M. RESISTOR CH 1/16W 220	2		R757, 58	ERJ3GEYJ105	M. RESISTOR CH 1/16W 1M	2	
R242	ERJ3GEYG152	M. RESISTOR CH 1/16W 1.5K	1		R761	ERJ3GEYJ272	M. RESISTOR CH 1/16W 2.7K	1	
R243	ERJ3GEYJ182	M. RESISTOR CH 1/16W 1.8K	1		R770, 71	ERJ3GEYJ105	M. RESISTOR CH 1/16W 1M	2	
R244	ERJ3GEYJ222	M. RESISTOR CH 1/16W 2.2K	1		R1001	ERJ6RBD822	M. RESISTOR CH 1/10W 8.2K	1	
R245	ERJ3GEYJ561	M. RESISTOR CH 1/16W 560	1		R1002	ERJ6RBD272	M. RESISTOR CH 1/10W 2.7K	1	
R246	ERJ3GEYJ473	M. RESISTOR CH 1/16W 47K	1		R1005	ERJ3RBD472	M. RESISTOR CH 1/16W 4.7K	1	
R249	ERJ3GEYJ104	M. RESISTOR CH 1/16W 100K	1		R1006	ERJ3RBD272	M. RESISTOR CH 1/16W 2.7K	1	
R250	ERJ3RBD123	M. RESISTOR CH 1/16W 12K	1		R1007	ERJ8GEYJ330	M. RESISTOR CH 1/8W 33	1	
R251	ERJ3RBD223	M. RESISTOR CH 1/16W 22K	1		R1008	ERJ3RBD223	M. RESISTOR CH 1/16W 22K	1	
R301	ERJ3GEYJ563	M. RESISTOR CH 1/16W 56K	1		R1009	ERJ3RBD152	M. RESISTOR CH 1/16W 1.5K	1	
R302	ERJ3GEYJ683	M. RESISTOR CH 1/16W 68K	1		R1012	ERJ6RHD1872	M. RESISTOR CH 1/10W 18.7K	1	
R303	ERJ3GEYJ223	M. RESISTOR CH 1/16W 22K	1		R1013	ERJ6RBD473	M. RESISTOR CH 1/10W 47K	1	
R304	ERJ3GEYJ105	M. RESISTOR CH 1/16W 1M	1		R1014, 15	ERJ6RBD182	M. RESISTOR CH 1/10W 1.8K	2	
R305	ERJ3GEYG102	M. RESISTOR CH 1/16W 1K	1		R1016	ERJ3RBD153	M. RESISTOR CH 1/16W 15K	1	
R306	ERJ6GEYOR00	M. RESISTOR CH 1/10W 0	1		R1017	ERJ6GEYG102	M. RESISTOR CH 1/10W 1K	1	
R307	ERJ3GEYG472	M. RESISTOR CH 1/16W 4.7K	1		R1018	ERJ3GEYJ151	M. RESISTOR CH 1/16W 150	1	
R308	ERJ3GEYJ272	M. RESISTOR CH 1/16W 2.7K	1		R1019	ERJ6GEYG102	M. RESISTOR CH 1/10W 1K	1	
R310	ERJ3GEYG102	M. RESISTOR CH 1/16W 1K	1		R1020	ERJ3GEYJ151	M. RESISTOR CH 1/16W 150	1	
R312, 13	ERJ3GEYG102	M. RESISTOR CH 1/16W 1K	2		R1021	ERJ3GEYJ330	M. RESISTOR CH 1/16W 33	1	
R314	ERJ3GEYOR00	M. RESISTOR CH 1/16W 0	1		R1022	ERJ3GEYJ150	M. RESISTOR CH 1/16W 15	1	
R315	ERJ3GEYG152	M. RESISTOR CH 1/16W 1.5K	1		R1023	ERJ3GEYJ182	M. RESISTOR CH 1/16W 1.8K	1	
					R1024	ERJ3GEYJ470	M. RESISTOR CH 1/16W 47	1	

Ref.No.	Part No.	Part Name & Description	Pcs	Remarks	Ref.No.	Part No.	Part Name & Description	Pcs	Remarks
R1025	ERJ6EY6102	M. RESISTOR CH 1/10W 1K	1		R4025	ERJ3GEYJ334	M. RESISTOR CH 1/16W 330K	1	
R1035	ERJ3GEYJ470	M. RESISTOR CH 1/16W 47	1		R4026	ERJ3GEYJ684	M. RESISTOR CH 1/16W 680K	1	
R1038	ERJ3RED510	M. RESISTOR CH 1/16W 51	1		R4027, 28	ERJ3GEYJ103	M. RESISTOR CH 1/16W 10K	2	
R1039	ERJ3RBD391	M. RESISTOR CH 1/16W 390	1		R4029	ERJ3GEYJ562	M. RESISTOR CH 1/16W 5.6K	1	
R1040	ERJ3RBD121	M. RESISTOR CH 1/16W 120	1		R4030	ERJ3RBD223	M. RESISTOR CH 1/16W 22K	1	
R1051	ERJ3RBD273	M. RESISTOR CH 1/16W 27K	1		R4031	ERJ3RBD203	M. RESISTOR CH 1/16W 20K	1	
R1052	ERJ3RBD473	M. RESISTOR CH 1/16W 47K	1		R4032	ERJ3RBD181	M. RESISTOR CH 1/16W 180	1	
R1063	ERJ3GEYJ103	M. RESISTOR CH 1/16W 10K	1		R4033	ERJ3GEYJ334	M. RESISTOR CH 1/16W 330K	1	
R1065	ERJ3GEYJ122	M. RESISTOR CH 1/16W 1.2K	1		R4034	ERJ3GEYJ223	M. RESISTOR CH 1/16W 22K	1	
R1071	ERJ3GEY6102	M. RESISTOR CH 1/16W 1K	1		R4035	ERJ3GEYJ273	M. RESISTOR CH 1/16W 27K	1	
R1072	ERJ3GEYJ104	M. RESISTOR CH 1/16W 100K	1		R4036	ERJ3GEYJ222	M. RESISTOR CH 1/16W 2.2K	1	
R1073	ERJ3GEYJ101	M. RESISTOR CH 1/16W 100	1		R4037	ERJ3GEYJ123	M. RESISTOR CH 1/16W 12K	1	
R1080	ERJ8GEYOR00	M. RESISTOR CH 1/8W 0	1		R4038	ERJ3GEYJ680	M. RESISTOR CH 1/16W 68	1	
R1085, 86	ERJ3GEY6102	M. RESISTOR CH 1/16W 1K	2		R4039	ERJ3GEYJ224	M. RESISTOR CH 1/16W 220K	1	
R2001	ERJ3GEY6102	M. RESISTOR CH 1/16W 1K	1		R4040	ERJ3GEY6102	M. RESISTOR CH 1/16W 1K	1	
R2002	ERJ3GEYJ224	M. RESISTOR CH 1/16W 220K	1		R4041	ERJ3GEY6822	M. RESISTOR CH 1/16W 8.2K	1	
R2003	ERJ3GEYJ222	M. RESISTOR CH 1/16W 2.2K	1		R4042	ERJ3GEYJ183	M. RESISTOR CH 1/16W 18K	1	
R2004	ERJ3GEYJ154	M. RESISTOR CH 1/16W 150K	1		R4043-45	ERJ3GEYOR00	M. RESISTOR CH 1/16W 0	3	
R2005	ERJ3GEYJ392	M. RESISTOR CH 1/16W 3.9K	1		R4054	ERJ3GEY6102	M. RESISTOR CH 1/16W 1K	1	
R2006	ERJ3GEYJ474	M. RESISTOR CH 1/16W 470K	1		R4060	ERJ3GEYJ153	M. RESISTOR CH 1/16W 15K	1	
R2007	ERJ8GEYJR47	M. RESISTOR CH 1/8W 0.47	1		R4068	ERJ3GEYOR00	M. RESISTOR CH 1/16W 0	1	
R2008	ERJ8GEYJR33	M. RESISTOR CH 1/8W 0.33	1		R4069	ERJ3GEYJ222	M. RESISTOR CH 1/16W 2.2K	1	
R2009	ERJ3GEYJ561	M. RESISTOR CH 1/16W 560	1		R4070	ERJ3GEYJ432	M. RESISTOR CH 1/16W 4.3K	1	
R2010	ERJ3GEYJ103	M. RESISTOR CH 1/16W 10K	1		R4071	ERJ3GEYJ273	M. RESISTOR CH 1/16W 27K	1	
R2012	ERJ3GEYJ684	M. RESISTOR CH 1/16W 680K	1		R4072	ERJ3GEYJ333	M. RESISTOR CH 1/16W 33K	1	
R2015	ERJ3GEYJ473	M. RESISTOR CH 1/16W 47K	1		R4073	ERJ3GEYJ473	M. RESISTOR CH 1/16W 47K	1	
R2016	ERJ3GEYJ222	M. RESISTOR CH 1/16W 2.2K	1		R4074	ERJ3GEYJ122	M. RESISTOR CH 1/16W 1.2K	1	
R2017	ERJ3GEY6102	M. RESISTOR CH 1/16W 1K	1		R4075	ERJ3GEYJ563	M. RESISTOR CH 1/16W 56K	1	
R2018	ERJ3GEY6472	M. RESISTOR CH 1/16W 4.7K	1		R5001	ERJ3GEYJ100	M. RESISTOR CH 1/16W 10	1	
R2019, 20	ERJ3GEY6471	M. RESISTOR CH 1/16W 470	2		R5002, 03	ERJ3GEYJ680	M. RESISTOR CH 1/16W 68	2	
R2021	ERJ6EY6101	M. RESISTOR CH 1/10W 100	1		R5004	ERJ3GEY6332	M. RESISTOR CH 1/16W 3.3K	1	
R2022	ERJ8GEYJR33	M. RESISTOR CH 1/8W 0.33	1		R5005	ERJ2RHD113	M. RESISTOR CH 2W 11K	1	
R2024	ERJ3GEYJ101	M. RESISTOR CH 1/16W 100	1		R5007	ERJ3GEYJ561	M. RESISTOR CH 1/16W 560	1	
R2040-42	ERJ3GEYJ331	M. RESISTOR CH 1/16W 330	3		R5008	ERJ6EYJ4R7	M. RESISTOR CH 1/10W 4.7	1	
R3001	ERJ3GEYJ122	M. RESISTOR CH 1/16W 1.2K	1		R5009	ERJ3GEYJ274	M. RESISTOR CH 1/16W 270K	1	
R3002	ERJ3GEYOR00	M. RESISTOR CH 1/16W 0	1		R5052	ERJ3GEY6102	M. RESISTOR CH 1/16W 1K	1	
R3004	ERJ3GEYJ122	M. RESISTOR CH 1/16W 1.2K	1		R5500	ERJ3GEY6102	M. RESISTOR CH 1/16W 1K	1	
R3005	ERJ3GEYJ392	M. RESISTOR CH 1/16W 3.9K	1		R5501	ERJ3GEYJ563	M. RESISTOR CH 1/16W 56K	1	
R3006	ERJ2RHD682	M. RESISTOR CH 2W 6.8K	1		R5504	ERJ3GEYJ273	M. RESISTOR CH 1/16W 27K	1	
R3007	ERJ2RHD222	M. RESISTOR CH 2W 2.2K	1		R5505	ERJ3GEYJ222	M. RESISTOR CH 1/16W 2.2K	1	
R3008	ERJ3GEY6102	M. RESISTOR CH 1/16W 1K	1		R5508	ERJ3GEY6102	M. RESISTOR CH 1/16W 1K	1	
R3009	ERJ3GEYJ393	M. RESISTOR CH 1/16W 39K	1		R5509	ERJ3GEYJ222	M. RESISTOR CH 1/16W 2.2K	1	
R3010	ERJ3GEYJ333	M. RESISTOR CH 1/16W 33K	1		R5510	ERJ3GEY6102	M. RESISTOR CH 1/16W 1K	1	
R3013	ERJ3GEYOR00	M. RESISTOR CH 1/16W 0	1		R5513	ERJ3GEYJ225	M. RESISTOR CH 1/16W 2.2M	1	
R3017	ERJ3GEYOR00	M. RESISTOR CH 1/16W 0	1		R5514, 15	ERJ3GEY6102	M. RESISTOR CH 1/16W 1K	2	
R3018	ERJ3GEYJ225	M. RESISTOR CH 1/16W 2.2M	1		R5516, 17	ERJ3GEYOR00	M. RESISTOR CH 1/16W 0	2	
R3020	ERJ3GEYJ183	M. RESISTOR CH 1/16W 18K	1		R5520	ERJ3GEY6472	M. RESISTOR CH 1/16W 4.7K	1	
R3022	ERJ3GEYJ223	M. RESISTOR CH 1/16W 22K	1		R5521	ERJ3GEY6471	M. RESISTOR CH 1/16W 470	1	
R3023	ERJ3GEYJ273	M. RESISTOR CH 1/16W 27K	1		R6001	ERJ3GEYJ821	M. RESISTOR CH 1/16W 820	1	
R3025	ERJ3GEYJ123	M. RESISTOR CH 1/16W 12K	1		R6002	ERJ3GEYJ473	M. RESISTOR CH 1/16W 47K	1	
R3026	ERJ3GEYJ393	M. RESISTOR CH 1/16W 39K	1		R6003	ERJ3GEYJ274	M. RESISTOR CH 1/16W 270K	1	
R3031, 32	ERJ3GEY6102	M. RESISTOR CH 1/16W 1K	2		R6004	ERJ3GEYJ273	M. RESISTOR CH 1/16W 27K	1	
R3034	ERJ3GEY6102	M. RESISTOR CH 1/16W 1K	1		R6006	ERJ3GEYOR00	M. RESISTOR CH 1/16W 0	1	
R3057	ERJ3GEYJ103	M. RESISTOR CH 1/16W 10K	1		R6007	ERJ3GEYJ562	M. RESISTOR CH 1/16W 5.6K	1	
R3058	ERJ3GEYJ182	M. RESISTOR CH 1/16W 1.8K	1		R6008	ERJ3GEYJ223	M. RESISTOR CH 1/16W 22K	1	
R3059	ERJ3GEYJ821	M. RESISTOR CH 1/16W 820	1		R6009	ERJ3GEYJ473	M. RESISTOR CH 1/16W 47K	1	
R3060	ERJ2RKD620	M. RESISTOR CH 1/16W 62	1		R6010	ERJ3GEYJ104	M. RESISTOR CH 1/16W 100K	1	
R3063	ERJ3GEYOR00	M. RESISTOR CH 1/16W 0	1		R6011	ERJ3GEYOR00	M. RESISTOR CH 1/16W 0	1	
R4001	ERJ3GEYJ100	M. RESISTOR CH 1/16W 10	1		R6013	ERJ3GEYJ103	M. RESISTOR CH 1/16W 10K	1	
R4002	ERJ3GEYJ334	M. RESISTOR CH 1/16W 330K	1		R6014	ERJ3GEYJ105	M. RESISTOR CH 1/16W 1M	1	
R4003	ERJ3GEYJ331	M. RESISTOR CH 1/16W 330	1		R6015	ERJ3GEYJ103	M. RESISTOR CH 1/16W 10K	1	
R4004	ERJ3GEYJ222	M. RESISTOR CH 1/16W 2.2K	1		R6016	ERJ3GEY6472	M. RESISTOR CH 1/16W 4.7K	1	
R4005	ERJ3GEYJ684	M. RESISTOR CH 1/16W 680K	1		R6018	ERJ3GEYOR00	M. RESISTOR CH 1/16W 0	1	
R4006	ERJ3GEYJ473	M. RESISTOR CH 1/16W 47K	1		R6020	ERJ3GEYJ222	M. RESISTOR CH 1/16W 2.2K	1	
R4007	ERJ3GEYJ223	M. RESISTOR CH 1/16W 22K	1		R6021	ERJ8GEYJ120	M. RESISTOR CH 1/8W 12	1	
R4008	ERJ3GEYOR00	M. RESISTOR CH 1/16W 0	1		R6022	ERJ3GEYJ223	M. RESISTOR CH 1/16W 22K	1	
R4009	ERJ3GEYJ225	M. RESISTOR CH 1/16W 2.2M	1		R6023	ERJ3GEYJ222	M. RESISTOR CH 1/16W 2.2K	1	
R4010	ERJ3GEYJ271	M. RESISTOR CH 1/16W 270	1		R6024	ERJ3GEYJ474	M. RESISTOR CH 1/16W 470K	1	
R4011	ERJ3GEYJ223	M. RESISTOR CH 1/16W 22K	1		R6026	ERJ3GEYJ222	M. RESISTOR CH 1/16W 2.2K	1	
R4012	ERJ3GEY6472	M. RESISTOR CH 1/16W 4.7K	1		R6027	ERJ6EY6221	M. RESISTOR CH 1/10W 220	1	
R4013	ERJ3GEYJ680	M. RESISTOR CH 1/16W 68	1		R6028	ERJ3GEYJ222	M. RESISTOR CH 1/16W 2.2K	1	
R4014	ERJ3RBD123	M. RESISTOR CH 1/16W 12K	1		R6029	ERJ3GEY6102	M. RESISTOR CH 1/16W 1K	1	
R4015, 16	ERJ3GEY6472	M. RESISTOR CH 1/16W 4.7K	2		R6030	ERJ3GEYJ474	M. RESISTOR CH 1/16W 470K	1	
R4019	ERJ3GEYJ561	M. RESISTOR CH 1/16W 560	1		R6032	ERJ3GEY6472	M. RESISTOR CH 1/16W 4.7K	1	
R4023	ERJ3GEYJ163	M. RESISTOR CH 1/16W 16K	1		R6033	ERJ3GEYJ181	M. RESISTOR CH 1/16W 180	1	

Ref.No.	Part No.	Part Name & Description	Pcs	Remarks	Ref.No.	Part No.	Part Name & Description	Pcs	Remarks
R6034	ERJ3GEYG102	M. RESISTOR CH 1/16W 1K	1		X301	VXS0564	CRYSTAL OSCILLATOR	1	
R6035	ERJ3GEYJ103	M. RESISTOR CH 1/16W 10K	1		X701	EF0S1205E5	CERAMIC OSCILLATOR	1	
R6037, 38	ERJ3GEYJ104	M. RESISTOR CH 1/16W 100K	2		X5501	VXS0794	CRYSTAL OSCILLATOR	1	
R6039	ERJ8GEYJ2R2	M. RESISTOR CH 1/8W 2.2	1		X6001	VXS0654	CRYSTAL OSCILLATOR	1	
R6040	ERJ2RHD104	M. RESISTOR CH 2W 100K	1		X6002	VXS0601	CRYSTAL OSCILLATOR	1	
R6042	ERJ2RHD223	M. RESISTOR CH 2W 22K	1				MISCELLANEOUS		
R6043	ERJ3GEYOR00	M. RESISTOR CH 1/16W 0	1			VSC4419	POWER SHIELD COVER (TOP)	1	
R6044	ERJ2RHD153	M. RESISTOR CH 2W 15K	1			VSC4420	POWER SHIELD COVER (BOTT.)	1	
R6045	ERJ2RHD123	M. RESISTOR CH 2W 12K	1			VSC4622	CAMERA SHIELD COVER (BOTT)	1	
R6046	ERJ3GEYG472	M. RESISTOR CH 1/16W 4.7K	1			VMZ2278	SCREW BARRIER	1	
R6047	ERJ3GEYJ104	M. RESISTOR CH 1/16W 100K	1						
R6048	ERJ3GEYJ272	M. RESISTOR CH 1/16W 2.7K	1						
R6049	ERJ3GEYJ473	M. RESISTOR CH 1/16W 47K	1						
R6050, 51	ERJ3GEYJ222	M. RESISTOR CH 1/16W 2.2K	2			■ VEP23432A	CAMERA/MAIN C. B. A.		(RTL)
R6052-54	ERJ3GEYOR00	M. RESISTOR CH 1/16W 0	3						NV-RX19B
R6055	ERJ3GEYJ683	M. RESISTOR CH 1/16W 68K	1						NV-RX20EG/EN/ENH/EU
R6056	ERJ3GEYJ104	M. RESISTOR CH 1/16W 100K	1						
R6057, 58	ERJ3GEYJ474	M. RESISTOR CH 1/16W 470K	2		G201	ECSTOJY106Z	T. CAPACITOR CH 6.3V 10U	1	
R6059	ERJ3GEYG102	M. RESISTOR CH 1/16W 1K	1		G202	EGUX1C104ZFV	C. CAPACITOR CH 16V 0.1U	1	
R6061	ERJ3GEYJ103	M. RESISTOR CH 1/16W 10K	1		G203	ECSTOJY156Z	T. CAPACITOR CH 6.3V 15U	1	
R6062, 63	ERJ3GEYJ474	M. RESISTOR CH 1/16W 470K	2		G204	EGUX1C104ZFV	C. CAPACITOR CH 16V 0.1U	1	
R6064	ERJ3GEYG102	M. RESISTOR CH 1/16W 1K	1		G205	ECUM1C105ZFN	C. CAPACITOR CH 16V 1U	1	
R6065	ERJ3GEYJ333	M. RESISTOR CH 1/16W 33K	1		G206-12	EGUX1C104ZFV	C. CAPACITOR CH 16V 0.1U	7	
R6067	ERJ3GEYJ124	M. RESISTOR CH 1/16W 120K	1		G213	ECUX1H180JCV	C. CAPACITOR CH 50V 18P	1	
R6068	ERJ3GEYJ474	M. RESISTOR CH 1/16W 470K	1		G214	EGUX1C104ZFV	C. CAPACITOR CH 16V 0.1U	1	
R6069	ERJ3GEYJ334	M. RESISTOR CH 1/16W 330K	1		G216	ECUX1H101JCV	C. CAPACITOR CH 50V 100P	1	
R6080	ERJ3GEYJ473	M. RESISTOR CH 1/16W 47K	1		G218	ECSTOJY106Z	T. CAPACITOR CH 6.3V 10U	1	
R6082	ERJ3GEYJ103	M. RESISTOR CH 1/16W 10K	1		G219	ECUX1C104ZFV	C. CAPACITOR CH 16V 0.1U	1	
R6085	ERJ3GEYJ473	M. RESISTOR CH 1/16W 47K	1		G220	ECUX1H120JCV	C. CAPACITOR CH 50V 12P	1	
R6086	ERJ3GEYJ103	M. RESISTOR CH 1/16W 10K	1		G221	ECUM1C105ZFN	C. CAPACITOR CH 16V 1U	1	
R6087	ERJ3GEYJ683	M. RESISTOR CH 1/16W 68K	1		G222	ECSTOJY106Z	T. CAPACITOR CH 6.3V 10U	1	
R6089	ERJ3GEYJ122	M. RESISTOR CH 1/16W 1.2K	1		G223	EGUX1C104ZFV	C. CAPACITOR CH 16V 0.1U	1	
R6091	ERJ3GEYJ121	M. RESISTOR CH 1/16W 120	1		G224	ECSTOJY106Z	T. CAPACITOR CH 6.3V 10U	1	
R6095	ERJ3GEYJ151	M. RESISTOR CH 1/16W 150	1		G225	EGUX1C104ZFV	C. CAPACITOR CH 16V 0.1U	1	
R6201	ERJ3GEYJ473	M. RESISTOR CH 1/16W 47K	1		G226	ECST1CY475Z	T. CAPACITOR CH 16V 4.7U	1	
R6202	ERJ8GEYJ2R2	M. RESISTOR CH 1/8W 2.2	1		G227	EGUX1H330JCV	C. CAPACITOR CH 50V 33P	1	
R6203	ERJ3GEYJ101	M. RESISTOR CH 1/16W 100	1		G228	EGUX1C104ZFV	C. CAPACITOR CH 16V 0.1U	1	
R6204	ERJ3GEYJ103	M. RESISTOR CH 1/16W 10K	1		G229	ECST1GX155Z	T. CAPACITOR CH 4V 2.2U	1	
R6205	ERJ3GEYJ222	M. RESISTOR CH 1/16W 2.2K	1		G230	ECUM1H104ZFN	C. CAPACITOR CH 50V 0.1U	1	
R6206-08	ERJ3GEYJ104	M. RESISTOR CH 1/16W 100K	3		G231, 32	ECUM1C105ZFN	C. CAPACITOR CH 16V 1U	2	
R6209	ERJ3GEYJ222	M. RESISTOR CH 1/16W 2.2K	1		G235, 36	EGUX1C104ZFV	C. CAPACITOR CH 16V 0.1U	2	
R6210	ERJ3GEYJ224	M. RESISTOR CH 1/16W 220K	1		G238	EGUX1C104ZFV	C. CAPACITOR CH 16V 0.1U	1	
R6211	ERJ3GEYJ474	M. RESISTOR CH 1/16W 470K	1		G243	ECEVOJA101	E. CAPACITOR CH 6.3V 100U	1	
					G244	EGUX1H330JCV	C. CAPACITOR CH 50V 33P	1	
RA6001	EXBV8V102J	RESISTOR ARRAY	1		G301, 02	EGUX1H103KBV	C. CAPACITOR CH 50V 0.01U	2	
RA6002	EXBV8V473J	RESISTOR ARRAY	1		G304	ECUM1C224ZFN	C. CAPACITOR CH 16V 0.22U	1	
RA6003	EXBV4V102J	RESISTOR ARRAY	1		G306	EGUX1H120JCV	C. CAPACITOR CH 50V 12P	1	
RA6004, 05	EXBV8V102J	RESISTOR ARRAY	2		G307	EGUX1H080CCV	C. CAPACITOR CH 50V 8P	1	
RA6006	EXBV4V473J	RESISTOR ARRAY	1		G309	ECSTOJY106Z	T. CAPACITOR CH 6.3V 10U	1	
RA6008	EXBV4V104J	RESISTOR ARRAY	1		G310	EGUX1H102KBV	C. CAPACITOR CH 50V 1000P	1	
RA6009	EXBV4V102J	RESISTOR ARRAY	1		G311	ECST1AY225Z	T. CAPACITOR CH 10V 2.2U	1	
RA6010	EXBV4V473J	RESISTOR ARRAY	1		G312	EGUX1H103KBV	C. CAPACITOR CH 50V 0.01U	1	
RA6011	EXBV4V102J	RESISTOR ARRAY	1		G321	EGUX1H220JCV	C. CAPACITOR CH 50V 22P	1	
RA6013	EXBV8V102J	RESISTOR ARRAY	1		G322	EGUX1H103KBV	C. CAPACITOR CH 50V 0.01U	1	
RA6014	EXBV8V473J	RESISTOR ARRAY	1		G403	ECSTOJY106Z	T. CAPACITOR CH 6.3V 10U	1	
RA6015	EXBV8V683J	RESISTOR ARRAY	1		G405	EGUX1C104ZFV	C. CAPACITOR CH 16V 0.1U	1	
					G406	EGUX1H103KBV	C. CAPACITOR CH 50V 0.01U	1	
T1001	ELL04T061R	CHOKE COIL	1		G407, 08	EGUX1C104KBV	C. CAPACITOR CH 16V 0.1U	2	
T1002	YTP0357	CRYSTAL OSCILLATOR	1		G409	ECUM1C105KBM	C. CAPACITOR CH 16V 1U	1	
T4001	E106QB008	TRANSFORMER	1		G410	EGUX1H103KBV	C. CAPACITOR CH 50V 0.01U	1	
					G411	ECUM1C105KBM	C. CAPACITOR CH 16V 1U	1	
VC308	ECRJA020E11	TRIMMER	2P	1	G412	EGUX1H103KBV	C. CAPACITOR CH 50V 0.01U	1	
					G413	EGUX1H470JCV	C. CAPACITOR CH 50V 47P	1	
W201	ERJ3GEYOR00	M. RESISTOR CH 1/16W 0	1		G414	ECST1CY105Z	T. CAPACITOR CH 16V 1U	1	
W209	ERJ3GEYOR00	M. RESISTOR CH 1/16W 0	1		G415	ECUM1C105KBM	C. CAPACITOR CH 16V 1U	1	
W213, 14	ERJ3GEYOR00	M. RESISTOR CH 1/16W 0	2		G416	EGUX1C104ZFV	C. CAPACITOR CH 16V 0.1U	1	
W217	ERJ3GEYOR00	M. RESISTOR CH 1/16W 0	1		G417	ECSTOJY106Z	T. CAPACITOR CH 6.3V 10U	1	
W302	ERJ3GEYOR00	M. RESISTOR CH 1/16W 0	1		G418	EGUX1H220JCV	C. CAPACITOR CH 50V 22P	1	
W303	ERJ6GEYOR00	M. RESISTOR CH 1/10W 0	1		G701	EGUX1H332KBV	C. CAPACITOR CH 50V 3300P	1	
W305, 06	ERJ6GEYOR00	M. RESISTOR CH 1/10W 0	2		G703	EGUX1H103KBV	C. CAPACITOR CH 50V 0.01U	1	
W701	ERJ3GEYOR00	M. RESISTOR CH 1/16W 0	1		G704	ECSTOJY106Z	T. CAPACITOR CH 6.3V 10U	1	
W3004	ERJ3GEYOR00	M. RESISTOR CH 1/16W 0	1		G705	EGUX1C104ZFV	C. CAPACITOR CH 16V 0.1U	1	
W3007, 08	ERJ3GEYOR00	M. RESISTOR CH 1/16W 0	2		G706, 07	EGUX1C104KBV	C. CAPACITOR CH 16V 0.1U	2	
W6001	ERJ3GEYOR00	M. RESISTOR CH 1/16W 0	1		G708, 09	EGUX1H102KBV	C. CAPACITOR CH 50V 1000P	2	
					G711	ECEV1GA470	E. CAPACITOR CH 16V 47U	1	
					G712	EGUX1H102KBV	C. CAPACITOR CH 50V 1000P	1	

Ref.No.	Part No.	Part Name & Description	Pcs	Remarks
G713	ECUX1H332KBV	G. CAPACITOR CH 50V 3300P	1	
G714	EGST0JY106Z	T. CAPACITOR CH 6.3V 10U	1	
G715	ECUM1C105KBM	G. CAPACITOR CH 16V 1U	1	
G716	ECUM1H104ZFN	G. CAPACITOR CH 50V 0.1U	1	
G718	ECUX1C104KBV	G. CAPACITOR CH 16V 0.1U	1	
G719	ECUX1H102KBV	G. CAPACITOR CH 50V 1000P	1	
G720	ECUM1A105KBN	G. CAPACITOR CH 10V 1U	1	
G721	ECUX1H102KBV	G. CAPACITOR CH 50V 1000P	1	
G722	ECUM1H104ZFN	G. CAPACITOR CH 50V 0.1U	1	
G724	ECUX1C104KBV	G. CAPACITOR CH 16V 0.1U	1	
G726, 27	ECUX1C104KBV	G. CAPACITOR CH 16V 0.1U	2	
G1002	ECUM1A225KBM	G. CAPACITOR CH 10V 2.2U	1	
G1003	ECUM1A335KBM	G. CAPACITOR CH 10V 3.3U	1	
G1004	ECUX1H331JCV	G. CAPACITOR CH 50V 330P	1	
G1005	ECUM1C105KBM	G. CAPACITOR CH 16V 1U	1	
G1008	ECUM1A335KBM	G. CAPACITOR CH 10V 3.3U	1	
G1009	ECUX1H331JCV	G. CAPACITOR CH 50V 330P	1	
G1010	ECUM1C105KBM	G. CAPACITOR CH 16V 1U	1	
G1012	ECUX1H102KBV	G. CAPACITOR CH 50V 1000P	1	
G1014	ECUX1H561JCV	G. CAPACITOR CH 50V 560P	1	
G1017	ECUM1E105KB	G. CAPACITOR CH 25V 1U	1	
G1019	ECUM1E334KBM	G. CAPACITOR CH 25V 0.33U	1	
G1020	ECUM1C105ZFN	G. CAPACITOR CH 16V 1U	1	
G1022	ECUM1H104ZFN	G. CAPACITOR CH 50V 0.1U	1	
G1024	ECUM1A105KBN	G. CAPACITOR CH 10V 1U	1	
G1025	ECUX1C104KBV	G. CAPACITOR CH 16V 0.1U	1	
G1026	ECEV1HA010	E. CAPACITOR CH 50V 1U	1	
G1027	ECUX1H101JCV	G. CAPACITOR CH 50V 100P	1	
G1028	ECEV1HAR47	E. CAPACITOR CH 50V 0.47U	1	
G1029	ECUX1H471JCV	G. CAPACITOR CH 50V 470P	1	
G1030	ECUX1H822KBV	G. CAPACITOR CH 50V 8200P	1	
G1031	ECUX1H471JCV	G. CAPACITOR CH 50V 470P	1	
G1032	ECUX1H822KBV	G. CAPACITOR CH 50V 8200P	1	
G1033-35	ECUX1H102KBV	G. CAPACITOR CH 50V 1000P	3	
G1036	ECUX1H471JCV	G. CAPACITOR CH 50V 470P	1	
G1037	ECUX1H822KBV	G. CAPACITOR CH 50V 8200P	1	
G1040, 41	ECUX1H103KBV	G. CAPACITOR CH 50V 0.01U	2	
G1051	ECUM1C334KBN	G. CAPACITOR CH 16V 0.33U	1	
G1055	ECUM1C105KBM	G. CAPACITOR CH 16V 1U	1	
G1057	ECUM1C105KBM	G. CAPACITOR CH 16V 1U	1	
G1064	ECUM1C105KBM	G. CAPACITOR CH 16V 1U	1	
G1066	ECUM1C105ZFN	G. CAPACITOR CH 16V 1U	1	
G1071	ECUM1C105KBM	G. CAPACITOR CH 16V 1U	1	
G1073	ECUX1H103KBV	G. CAPACITOR CH 50V 0.01U	1	
G1080, 81	ECUX1C473KBV	G. CAPACITOR CH 16V 0.047U	2	
G1112	ECUM1A225KBM	G. CAPACITOR CH 10V 2.2U	1	
G2001, 02	ECEV1HA010	E. CAPACITOR CH 50V 1U	2	
G2003	ECUX1H332KBV	G. CAPACITOR CH 50V 3300P	1	
G2004	ECUX1H101JCV	G. CAPACITOR CH 50V 100P	1	
G2005	ECUX1H152KBV	G. CAPACITOR CH 50V 1500P	1	
G2007	ECEV1HA010	E. CAPACITOR CH 50V 1U	1	
G2009	ECUX1C104KBV	G. CAPACITOR CH 16V 0.1U	1	
G2010	ECUX1C104ZFN	G. CAPACITOR CH 16V 0.1U	1	
G2011	ECUX1H101JCV	G. CAPACITOR CH 50V 100P	1	
G2012, 13	ECUX1H103KBV	G. CAPACITOR CH 50V 0.01U	2	
G2014	ECEV1CA100	E. CAPACITOR CH 16V 10U	1	
G2015-17	ECUX1C104KBV	G. CAPACITOR CH 16V 0.1U	3	
G2018	ECEV0JA220	E. CAPACITOR CH 6.3V 22U	1	
G2020-22	ECUX1H103KBV	G. CAPACITOR CH 50V 0.01U	3	
G2023	ECUM1C105KBM	G. CAPACITOR CH 16V 1U	1	
G2025-27	ECUX1C104ZFN	G. CAPACITOR CH 16V 0.1U	3	
G2028	ECEV0JA220	E. CAPACITOR CH 6.3V 22U	1	
G2029	ECUX1H103ZFN	G. CAPACITOR CH 50V 0.01U	1	
G2033	ECUM1C105ZFN	G. CAPACITOR CH 16V 1U	1	
G2040-42	ECUX1C473KBV	G. CAPACITOR CH 16V 0.047U	3	
G2043	ECUX1C104ZFN	G. CAPACITOR CH 16V 0.1U	1	
G2070	ECUX1H103KBV	G. CAPACITOR CH 50V 0.01U	1	
G3001	ECUX1H680JCV	G. CAPACITOR CH 50V 68P	1	
G3004	ECUX1C104KBV	G. CAPACITOR CH 16V 0.1U	1	
G3005	ECEV05A470	E. CAPACITOR CH 4V 47U	1	
G3006	ECUX1H103KBV	G. CAPACITOR CH 50V 0.01U	1	
G3008	ECUX1C104KBV	G. CAPACITOR CH 16V 0.1U	1	
G3009, 10	ECUX1H103KBV	G. CAPACITOR CH 50V 0.01U	2	
G3016	ECUX1H151JCV	G. CAPACITOR CH 50V 150P	1	
G3017	ECUX1C104KBV	G. CAPACITOR CH 16V 0.1U	1	

Ref.No.	Part No.	Part Name & Description	Pcs	Remarks
G3018	ECUX1H330JCV	G. CAPACITOR CH 50V 33P	1	
G3019, 20	ECUX1C104KBV	G. CAPACITOR CH 16V 0.1U	2	
G3022	ECUX1C104KBV	G. CAPACITOR CH 16V 0.1U	1	
G3023	ECUM1C105KBM	G. CAPACITOR CH 16V 1U	1	
G3024	ECUX1C104KBV	G. CAPACITOR CH 16V 0.1U	1	
G3026	ECUX1C104KBV	G. CAPACITOR CH 16V 0.1U	1	
G3027	ECUM1A225KBM	G. CAPACITOR CH 10V 2.2U	1	
G3028	ECEV06A471	E. CAPACITOR CH 4V 470U	1	
G3029	ECEV1AAN100	E. CAPACITOR CH 10V 10U	1	
G3030	ECUM1C105KBM	G. CAPACITOR CH 16V 1U	1	
G3031	ECUX1C104KBV	G. CAPACITOR CH 16V 0.1U	1	
G3032	ECEV05A470	E. CAPACITOR CH 4V 47U	1	
G3033	ECUX1H103KBV	G. CAPACITOR CH 50V 0.01U	1	
G3035	EGST0JY106Z	T. CAPACITOR CH 6.3V 10U	1	
G4001	ECYX1H821JCV	G. CAPACITOR CH 50V 820P	1	
G4002	ECUM1C105ZFN	G. CAPACITOR CH 16V 1U	1	
G4003	ECUX1H822KBV	G. CAPACITOR CH 50V 8200P	1	
G4008	ECUM1C105ZFN	G. CAPACITOR CH 16V 1U	1	
G4011	ECEV05A470	E. CAPACITOR CH 4V 47U	1	
G4012	EGST0JX226Z	T. CAPACITOR CH 6.3V 22U	1	
G4014	ECUX1C223KBV	G. CAPACITOR CH 16V 0.022U	1	
G4015	ECUX1H682KBV	G. CAPACITOR CH 50V 6800P	1	
G4016	ECUM2A472JCM	G. CAPACITOR CH 100V 4700P	1	
G4017	ECUX1H102KBV	G. CAPACITOR CH 50V 1000P	1	
G4019, 20	ECUM1C474KBN	G. CAPACITOR CH 16V 0.47U	2	
G4021, 22	ECUX1H103KBV	G. CAPACITOR CH 50V 0.01U	2	
G4023	ECUX1H272KBV	G. CAPACITOR CH 50V 2700P	1	
G4024	EGST1CY475Z	T. CAPACITOR CH 16V 4.7U	1	
G4025	EGST0JY685Z	T. CAPACITOR CH 6.3V 6.8U	1	
G4026	ECUX1H103KBV	G. CAPACITOR CH 50V 0.01U	1	
G4027	EGST1AY225Z	T. CAPACITOR CH 10V 2.2U	1	
G4028	ECUX1H102KBV	G. CAPACITOR CH 50V 1000P	1	
G4029	ECUX1H222KBV	G. CAPACITOR CH 50V 2200P	1	
G4030	ECUX1H562KBV	G. CAPACITOR CH 50V 5600P	1	
G4031	ECUX1H102KBV	G. CAPACITOR CH 50V 1000P	1	
G4032	ECUM1C105KBM	G. CAPACITOR CH 16V 1U	1	
G4033, 34	ECUM1C105ZFN	G. CAPACITOR CH 16V 1U	2	
G4035	ECUM1C105KBM	G. CAPACITOR CH 16V 1U	1	
G4036	EGST0JY335Z	T. CAPACITOR CH 6.3V 3.3U	1	
G4040	ECUM1C105ZFN	G. CAPACITOR CH 16V 1U	1	
G4045-47	ECUM1C105ZFN	G. CAPACITOR CH 16V 1U	3	
G4048	ECUX1H103KBV	G. CAPACITOR CH 50V 0.01U	1	
G4049	EGST0JY106Z	T. CAPACITOR CH 6.3V 10U	1	
G4050	ECEV05A470	E. CAPACITOR CH 4V 47U	1	
G4051	ECUX1H270JCV	G. CAPACITOR CH 50V 27P	1	
G5001-04	ECUX1H103ZFN	G. CAPACITOR CH 50V 0.01U	4	
G5005-08	ECUX1H270JCV	G. CAPACITOR CH 50V 27P	4	
G5009, 10	ECUX1H103ZFN	G. CAPACITOR CH 50V 0.01U	2	
G5011	ECUM1E473KBN	G. CAPACITOR CH 25V 0.047U	1	
G5012, 13	ECUX1H103KBV	G. CAPACITOR CH 50V 0.01U	2	
G5014	EGST0JY106Z	T. CAPACITOR CH 6.3V 10U	1	
G5016	EGST0JY106Z	T. CAPACITOR CH 6.3V 10U	1	
G5017	ECUX1H103ZFN	G. CAPACITOR CH 50V 0.01U	1	
G5018	EGST0JY106Z	T. CAPACITOR CH 6.3V 10U	1	
G5019	ECUM1C105ZFN	G. CAPACITOR CH 16V 1U	1	
G5020, 21	ECUX1H103ZFN	G. CAPACITOR CH 50V 0.01U	2	
G5022	ECUM1C104KBN	G. CAPACITOR CH 16V 0.1U	1	
G5023	ECUX1H103ZFN	G. CAPACITOR CH 50V 0.01U	1	
G5024, 25	ECUX1H103KBV	G. CAPACITOR CH 50V 0.01U	2	
G5041	ECUX1H101JCV	G. CAPACITOR CH 50V 100P	1	
G5501, 02	ECUX1H103KBV	G. CAPACITOR CH 50V 0.01U	2	
G5503	ECUX1C473KBV	G. CAPACITOR CH 16V 0.047U	1	
G5504-06	ECUX1H103KBV	G. CAPACITOR CH 50V 0.01U	3	
G5507	ECEV05A470	E. CAPACITOR CH 4V 47U	1	
G5508	ECUX1H103KBV	G. CAPACITOR CH 50V 0.01U	1	
G5509	ECEV05A470	E. CAPACITOR CH 4V 47U	1	
G5510	ECUM1C105KBM	G. CAPACITOR CH 16V 1U	1	
G5511	ECUX1C104KBV	G. CAPACITOR CH 16V 0.1U	1	
G5512	EGST06Y226Z	T. CAPACITOR CH 4V 22U	1	
G5513	ECUX1C473KBV	G. CAPACITOR CH 16V 0.047U	1	
G5514	ECUM1C105KBM	G. CAPACITOR CH 16V 1U	1	
G5515	ECUX1H181JCV	G. CAPACITOR CH 50V 180P	1	
G5516	ECUX1H390JCV	G. CAPACITOR CH 50V 39P	1	
G5517	ECUM1C474KBN	G. CAPACITOR CH 16V 0.47U	1	
G5518	ECUX1H103KBV	G. CAPACITOR CH 50V 0.01U	1	

Ref.No.	Part No.	Part Name & Description	Pcs	Remarks	Ref.No.	Part No.	Part Name & Description	Pcs	Remarks
C5519	ECUX1G104KBV	C. CAPACITOR CH 16V 0.1U	1		FP4002	VJS3320B026	CONNECTOR (FEMALE) 26P	1	
C5520	ECUM1H333KBN	C. CAPACITOR CH 50V 0.033U	1		FP5001	VJS2959B013	CONNECTOR (FEMALE) 13P	1	
C5523	ECUX1H180JCV	C. CAPACITOR CH 50V 18P	1		FP6001	VJS2959D018	CONNECTOR (FEMALE) 18P	1	
C5524	ECUX1H150JCV	C. CAPACITOR CH 50V 15P	1		FP6002	VJS2959B006	CONNECTOR (FEMALE) 6P	1	
C5526	ECUX1H040GCV	C. CAPACITOR CH 50V 4P	1		FP6006	VJS3319B021	CONNECTOR (FEMALE) 21P	1	
C5527	ECUX1G104KBV	C. CAPACITOR CH 16V 0.1U	1		IC201	MN5224	IC	1	
C5530	ECUX1H331JCV	C. CAPACITOR CH 50V 330P	1		IC202	MN31121SA	IC	1	
C5531	ECUX1H103KBV	C. CAPACITOR CH 50V 0.01U	1		IC203	NN2035FAQ	IC	1	
C5533	EGUX1C273KBV	C. CAPACITOR CH 16V 0.027U	1		IC205	AN1358S	IC	1	
C6001-03	ECUX1G104ZV	C. CAPACITOR CH 16V 0.1U	3		IC301	F436002APZ	IC	1	
C6004	ECUX1G104KBV	C. CAPACITOR CH 16V 0.1U	1		IC302	M62367GP	IC	1	
C6005	ECUX1H103KBV	C. CAPACITOR CH 50V 0.01U	1		IC701, 02	TB6526F	IC	2	
C6006	ECUX1H080GCV	C. CAPACITOR CH 50V 8P	1		IC706	NJM2115VA	IC	1	
C6007	ECUX1H150JCV	C. CAPACITOR CH 50V 15P	1		IC710	MN1882421M9S	IC	1	
C6008, 09	ECUX1G104ZV	C. CAPACITOR CH 16V 0.1U	2		IC711	TA75W01FU	IC	1	
C6011	ECUX1G104ZV	C. CAPACITOR CH 16V 0.1U	1		IC1001	BA9706K	IC	1	
C6012	ECUX1H070DCV	C. CAPACITOR CH 50V 7P	1		IC2001	TB6518F	IC	1	
C6013	ECUX1H100GCV	C. CAPACITOR CH 50V 10P	1		IC2002, 03	MDC05TR	IC	2	
C6014, 15	ECUX1G104ZV	C. CAPACITOR CH 16V 0.1U	2		IC3001	HA118403F	IC	1	
C6017	ECUX1G104ZV	C. CAPACITOR CH 16V 0.1U	1		IC4001	UPC4572G2	IC	1	
C6020	ECUX1G104ZV	C. CAPACITOR CH 16V 0.1U	1		IC5001	AN3355FHP	IC	1	
C6025	ECUX1G104ZV	C. CAPACITOR CH 16V 0.1U	1		IC5501	MSM7470-73MS	IC	1	
C6027	ECEVOGA101	E. CAPACITOR CH 4V 100U	1		IC6001	MN675556M9R	IC	1	
C6029	ECUM1G105KBM	C. CAPACITOR CH 16V 1U	1		IC6002	MM1355XFFE	IC	1	
C6030	ECUM1A105KBN	C. CAPACITOR CH 10V 1U	1		IC6003	UPD6462GS618	IC	1	
C6031	ECUX1G104ZV	C. CAPACITOR CH 16V 0.1U	1		IC6004	AK6440HF	IC	1	
C6032	ECUX1G104KBV	C. CAPACITOR CH 16V 0.1U	1		IC6005	BA6289F	IC	1	
C6033, 34	ECUX1H101JCV	C. CAPACITOR CH 50V 100P	2		IC6006	TA75W393FU	IC	1	
C6035	ECUX1H102KBV	C. CAPACITOR CH 50V 1000P	1		IC6008	TC7W04F	IC	1	
C6036	ECUX1H103KBV	C. CAPACITOR CH 50V 0.01U	1		IC6009	TC7S08F	IC	1	
C6038	ECUX1H103KBV	C. CAPACITOR CH 50V 0.01U	1		IC6011	UPD7564G557	IC	1	
C6039	ECUM1A105KBN	C. CAPACITOR CH 10V 1U	1		IC6012	TC4W53F	IC	1	
C6040	ECUX1G104KBV	C. CAPACITOR CH 16V 0.1U	1		L201	ELJFA330JB	G01L 33UH	1	
C6042	ECUX1H103KBV	C. CAPACITOR CH 50V 0.01U	1		L202	VLQ0426J680	G01L 68UH	1	
C6046-48	ECUX1H103KBV	C. CAPACITOR CH 50V 0.01U	3		L203	VLQ0426J820	G01L 82UH	1	
C6049, 50	ECEV1GA100	E. CAPACITOR CH 16V 10U	2		L204	ELJFA220JB	G01L 22UH	1	
C6051	ECUX1C223KBV	C. CAPACITOR CH 16V 0.022U	1		L205	VLQ0426J8R2	G01L 8.2UH	1	
C6052	ECUX1H561JCV	C. CAPACITOR CH 50V 560P	1		L206	ELJFA220JB	G01L 22UH	1	
C6060	ECUM1A105KBN	C. CAPACITOR CH 10V 1U	1		L208	ELJFA220JB	G01L 22UH	1	
C6061	ECUX1G104KBV	C. CAPACITOR CH 16V 0.1U	1		L212	VLQ0426J270	G01L 27UH	1	
C6100	ECSTOJY106Z	T. CAPACITOR CH 6.3V 10U	1		L402	VLQ0319K220	G01L 22UH	1	
C6201, 02	ECUX1G104KBV	C. CAPACITOR CH 16V 0.1U	2		L403	VLQ0426J470	G01L 47UH	1	
C6203	ECSTOJY106Z	T. CAPACITOR CH 6.3V 10U	1		L404	VLQ0319K220	G01L 22UH	1	
C6204	ECUM1G105KBM	C. CAPACITOR CH 16V 1U	1		L701, 02	VLQ0319K220	G01L 22UH	2	
C6205	ECUX1G104ZV	C. CAPACITOR CH 16V 0.1U	1		L703	VLQ0319F150	G01L 15UH	1	
C6206	ECEVOGA101	E. CAPACITOR CH 4V 100U	1		L704, 05	VLQ0319K220	G01L 22UH	2	
C6207	ECUX1H103KBV	C. CAPACITOR CH 50V 0.01U	1		L708	VLQ0319K220	G01L 22UH	1	
C6208	ECUX1G104KBV	C. CAPACITOR CH 16V 0.1U	1		L1001	VLQ0759	G01L	1	
C6209	ECSTOJX226Z	T. CAPACITOR CH 6.3V 22U	1		L1002	VLQ0760	G01L	1	
C6210	ECUM1G105KBM	C. CAPACITOR CH 16V 1U	1		L1003	VLQ0763	G01L	1	
D202	1SS355	DIODE	1		L1004	VLQ0319K100	G01L 10UH	1	
D203	RB751V40	DIODE	1		L1006	VLQ0319F150	G01L 15UH	1	
D204	1SS355	DIODE	1		L1007	VLQ0761	G01L	1	
D481, 82	RB751V40	DIODE	2		L1008	VLQ0319M4R7	G01L 4.7UH	1	
D1002	EC20QSO6	DIODE	1		L1010	VLQ0319K100	G01L 10UH	1	
D1006, 07	MA111	DIODE	2		L1011	VLQ0319K101	G01L 100UH	1	
D1015	EC15QSO4	DIODE	1		L1014	VLQ0319K100	G01L 10UH	1	
D3004	1SS355	DIODE	1		L1015	VLQ0319K470	G01L 47UH	1	
D4004	1SS355	DIODE	1		L1062	VLQ0762	G01L	1	
D6001, 02	MA132WA	DIODE	2		L3002	VLQ0319K100	G01L 10UH	1	
D6003	1SS355	DIODE	1		L3003	VLQ0163J820	G01L 82UH	1	
D6006	RB751V40	DIODE	1		L3021	VLQ0319K470	G01L 47UH	1	
D6007	MA132WK	DIODE	1		L4005	VLQ0319K101	G01L 100UH	1	
D6008	1SS355	DIODE	1		L5001-04	VLQ0319K470	G01L 47UH	4	
D6009	MA133	DIODE	1		L5501	VLQ0319K100	G01L 10UH	1	
D6010	1SS355	DIODE	1		L5502	ELJFA100JB	G01L 10UH	1	
D6016	MA133	DIODE	1		L5503	VLQ0426J120	G01L 12UH	1	
D6201	1SS355	DIODE	1		L5504	ELJFA390JB	G01L 39UH	1	
FP302	VJS3654B011	CONNECTOR (FEMALE) 11P	1		L5505	ELJFA150JB	G01L 15UH	1	
FP701	VJS3319B018	CONNECTOR (FEMALE) 18P	1		L5506	VLQ0319K470	G01L 47UH	1	
FP2001	VJS3654D007	CONNECTOR (FEMALE) 7P	1		L5508	VLQ0163J471	G01L 470UH	1	
FP2002	VJS2958B018	CONNECTOR (FEMALE) 18P	1		L6002	VLQ0319K101	G01L 100UH	1	
FP4001	VJS2958D009	CONNECTOR (FEMALE) 9P	1						

Ref.No.	Part No.	Part Name & Description	Pcs	Remarks
LB209, 10	ERJ3GEYJ330	M. RESISTOR CH 1/16W	33	2
LB211	VLP0154	COIL	1	
LB213	VLP0146	COIL	1	
LB301	VLP0323A102	COIL	1	
LB307	VLP0323A102	COIL	1	
LB308	VLP0140	COIL	1	
LB309	VLP0304	COIL	1	
LB6001	VLP0323A102	COIL	1	
PP201	VJP3358C012	CONNECTOR (MALE)	12P	1
PP401	VJP2962C024	CONNECTOR (MALE)	24P	1
PP3001	VJP3358C016	CONNECTOR (MALE)	16P	1
PS1001	VJS2961C024	CONNECTOR (FEMALE)	24P	1
Q201	2SD2216	TRANSISTOR	1	
Q203	XP4601	TRANSISTOR-TRANSISTOR	1	
Q205	XP4601	TRANSISTOR-TRANSISTOR	1	
Q206	2SD1030	TRANSISTOR	1	
Q404	XP4501	TRANSISTOR-TRANSISTOR	1	
Q405	2SD2216	TRANSISTOR	1	
Q701-03	XN4404	TRANSISTOR	3	
Q704	2SD601A	TRANSISTOR	1	
Q705	2SD2216	TRANSISTOR	1	
Q706	XN4404	TRANSISTOR	1	
Q1001	2SA1731-R	TRANSISTOR	1	
Q1003	MPL1	TRANSISTOR	1	
Q1004	2SD2210	TRANSISTOR	1	
Q1062	MPL1	TRANSISTOR	1	
Q3001	XP4501	TRANSISTOR-TRANSISTOR	1	
Q3002	XP4401	TRANSISTOR	1	
Q3010, 11	2SD2216	TRANSISTOR	2	
Q4002	2SD602-R	TRANSISTOR	1	
Q4003	2SB1219	TRANSISTOR	1	
Q4004	XP4501	TRANSISTOR-TRANSISTOR	1	
Q4006	2SD2216	TRANSISTOR	1	
Q4007	XP4501	TRANSISTOR-TRANSISTOR	1	
Q4009	2SD2216	TRANSISTOR	1	
Q4012	2SD2216	TRANSISTOR	1	
Q4014	2SB1462	TRANSISTOR	1	
Q4015, 16	2SD2216	TRANSISTOR	2	
Q4017, 18	2SD1328-S	TRANSISTOR	2	
Q4019	2SD2216	TRANSISTOR	1	
Q5001, 02	XN4504	TRANSISTOR	2	
Q5003	2SA812	TRANSISTOR	1	
Q5502	2SD2216	TRANSISTOR	1	
Q6002, 03	2SD2216	TRANSISTOR	2	
Q6005	2SD2216	TRANSISTOR	1	
Q6006	2SB1462	TRANSISTOR	1	
Q6007, 08	2SD2216	TRANSISTOR	2	
Q6201	2SB1462	TRANSISTOR	1	
QR401	MRN1103	TRANSISTOR-RESISTOR	1	
QR402	MRN1102	TRANSISTOR-RESISTOR	1	
QR701	MRN1102	TRANSISTOR-RESISTOR	1	
QR1001	MRN2102	TRANSISTOR-RESISTOR	1	
QR1061	MRN2111	TRANSISTOR-RESISTOR	1	
QR2002	MRN1111	TRANSISTOR-RESISTOR	1	
QR3001	MRN1104	TRANSISTOR-RESISTOR	1	
QR4003	MRN2103	TRANSISTOR-RESISTOR	1	
QR4004	XP1215	TRANSISTOR-RESISTOR	1	
QR4005	MRN1104	TRANSISTOR-RESISTOR	1	
QR4008	MRN1104	TRANSISTOR-RESISTOR	1	
QR5502	UN2130X	TRANSISTOR-RESISTOR	1	
QR5503	MRN1103	TRANSISTOR-RESISTOR	1	
QR5504	MRN1104	TRANSISTOR-RESISTOR	1	
QR6001	MRN2111	TRANSISTOR-RESISTOR	1	
QR6003	MRN2103	TRANSISTOR-RESISTOR	1	
QR6004	XP4115	TRANSISTOR-RESISTOR	1	
QR6006	MRN1104	TRANSISTOR-RESISTOR	1	
QR6007	MRN1102	TRANSISTOR-RESISTOR	1	
QR6008	MRN1104	TRANSISTOR-RESISTOR	1	
QR6012	MRN1104	TRANSISTOR-RESISTOR	1	
QR6014	UN9210	TRANSISTOR-RESISTOR	1	
QR6015	MRN1111	TRANSISTOR-RESISTOR	1	

Ref.No.	Part No.	Part Name & Description	Pcs	Remarks
QR6050	XP1211	TRANSISTOR-RESISTOR	1	
R202	ERJ3GEYJ182	M. RESISTOR CH 1/16W 1.8K	1	
R203	ERJ3GEYJ105	M. RESISTOR CH 1/16W 1M	1	
R204	ERJ3GEYJ391	M. RESISTOR CH 1/16W 390	1	
R205	ERJ3GEYOR00	M. RESISTOR CH 1/16W 0	1	
R206	ERJ3GEY6472	M. RESISTOR CH 1/16W 4.7K	1	
R207, 08	ERJ3GEY6102	M. RESISTOR CH 1/16W 1K	2	
R209	ERJ3GEY6152	M. RESISTOR CH 1/16W 1.5K	1	
R210	ERJ3GEYJ391	M. RESISTOR CH 1/16W 390	1	
R211	ERJ3GEY822	M. RESISTOR CH 1/16W 8.2K	1	
R212	ERJ3GEYJ335	M. RESISTOR CH 1/16W 3.3M	1	
R213	ERJ3GEYJ563	M. RESISTOR CH 1/16W 56K	1	
R214	ERJ3GEY6472	M. RESISTOR CH 1/16W 4.7K	1	
R215	ERJ2RHD753	M. RESISTOR CH 2W 75K	1	
R216	ERJ2RHD153	M. RESISTOR CH 2W 15K	1	
R217	ERJ3GEYJ113	M. RESISTOR CH 1/16W 11K	1	
R218	ERJ3GEY6183	M. RESISTOR CH 1/16W 18K	1	
R219	ERJ3GEYJ221	M. RESISTOR CH 1/16W 220	1	
R220	ERJ3GEY6472	M. RESISTOR CH 1/16W 4.7K	1	
R221	ERJ3GEYJ105	M. RESISTOR CH 1/16W 1M	1	
R224	ERJ3GEY6222	M. RESISTOR CH 1/16W 2.2K	1	
R225	ERJ3GEY6102	M. RESISTOR CH 1/16W 1K	1	
R226, 27	ERJ3GEYJ105	M. RESISTOR CH 1/16W 1M	2	
R228	ERJ3GEYJ683	M. RESISTOR CH 1/16W 68K	1	
R229	ERJ3GEYJ123	M. RESISTOR CH 1/16W 12K	1	
R233	ERJ6GEYOR00	M. RESISTOR CH 1/10W 0	1	
R234	ERJ3GEY6131	M. RESISTOR CH 1/16W 130	1	
R235	ERJ3GEYJ561	M. RESISTOR CH 1/16W 560	1	
R236	ERJ3GEYOR00	M. RESISTOR CH 1/16W 0	1	
R239	ERJ3GEY6471	M. RESISTOR CH 1/16W 470	1	
R240, 41	ERJ3GEYJ221	M. RESISTOR CH 1/16W 220	2	
R242	ERJ3GEY6152	M. RESISTOR CH 1/16W 1.5K	1	
R243	ERJ3GEYJ182	M. RESISTOR CH 1/16W 1.8K	1	
R244	ERJ3GEYJ222	M. RESISTOR CH 1/16W 2.2K	1	
R245	ERJ3GEYJ561	M. RESISTOR CH 1/16W 560	1	
R246	ERJ3GEYJ473	M. RESISTOR CH 1/16W 47K	1	
R249	ERJ3GEYJ104	M. RESISTOR CH 1/16W 100K	1	
R250	ERJ3RBD123	M. RESISTOR CH 1/16W 12K	1	
R251	ERJ3RBD223	M. RESISTOR CH 1/16W 22K	1	
R301	ERJ3GEYJ563	M. RESISTOR CH 1/16W 56K	1	
R302	ERJ3GEYJ683	M. RESISTOR CH 1/16W 68K	1	
R303	ERJ3GEYJ223	M. RESISTOR CH 1/16W 22K	1	
R304	ERJ3GEYJ105	M. RESISTOR CH 1/16W 1M	1	
R305	ERJ3GEY6102	M. RESISTOR CH 1/16W 1K	1	
R306	ERJ6GEYOR00	M. RESISTOR CH 1/10W 0	1	
R307	ERJ3GEY6472	M. RESISTOR CH 1/16W 4.7K	1	
R308	ERJ3GEYJ272	M. RESISTOR CH 1/16W 2.7K	1	
R310	ERJ3GEY6102	M. RESISTOR CH 1/16W 1K	1	
R312, 13	ERJ3GEY6102	M. RESISTOR CH 1/16W 1K	2	
R314	ERJ3GEYOR00	M. RESISTOR CH 1/16W 0	1	
R315	ERJ3GEY6152	M. RESISTOR CH 1/16W 1.5K	1	
R318	ERJ6GEYOR00	M. RESISTOR CH 1/10W 0	1	
R320	ERJ3GEYOR00	M. RESISTOR CH 1/16W 0	1	
R321	ERJ3GEYJ182	M. RESISTOR CH 1/16W 1.8K	1	
R323	ERJ3GEYOR00	M. RESISTOR CH 1/16W 0	1	
R325	ERJ3GEYOR00	M. RESISTOR CH 1/16W 0	1	
R327	ERJ3GEYJ821	M. RESISTOR CH 1/16W 820	1	
R333	ERJ3GEYOR00	M. RESISTOR CH 1/16W 0	1	
R336	ERJ3GEYJ182	M. RESISTOR CH 1/16W 1.8K	1	
R337	ERJ3GEYOR00	M. RESISTOR CH 1/16W 0	1	
R406	ERJ3GEYOR00	M. RESISTOR CH 1/16W 0	1	
R409	ERJ3GEYOR00	M. RESISTOR CH 1/16W 0	1	
R411	ERJ3GEY6472	M. RESISTOR CH 1/16W 4.7K	1	
R412	ERJ3GEYJ272	M. RESISTOR CH 1/16W 2.7K	1	
R413	ERJ3GEYJ103	M. RESISTOR CH 1/16W 10K	1	
R415	ERJ3GEY6152	M. RESISTOR CH 1/16W 1.5K	1	
R417, 18	ERJ3RBD123	M. RESISTOR CH 1/16W 12K	2	
R419	ERJ3RBD223	M. RESISTOR CH 1/16W 22K	1	
R420	ERJ3RBD473	M. RESISTOR CH 1/16W 47K	1	
R423	ERJ3GEYJ103	M. RESISTOR CH 1/16W 10K	1	
R424	ERJ3GEYJ132	M. RESISTOR CH 1/16W 1.3K	1	
R425	ERJ3GEYJ911	M. RESISTOR CH 1/16W 710K	1	
R426	ERJ3GEYJ222	M. RESISTOR CH 1/16W 2.2K	1	
R428	ERJ3GEY6152	M. RESISTOR CH 1/16W 1.5K	1	

Ref.No.	Part No.	Part Name & Description	Pcs	Remarks	Ref.No.	Part No.	Part Name & Description	Pcs	Remarks
R429	ERJ3GEYJ821	M. RESISTOR CH 1/16W 820	1		R2010	ERJ3GEYJ103	M. RESISTOR CH 1/16W 10K	1	
R430	ERJ3GEYJ103	M. RESISTOR CH 1/16W 10K	1		R2012	ERJ3GEYJ684	M. RESISTOR CH 1/16W 680K	1	
R481	ERJ3GEYJ103	M. RESISTOR CH 1/16W 10K	1		R2015	ERJ3GEYJ473	M. RESISTOR CH 1/16W 47K	1	
R701, 02	ERJ3GEYJ3R3	M. RESISTOR CH 1/16W 3.3	2		R2016	ERJ3GEYJ222	M. RESISTOR CH 1/16W 2.2K	1	
R703, 04	ERJ3GEYJ2R2	M. RESISTOR CH 1/16W 2.2	2		R2017	ERJ3GEYJ6102	M. RESISTOR CH 1/16W 1K	1	
R705, 06	ERJ3GEYJ473	M. RESISTOR CH 1/16W 47K	2		R2018	ERJ3GEYJ6472	M. RESISTOR CH 1/16W 4.7K	1	
R707	ERJ3GEYJ101	M. RESISTOR CH 1/16W 100	1		R2019, 20	ERJ3GEYJ6471	M. RESISTOR CH 1/16W 470	2	
R708, 09	ERJ3GEYJ473	M. RESISTOR CH 1/16W 47K	2		R2021	ERJ6GEYJ101	M. RESISTOR CH 1/10W 100	1	
R713	ERJ3GEYJ6102	M. RESISTOR CH 1/16W 1K	1		R2022	ERJ8GEYJ33	M. RESISTOR CH 1/8W 0.33	1	
R716	ERJ3GEYJ6472	M. RESISTOR CH 1/16W 4.7K	1		R2024	ERJ3GEYJ101	M. RESISTOR CH 1/16W 100	1	
R717	ERJ3GEYJ221	M. RESISTOR CH 1/16W 220	1		R2040-42	ERJ3GEYJ331	M. RESISTOR CH 1/16W 330	3	
R718	ERJ3GEYJ223	M. RESISTOR CH 1/16W 22K	1		R3001	ERJ3GEYJ122	M. RESISTOR CH 1/16W 1.2K	1	
R719	ERJ3GEYOR00	M. RESISTOR CH 1/16W 0	1		R3002	ERJ3GEYOR00	M. RESISTOR CH 1/16W 0	1	
R720, 21	ERJ3GEYJ103	M. RESISTOR CH 1/16W 10K	2		R3004	ERJ3GEYJ122	M. RESISTOR CH 1/16W 1.2K	1	
R722	ERJ3GEYJ104	M. RESISTOR CH 1/16W 100K	1		R3005	ERJ3GEYJ392	M. RESISTOR CH 1/16W 3.9K	1	
R723	ERJ3GEYJ103	M. RESISTOR CH 1/16W 10K	1		R3006	ERJ2RHD682	M. RESISTOR CH 2W 6.8K	1	
R724	ERJ3GEYJ6102	M. RESISTOR CH 1/16W 1K	1		R3007	ERJ2RHD222	M. RESISTOR CH 2W 2.2K	1	
R725	ERJ3GEYJ101	M. RESISTOR CH 1/16W 100	1		R3008	ERJ3GEYJ6102	M. RESISTOR CH 1/16W 1K	1	
R726	ERJ3GEYJ6102	M. RESISTOR CH 1/16W 1K	1		R3009	ERJ3GEYJ393	M. RESISTOR CH 1/16W 39K	1	
R727	ERJ3GEYJ223	M. RESISTOR CH 1/16W 22K	1		R3010	ERJ3GEYJ333	M. RESISTOR CH 1/16W 33K	1	
R728	ERJ3GEYJ273	M. RESISTOR CH 1/16W 27K	1		R3013	ERJ3GEYOR00	M. RESISTOR CH 1/16W 0	1	
R729	ERJ3GEYJ153	M. RESISTOR CH 1/16W 15K	1		R3017	ERJ3GEYOR00	M. RESISTOR CH 1/16W 0	1	
R730	ERJ3GEYJ103	M. RESISTOR CH 1/16W 10K	1		R3018	ERJ3GEYJ225	M. RESISTOR CH 1/16W 2.2M	1	
R732	ERJ3GEYJ333	M. RESISTOR CH 1/16W 33K	1		R3020	ERJ3GEYJ183	M. RESISTOR CH 1/16W 18K	1	
R733	ERJ3GEYJ684	M. RESISTOR CH 1/16W 680K	1		R3022	ERJ3GEYJ223	M. RESISTOR CH 1/16W 22K	1	
R734, 35	ERJ3GEYJ123	M. RESISTOR CH 1/16W 12K	2		R3023	ERJ3GEYJ273	M. RESISTOR CH 1/16W 27K	1	
R736	ERJ3GEYJ474	M. RESISTOR CH 1/16W 470K	1		R3025	ERJ3GEYJ123	M. RESISTOR CH 1/16W 12K	1	
R737	ERJ3GEYJ684	M. RESISTOR CH 1/16W 680K	1		R3026	ERJ3GEYJ393	M. RESISTOR CH 1/16W 39K	1	
R738	ERJ3GEYJ124	M. RESISTOR CH 1/16W 120K	1		R3031, 32	ERJ3GEYJ6102	M. RESISTOR CH 1/16W 1K	2	
R740	ERJ3GEYJ333	M. RESISTOR CH 1/16W 33K	1		R3034	ERJ3GEYJ6102	M. RESISTOR CH 1/16W 1K	1	
R757, 58	ERJ3GEYJ105	M. RESISTOR CH 1/16W 1M	2		R3057	ERJ3GEYJ103	M. RESISTOR CH 1/16W 10K	1	
R761	ERJ3GEYJ272	M. RESISTOR CH 1/16W 2.7K	1		R3058	ERJ3GEYJ182	M. RESISTOR CH 1/16W 1.8K	1	
R770, 71	ERJ3GEYJ105	M. RESISTOR CH 1/16W 1M	2		R3059	ERJ3GEYJ821	M. RESISTOR CH 1/16W 820	1	
R1001	ERJ6RBD822	M. RESISTOR CH 1/10W 8.2K	1		R3060	ERJ2RKD620	M. RESISTOR CH 2W 62	1	
R1002	ERJ6RBD272	M. RESISTOR CH 1/10W 2.7K	1		R3063	ERJ3GEYOR00	M. RESISTOR CH 1/16W 0	1	
R1005	ERJ3RBD472	M. RESISTOR CH 1/16W 4.7K	1		R4001	ERJ3GEYJ100	M. RESISTOR CH 1/16W 10	1	
R1006	ERJ3RBD272	M. RESISTOR CH 1/16W 2.7K	1		R4002	ERJ3GEYJ334	M. RESISTOR CH 1/16W 330K	1	
R1007	ERJ8GEYJ330	M. RESISTOR CH 1/8W 33	1		R4003	ERJ3GEYJ331	M. RESISTOR CH 1/16W 330	1	
R1008	ERJ3RBD223	M. RESISTOR CH 1/16W 22K	1		R4004	ERJ3GEYJ222	M. RESISTOR CH 1/16W 2.2K	1	
R1009	ERJ3RBD152	M. RESISTOR CH 1/16W 1.5K	1		R4005	ERJ3GEYJ684	M. RESISTOR CH 1/16W 680K	1	
R1012	ERJ6RHD1872	M. RESISTOR CH 1/10W 18.7K	1		R4006	ERJ3GEYJ473	M. RESISTOR CH 1/16W 47K	1	
R1013	ERJ6RBD473	M. RESISTOR CH 1/10W 47K	1		R4007	ERJ3GEYJ223	M. RESISTOR CH 1/16W 22K	1	
R1014, 15	ERJ6RBD182	M. RESISTOR CH 1/10W 1.8K	2		R4008	ERJ3GEYOR00	M. RESISTOR CH 1/16W 0	1	
R1016	ERJ3RBD153	M. RESISTOR CH 1/16W 15K	1		R4009	ERJ3GEYJ225	M. RESISTOR CH 1/16W 2.2M	1	
R1017	ERJ6GEYJ6102	M. RESISTOR CH 1/10W 1K	1		R4010	ERJ3GEYJ271	M. RESISTOR CH 1/16W 270	1	
R1018	ERJ3GEYJ151	M. RESISTOR CH 1/16W 150	1		R4011	ERJ3GEYJ223	M. RESISTOR CH 1/16W 22K	1	
R1019	ERJ6GEYJ6102	M. RESISTOR CH 1/10W 1K	1		R4012	ERJ3GEYJ6472	M. RESISTOR CH 1/16W 4.7K	1	
R1020	ERJ3GEYJ151	M. RESISTOR CH 1/16W 150	1		R4013	ERJ3GEYJ680	M. RESISTOR CH 1/16W 68	1	
R1021	ERJ3GEYJ330	M. RESISTOR CH 1/16W 33	1		R4014	ERJ3RBD123	M. RESISTOR CH 1/16W 12K	1	
R1022	ERJ3GEYJ150	M. RESISTOR CH 1/16W 15	1		R4015, 16	ERJ3GEYJ6472	M. RESISTOR CH 1/16W 4.7K	2	
R1023	ERJ3GEYJ182	M. RESISTOR CH 1/16W 1.8K	1		R4019	ERJ3GEYJ561	M. RESISTOR CH 1/16W 560	1	
R1024	ERJ3GEYJ470	M. RESISTOR CH 1/16W 47	1		R4023	ERJ3GEYJ163	M. RESISTOR CH 1/16W 16K	1	
R1025	ERJ6GEYJ6102	M. RESISTOR CH 1/10W 1K	1		R4025	ERJ3GEYJ334	M. RESISTOR CH 1/16W 330K	1	
R1035	ERJ3GEYJ470	M. RESISTOR CH 1/16W 47	1		R4026	ERJ3GEYJ684	M. RESISTOR CH 1/16W 680K	1	
R1038	ERJ3RED510	M. RESISTOR CH 1/16W 51	1		R4027, 28	ERJ3GEYJ103	M. RESISTOR CH 1/16W 10K	2	
R1039	ERJ3RBD391	M. RESISTOR CH 1/16W 390	1		R4029	ERJ3GEYJ562	M. RESISTOR CH 1/16W 5.6K	1	
R1040	ERJ3RBD121	M. RESISTOR CH 1/16W 120	1		R4030	ERJ3RBD223	M. RESISTOR CH 1/16W 22K	1	
R1051	ERJ3RBD273	M. RESISTOR CH 1/16W 27K	1		R4031	ERJ3RBD203	M. RESISTOR CH 1/16W 20K	1	
R1052	ERJ3RBD473	M. RESISTOR CH 1/16W 47K	1		R4032	ERJ3RBD181	M. RESISTOR CH 1/16W 180	1	
R1063	ERJ3GEYJ103	M. RESISTOR CH 1/16W 10K	1		R4033	ERJ3GEYJ334	M. RESISTOR CH 1/16W 330K	1	
R1065	ERJ3GEYJ122	M. RESISTOR CH 1/16W 1.2K	1		R4034	ERJ3GEYJ223	M. RESISTOR CH 1/16W 22K	1	
R1071	ERJ3GEYJ6102	M. RESISTOR CH 1/16W 1K	1		R4035	ERJ3GEYJ273	M. RESISTOR CH 1/16W 27K	1	
R1072	ERJ3GEYJ104	M. RESISTOR CH 1/16W 100K	1		R4036	ERJ3GEYJ222	M. RESISTOR CH 1/16W 2.2K	1	
R1073	ERJ3GEYJ101	M. RESISTOR CH 1/16W 100	1		R4037	ERJ3GEYJ123	M. RESISTOR CH 1/16W 12K	1	
R1080	ERJ8GEYOR00	M. RESISTOR CH 1/8W 0	1		R4038	ERJ3GEYJ680	M. RESISTOR CH 1/16W 68	1	
R1085, 86	ERJ3GEYJ6102	M. RESISTOR CH 1/16W 1K	2		R4039	ERJ3GEYJ224	M. RESISTOR CH 1/16W 220K	1	
R2001	ERJ3GEYJ6102	M. RESISTOR CH 1/16W 1K	1		R4040	ERJ3GEYJ6102	M. RESISTOR CH 1/16W 1K	1	
R2002	ERJ3GEYJ224	M. RESISTOR CH 1/16W 220K	1		R4041	ERJ3GEYJ6822	M. RESISTOR CH 1/16W 8.2K	1	
R2003	ERJ3GEYJ222	M. RESISTOR CH 1/16W 2.2K	1		R4042	ERJ3GEYJ183	M. RESISTOR CH 1/16W 18K	1	
R2004	ERJ3GEYJ154	M. RESISTOR CH 1/16W 150K	1		R4043-45	ERJ3GEYOR00	M. RESISTOR CH 1/16W 0	3	
R2005	ERJ3GEYJ392	M. RESISTOR CH 1/16W 3.9K	1		R4050	ERJ3GEYJ473	M. RESISTOR CH 1/16W 47K	1	
R2006	ERJ3GEYJ474	M. RESISTOR CH 1/16W 470K	1		R4052	ERJ3GEYJ153	M. RESISTOR CH 1/16W 15K	1	
R2007	ERJ8GEYJR47	M. RESISTOR CH 1/8W 0.47	1		R4053	ERJ3GEYJ333	M. RESISTOR CH 1/16W 33K	1	
R2008	ERJ8GEYJR33	M. RESISTOR CH 1/8W 0.33	1		R4054	ERJ3GEYJ6102	M. RESISTOR CH 1/16W 1K	1	
R2009	ERJ3GEYJ561	M. RESISTOR CH 1/16W 560	1		R4060	ERJ3GEYJ153	M. RESISTOR CH 1/16W 15K	1	

Ref.No.	Part No.	Part Name & Description	Pcs	Remarks
R4061	ERJ36EYJ683	M. RESISTOR CH 1/16W 68K	1	
R4062	ERJ36EYJ6472	M. RESISTOR CH 1/16W 4.7K	1	
R4063	ERJ36EYJ6332	M. RESISTOR CH 1/16W 3.3K	1	
R4064	ERJ36EYJ104	M. RESISTOR CH 1/16W 100K	1	
R4065	ERJ36EYJ563	M. RESISTOR CH 1/16W 56K	1	
R4066	ERJ36EYJ103	M. RESISTOR CH 1/16W 10K	1	
R4067	ERJ36EYJ562	M. RESISTOR CH 1/16W 5.6K	1	
R4069	ERJ36EYJ222	M. RESISTOR CH 1/16W 2.2K	1	
R4070	ERJ36EYJ432	M. RESISTOR CH 1/16W 4.3K	1	
R4071	ERJ36EYJ273	M. RESISTOR CH 1/16W 27K	1	
R4072	ERJ36EYJ333	M. RESISTOR CH 1/16W 33K	1	
R4073	ERJ36EYJ473	M. RESISTOR CH 1/16W 47K	1	
R4074	ERJ36EYJ122	M. RESISTOR CH 1/16W 1.2K	1	
R4075	ERJ36EYJ563	M. RESISTOR CH 1/16W 56K	1	
R5001	ERJ36EYJ100	M. RESISTOR CH 1/16W 10	1	
R5002, 03	ERJ36EYJ680	M. RESISTOR CH 1/16W 68	2	
R5004	ERJ36EYJ6332	M. RESISTOR CH 1/16W 3.3K	1	
R5005	ERJ2RHD113	M. RESISTOR CH 2W 11K	1	
R5007	ERJ36EYJ561	M. RESISTOR CH 1/16W 560	1	
R5008	ERJ66EYJ47	M. RESISTOR CH 1/10W 4.7	1	
R5009	ERJ36EYJ274	M. RESISTOR CH 1/16W 270K	1	
R5052	ERJ36EYJ102	M. RESISTOR CH 1/16W 1K	1	
R5500	ERJ36EYJ102	M. RESISTOR CH 1/16W 1K	1	
R5501	ERJ36EYJ563	M. RESISTOR CH 1/16W 56K	1	
R5504	ERJ36EYJ273	M. RESISTOR CH 1/16W 27K	1	
R5505	ERJ36EYJ222	M. RESISTOR CH 1/16W 2.2K	1	
R5508	ERJ36EYJ102	M. RESISTOR CH 1/16W 1K	1	
R5509	ERJ36EYJ222	M. RESISTOR CH 1/16W 2.2K	1	
R5510	ERJ36EYJ102	M. RESISTOR CH 1/16W 1K	1	
R5513	ERJ36EYJ225	M. RESISTOR CH 1/16W 2.2M	1	
R5514, 15	ERJ36EYJ102	M. RESISTOR CH 1/16W 1K	2	
R5516, 17	ERJ36EYJ000	M. RESISTOR CH 1/16W 0	2	
R5520	ERJ36EYJ6472	M. RESISTOR CH 1/16W 4.7K	1	
R5521	ERJ36EYJ6471	M. RESISTOR CH 1/16W 470	1	
R6001	ERJ36EYJ821	M. RESISTOR CH 1/16W 820	1	
R6002	ERJ36EYJ473	M. RESISTOR CH 1/16W 47K	1	
R6003	ERJ36EYJ274	M. RESISTOR CH 1/16W 270K	1	
R6004	ERJ36EYJ273	M. RESISTOR CH 1/16W 27K	1	
R6006	ERJ36EYJ000	M. RESISTOR CH 1/16W 0	1	
R6007	ERJ36EYJ562	M. RESISTOR CH 1/16W 5.6K	1	
R6008	ERJ36EYJ223	M. RESISTOR CH 1/16W 22K	1	
R6009	ERJ36EYJ473	M. RESISTOR CH 1/16W 47K	1	
R6010	ERJ36EYJ104	M. RESISTOR CH 1/16W 100K	1	
R6011	ERJ36EYJ000	M. RESISTOR CH 1/16W 0	1	
R6013	ERJ36EYJ103	M. RESISTOR CH 1/16W 10K	1	
R6014	ERJ36EYJ105	M. RESISTOR CH 1/16W 1M	1	
R6015	ERJ36EYJ103	M. RESISTOR CH 1/16W 10K	1	
R6016	ERJ36EYJ6472	M. RESISTOR CH 1/16W 4.7K	1	
R6018	ERJ36EYJ000	M. RESISTOR CH 1/16W 0	1	
R6020	ERJ36EYJ222	M. RESISTOR CH 1/16W 2.2K	1	
R6021	ERJ86EYJ120	M. RESISTOR CH 1/8W 12	1	
R6022	ERJ36EYJ223	M. RESISTOR CH 1/16W 22K	1	
R6023	ERJ36EYJ222	M. RESISTOR CH 1/16W 2.2K	1	
R6024	ERJ36EYJ474	M. RESISTOR CH 1/16W 470K	1	
R6026	ERJ36EYJ222	M. RESISTOR CH 1/16W 2.2K	1	
R6027	ERJ66EYJ221	M. RESISTOR CH 1/10W 220	1	
R6028	ERJ36EYJ222	M. RESISTOR CH 1/16W 2.2K	1	
R6029	ERJ36EYJ102	M. RESISTOR CH 1/16W 1K	1	
R6030	ERJ36EYJ474	M. RESISTOR CH 1/16W 470K	1	
R6032	ERJ36EYJ6472	M. RESISTOR CH 1/16W 4.7K	1	
R6033	ERJ36EYJ181	M. RESISTOR CH 1/16W 180	1	
R6034	ERJ36EYJ102	M. RESISTOR CH 1/16W 1K	1	
R6035	ERJ36EYJ103	M. RESISTOR CH 1/16W 10K	1	
R6037, 38	ERJ36EYJ104	M. RESISTOR CH 1/16W 100K	2	
R6039	ERJ86EYJ2R2	M. RESISTOR CH 1/8W 2.2	1	
R6040	ERJ2RHD104	M. RESISTOR CH 2W 100K	1	
R6042	ERJ2RHD223	M. RESISTOR CH 2W 22K	1	
R6043	ERJ36EYJ104	M. RESISTOR CH 1/16W 100K	1	
R6044	ERJ2RHD153	M. RESISTOR CH 2W 15K	1	
R6045	ERJ2RHD123	M. RESISTOR CH 2W 12K	1	
R6046	ERJ36EYJ6472	M. RESISTOR CH 1/16W 4.7K	1	
R6047	ERJ36EYJ104	M. RESISTOR CH 1/16W 100K	1	
R6048	ERJ36EYJ272	M. RESISTOR CH 1/16W 2.7K	1	
R6049	ERJ36EYJ473	M. RESISTOR CH 1/16W 47K	1	
R6050, 51	ERJ36EYJ222	M. RESISTOR CH 1/16W 2.2K	2	

Ref.No.	Part No.	Part Name & Description	Pcs	Remarks
R6052-54	ERJ36EYJ000	M. RESISTOR CH 1/16W 0	3	
R6055	ERJ36EYJ683	M. RESISTOR CH 1/16W 68K	1	
R6056	ERJ36EYJ104	M. RESISTOR CH 1/16W 100K	1	
R6057, 58	ERJ36EYJ474	M. RESISTOR CH 1/16W 470K	2	
R6059	ERJ36EYJ102	M. RESISTOR CH 1/16W 1K	1	
R6061	ERJ36EYJ103	M. RESISTOR CH 1/16W 10K	1	
R6062, 63	ERJ36EYJ474	M. RESISTOR CH 1/16W 470K	2	
R6064	ERJ36EYJ102	M. RESISTOR CH 1/16W 1K	1	
R6065	ERJ36EYJ333	M. RESISTOR CH 1/16W 33K	1	
R6067	ERJ36EYJ124	M. RESISTOR CH 1/16W 120K	1	
R6068	ERJ36EYJ474	M. RESISTOR CH 1/16W 470K	1	
R6069	ERJ36EYJ334	M. RESISTOR CH 1/16W 330K	1	
R6080	ERJ36EYJ473	M. RESISTOR CH 1/16W 47K	1	
R6082	ERJ36EYJ103	M. RESISTOR CH 1/16W 10K	1	
R6085	ERJ36EYJ473	M. RESISTOR CH 1/16W 47K	1	
R6086	ERJ36EYJ103	M. RESISTOR CH 1/16W 10K	1	
R6087	ERJ36EYJ683	M. RESISTOR CH 1/16W 68K	1	
R6089	ERJ36EYJ122	M. RESISTOR CH 1/16W 1.2K	1	
R6091	ERJ36EYJ121	M. RESISTOR CH 1/16W 120	1	
R6095	ERJ36EYJ151	M. RESISTOR CH 1/16W 150	1	
R6097	ERJ36EYJ473	M. RESISTOR CH 1/16W 47K	1	
R6098, 99	ERJ36EYJ682	M. RESISTOR CH 1/16W 6.8K	2	
R6100	ERJ36EYJ103	M. RESISTOR CH 1/16W 10K	1	
R6113, 14	ERJ36EYJ000	M. RESISTOR CH 1/16W 0	2	
R6201	ERJ36EYJ473	M. RESISTOR CH 1/16W 47K	1	
R6202	ERJ86EYJ2R2	M. RESISTOR CH 1/8W 2.2	1	
R6203	ERJ36EYJ101	M. RESISTOR CH 1/16W 100	1	
R6204	ERJ36EYJ103	M. RESISTOR CH 1/16W 10K	1	
R6205	ERJ36EYJ222	M. RESISTOR CH 1/16W 2.2K	1	
R6206-08	ERJ36EYJ104	M. RESISTOR CH 1/16W 100K	3	
R6209	ERJ36EYJ222	M. RESISTOR CH 1/16W 2.2K	1	
R6210	ERJ36EYJ224	M. RESISTOR CH 1/16W 220K	1	
R6211	ERJ36EYJ474	M. RESISTOR CH 1/16W 470K	1	
RA6001	EXBV8V102J	RESISTOR ARRAY	1	
RA6002	EXBV8V473J	RESISTOR ARRAY	1	
RA6003	EXBV4V102J	RESISTOR ARRAY	1	
RA6004, 05	EXBV8V102J	RESISTOR ARRAY	2	
RA6006	EXBV4V473J	RESISTOR ARRAY	1	
RA6008	EXBV4V104J	RESISTOR ARRAY	1	
RA6009	EXBV4V102J	RESISTOR ARRAY	1	
RA6010	EXBV4V473J	RESISTOR ARRAY	1	
RA6011	EXBV4V102J	RESISTOR ARRAY	1	
RA6013	EXBV8V102J	RESISTOR ARRAY	1	
RA6014	EXBV8V473J	RESISTOR ARRAY	1	
RA6015	EXBV8V683J	RESISTOR ARRAY	1	
T1001	ELLO4T061R	CHOKE COIL	1	
T1002	VTP0357	CRYSTAL OSCILLATOR	1	
T4001	EIQ6QB008	TRANSFORMER	1	
VC308	ECRJA020E11	TRIMMER	2P 1	
W201	ERJ36EYJ000	M. RESISTOR CH 1/16W 0	1	
W209	ERJ36EYJ000	M. RESISTOR CH 1/16W 0	1	
W213, 14	ERJ36EYJ000	M. RESISTOR CH 1/16W 0	2	
W217	ERJ36EYJ000	M. RESISTOR CH 1/16W 0	1	
W302	ERJ36EYJ000	M. RESISTOR CH 1/16W 0	1	
W303	ERJ66EYJ000	M. RESISTOR CH 1/10W 0	1	
W305, 06	ERJ66EYJ000	M. RESISTOR CH 1/10W 0	2	
W701	ERJ36EYJ000	M. RESISTOR CH 1/16W 0	1	
W3004	ERJ36EYJ000	M. RESISTOR CH 1/16W 0	1	
W3007, 08	ERJ36EYJ000	M. RESISTOR CH 1/16W 0	2	
W6001	ERJ36EYJ000	M. RESISTOR CH 1/16W 0	1	
X301	VXS0564	CRYSTAL OSCILLATOR	1	
X701	EFOS1205E5	CERAMIC OSCILLATOR	1	
X5501	VXS0794	CRYSTAL OSCILLATOR	1	
X6001	VXS0654	CRYSTAL OSCILLATOR	1	
X6002	VXS0601	CRYSTAL OSCILLATOR	1	
X6003	VXS0678	CRYSTAL OSCILLATOR	1	
		MISCELLANEOUS		
	VSC4419	POWER SHIELD COVER (BOTT)	1	
	VSC4420	POWER SHIELD COVER (BOTT)	1	

Ref.No.	Part No.	Part Name & Description	Pcs	Remarks	Ref.No.	Part No.	Part Name & Description	Pcs	Remarks
	VSC4622	CAMERA SHIELD COVER(BOTT)	1		R851	ERJ3RBD392	M.RESISTOR CH 1/16W 3.9K	1	
	VMZ2278	SCREW BARRIER	1		R852	ERJ6GEYF822	M.RESISTOR CH 1/10W 8.2K	1	
					R853	ERJ6GEYG103	M.RESISTOR CH 1/10W 10K	1	
					R855	ERJ3GEYJ151	M.RESISTOR CH 1/16W 150	1	
	■ VEP28229M	E.V.F. C.B.A.		(RTL)	R865	ERJ3GEYOR00	M.RESISTOR CH 1/16W 0	1	
				NV-RX9B	R884	ERJ3GEYOR00	M.RESISTOR CH 1/16W 0	1	
				NV-RX10EG/A/EN/ENH/EU	△ R1601	VSF0226D25T	FUSE	1	
C801	ECQV1H104JL	P.CAPACITOR 50V 0.1U	1		R1602	ERJ3GEYJ474	M.RESISTOR CH 1/16W 470K	1	
C802-04	ECUM1C105ZFN	C.CAPACITOR CH 16V 1U	3		R1603	ERJ3GEYJ564	M.RESISTOR CH 1/16W 560K	1	
C805	ECEA0JKE221	E.CAPACITOR 6.3V 220U	1		R1699	ERJ3GEYJ181	M.RESISTOR CH 1/16W 180	1	
C806	ECUX1C123KBV	C.CAPACITOR CH 16V 0.012U	1		R1724	ERJ3GEYOR00	M.RESISTOR CH 1/16W 0	1	
C807	ECUM1C105KBM	C.CAPACITOR CH 16V 1U	1		R1726	ERJ3GEYG472	M.RESISTOR CH 1/16W 4.7K	1	
C809	ECA1CKF470	E.CAPACITOR 16V 47U	1		R1727	ERJ3GEYJ392	M.RESISTOR CH 1/16W 3.9K	1	
C810	ECUM2A512JUM	C.CAPACITOR CH 100V 5100P	1						
C811	ECEA1CKE101	E.CAPACITOR 16V 100U	1		S801	VEE9711	CRT SOCKET	1	
C812	ECUX1H180JCV	C.CAPACITOR CH 50V 18P	1						
C813	ECUM2J221KBM	C.CAPACITOR CH 630V 220P	1		T801	ECXC2802B	TRANSFORMER	1	
C814	ECEA1HSN010	E.CAPACITOR 50V 1U	1						
C815	ECUM2H331KBM	C.CAPACITOR CH 500V 330P	1		VR801	EVM7JGA00BE2	V.RESISTOR 220	1	
C816	ECUM1H104ZFN	C.CAPACITOR CH 50V 0.1U	1		VR803	EVMLRGA00BV6	V.RESISTOR	1	
C817	ECUM2A331JUM	C.CAPACITOR CH 100V 330P	1		VR804	EVM7BSX30B55	V.RESISTOR 500K	1	
C818	ECUX1H390JCV	C.CAPACITOR CH 50V 39P	1						
C831	ECUM1H104ZFN	C.CAPACITOR CH 50V 0.1U	1		Z1601	VL2330/1HF	LITHIUM BATTERY	1	
G1603	ECEV1CA220	E.CAPACITOR CH 16V 22U	1				MISCELLANEOUS		
						VMP4952	DC-JACK EARTH ANGLE	1	
D803	MA142WA	DIODE	1						
D1601	MA8130M	DIODE	1						
D1603	MA8130M	DIODE	1						
						■ VEP28229L	E.V.F. C.B.A.		(RTL)
IC801	AN2516S	IC	1						NV-RX19B
									NV-RX20EG/EN/ENH/EU
J1601	VEK7724	RFU	1		C801	ECQV1H104JL	P.CAPACITOR 50V 0.1U	1	
					C802-04	ECUM1C105ZFN	C.CAPACITOR CH 16V 1U	3	
L801	VLQ0319K100	COIL 10UH	1		G805	ECEA0JKE221	E.CAPACITOR 6.3V 220U	1	
L802	ELH5L244	COIL	1		G806	ECUX1C123KBV	C.CAPACITOR CH 16V 0.012U	1	
L804	VLQ0163J680	COIL 68UH	1		G807	ECUM1C105KBM	C.CAPACITOR CH 16V 1U	1	
L805	VLQ0319K100	COIL 10UH	1		G809	ECA1CKF470	E.CAPACITOR 16V 47U	1	
L806	VLQ0426J330	COIL 33UH	1		G810	ECUM2A512JUM	C.CAPACITOR CH 100V 5100P	1	
L1601, 02	VLP0307	COIL	2		G811	ECEA1CKE101	E.CAPACITOR 16V 100U	1	
					G812	ECUX1H180JCV	C.CAPACITOR CH 50V 18P	1	
P801	VJP1597T	CONNECTOR (MALE) 4P	1		G813	ECUM2J221KBM	C.CAPACITOR CH 630V 220P	1	
P803	VJP1596T	CONNECTOR (MALE) 3P	1		G814	ECEA1HSN010	E.CAPACITOR 50V 1U	1	
P804	VJP1242T	CONNECTOR (MALE) 2P	1		G815	ECUM2H331KBM	C.CAPACITOR CH 500V 330P	1	
					G816	ECUM1H104ZFN	C.CAPACITOR CH 50V 0.1U	1	
PP1601	VJP3126B024	CONNECTOR (MALE) 24P	1		G817	ECUM2A331JUM	C.CAPACITOR CH 100V 330P	1	
					G818	ECUX1H390JCV	C.CAPACITOR CH 50V 39P	1	
Q801	2SB1462	TRANSISTOR	1		G831	ECUM1H104ZFN	C.CAPACITOR CH 50V 0.1U	1	
Q802	2SD968A-S	TRANSISTOR	1		G1603	ECEV1CA220	E.CAPACITOR CH 16V 22U	1	
Q803, 04	2SA1748	TRANSISTOR	2						
					D803	MA142WA	DIODE	1	
R801	ERJ6ENF4422	M.RESISTOR CH 1/10W 44.2K	1		D1601	MA8130M	DIODE	1	
R802	ERJ6GEYJ3R9	M.RESISTOR CH 1/10W 3.9	1		D1603	MA8130M	DIODE	1	
R803	ERJ3GEYG102	M.RESISTOR CH 1/16W 1K	1						
R804	ERJ3GEYJ122	M.RESISTOR CH 1/16W 1.2K	1		IC801	AN2516S	IC	1	
R805	ERJ3GEYG102	M.RESISTOR CH 1/16W 1K	1						
R806	ERJ3GEYJ122	M.RESISTOR CH 1/16W 1.2K	1		J1601	VEK7724	RFU	1	
R807	ERJ3GEYJ150	M.RESISTOR CH 1/16W 15	1						
R808	ERJ3RBD242	M.RESISTOR CH 1/16W 2.4K	1		L801	VLQ0319K100	COIL 10UH	1	
R809	ERJ3GEYJ564	M.RESISTOR CH 1/16W 560K	1		L802	ELH5L244	COIL	1	
R810	ERJ3RBD104	M.RESISTOR CH 1/16W 100K	1		L804	VLQ0163J680	COIL 68UH	1	
R815	ERJ3GEYG102	M.RESISTOR CH 1/16W 1K	1		L805	VLQ0319K100	COIL 10UH	1	
R816, 17	ERJ3GEYG472	M.RESISTOR CH 1/16W 4.7K	2		L806	VLQ0426J330	COIL 33UH	1	
R818	ERJ3GEYJ223	M.RESISTOR CH 1/16W 22K	1		L1601, 02	VLP0307	COIL	2	
R819, 20	ERJ6GEYJ275	M.RESISTOR CH 1/10W 2.7M	2						
R821	ERJ6GEYJ225	M.RESISTOR CH 1/10W 2.2M	1		P801	VJP1597T	CONNECTOR (MALE) 4P	1	
R823	ERJ3GEYJ120	M.RESISTOR CH 1/16W 12	1		P803	VJP1596T	CONNECTOR (MALE) 3P	1	
R829	ERJ6ENF4222	M.RESISTOR CH 1/10W 42.2K	1		P804	VJP1242T	CONNECTOR (MALE) 2P	1	
R834	ERJ3GEYJ122	M.RESISTOR CH 1/16W 1.2K	1						
R835	ERJ3GEYJ223	M.RESISTOR CH 1/16W 22K	1		PP1601	VJP3126B024	CONNECTOR (MALE) 24P	1	
R840	ERJ8GEYJ305	M.RESISTOR CH 1/8W 3M	1						
R841, 42	ERD21LLJ225	C.RESISTOR 1/8W 2.2M	2		Q801	2SB1462	TRANSISTOR	1	
R843	ERJ3GEYJ334	M.RESISTOR CH 1/16W 330K	1		Q802	2SD968A-S	TRANSISTOR	1	
R844	ERJ3GEYJ390	M.RESISTOR CH 1/16W 39	1		Q803, 04	2SA1748	TRANSISTOR	2	
R845	ERJ3GEYJ221	M.RESISTOR CH 1/16W 220	1						
R850	ERJ3RBD822	M.RESISTOR CH 1/16W 8.2K	1		QR881	UN5212	TRANSISTOR-RESISTOR	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
QR882	UN2130X	TRANSISTOR-RESISTOR	1	
R801	ERJ6ENF4422	M. RESISTOR CH 1/10W 44.2K	1	
R802	ERJ6EYJ3R9	M. RESISTOR CH 1/10W 3.9	1	
R803	ERJ3GEY6102	M. RESISTOR CH 1/16W 1K	1	
R804	ERJ3GEYJ122	M. RESISTOR CH 1/16W 1.2K	1	
R805	ERJ3GEY6102	M. RESISTOR CH 1/16W 1K	1	
R806	ERJ3GEYJ122	M. RESISTOR CH 1/16W 1.2K	1	
R807	ERJ3GEYJ150	M. RESISTOR CH 1/16W 15	1	
R808	ERJ3RBD242	M. RESISTOR CH 1/16W 2.4K	1	
R809	ERJ3GEYJ564	M. RESISTOR CH 1/16W 560K	1	
R810	ERJ3RBD104	M. RESISTOR CH 1/16W 100K	1	
R815	ERJ3GEY6102	M. RESISTOR CH 1/16W 1K	1	
R816, 17	ERJ3GEY6472	M. RESISTOR CH 1/16W 4.7K	2	
R818	ERJ3GEYJ223	M. RESISTOR CH 1/16W 22K	1	
R819, 20	ERJ6EYJ275	M. RESISTOR CH 1/10W 2.7M	2	
R821	ERJ6EYJ225	M. RESISTOR CH 1/10W 2.2M	1	
R823	ERJ3GEYJ120	M. RESISTOR CH 1/16W 12	1	
R829	ERJ6ENF4222	M. RESISTOR CH 1/10W 42.2K	1	
R834	ERJ3GEYJ122	M. RESISTOR CH 1/16W 1.2K	1	
R835	ERJ3GEYJ223	M. RESISTOR CH 1/16W 22K	1	
R840	ERJ8GEYJ305	M. RESISTOR CH 1/8W 3M	1	
R841, 42	ERD21LLJ225	C. RESISTOR 1/8W 2.2M	2	
R843	ERJ3GEYJ334	M. RESISTOR CH 1/16W 330K	1	
R844	ERJ3GEYJ390	M. RESISTOR CH 1/16W 39	1	
R845	ERJ3GEYJ221	M. RESISTOR CH 1/16W 220	1	
R850	ERJ3RBD822	M. RESISTOR CH 1/16W 8.2K	1	
R851	ERJ3RBD392	M. RESISTOR CH 1/16W 3.9K	1	
R852	ERJ6EYF822	M. RESISTOR CH 1/10W 8.2K	1	
R853	ERJ6EY6103	M. RESISTOR CH 1/10W 10K	1	
R855	ERJ3GEYJ151	M. RESISTOR CH 1/16W 150	1	
R865	ERJ3GEYOR00	M. RESISTOR CH 1/16W 0	1	
R883	ERJ3GEY6472	M. RESISTOR CH 1/16W 4.7K	1	
▲ R1601	VSF0226D25T	FUSE	1	
R1602	ERJ3GEYJ474	M. RESISTOR CH 1/16W 470K	1	
R1603	ERJ3GEYJ564	M. RESISTOR CH 1/16W 560K	1	
R1690	ERJ3GEYJ683	M. RESISTOR CH 1/16W 68K	1	
R1699	ERJ3GEYJ181	M. RESISTOR CH 1/16W 180	1	
R1724	ERJ3GEYOR00	M. RESISTOR CH 1/16W 0	1	
R1726	ERJ3GEY6472	M. RESISTOR CH 1/16W 4.7K	1	
R1727	ERJ3GEYJ392	M. RESISTOR CH 1/16W 3.9K	1	
S801	VEE9711	CRT SOCKET	1	
SW1695	VSQ0851	SWITCH	1	
SW1696	VSS0392	SWITCH	1	
T801	ECXC2802B	TRANSFORMER	1	
VR801	EVM7JGA00BE2	V. RESISTOR 220	1	
VR803	EVM7JGA00BV6	V. RESISTOR	1	
VR804	EVM7BSX30B55	V. RESISTOR 500K	1	
Z1601	VL2330/1HF	LITHIUM BATTERY	1	
		MISCELLANEOUS		
	VMP4952	DC-JACK EARTH ANGLE	1	
	■ VEP22248A	CCD FLEX. CARD C.B.A.		(RTL)
B291	VJS3500G012	CONNECTOR (FEMALE) 12P	1	
C292	ECST1VX225Z	T. CAPACITOR CH 35V 2.2U	1	
C294	ECUM1H473KBN	C. CAPACITOR CH 50V 0.047U	1	
C295	ECUM1E104ZFN	C. CAPACITOR CH 25V 0.1U	1	
D291	MA153	DIODE	1	
Q291	2SC2295	TRANSISTOR	1	
R291	ERJ6EY6560	M. RESISTOR CH 1/10W 56	1	
R292	ERJ6EYF472	M. RESISTOR CH 1/10W 4.7K	1	
R293	ERJ6EYOR00	M. RESISTOR CH 1/10W 0	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
		MISCELLANEOUS		
	VJB22248	FLEX. CARD	1	
	■ VEK8063	LENS FLEX. CARD C.B.A.		(RTL)
		MISCELLANEOUS		
	ON1004-R	PHOTO INTERRUPTER	1	
	SG-211S	PHOTO INTERRUPTER	1	
	■ VEK8058	MIC UNIT		(RTL)
				NV-RX9B
				NV-RX10EG/A/EN/ENH/EU
C1501	ECUM1H102KBN	C. CAPACITOR CH 50V 1000P	1	
C1502	ECUM1H222KBN	C. CAPACITOR CH 50V 2200P	1	
C1504	ECUM1H821JCN	C. CAPACITOR CH 50V 820P	1	
C1505	ECUM1H103KBN	C. CAPACITOR CH 50V 0.01U	1	
C1506	ECUM1C683KBN	C. CAPACITOR CH 16V 0.068U	1	
C4801	ECUM1C823KBN	C. CAPACITOR CH 16V 0.082U	1	
C4803	ECUX1H273KBN	C. CAPACITOR CH 50V 0.027U	1	
C4804	ECUM1H102KBN	C. CAPACITOR CH 50V 1000P	1	
C4805, 06	ECUX1H273KBN	C. CAPACITOR CH 50V 0.027U	2	
C4807	ECEA0JKS470	E. CAPACITOR 6.3V 47U	1	
D1501	MA153	DIODE	1	
D6802	PH310	DIODE	1	
FP1501	VJS2582B012	CONNECTOR (FEMALE) 12P	1	
J1501	VEJ1758	AV JACK BOARD	1	
LB1501	VLP0171	COIL	1	
LB1502	VLP0153	COIL	1	
Q4801-03	2SD601A	TRANSISTOR	3	
R1501	ERJ6EY6331	M. RESISTOR CH 1/10W 330	1	
R4801	ERJ6EYF561	M. RESISTOR CH 1/10W 560	1	
R4802	ERJ6EY6222	M. RESISTOR CH 1/10W 2.2K	1	
R4803	ERJ6EYJ334	M. RESISTOR CH 1/10W 330K	1	
R4804	ERJ6EYF822	M. RESISTOR CH 1/10W 8.2K	1	
R4805	ERJ6EYJ224	M. RESISTOR CH 1/10W 220K	1	
R4806	ERJ6EY6152	M. RESISTOR CH 1/10W 1.5K	1	
R4807	ERJ6EYF123	M. RESISTOR CH 1/10W 12K	1	
R4808, 09	ERJ6EY6683	M. RESISTOR CH 1/10W 68K	2	
R4810	ERJ6EY6332	M. RESISTOR CH 1/10W 3.3K	1	
R4811	ERJ6EY6103	M. RESISTOR CH 1/10W 10K	1	
S4801	EVQPA205R	SWITCH	1	
W1501	ERJ6EYOR00	M. RESISTOR CH 1/10W 0	1	
W1503	ERJ6EYOR00	M. RESISTOR CH 1/10W 0	1	
W1505	ERJ6EYOR00	M. RESISTOR CH 1/10W 0	1	
	■ VEK7707	MIC UNIT		(RTL)
				NV-RX19B
				NV-RX20EG/EN/ENH/EU
C4801	ECUM1C823KBN	C. CAPACITOR CH 16V 0.082U	1	
C4803	ECUX1H273KBN	C. CAPACITOR CH 50V 0.027U	1	
C4804	ECUM1H102KBN	C. CAPACITOR CH 50V 1000P	1	
C4805, 06	ECUX1H273KBN	C. CAPACITOR CH 50V 0.027U	2	
C4807	ECEA0JKS470	E. CAPACITOR 6.3V 47U	1	
C6801	ECST0JY106Z	T. CAPACITOR CH 6.3V 10U	1	
D6801	BR2202S-20B1	DIODE	1	
FP4801	VJS3623A008W	CONNECTOR (FEMALE) 8P	1	
IC6801	VEK6546	IC	1	
Q4801-03	2SD601A	TRANSISTOR	3	



Memo

1. 2024年10月10日，上午9:00，在会议室召开了2024年度工作总结会议。会议由王经理主持，参会人员包括各部门负责人及骨干员工。会议主要议程如下：

2. 王经理首先对2024年度公司整体业绩进行了回顾，并肯定了各部门在各自领域取得的成就。随后，各部门依次进行了工作总结汇报。

3. 市场部汇报了2024年度营销计划的执行情况，重点分析了线上渠道的拓展效果。销售部则详细阐述了客户开发及维护工作的进展，并提出了下一年度的销售目标。

4. 人力资源部汇报了2024年度招聘、培训及员工福利工作的落实情况。财务部则对2024年度财务预算执行情况进行了分析，并提出了优化成本控制的建议。

5. 在各部门汇报结束后，王经理对各部门的工作进行了点评，并提出了具体的改进意见。最后，会议总结了2024年度的工作成果，并对2025年度的工作方向进行了展望。

6. 会议决定，各部门应根据本次会议的精神，制定2025年度的详细工作计划，并于下月15日前提交至人力资源部备案。

7. 会议在热烈的掌声中圆满结束。