

7. Electric Parts List

7-1 CK565BSR3X/NWT (CK564BVR3S AND CK565BSR3X Dissimilar Parts)

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
ASSY-PCB,MAIN(OPT) BUYER : SRSC				CN05A	AA39-20069A	LEAD-CONNECTOR,ASSY;- ,YBNH025-05,67096-005,5P,500,	
* AA94-00264A ASSY-PCB,MAIN(OPT);CK565BR3S/NWT,S51A,UKRAINE,				CN06A	AA39-20499B	LEAD CONNECTOR-ASSY;- ,YBNH025-04,SMP025-04,4P,200	
CN602	3711-002644	CONNECTOR-HEADER:BOX,5P,1R,2.5mm,STRAIGHT,SN		JE01	3722-000143	JACK-PHONE:1P(VER),3.4mm,AG,BLK,NO	
CN701	3711-002647	CONNECTOR-HEADER:BOX,8P,1R,2.5mm,STRAIGHT,SN		JR01	3722-001031	JACK-RCA:3P,3.6mm,#18,AU	
JA701	3722-000195	JACK-SCART:42P,-,SN,BLK,NO		LA04	2701-000180	INDUCTOR-AXIAL:33uH,5%,2.5x3.4mm	
ASSY-PCB,A/V FRONT				LA05	2701-000180	INDUCTOR-AXIAL:33uH,5%,2.5x3.4mm	
* AA95-00031A ASSY-PCB,A/V FRONT:DP,22,77,02,3399,S51A,-,-,-				RA01	2001-000028	R-CARBON(S):100OHM,5%,1/2W,AA,TP,-	
CA04	2202-000720	C-CERAMIC,MLC-AXIAL:8.2nF,20%,16V,Y5R,TP,3.5x19,-		RA02	2001-000028	R-CARBON(S):100OHM,5%,1/2W,AA,TP,-	
CA05	2202-000720	C-CERAMIC,MLC-AXIAL:8.2nF,20%,16V,Y5R,TP,3.5x19,-		ASSY-SPEAKER			
CA06	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11,5		3001-001038 SPEAKER:6W,16ohm,92dB,140Hz			
CA07	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11,5		AA39-20504D LEAD CONNECTOR-ASSY;- ,SMH025-04,REC,4P,700,500mm,			
CN01A	AA39-20068E	LEAD-CONNECTOR,ASSY;- ,YBNH025-08,67096-008,8P,500,					

7-2 CK566BSX3S/NWT (CK564BVR3S AND CK566BSX3S Dissimilar Parts)

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
ASSY-PCB,MAIN(OPT) BUYER : SRSC				ASSY-SPEAKER			
* AA94-00269A ASSY-PCB,MAIN(OPT);CK566BX3S/NWT,S51A,UKRAINE,				3001-001038 SPEAKER:6W,16ohm,92dB,140Hz			
CN602	3711-002644	CONNECTOR-HEADER:BOX,5P,1R,2.5mm,STRAIGHT,SN		AA39-20504D LEAD CONNECTOR-ASSY;- ,SMH025-04,REC,4P,700,500mm,			
CN701	3711-002647	CONNECTOR-HEADER:BOX,8P,1R,2.5mm,STRAIGHT,SN		REMOCON			
CT03	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3		* AA59-10116A REMOCON;- ,TM59,SS,SZM503AT,29,-,-,L/GR			
CT05	2202-000164	C-CERAMIC,MLC-AXIAL:18nF,10%,50V,Y5P,TP,3.5X1.9MM,					
JA701	3722-000195	JACK-SCART:42P,-,SN,BLK,NO					
QT01	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,TP,120-					
RT03	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-					
RT04	2001-000003	R-CARBON:330OHM,5%,1/8W,AA,TP,-					
RT05	2001-000780	R-CARBON:470OHM,5%,1/8W,AA,TP,-					
ASSY-PCB,A/V FRONT							
* AA95-00031A ASSY-PCB,A/V FRONT:DP,22,77,02,3399,S51A,-,-,-							
CA04	2202-000720	C-CERAMIC,MLC-AXIAL:8.2nF,20%,16V,Y5R,TP,3.5x19,-					
CA05	2202-000720	C-CERAMIC,MLC-AXIAL:8.2nF,20%,16V,Y5R,TP,3.5x19,-					
CA06	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11,5					
CA07	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11,5					
CN01A	AA39-20068E	LEAD-CONNECTOR,ASSY;- ,YBNH025-08,67096-008,8P,500,					
CN05A	AA39-20069A	LEAD-CONNECTOR,ASSY;- ,YBNH025-05,67096-005,5P,500,					
CN06A	AA39-20499B	LEAD CONNECTOR-ASSY;- ,YBNH025-04,SMP025-04,4P,200					
JE01	3722-000143	JACK-PHONE:1P(VER),3.4mm,AG,BLK,NO					
JR01	3722-001031	JACK-RCA:3P,3.6mm,#18,AU					
LA04	2701-000180	INDUCTOR-AXIAL:33uH,5%,2.5x3.4mm					
LA05	2701-000180	INDUCTOR-AXIAL:33uH,5%,2.5x3.4mm					
RA01	2001-000028	R-CARBON(S):100OHM,5%,1/2W,AA,TP,-					
RA02	2001-000028	R-CARBON(S):100OHM,5%,1/2W,AA,TP,-					

7-3 CK568BSX3S/NWT (CK564BVR3S AND CK568BSX3S Dissimilar Parts)

Loc. No.	Code No.	Description ; Specification	Remark
		ASSY-PCB,MAIN(OPT)	
		BUYER : SRSC	
		CK568BX3S/NWT	
*	AA94-00265A	ASSY-PCB,MAIN(OPT);CK568BX3S/NWT,S51A,UKRAINE, CK568BX3X/NWT	
*	AA94-00270A	ASSY-PCB,MAIN(OPT);CK568BX3X/NWT,S51A,UKRAINE,	
CN602	3711-002644	CONNECTOR-HEADER:BOX,5P,1R,2.5mm,STRAIGHT,SN	
CN701	3711-002647	CONNECTOR-HEADER:BOX,8P,1R,2.5mm,STRAIGHT,SN	
CT03	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.	
CT05	2202-000164	C-CERAMIC,MLC-AXIAL:18nF,10%,50V,Y5P,TP,3.5X1.9MM,	
JA701	3722-000195	JACK-SCART:42P,-,SN,BLK,NO	
QT01	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,TP,120-	
RT03	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-	
RT04	2001-000003	R-CARBON:330OHM,5%,1/8W,AA,TP,-	
RT05	2001-000780	R-CARBON:470OHM,5%,1/8W,AA,TP,-	

ASSY-PCB,A/V FRONT

*	AA95-00031A	ASSY-PCB,A/V FRONT:DP,22,77,02,3399,S51A,-,-,-	
CA04	2202-000720	C-CERAMIC,MLC-AXIAL:8.2nF,20%,16V,Y5R,TP,3.5x19,-	
CA05	2202-000720	C-CERAMIC,MLC-AXIAL:8.2nF,20%,16V,Y5R,TP,3.5x19,-	
CA06	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11,5	
CA07	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11,5	
CN01A	AA39-20068E	LEAD-CONNECTOR,ASSY:-,YBNH025-08,67096-008,8P,500,	
CN05A	AA39-20069A	LEAD-CONNECTOR,ASSY:-,YBNH025-05,67096-005,5P,500,	
CN06A	AA39-20499B	LEAD CONNECTOR,ASSY:-,YBNH025-04,SMP025-04,4P,200	

Loc. No.	Code No.	Description ; Specification	Remark
JE01	3722-000143	JACK-PHONE:1P(VER),3.4mm,AG,BLK,NO	
JR01	3722-001031	JACK-RCA:3P,3.6mm,#18,AU	
LA04	2701-000180	INDUCTOR-AXIAL:33uH,5%,2.5x3.4mm	
LA05	2701-000180	INDUCTOR-AXIAL:33uH,5%,2.5x3.4mm	
RA01	2001-000028	R-CARBON(S):100OHM,5%,1/2W,AA,TP,-	
RA02	2001-000028	R-CARBON(S):100OHM,5%,1/2W,AA,TP,-	

REMOCON

*	AA59-10116A	REMOCON:-,TM59,SS,SZM503AT,29,-,-,L/GR	
---	-------------	--	--

ASSY-HOLDER,SPK

		CK568BSX3S/NWT	
*	AA91-60307A	ASSY-HOLDER,SPK:DP,PP,AA9160290A,8ohm10W,568B, CK568BSX3X/NWT	
*	AA91-60290A	ASSY-HOLDER,SPK:-,PP,HB,8ohm 10W,-,-,567B	

ASSY-CRT

		CK568BSX3X/NWT OPTION	
AA03-10026K	CRT-COLOR:-,A53QCA891X(B),+380mG,22,90d		
AA27-00002A	MAGNET-CONVERGENCE:-,JH291-SC-OB,29.1MM		
AA27-50004N	DEFLECTION-YOKE:		
AA63-60028A	SPACER-DY:NEOPRENE,-,BLK,V0 W12,-,-		

7-4 CK564BVR3S/NWT Parts List

Loc. No.	Code No.	Description ; Specification	Remark
		ASSY-PCB,MAIN(OPT)	
		BUYER : SRSC	
*	AA94-00268A	ASSY-PCB,MAIN(OPT);CK564BVR3S/NWT,S51A,UKRAINE,	
C102	2401-002594	C-AL:220uF,20%,16V,GP,TP,8x11,5,5	
C103	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.	
C104	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.	
C105	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.	
C106	2401-001082	C-AL:330nF,20%,50V,GP,TP,5x11,5	
C107	2401-000914	C-AL:22uF,20%,16V,GP,TP,5x11,5	
C109	2202-000796	C-CERAMIC,MLC-AXIAL:1nF,10%,50V,Y5P,TP,3.5X1.9MM,-	
C207	2401-001026	C-AL:3.3uF,20%,50V,GP,TP,5x11,5	
C210	2306-000122	C-FILM,MPPF:100nF,5%,50V,TP,7.3x4.0x5.0mm,	
C211	2401-002619	C-AL:47uF,20%,25V,GP,TP,5x11,5	
C213	2301-000224	C-FILM,PEF:22nF,5%,50V,TP,7.4x3.9x13mm,5m	
C214	2401-000660	C-AL:2.2uF,20%,50V,GP,TP,5x11,5	
C215	2305-000412	C-FILM,MPEF:470nF,5%,63V,TP,-,5mm	
C216	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11,5	
C217	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0mm,	
C218	2305-000411	C-FILM,MPEF:470nF,5%,50V,TP,7.3x4.8x5.5mm,	
C219	2401-002144	C-AL:47uF,20%,16V,GP,TP,5x11,5	
C220	2401-000302	C-AL:100uF,20%,25V,GP,TP,6.3x11,5	
C221	2305-000289	C-FILM,MPEF:220nF,5%,63V,TP,-,5mm	
C222	2305-000412	C-FILM,MPEF:470nF,5%,63V,TP,-,5mm	
C223	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.	
C224	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.	
C225	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.	
C226	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
C227	2201-000986	C-CERAMIC,DISC:12pF,5%,50V,NPO,TP,5x3mm,2.5mm	
C228	2201-000273	C-CERAMIC,DISC:18pF,5%,50V,CH,TP,5x3mm,5	

Loc. No.	Code No.	Description ; Specification	Remark
C229	2301-000356	C-FILM,PEF:47nF,5%,50V,TP,7.5x4.0x6.5,5mm	
C230	2301-000192	C-FILM,PEF:1nF,5%,50V,TP,5.3x10mm,5mm	
C231	2202-000183	C-CERAMIC,MLC-AXIAL:2.2nF,20%,16V,Y5R,TP,3.5X1.9MM,	
C232	2202-000796	C-CERAMIC,MLC-AXIAL:1nF,10%,50V,Y5P,TP,3.5X1.9MM,-	
C233	2309-000138	C-FILM,PE-PFF:100nF,5%,50V,TP,20x16x8.5,7.5m	
C234	2305-000289	C-FILM,MPEF:220nF,5%,63V,TP,-,5mm	
C235	2202-000849	C-CERAMIC,MLC-AXIAL:18pF,5%,50V,CH,TP,3.5x1.9,-	
C236	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.	
C237	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0mm,	
C238	2301-000383	C-FILM,PEF:10nF,5%,50V,TP,6x7x3.2mm,5mm	
C239	2301-000445	C-FILM,PEF:4.7nF,5%,50V,TP,5.5x7x3mm,5mm	
C240	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11,5	
C241	2401-000603	C-AL:1uF,20%,50V,GP,TP,5x11,5	
C242	2202-000806	C-CERAMIC,MLC-AXIAL:220pF,10%,50V,Y5P,TP,3.5x19,-	
C243	2401-000603	C-AL:1uF,20%,50V,GP,TP,5x11,5	
C244	2301-000224	C-FILM,PEF:22nF,5%,50V,TP,7.4x3.9x13mm,5m	
C245	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0mm,	
C301	2301-000254	C-FILM,PEF:39nF,5%,50V,TP,7.5x3.5x6.5mm,5	
C302	2401-000360	C-AL:100uF,20%,50V,GP,TP,8x11,5,5	
C303	2201-000259	C-CERAMIC,DISC:180pF,10%,500V,Y5P,TP,6x4,5	
C304	2305-000285	C-FILM,MPEF:220nF,5%,100V,TP,10.5X5.5X15MM,5	
C305	2305-000149	C-FILM,MPEF:100nF,5%,100V,TP,12x12.5x6.5,5	
C306	2305-000149	C-FILM,MPEF:100nF,5%,100V,TP,12x12.5x6.5,5	
C307	2401-000360	C-AL:100uF,20%,50V,GP,TP,8x11,5,5	
C308	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
C309	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11,5	
C403	2401-000901	C-AL:22uF,20%,160V,GP,TP,10x20,5	
C404	2201-000291	C-CERAMIC,DISC:1nF,10%,500V,Y5P,TP,8.5x5MM,5	
C405	2401-002268	C-AL:2.2uF,20%,250V,LZ,TP,8X11,5	
C406	2306-000195	C-FILM,MPPF:360nF,5%,400V,TP,26x19x11.5,20	
C407	2201-000984	C-CERAMIC,DISC:680pF,10%,2KV,Y5P,TP,11x6,7.5m	
C408	2305-000382	C-FILM,MPEF:4.7nF,5%,400V,TP,-,5mm	

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
C409	2201-000551	C-CERAMIC,DISC:470pF,10%,1KV,Y5P,TP,8x5,5		C827	2401-002235	C-AL:10uF,20%,16V,GP,TP,5x11mm,5mm	
C410	2401-001397	C-AL:470uF,20%,25V,GP,TP,10x16,5		C828	2401-000493	C-AL:10uF,20%,50V,LZ,TP,5x11mm,5mm	
C411	2305-000178	C-FILM,MPEF:10nF,5%,100V,TP,-5mm		C829	2401-000302	C-AL:100uF,20%,25V,GP,TP,6.3x11,5	
C412	2201-000599	C-CERAMIC,DISC:560pF,10%,500V,Y5P,TP,7x4,5		C830	2401-000611	C-AL:1uF,20%,50V,WT,TP,5x11,5	
C413	2401-000302	C-AL:100uF,20%,25V,GP,TP,6.3x11,5		C831	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
C415	2306-000327	C-FILM,MPPF:6.3nF,3%,1.6KV,TP,28.5x18x10,2		C832	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11,5	
C416	2303-001026	C-FILM,PPF:33nF,10%,400V,TP,20x15x8,7,5		C833	2401-002144	C-AL:47uF,20%,16V,GP,TP,5x11,5	
C417	2306-000102	C-FILM,MPPF:1.2uF,5%,250V,TP,29*31*14,5,20		C835	2401-002286	C-AL:470uF,20%,16V,WT,TP,10x12,5,5	
C418	2201-000556	C-CERAMIC,DISC:470pF,10%,500V,Y5P,TP,7x4,5		C901	2201-000234	C-CERAMIC,DISC:150pF,5%,50V,CH,TP,9.5x3,5	
C419	2401-001397	C-AL:470uF,20%,25V,GP,TP,10x16,5		C902	2301-000108	C-FILM,PEF:1.5nF,5%,50V,TP,6.5x3.0x5.5mm,	
C421	2401-002619	C-AL:47uF,20%,25V,GP,TP,5x11,5		C903	2201-000119	C-CERAMIC,DISC:100nF,+80-20%,50V,Y5V,TP,8x3,5	
C422	2306-000122	C-FILM,MPPF:100nF,5%,50V,TP,7.3x4.0x5.0mm,		C904	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
C423	2201-000556	C-CERAMIC,DISC:470pF,10%,500V,Y5P,TP,7x4,5		C905	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0mm,	
C424	2401-001527	C-AL:47uF,20%,250V,HR,TP,13x25mm,5m		C906	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0mm,	
C425	2305-000154	C-FILM,MPEF:100nF,5%,400V,TP,21.5x6.5x11.5		C907	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.	
C504	2202-000862	C-CERAMIC,MLC-AXIAL:390pF,10%,50V,Y5P,TP,3.5x1.9,-		C908	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.	
C506	2301-000213	C-FILM,PEF:220nF,5%,250V,TP,21.5x11,7,5		C909	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.	
C510	2401-000430	C-AL:10uF,20%,250V,GP,TP,10x16mm,5m		C910	2202-000796	C-CERAMIC,MLC-AXIAL:1nF,10%,50V,Y5P,TP,3.5X1.9MM,-	
C520	2401-001232	C-AL:4.7uF,20%,250V,GP,TP,10x12,5,5		C911	2202-000796	C-CERAMIC,MLC-AXIAL:1nF,10%,50V,Y5P,TP,3.5X1.9MM,-	
C530	2201-002063	C-CERAMIC,DISC:10nF,+80-20%,3KV,Y5V,TP,16x5,7		C913	2301-000445	C-FILM,PEF:4.7nF,5%,50V,TP,5.5x7x3mm,5mm	
C601	2401-001914	C-AL:1uF,20%,50V,BP,TP,5x11,5		C914	2401-002144	C-AL:47uF,20%,16V,GP,TP,5x11,5	
C602	2301-000445	C-FILM,PEF:4.7nF,5%,50V,TP,5.5x7x3mm,5mm		C915	2401-002144	C-AL:47uF,20%,16V,GP,TP,5x11,5	
C603	2401-001333	C-AL:470nF,20%,50V,GP,TP,5x11,5		C916	2201-000980	C-CERAMIC,DISC:30pF,5%,50V,CH,TP,5.0x3.0,5mm	
C604	2301-000192	C-FILM,PEF:1nF,5%,50V,TP,5.3x10mm,5mm		C917	2201-000980	C-CERAMIC,DISC:30pF,5%,50V,CH,TP,5.0x3.0,5mm	
C605	2401-001914	C-AL:1uF,20%,50V,BP,TP,5x11,5		C918	2301-000192	C-FILM,PEF:1nF,5%,50V,TP,5.3x10mm,5mm	
C606	2301-000445	C-FILM,PEF:4.7nF,5%,50V,TP,5.5x7x3mm,5mm		C919	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.	
C607	2401-001998	C-AL:1000uF,20%,25V,GP,TP,10x20,5mm		C920	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
C701	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.		C921	2202-000796	C-CERAMIC,MLC-AXIAL:1nF,10%,50V,Y5P,TP,3.5X1.9MM,-	
C702	2401-002144	C-AL:47uF,20%,16V,GP,TP,5x11,5		C922	2401-000302	C-AL:100uF,20%,25V,GP,TP,6.3x11,5	
C703	2202-000243	C-CERAMIC,MLC-AXIAL:33pF,5%,50V,SL,TP,3.5x19,-		C923	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.	
C705	2305-000289	C-FILM,MPEF:220nF,5%,63V,TP,-5mm		C924	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
C707	2401-000302	C-AL:100uF,20%,25V,GP,TP,6.3x11,5		C925	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.	
C709	2306-000122	C-FILM,MPPF:100nF,5%,50V,TP,7.3x4.0x5.0mm,		C926	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.	
C710	2401-000302	C-AL:100uF,20%,25V,GP,TP,6.3x11,5		C927	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.	
C711	2401-002235	C-AL:10uF,20%,16V,GP,TP,5x11mm,5mm		C928	2401-001333	C-AL:470nF,20%,50V,GP,TP,5x11,5	
C712	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5		CE01	2401-002597	C-AL:220uF,20%,35V,GP,TP,10x12,5,5	
C713	2301-000247	C-FILM,PEF:33nF,5%,50V,TP,8.1x4.5x13mm,5m		CE02	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0mm,	
C714	2301-000289	C-FILM,PEF:5.6nF,5%,50V,TP,7x6x3,5		CE03	2305-000470	C-FILM,MPEF:68nF,5%,100V,TP,-5mm	
C715	2401-000647	C-AL:2.2uF,20%,50V,BP,TP,5x11,5		CN501B	AA39-20604A	LEAD CONNECTOR-ASSY:-,YBNH250-09,YBNH05/04,5/4P,5	
C716	2401-000647	C-AL:2.2uF,20%,50V,BP,TP,5x11,5		CN603	3711-002642	CONNECTOR-HEADER:BOX,3P,1R,2.5mm,STRAIGHT,SN	
C717	2301-000289	C-FILM,PEF:5.6nF,5%,50V,TP,7x6x3,5		CN802	AA27-20004P	COIL-DEGAUSSING:-,22,18.9ohm,30T,L2480,E	
C718	2301-000247	C-FILM,PEF:33nF,5%,50V,TP,8.1x4.5x13mm,5m		CN901A	3711-002643	CONNECTOR-HEADER:BOX,4P,1R,2.5mm,STRAIGHT,SN	
C719	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5		CT01	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0mm,	
C720	2401-002235	C-AL:10uF,20%,16V,GP,TP,5x11mm,5mm		CT02	2401-000242	C-AL:100uF,20%,10V,GP,TP,5x11,5	
C721	2301-000175	C-FILM,PEF:15nF,5%,50V,TP,7.1x3.5x13mm,5m		CT04	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.	
C722	2305-000289	C-FILM,MPEF:220nF,5%,63V,TP,-5mm		CT06	2401-002144	C-AL:47uF,20%,16V,GP,TP,5x11,5	
C723	2301-000175	C-FILM,PEF:15nF,5%,50V,TP,7.1x3.5x13mm,5m		CT07	2301-000235	C-FILM,PEF:3.9nF,5%,50V,TP,6.5x3.0x5.5mm,	
C725	2305-000289	C-FILM,MPEF:220nF,5%,63V,TP,-5mm		CT08	2401-001914	C-AL:1uF,20%,50V,BP,TP,5x11,5	
C727	2305-000289	C-FILM,MPEF:220nF,5%,63V,TP,-5mm		CT09	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0mm,	
C730	2202-000231	C-CERAMIC,MLC-AXIAL:330pF,10%,50V,Y5P,TP,3.5x19,-		CW701	2503-000161	C-NETWORK:330pF,8,20%,50V,MCCB1H331MX8YT	
C731	2202-000231	C-CERAMIC,MLC-AXIAL:330pF,10%,50V,Y5P,TP,3.5x19,-		CW901	2503-000156	C-NETWORK:100pF,4,20%,50V	
C732	2202-000231	C-CERAMIC,MLC-AXIAL:330pF,10%,50V,Y5P,TP,3.5x19,-		D201	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,TP	
C733	2202-000231	C-CERAMIC,MLC-AXIAL:330pF,10%,50V,Y5P,TP,3.5x19,-		D202	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,TP	
C801	2306-000321	C-FILM,MPPF:470nF,5%,275V,TP,-22,5		D203	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,TP	
C802	2306-000321	C-FILM,MPPF:470nF,5%,275V,TP,-22,5		D204	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,TP	
C804	2201-000332	C-CERAMIC,DISC:2.2nF,20%,250VAC,Y5U,TP,11x7,7		D205	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,TP	
C805	2201-000332	C-CERAMIC,DISC:2.2nF,20%,250VAC,Y5U,TP,11x7,7		D209	0402-000216	DIODE-RECTIFIER:ERC24-06,600V,1.0A,DO-204	
C806	2401-002227	C-AL:330uF,20%,450V,GP,BK,35x45,10		D210	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,TP	
C807	2303-000163	C-FILM,PPF:2.2nF,5%,800V,TP,15x13x8.5,7,5		D217	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,TP	
C808	2401-002292	C-AL:47uF,20%,25V,WT,TP,8X11,5		D301	0402-001105	DIODE-RECTIFIER:ERB43-04SV1,400V,1.0A,-,TP	
C809	2301-000224	C-FILM,PEF:22nF,5%,50V,TP,7.4x3.9x13mm,5m		D302	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,TP	
C811	2301-000310	C-FILM,PEF:68nF,5%,50V,TP,8.0X8.5X4.0X5,5		D303	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,TP	
C812	2201-002002	C-CERAMIC,DISC:4700pF,20%,400V,+20%~-55%,TP,2		D304	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,TP	
C813	2201-002002	C-CERAMIC,DISC:4700pF,20%,400V,+20%~-55%,TP,2		D401	0402-000493	DIODE-RECTIFIER:1R5GU41,400V,1.5A,DO-15L,TP	
C814	2201-000683	C-CERAMIC,DISC:850pF,10%,1KV,Y5P,TP,10x5,5		D402	0402-000132	DIODE-RECTIFIER:1N4004,400V,1A,DO-41,TP	
C815	2401-003026	C-AL:330uF,20%,200V,GP,ST,22x35,10		D403	0402-000132	DIODE-RECTIFIER:1N4004,400V,1A,DO-41,TP	
C816	2401-000293	C-AL:100uF,+30-10%,200V,GP,TP,16x25		D404	0402-001012	DIODE-RECTIFIER:FMP-3FU,1500V,5A,TO-3PF	
C817	2201-000599	C-CERAMIC,DISC:560pF,10%,500V,Y5P,TP,7x4,5		D406	0402-001105	DIODE-RECTIFIER:ERB43-04SV1,400V,1.0A,-,TP	
C818	2401-000722	C-AL:2200uF,20%,25V,WT,TP,16x25,7,5		D407	0402-000216	DIODE-RECTIFIER:ERC24-06,600V,1.0A,DO-204	
C819	2201-000599	C-CERAMIC,DISC:560pF,10%,500V,Y5P,TP,7x4,5		D410	0402-000493	DIODE-RECTIFIER:1R5GU41,400V,1.5A,DO-15L,TP	
C820	2401-000722	C-AL:2200uF,20%,25V,WT,TP,16x25,7,5		D507	0402-001105	DIODE-RECTIFIER:ERB43-04SV1,400V,1.0A,-,TP	
C821	2301-000192	C-FILM,PEF:1nF,5%,50V,TP,5.3x10mm,5mm		D508	0402-001105	DIODE-RECTIFIER:ERB43-04SV1,400V,1.0A,-,TP	
C822	2201-000599	C-CERAMIC,DISC:560pF,10%,500V,Y5P,TP,7x4,5		D509	0402-001105	DIODE-RECTIFIER:ERB43-04SV1,400V,1.0A,-,TP	
C823	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11,5		D520	0402-000132	DIODE-RECTIFIER:1N4004,400V,1A,DO-41,TP	
C824	2305-000289	C-FILM,MPEF:220nF,5%,63V,TP,-5mm		D601	0403-000296	DIODE-ZENER:MTZ5.6B,5.6V,5.45-5.73V,500mW,	
C825	2306-000122	C-FILM,MPPF:100nF,5%,50V,TP,7.3x4.0x5.0mm,		D602	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,TP	
C826	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11,5		D801	0402-000213	DIODE-RECTIFIER:ERB12-06,600V,1.0A,DO-41,TP	

Electric Parts List

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
D802	0402-001160	DIODE-BRIDGE:D5SB60,600V,2.8A,SIP-4,ST		L202	2701-000197	INDUCTOR-AXIAL:5.6uH,10%,2.5x3.4mm	
D803	0402-001105	DIODE-RECTIFIER:ERB43-04SV1,400V,1.0A,-,TP		L205	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
D804	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,TP		L206	2701-000142	INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm	
D805	0402-000231	DIODE-RECTIFIER:FMG-G26S,600V,4A,TO-220F,ST		L207	2701-000142	INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm	
D806	0402-000493	DIODE-RECTIFIER:1R5GU41,400V,1.5A,DO-15L,TP		L208	2701-000142	INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm	
D807	0402-000233	DIODE-RECTIFIER:FML-G12S,200V,5A,-,-		L303	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
D809	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,TP		L401	AA27-40003J	COIL-HORIZ,WIDTH:-,3mH,ER14 20,P10.35,ST	
D810	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,TP		L402	AA27-30003L	COIL-LINERITY:-,73uH,DR12x15,0.55mm,-,BK,15%	
D813	0402-000493	DIODE-RECTIFIER:1R5GU41,400V,1.5A,DO-15L,TP		L403	3301-000287	CORE-FERRITE BEAD:AA,3.5x1.0x6.0mm,1500,2400G	
D901	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,TP		L404	AA27-40003L	COIL-HORIZ,WIDTH:-,1.0mH,DR14x20,2UEW0.45,ST	
D906	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,TP		L501	2901-000297	FILTER-EMI ON BOARD:-,3A,-,-,3.5x5,TP,-	
D907	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,TP		L601	3301-000287	CORE-FERRITE BEAD:AA,3.5x1.0x6.0mm,1500,2400G	
DE01	0402-001105	DIODE-RECTIFIER:ERB43-04SV1,400V,1.0A,-,TP		L603	3301-000287	CORE-FERRITE BEAD:AA,3.5x1.0x6.0mm,1500,2400G	
DT01	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,TP		L701	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
DT02	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,TP		L702	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
DT05	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,TP		L703	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
DV801	1405-000187	VARISTOR:750V,1250A,12.5x7mm,TP		L704	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
DV802	1405-000187	VARISTOR:750V,1250A,12.5x7mm,TP		L705	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
DZ201	0403-000297	DIODE-ZENER:MTZ6.2B,6.2V,5.96-6.27V,500mW,		L706	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
DZ202	0403-000297	DIODE-ZENER:MTZ6.2B,6.2V,5.96-6.27V,500mW,		L707	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
DZ203	0403-000298	DIODE-ZENER:MTZ6.8C,6.8V,6.66-7.01V,500mW,		L708	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
DZ204	0403-000662	DIODE-ZENER:MTZ3.0B,3.0V,3.01-3.22V,500mW,		L709	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
DZ205	0403-000551	DIODE-ZENER:MTZ3.9B,3.9V,3.89-4.16V,500mW,		L801	AA29-30002F	FILTER-LINE NOISE:-,6mH,2.45A,-,-	
DZ206	0403-000294	DIODE-ZENER:MTZ4.7B,4.7V,4.45-4.80V,500mW,		L802	3301-000287	CORE-FERRITE BEAD:AA,3.5x1.0x6.0mm,1500,2400G	
DZ210	0403-000659	DIODE-ZENER:MTZ2.0A,2V,1.88-2.10V,500mW,DO		L803	3301-000287	CORE-FERRITE BEAD:AA,3.5x1.0x6.0mm,1500,2400G	
DZ302	0403-000545	DIODE-ZENER:MTZ24B,24V,22.61-23.77V,500mW,		L804	2901-000299	FILTER-EMI ON BOARD:-,6A,UL/CSA,-,9x7.5,TP,-	
DZ303	0403-000545	DIODE-ZENER:MTZ24B,24V,22.61-23.77V,500mW,		L805	2701-001032	INDUCTOR-AXIAL:100uH,10%,5x14mm	
DZ304	0403-000545	DIODE-ZENER:MTZ24B,24V,22.61-23.77V,500mW,		L806	2901-000297	FILTER-EMI ON BOARD:-,3A,-,-,3.5x5,TP,-	
DZ305	0403-000494	DIODE-ZENER:MTZ39,39V,35.36-37.2V,500mW,DO		L807	3301-000287	CORE-FERRITE BEAD:AA,3.5x1.0x6.0mm,1500,2400G	
DZ306	0403-000700	DIODE-ZENER:TZP33A,33V,31-35V,1W,DO-41,TP		L808	3301-000287	CORE-FERRITE BEAD:AA,3.5x1.0x6.0mm,1500,2400G	
DZ402	0403-000300	DIODE-ZENER:MTZ8.2B,8.2V,7.78-8.19V,500mW,		L901	2701-000189	INDUCTOR-AXIAL:470nH,10%,2.5x3.4mm	
DZ403	0403-000698	DIODE-ZENER:TZP12A,12V,11.4-12.6V,1W,DO-41		L903	2701-000197	INDUCTOR-AXIAL:5.6uH,10%,2.5x3.4mm	
DZ505	0403-000563	DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500mW,		L904	2701-000211	INDUCTOR-AXIAL:68uH,10%,2.5x3.4mm	
DZ601	0403-000545	DIODE-ZENER:MTZ24B,24V,22.61-23.77V,500mW,		L905	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
DZ602	0403-000545	DIODE-ZENER:MTZ24B,24V,22.61-23.77V,500mW,		L906	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
DZ603	0403-000545	DIODE-ZENER:MTZ24B,24V,22.61-23.77V,500mW,		L907	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
DZ604	0403-000545	DIODE-ZENER:MTZ24B,24V,22.61-23.77V,500mW,		LD901	AA96-30001B	ASSY-LED,GUIDE:-,AA61-50055A,DL-G5RGA,-	
DZ701	0403-000563	DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500mW,		LT01	2901-000299	FILTER-EMI ON BOARD:-,6A,UL/CSA,-,9x7.5,TP,-	
DZ702	0403-000563	DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500mW,		LT02	2901-000299	FILTER-EMI ON BOARD:-,6A,UL/CSA,-,9x7.5,TP,-	
DZ703	0403-000563	DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500mW,		Q201	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,TP,120-	
DZ704	0403-000563	DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500mW,		Q202	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,TP,120-	
DZ705	0403-000563	DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500mW,		Q204	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,TP,120-	
DZ801	0403-000300	DIODE-ZENER:MTZ8.2B,8.2V,7.78-8.19V,500mW,		Q207	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,TP,120-	
DZ802	0403-000296	DIODE-ZENER:MTZ5.6B,5.6V,5.45-5.73V,500mW,		Q210	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,TP,120-	
DZ803	0403-000296	DIODE-ZENER:MTZ5.6B,5.6V,5.45-5.73V,500mW,		Q301	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,TP,120-	
DZ805	1203-001217	IC-POS1,ADJUST REG.:431,TO-92,3P4.58MIL,PLASTIC,2		Q302	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,TP,120-	
DZ807	0403-000296	DIODE-ZENER:MTZ5.6B,5.6V,5.45-5.73V,500mW,		Q401	0502-000298	TR-POWER:KSD73,NPN,30W,TO-220,-,120-240	
DZ808	0403-000562	DIODE-ZENER:MTZ7.5B,7.5V,7.07-7.45V,500mW,		Q402	0502-001007	TR-POWER:KSC2073-H2,NPN,25W,TO-220,ST,6	
DZ901	1203-000451	IC-VOLTAGE REGULATOR:33,TO-92,3P,-,PLASTIC,31/35V,2		Q403	0502-001135	TR-POWER:	
DZ904	0403-000563	DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500mW,		Q701	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,TP,120-	
DZ905	0403-000296	DIODE-ZENER:MTZ5.6B,5.6V,5.45-5.73V,500mW,		Q702	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,TP,120-	
DZ906	0403-000296	DIODE-ZENER:MTZ5.6B,5.6V,5.45-5.73V,500mW,		Q901	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,TP,120-	
DZT01	0403-000355	DIODE-ZENER:UZ5.1BSB,5.1V,4.97-5.18V,500mW		Q902	0504-000123	TR-DIGITAL:KSR1010,NPN,300mW,10K,TO-92,TP	
F801	3601-000281	FUSE-FERRULE:250V,4A,TL,GLASS,5.2x20mm		Q903	0504-000123	TR-DIGITAL:KSR1010,NPN,300mW,10K,TO-92,TP	
F801A	3602-000114	FUSE-HOLDER:-,30mohm		Q904	0504-000123	TR-DIGITAL:KSR1010,NPN,300mW,10K,TO-92,TP	
F801B	3602-000114	FUSE-HOLDER:-,30mohm		Q905	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,TP,120-	
F802	3601-001086	FUSE-FERRULE:125V,5A,FA,GLASS,2.4x7.5mm		Q907	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,TP,120-	
F803	3601-001086	FUSE-FERRULE:125V,5A,FA,GLASS,2.4x7.5mm		Q908	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,TP,120-	
GT804A	AA39-20010B	LEAD-CONNECTOR,ASSY:-,YFH800-01,S,1P,500,1617#22		QE01	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,TP,120-	
HC101	AA13-20004WIC-HYBRID:-,PAP103T,SIP,6P,PRE-AMP,TP		QT02	0504-000125	TR-DIGITAL:KSR1012,NPN,300mW,47K,TO-92,TP		
IC201	0904-001294	IC-BUS CONTROLLER:		QT03	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,TP,120-	
IC301	1204-000517	IC-VERTICAL DEF.:LA7845,SIP,7P,-,PLASTIC,40V,11		R201	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,-	
IC501	1201-001330	IC-VIDEO AMP:6108,ZSIP,9P,-,SINGLE,-,PLASTI		R202	2001-000786	R-CARBON:47KOHM,5%,1/8W,AA,TP,-	
IC601	1201-001064	IC-POWER AMP:7297,ZIP,15P,-,DUAL,32dB,PLAST		R203	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,-	
IC701	1204-000473	IC-AUDIO PROCESSOR:TDA9859,DIP,32P,-,PLASTIC,-,-		R204	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,-	
IC801	1203-001494	IC-PWM CONTROLLER:3S0680RF,T03PF-5L,5,210,PLASTI		R212	2001-000005	R-CARBON:390OHM,5%,1/8W,AA,TP,-	
IC802	0604-001038	PHOTO-COUPLER:TR,130-260%,200mW,DIP,4,ST		R214	2001-000793	R-CARBON:470OHM,5%,1/8W,AA,TP,-	
IC803	1203-001006	IC-VOLTAGE REGULATOR:78R05,TO-220F,4P,-,PLASTIC,4.8		R215	2001-000780	R-CARBON:470OHM,5%,1/8W,AA,TP,-	
IC804	1203-000644	IC-POS1,FIXED REG.:7630,SIP,10P,-,PLASTIC,5.1/8V,		R218	2001-000515	R-CARBON:220OHM,5%,1/8W,AA,TP,-	
IC901	AA13-30021MIC-MCU:-,SAA5291PS-135,8bit,SDIP,CK29		R219	2001-000343	R-CARBON:130OHM,5%,1/8W,AA,TP,-		
IC902	1103-000156	IC-EEPROM:24C04,512x8BIT,DIP,8P,300MIL,1		R220	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,-	
ICE01	1201-000191	IC-OP AMP:4558,DIP,8P,300MIL,DUAL,20V,mV		R221	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,-	
J206	3301-000287	CORE-FERRITE BEAD:AA,3.5x1.0x6.0mm,1500,2400G		R222	2701-000142	INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm	
JA701	3722-000183	JACK-SCART:21P,4mm,SN,BLK,NO		R223	2001-000617	R-CARBON:3.9MOHM,5%,1/8W,AA,TP,-	
L101	2701-000326	INDUCTOR-AXIAL:560nH,10%,2.3x3.4mm		R224	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-	
L102	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm		R225	2001-001026	R-CARBON:910OHM,5%,1/8W,AA,TP,-	
L103	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm		R226	2001-000793	R-CARBON:470OHM,5%,1/8W,AA,TP,-	

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
R230	2001-000331	R-CARBON:12KOHM,5%,1/8W,AA,TP-		R602	2008-001002	R-FUSIBLE(S):0.18ohm,5%,2W,AA,TP,3.9x10mm	
R233	2001-000780	R-CARBON:470OHM,5%,1/8W,AA,TP-		R603	2001-000472	R-CARBON:2.7KOHM,5%,1/8W,AA,TP-	
R234	2001-000780	R-CARBON:470OHM,5%,1/8W,AA,TP-		R604	2001-000331	R-CARBON:12KOHM,5%,1/8W,AA,TP-	
R235	2001-000780	R-CARBON:470OHM,5%,1/8W,AA,TP-		R605	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP-	
R237	2001-000007	R-CARBON:3KOHM,5%,1/8W,AA,TP-		R606	2001-000472	R-CARBON:2.7KOHM,5%,1/8W,AA,TP-	
R238	2001-001110	R-CARBON(S):240KOHM,5%,1/2W,AA,TP-		R607	2001-000331	R-CARBON:12KOHM,5%,1/8W,AA,TP-	
R239	2001-000008	R-CARBON:15KOHM,5%,1/8W,AA,TP-		R701	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP-	
R240	2001-001125	R-CARBON(S):300KOHM,5%,1/2W,AA,TP-		R702	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP-	
R241	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP-		R703	2001-000515	R-CARBON:220OHM,5%,1/8W,AA,TP-	
R243	2001-000232	R-CARBON:1.3KOHM,5%,1/8W,AA,TP-		R704	2001-000515	R-CARBON:220OHM,5%,1/8W,AA,TP-	
R246	2001-000273	R-CARBON:100KOHM,5%,1/8W,AA,TP-		R705	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP-	
R247	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP-		R706	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP-	
R248	2001-000793	R-CARBON:47OHM,5%,1/8W,AA,TP-		R707	2001-000515	R-CARBON:220OHM,5%,1/8W,AA,TP-	
R249	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP-		R708	2001-000515	R-CARBON:220OHM,5%,1/8W,AA,TP-	
R250	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP-		R709	2001-000969	R-CARBON:75OHM,5%,1/8W,AA,TP-	
R251	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP-		R712	2001-000539	R-CARBON:24KOHM,5%,1/8W,AA,TP-	
R252	2001-000563	R-CARBON:27KOHM,5%,1/8W,AA,TP-		R713	2001-000969	R-CARBON:75OHM,5%,1/8W,AA,TP-	
R253	2001-000591	R-CARBON:3.3KOHM,5%,1/8W,AA,TP-		R714	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP-	
R255	2001-000008	R-CARBON:15KOHM,5%,1/8W,AA,TP-		R715	2001-000969	R-CARBON:75OHM,5%,1/8W,AA,TP-	
R256	2004-001234	R-METAL:75Kohm,5%,1/8W,AA,TP,1.8x3.2mm		R716	2001-000660	R-CARBON:33KOHM,5%,1/8W,AA,TP-	
R257	2001-000563	R-CARBON:27KOHM,5%,1/8W,AA,TP-		R717	2001-000539	R-CARBON:24KOHM,5%,1/8W,AA,TP-	
R258	2004-001914	R-METAL:39Kohm,2%,1/8W,AA,TP,1.8x3.5mm		R718	2001-000969	R-CARBON:75OHM,5%,1/8W,AA,TP-	
R259	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP-		R719	2001-000527	R-CARBON:220OHM,5%,1/8W,AA,TP-	
R260	2001-001015	R-CARBON:9.1KOHM,5%,1/8W,AA,TP-		R720	2001-000387	R-CARBON:16KOHM,5%,1/8W,AA,TP-	
R261	2001-000331	R-CARBON:12KOHM,5%,1/8W,AA,TP-		R721	2001-000786	R-CARBON:47KOHM,5%,1/8W,AA,TP-	
R262	2001-001015	R-CARBON:9.1KOHM,5%,1/8W,AA,TP-		R722	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP-	
R301	2001-001045	R-CARBON(S):1.2KOHM,5%,1/2W,AA,TP-		R723	2001-000387	R-CARBON:16KOHM,5%,1/8W,AA,TP-	
R302	2001-001049	R-CARBON(S):1.3KOHM,5%,1/2W,AA,TP-		R724	2001-000786	R-CARBON:47KOHM,5%,1/8W,AA,TP-	
R303	2001-000016	R-CARBON(S):1OHM,5%,1/2W,AA,TP-		R725	2001-000969	R-CARBON:75OHM,5%,1/8W,AA,TP-	
R304	2008-001013	R-FUSIBLE(S):1.2ohm,5%,2W,AF,TP,3.9x10mm		R728	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP-	
R305	2003-002009	R-METAL OXIDE(S):390ohm,5%,2W,AF,TP,3.9x10mm		R729	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP-	
R308	2003-002009	R-METAL OXIDE(S):390ohm,5%,2W,AF,TP,3.9x10mm		R732	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP-	
R309	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP-		R733	2001-000969	R-CARBON:75OHM,5%,1/8W,AA,TP-	
R310	2001-000387	R-CARBON:16KOHM,5%,1/8W,AA,TP-		R734	2001-000969	R-CARBON:75OHM,5%,1/8W,AA,TP-	
R311	2001-000660	R-CARBON:33KOHM,5%,1/8W,AA,TP-		R735	2001-000969	R-CARBON:75OHM,5%,1/8W,AA,TP-	
R312	2001-000786	R-CARBON:47KOHM,5%,1/8W,AA,TP-		R736	2001-000660	R-CARBON:33KOHM,5%,1/8W,AA,TP-	
R313	2001-000449	R-CARBON:2.2KOHM,5%,1/8W,AA,TP-		R740	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
R314	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP-		R741	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
R315	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP-		R801	2002-001011	R-COMPOSITION:3.3Mohm,10%,1/2W,AA,TP,3.7x9mm	
R316	2001-000660	R-CARBON:33KOHM,5%,1/8W,AA,TP-		R802	2003-000994	R-METAL OXIDE(S):33Kohm,5%,2W,AF,TP,3.9x10mm	
R317	2001-000449	R-CARBON:2.2KOHM,5%,1/8W,AA,TP-		R803	2003-000994	R-METAL OXIDE(S):33Kohm,5%,2W,AF,TP,3.9x10mm	
R404	2008-001013	R-FUSIBLE(S):1.2ohm,5%,2W,AF,TP,3.9x10mm		R804	2001-001150	R-CARBON(S):470KOHM,5%,1/2W,AA,TP-	
R405	2001-001138	R-CARBON(S):390OHM,5%,1/2W,AA,TP-		R805	2001-001150	R-CARBON(S):470KOHM,5%,1/2W,AA,TP-	
R406	2003-002008	R-METAL OXIDE(S):18Kohm,5%,2W,AF,TP,3.9x10mm		R806	2003-001023	R-METAL OXIDE(S):120ohm,0.05,2W,AF,TP,3.9x10mm	
R407	2003-001025	R-METAL OXIDE(S):15Kohm,5%,2W,AF,TP,3.9x10mm		R807	2001-001178	R-CARBON(S):680OHM,5%,1/2W,AA,TP-	
R409	2008-000264	R-FUSIBLE(S):1ohm,5%,1W,AF,TP,3.9x10mm		R808	2002-001011	R-COMPOSITION:3.3Mohm,10%,1/2W,AA,TP,3.7x9mm	
R410	2001-001114	R-CARBON(S):270OHM,5%,1/2W,AA,TP-		R809	2002-001013	R-COMPOSITION:4.7Mohm,10%,1/2W,AA,TP,3.7x9mm	
R411	2001-001070	R-CARBON(S):120OHM,5%,1/2W,AA,TP-		R810	2003-000782	R-METAL OXIDE(S):7.5Kohm,5%,2W,AA,TP,4x12mm	
R412	2001-000020	R-CARBON(S):220OHM,5%,1/2W,AA,TP-		R811	2003-000462	R-METAL OXIDE(S):10Kohm,5%,2W,AA,TP,4x12mm	
R413	2008-000251	R-FUSIBLE(S):0.27ohm,10%,2W,AF,TP,3.9x10mm		R813	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP-	
R414	2008-000278	R-FUSIBLE(S):82ohm,5%,2W,AA,TP,3.9x10mm		R814	2001-000449	R-CARBON:2.2KOHM,5%,1/8W,AA,TP-	
R415	2008-000254	R-FUSIBLE(S):0.68ohm,5%,2W,AF,TP,3.9x10mm		R815	2004-001889	R-METAL(S):127Kohm,1%,1/2W,AA,TP,2.5x6.5mm	
R417	2001-001164	R-CARBON(S):56KOHM,5%,1/2W,AA,TP-		R816	2004-001983	R-METAL(S):2.49Kohm,1%,1/2W,AA,TP,2.4x6.4	
R418	2004-001967	R-METAL(S):68Kohm,1%,1/2W,AA,TP,2.5x6.5mm		R819	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP-	
R419	2004-001390	R-METAL(S):1Kohm,2%,1/2W,AA,TP,2.4x6.4mm		R820	2008-001047	R-FUSIBLE(S):68ohm,5%,2W,AF,TP,3.9x10mm	
R420	2001-001114	R-CARBON(S):270OHM,5%,1/2W,AA,TP-		R821	2008-000271	R-FUSIBLE(S):3.3ohm,5%,2W,AA,TP,3.9x10mm	
R421	2001-001043	R-CARBON(S):0OHM,5%,1/2W,AA,TP-		R822	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP-	
R422	2008-001013	R-FUSIBLE(S):1.2ohm,5%,2W,AF,TP,3.9x10mm		R823	2008-000264	R-FUSIBLE(S):1ohm,5%,1W,AF,TP,3.9x10mm	
R424	2001-001043	R-CARBON(S):0OHM,5%,1/2W,AA,TP-		R824	2001-001125	R-CARBON(S):300KOHM,5%,1/2W,AA,TP-	
R425	2001-001043	R-CARBON(S):0OHM,5%,1/2W,AA,TP-		R826	2001-001153	R-CARBON(S):47OHM,5%,1/2W,AA,TP-	
R428	2001-001043	R-CARBON(S):0OHM,5%,1/2W,AA,TP-		R901	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP-	
R429	2001-001043	R-CARBON(S):0OHM,5%,1/2W,AA,TP-		R902	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP-	
R430	2001-001043	R-CARBON(S):0OHM,5%,1/2W,AA,TP-		R903	2001-000066	R-CARBON(S):10KOHM,5%,1/2W,AA,TP-	
R501	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP-		R904	2004-000218	R-METAL:10Kohm,1%,1/8W,AA,TP,1.8x3.2mm	
R502	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP-		R905	2004-000218	R-METAL:10Kohm,1%,1/8W,AA,TP,1.8x3.2mm	
R503	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP-		R906	2004-000218	R-METAL:10Kohm,1%,1/8W,AA,TP,1.8x3.2mm	
R505	2008-000266	R-FUSIBLE(S):1ohm,5%,2W,AF,TP,3.9x10mm		R908	2001-000241	R-CARBON:1.5KOHM,5%,1/8W,AA,TP-	
R506	2008-000299	R-FUSIBLE(S):47ohm,5%,2W,AF,TP,3.9x10mm		R909	2001-000472	R-CARBON:2.7KOHM,5%,1/8W,AA,TP-	
R507	2001-000490	R-CARBON:200OHM,5%,1/8W,AA,TP-		R910	2001-000924	R-CARBON:680OHM,5%,1/8W,AA,TP-	
R508	2001-000490	R-CARBON:200OHM,5%,1/8W,AA,TP-		R911	2001-000214	R-CARBON:1.1KOHM,5%,1/8W,AA,TP-	
R509	2001-000490	R-CARBON:200OHM,5%,1/8W,AA,TP-		R912	2001-000449	R-CARBON:2.2KOHM,5%,1/8W,AA,TP-	
R510	2002-001009	R-COMPOSITION:2.7Kohm,10%,1/2W,AA,TP,3.7X9.0		R913	2001-000241	R-CARBON:1.5KOHM,5%,1/8W,AA,TP-	
R517	2002-001009	R-COMPOSITION:2.7Kohm,10%,1/2W,AA,TP,3.7X9.0		R914	2001-000472	R-CARBON:2.7KOHM,5%,1/8W,AA,TP-	
R518	2002-001009	R-COMPOSITION:2.7Kohm,10%,1/2W,AA,TP,3.7X9.0		R918	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP-	
R519	2002-001009	R-COMPOSITION:2.7Kohm,10%,1/2W,AA,TP,3.7X9.0		R919	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP-	
R520	2001-001062	R-CARBON(S):10MOHM,5%,1/2W,AA,TP-		R920	2001-000273	R-CARBON:100KOHM,5%,1/8W,AA,TP-	
R601	2008-001002	R-FUSIBLE(S):0.18ohm,5%,2W,AA,TP,3.9x10mm		R921	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP-	

Loc. No.	Code No.	Description ; Specification	Remark
R922	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-	
R923	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,-	
R924	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,-	
R925	2001-000924	R-CARBON:680OHM,5%,1/8W,AA,TP,-	
R926	2001-000924	R-CARBON:680OHM,5%,1/8W,AA,TP,-	
R927	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
R928	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
R929	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
R930	2001-000628	R-CARBON:300OHM,5%,1/8W,AA,TP,-	
R932	2001-000780	R-CARBON:470OHM,5%,1/8W,AA,TP,-	
R933	2001-000449	R-CARBON:2.2KOHM,5%,1/8W,AA,TP,-	
R934	2001-000449	R-CARBON:2.2KOHM,5%,1/8W,AA,TP,-	
R935	2001-000780	R-CARBON:470OHM,5%,1/8W,AA,TP,-	
R936	2001-000449	R-CARBON:2.2KOHM,5%,1/8W,AA,TP,-	
R937	2001-001062	R-CARBON(S):10MOHM,5%,1/2W,AA,TP,-	
R939	2001-000006	R-CARBON:2.4KOHM,5%,1/8W,AA,TP,-	
R941	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,-	
R942	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-	
R943	2001-000793	R-CARBON:47OHM,5%,1/8W,AA,TP,-	
R945	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,-	
R948	2001-000449	R-CARBON:2.2KOHM,5%,1/8W,AA,TP,-	
R951	2001-000449	R-CARBON:2.2KOHM,5%,1/8W,AA,TP,-	
R953	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,-	
R954	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,-	
R955	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-	
RE01	2004-001390	R-METAL(S):1Kohm,2%,1/2W,AA,TP,2.4x6.4mm	
RE02	2004-001914	R-METAL:39Kohm,2%,1/8W,AA,TP,1.8x3.5mm	
RE03	2001-000066	R-CARBON(S):10KOHM,5%,1/2W,AA,TP,-	
RE04	2001-000066	R-CARBON(S):10KOHM,5%,1/2W,AA,TP,-	
RE05	2001-000052	R-CARBON(S):3.3KOHM,5%,1/2W,AA,TP,-	
RE06	2001-001050	R-CARBON(S):1.5KOHM,5%,1/2W,AA,TP,-	
RE07	2003-002037	R-METAL OXIDE(S):270ohm,5%,2W,AF,TP,3.9x10mm	
RE08	2001-001120	R-CARBON(S):3.3OHM,5%,1/2W,AA,TP,-	
RE09	2001-001125	R-CARBON(S):300KOHM,5%,1/2W,AA,TP,-	
RE10	2001-001125	R-CARBON(S):300KOHM,5%,1/2W,AA,TP,-	
RM901	AA59-60001U	MODULE-REMOCON:-,ORC-50VF/SR-12V,38KHz,940nm,	
RP802	1404-001045	THERMISTOR-NTC:4.7ohm,15%,2900K,35.0mWV,TP	
RP803	1404-001048	THERMISTOR-PTC:7ohm,30%,200/220V,270V,19A,-,B	
RT01	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,-	
RT02	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,-	
RT06	2001-000563	R-CARBON:27KOHM,5%,1/8W,AA,TP,-	
RT07	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-	
RT08	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,-	
RT13	2001-000005	R-CARBON:390OHM,5%,1/8W,AA,TP,-	
RT14	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-	
RT15	2003-000676	R-METAL OXIDE(S):39ohm,5%,2W,AA,TP,4x12mm	
RT16	2001-000347	R-CARBON:13KOHM,5%,1/8W,AA,TP,-	
RT18	2001-000786	R-CARBON:47KOHM,5%,1/8W,AA,TP,-	
RT19	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,-	
RT20	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,-	
RW901	2011-000157	R-NETWORK:10K,5%,1/8W,A,SIP,6PBK	
SF101	2904-000302	FILTER-SAW AV:38.90MHz,-,ST,13.9dB,PAL-B/G,-	
SW801	3403-000179	SWITCH-PUSH:250V,5A,DPST,-,JPW-2104B	
SW901	3404-000244	SWITCH-TACT:15V,20mA,90-170gf,7.5x7mm,SPST	
SW902	3404-000244	SWITCH-TACT:15V,20mA,90-170gf,7.5x7mm,SPST	
SW903	3404-000244	SWITCH-TACT:15V,20mA,90-170gf,7.5x7mm,SPST	
SW904	3404-000244	SWITCH-TACT:15V,20mA,90-170gf,7.5x7mm,SPST	
SW905	3404-000244	SWITCH-TACT:15V,20mA,90-170gf,7.5x7mm,SPST	
T401	AA26-50001R	TRANS-HORIZ DRIVE:-,80MH,580UH,4UH,G11A EI19,ST	
T444	AA26-30005X	TRANS-FLYBACK:-,FSV-21B005A,22,130V	
T801	AA26-20007W	TRANS-SWITCHING:-,90-260V,130/15.5/12/8V,VDE,S	
TU101	AA40-10006H	TUNER-V/S:TELE4-108A,PAL-B/G,TR,181CH	
V999	3704-001105	SOCKET-CRT:11P,20PI,26.5PI,NL,-	
X202	2801-000274	CRYSTAL-UNIT:4.433619MHz,30ppm,28-AAM,20pF,	
X203	2801-000226	CRYSTAL-UNIT:3.579545MHz,20ppm,28-AAM,15pF,	
XT01	2801-003433	CRYSTAL-UNIT:12MHz,30ppm,28-AAA,30pF,30ohm,	
Z208	2903-000181	FILTER-CERAMIC:TR,5.5MHz,-,-,TP,TPS5.5MB-TF	

ASSY-SOUND

* AA95-00027A ASSY-SOUND:-,-,S51A,CK,MONO/LINE-STEREO,EUROPE

CFM01	2904-001054	FILTER-SAW AV:38.9MHz,SIP5P,-,13.9dB,NTSC-M/
CFM02	2904-001010	FILTER-SAW AV:32.9-33.4MHz,SIP5P,ST,14.4dB,P
CM01	2301-000383	C-FILM,PEF:10nF,5%,50V,TP,6x7x3.2mm,5mm
CM02	2401-000603	C-AL:1uF,20%,50V,GP,TP,5x11,5

Loc. No.	Code No.	Description ; Specification	Remark
CM03	2401-002300	C-AL:47uF,20%,50V,GP,TP,6.3x11,5	
CM04	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0mm,	
CM05	2202-000127	C-CERAMIC,MLC-AXIAL:10nF,+80-20%,25V,Y5V,TP,-,7.5	
CM06	2202-000127	C-CERAMIC,MLC-AXIAL:10nF,+80-20%,25V,Y5V,TP,-,7.5	
CM07	2301-000224	C-FILM,PEF:22nF,5%,50V,TP,7.4x3.9x13mm,5m	
CM08	2301-000383	C-FILM,PEF:10nF,5%,50V,TP,6x7x3.2mm,5mm	
CM09	2202-000127	C-CERAMIC,MLC-AXIAL:10nF,+80-20%,25V,Y5V,TP,-,7.5	
CM10	2202-000127	C-CERAMIC,MLC-AXIAL:10nF,+80-20%,25V,Y5V,TP,-,7.5	
CM11	2202-000127	C-CERAMIC,MLC-AXIAL:10nF,+80-20%,25V,Y5V,TP,-,7.5	
CM12	2401-001333	C-AL:470nF,20%,50V,GP,TP,5x11,5	
CM13	2401-001333	C-AL:470nF,20%,50V,GP,TP,5x11,5	
CM14	2401-000660	C-AL:2.2uF,20%,50V,GP,TP,5x11,5	
CM15	2401-000660	C-AL:2.2uF,20%,50V,GP,TP,5x11,5	
CM16	2401-000660	C-AL:2.2uF,20%,50V,GP,TP,5x11,5	
CM17	2401-000660	C-AL:2.2uF,20%,50V,GP,TP,5x11,5	
CNN01	3711-002704	CONNECTOR-HEADER:NOWALL,6P,1R,2.5mm,ANGLE,SN	
CNN02	3711-002705	CONNECTOR-HEADER:NOWALL,7P,1R,2.5mm,ANGLE,SN	
DM01	0401-001024	DIODE-SWITCHING:BAW75,25V,300mA,DO-35,TP	
DM02	0401-001024	DIODE-SWITCHING:BAW75,25V,300mA,DO-35,TP	
DM03	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,TP	
DM04	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,TP	
HN01	AA61-10068A	BRACKET-PCB:-,M2160,SPT,TO,3,-,-,-	
ICM01	1204-001491	IC-SOUND PROCESSOR:LA7566S,DIP,24P,300MIL,PLASTIC,1	
JM01	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
LM02	2701-000202	INDUCTOR-AXIAL:560nH,10%,2.5x3.4mm	
QM01	0504-000125	TR-DIGITAL:KSR1012,NPN,300mW,47K,TO-92,TP	
QM04	0504-000123	TR-DIGITAL:KSR1010,NPN,300mW,10K,TO-92,TP	
QM05	0504-000123	TR-DIGITAL:KSR1010,NPN,300mW,10K,TO-92,TP	
QM06	0504-000123	TR-DIGITAL:KSR1010,NPN,300mW,10K,TO-92,TP	
QM07	0504-000119	TR-DIGITAL:KSR1004,NPN,300mW,47K-47K,TO-9	
QM08	0504-000119	TR-DIGITAL:KSR1004,NPN,300mW,47K-47K,TO-9	
QM09	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,TP,120-	
RM01	2001-000411	R-CARBON:18KOHM,5%,1/8W,AA,TP,-	
RM02	2001-000362	R-CARBON:150OHM,5%,1/8W,AA,TP,-	
RM03	2001-000449	R-CARBON:2.2KOHM,5%,1/8W,AA,TP,-	
RM04	2001-000449	R-CARBON:2.2KOHM,5%,1/8W,AA,TP,-	
RM05	2001-000449	R-CARBON:2.2KOHM,5%,1/8W,AA,TP,-	
RM06	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-	
RM09	2001-000786	R-CARBON:47KOHM,5%,1/8W,AA,TP,-	
RM10	2001-000786	R-CARBON:47KOHM,5%,1/8W,AA,TP,-	
RM11	2001-000003	R-CARBON:330OHM,5%,1/8W,AA,TP,-	
RM13	2001-000003	R-CARBON:330OHM,5%,1/8W,AA,TP,-	
RM15	2001-000857	R-CARBON:560OHM,5%,1/8W,AA,TP,-	
RM16	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,-	
RM17	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,-	
RM18	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,-	
RM19	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,-	
RM20	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,-	
RM21	2001-000449	R-CARBON:2.2KOHM,5%,1/8W,AA,TP,-	
RM22	2001-000449	R-CARBON:2.2KOHM,5%,1/8W,AA,TP,-	
RM23	2001-000449	R-CARBON:2.2KOHM,5%,1/8W,AA,TP,-	
RM24	2001-000008	R-CARBON:15KOHM,5%,1/8W,AA,TP,-	
RM25	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,-	
TM01	AA26-10006L	TRANS-IF:-,7MG,VIF,-,7mm,39pF,38.9MHz,S	
ZM01	2903-000200	FILTER-CERAMIC:BP,6.5MHz,+,-70KHz,6dB,-,TP,-	
ZM03	2903-000185	FILTER-CERAMIC:BP,5.5MHz,+,-75KHz,6dB,-,TP,-	

ASSY-R/G/B SWITCHING

* AA95-90038K ASSY-R/G/B SWITCHING:-,-,S51A,PHILIPS MICOM ALL,-,-

CNS01	3711-002702	CONNECTOR-HEADER:NOWALL,4P,1R,2.5mm,ANGLE,SN
CNS02	3711-002703	CONNECTOR-HEADER:NOWALL,5P,1R,2.5mm,ANGLE,SN
CNS03	AA39-20052F	LEAD CONNECTOR-ASSY:-,YBNH025-04,YSH025-04,4P,200
CS01	2401-002619	C-AL:47uF,20%,25V,GP,TP,5x11,5
CS02	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0mm,
CS03	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.
CS04	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.
CS05	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.
CS06	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.
CS07	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.
CS08	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.
DS01	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,TP
ICS01	1001-000223	IC-VIDEO SWITCH:TEA5114A,-,DIP,16P,334MIL,SING
RS01	2001-000003	R-CARBON:330OHM,5%,1/8W,AA,TP,-
RS04	2001-000003	R-CARBON:330OHM,5%,1/8W,AA,TP,-

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
RS06	2001-000003	R-CARBON:330OHM,5%,1/8W,AA,TP,-					
RS07	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-					
RS08	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-					
RS09	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-					
RS10	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-					
RS11	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-					
RS12	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-					
RS13	2001-000003	R-CARBON:330OHM,5%,1/8W,AA,TP,-					
RS14	2001-000003	R-CARBON:330OHM,5%,1/8W,AA,TP,-					
RS15	2001-000003	R-CARBON:330OHM,5%,1/8W,AA,TP,-					
RS16	2001-000003	R-CARBON:330OHM,5%,1/8W,AA,TP,-					
RS17	2001-000003	R-CARBON:330OHM,5%,1/8W,AA,TP,-					
RS18	2001-000003	R-CARBON:330OHM,5%,1/8W,AA,TP,-					

ASSY-POWER,CORD



AA39-10006X POWER-CORD:-,KKP419C,KLCE-2F,2,286MT,3P,V
AA61-20284A HOLDER:-,P-CORD,PP,VO,BLK,KE-002

REMOCON

*

AA59-10116B REMOCON:-,TM59,SS,SZM503AT,25,-,L/GR

ASSY-SPEAKER

3001-001072 SPEAKER:5W,16ohm,90dB,180Hz
AA39-20500C LEAD CONNECTOR-ASSY:-,67096-003,REC,3(2),600,1007#

ASSY-CRT



AA03-10028MCRT-COLOR:-,A53QCA891X001(B),+380mG,22,

ASSY-ACCESSORY

AA26-90001C TRANS-MATCHING:-,300ohm/75ohm,PAL,40-890MHz
AA42-10001V ANT-ROD:-,3S,620mm,BRN,UL/CSA
AA68-00044A MANUAL-USERS:S51A,N-RUS,-,B5,W/P100(G),-