

SD 102	Si-N	NF/S-L, 50V, 3A, 62W, 15MHz	23a	2N3055	23a
SD 112	C-Di	=BA 102	31a	-	
SD 113	C-Di	FM-AFC, 35...55pF(0V)	31a	-	
SD 114	C-Di	AFC	31a	-	
SD 115	C-Di	FM-AFC, 10...16pf(4V)	31a	-	
SD 116	C-Di	FM-AFC, 6...12pF(4V)	31a	-	
SD 117	C-Di	FM-AFC, 4...8pF(4V)	31a	-	
SD 168	Si-N	TV-SN, -/300V, 3A, 12,5W(Tc=95°)	23a	BUW 11A	18j
SD 335	Si-N	NF/S-L, 45V, 1,5A, 12,5W, 210MHz	14h	BD 139	14h
SD 336	Si-P	NF/S-L, 45V, 1,5A, 12,5W, 210MHz	14h	BD 140	14h
SD 337	Si-N	=SD 335: 60V	14h	BD 139	14h
SD 338	Si-P	=SD 336: 60V	14h	BD 140	14h
SD 339	Si-N	=SD 335: 80V	14h	BD 139	14h
SD 340	Si-P	=SD 336: 80V	14h	BD 140	14h
SD 345	Si-N	NF/S-L, 45V, 3A, 20W, >60MHz	14h	-	
SD 346	Si-P	NF/S-L, 45V, 3A, 20W, >60MHz	14h	-	
SD 347	Si-N	=SD 345: 60V	14h	-	
SD 348	Si-P	=SD 346: 60V	14h	-	
SD 349	Si-N	=SD 345: 80V	14h	-	
SD 350	Si-P	=SD 346: 80V	14h	-	
SD 401	Si-N	NF/S-L, 45V, 10A, 90W	17j	BD 809	17j
SD 402	Si-P	NF/S-L, 45V, 10A, 90W	17j	BD 810	17j
SD 403	Si-N	=SD 401: 60V	17j	BD 809	17j
SD 404	Si-P	=SD 402: 60V	17j	BD 810	17j
SD 405	Si-N	=SD 401: 80V	17j	BD 809	17j
SD 406	Si-P	=SD 402: 80V	17j	BD 810	17j
SD 407	Si-N	=SD 401: 100V	17j	-	
SD 408	Si-P	=SD 402: 100V	17j	-	
SD 409	Si-N	=SD 401: 120V	17j	-	
SD 410	Si-P	=SD 402: 120V	17j	-	
SD 451	Si-N-Darl	NF/S-L, 45V, 10A, 90W, B>1000	17j	BDW 93 C	17j
SD 452	Si-P-Darl	NF/S-L, 45V, 10A, 90W, B>1000	17j	BDW 94 C	17j
SD 453	Si-N-Darl	=SD 451: 60V	17j	BDW 93 C	17j
SD 454	Si-P-Darl	=SD 452: 60V	17j	BDW 94 C	17j
SD 455	Si-N-Darl	=SD 451: 80V	17j	BDW 93 C	17j
SD 456	Si-P-Darl	=SD 452: 80V	17j	BDW 94 C	17j
SD 457	Si-N-Darl	=SD 451: 100V	17j	BDW 93 C	17j
SD 458	Si-P-Darl	=SD 452: 100V	17j	BDW 94 C	17j
SD 459	Si-N-Darl	=SD 451: 120V	17j	-	
SD 460	Si-P-Darl	=SD 452: 120V	17j	-	
SD 600	Si-N	S-L, 120/80V, 3A, 10W(Tc=80°)	23a	-	
SD 601	Si-N	S-L, 60/50V, 3A, 10W(Tc=80°)	23a	-	
SD 602	Si-N	S-L, 120/80V, 3A, 10W(Tc=80°)	23a	-	
SD 802	Si-N	S-L, 150/100V, 5A, 50W	23a	-	
SD 812	Si-N	S-L, 500/200V, 4A, 50W	23a	BU 426 A	18j
SDA 1000	LIN-IC	RDS, ARI-Decoder	20-DIP	-	
SDA 1010	LIN-IC	RDS, Decoder	22-DIP	-	
SDA 2002	LIN/MOS-IC	TV, PLL-Frequenzsynthese	18-DIP	-	**
SDA 2005	MOS-IC	TV, Einblendg./character insert contr.	18-DIP	-	**
SDA 2006	EAROM-IC	TV, EAROM, 512Bit (32x16Bit)	18-DIP	-	**
SDA 2007	MOS-IC	IR-FB Empfänger/receiver	18-DIP	-	**
SDA 2008	MOS-IC	IR-FB Sender/transmitter	18-DIP	-	
SDA 2010	µC-IC	8-Bit µComp, 2kB ROM, 64Byte RAM	40-DIP	-	
SDA 2011	µC-IC	8-Bit µComp, 2kB ROM, 64Byte RAM	40-DIP	-	
SDA 2014	LIN-IC	BCD LED-Display-Tr., 2/4 digits	18-DIP	-	
SDA 2020	µC-IC	8-Bit µComp., 1kB ROM, 64Byte RAM	28-DIP	-	**