

Model	L _{FBT} (mH)	+B (Vdc)	EHT (kV)	Beam (mA)	τ (μ s)	Focus (kV)	Screen (kV)	Video (Vdc)	VH (Vrms)	V1 (Vdc)	V2 (Vdc)	V3 (Vdc)	V4 (Vdc)	Earth Pin No.	L _{DY} (mH)	C _T (nF)
PET-22-16	3.35 (1-10)	118	24.7	1.0	11.0	5.0 - 8.5	0.2 -1.2	158.0 at10 k Ω pin 2	7.5 at 10 Ω pin 3	21.4 at 60 Ω pin 5				4,7,11	2.7	5.6
PET-22-17	2.8 (1-10)	85	24.0	1.0	11.2	5.0-8.2	0.2-1.2	159.0 at10 k Ω pin 2	6.8 at 10 Ω pin 3	21.0 at 60 Ω pin 5				4,7,11	1.5	8.8
PET-22-21	3.3 (2-1)	115	24.1	1.0	11.1	5.0-8.6	0.2-1.3	190.0 at 5k Ω pin 4	7.0 at10 Ω pin 5	9.4 at40 Ω pin 7	16.7 at40 Ω pin 9	45.9 at 1k Ω pin 6		8,10,11	2.0	7.7
PET-22-22B	3.45 (2 - 1)	125	23.6	1.0	11.2	5.0 - 8.1	0.2 -1.3	199 at10 k Ω pin 7	7.55 at 10 Ω pin 9	46.2 at 4 k Ω pin 6	13.4 at 60 Ω pin 3	16.9 at120 Ω pin 4		5,8,10, 11	2.2	8.2
PET-22-23	3.22 (3 - 1)	115	24.0	1.0	11.8	5.0 - 8.4	0.2 -1.2	190 at10 k Ω pin 2	7.0 at 10 Ω pin 9	14.6 at 60 Ω pin 5	49.7 at 4 k Ω pin 7			4,8,11	2.2	8.6
PET-22-25	3.55 (3-1)	145	27.1	1.0	11.4	5.7 – 9.3	0.2 – 1.2	192 at 10k Ω pin 2	7.4 at 20 Ω pin 9	16.3 at 55 Ω pin 5	47.1 at 3k Ω pin 7			4,8,11	1.5	11.6
PET-22-A5	3.2 (2-1)	112	22.0	1.0	11.7	4.5-7.7	0.2-1.2	146 at 10k Ω pin 10	6.1 at10 Ω pin 9	20.6 at80k Ω pin 5	12.2 at60 Ω pin 7	27.3 at 120 Ω pin 6		3,4,8,11	2.7	7.2
PET-22-B6	3.22 (3-1)	115	24.2	1.0	11.3	5.1-8.5	0.2-1.2	192 at10k Ω pin 2	6.9 at10 Ω pin 9	74.0 at80 Ω pin 10	14.2 at60 Ω pin 5	26.5 at120 Ω pin 6	37.1 at4.0k Ω pin 7	4,8,11	2.2	8.6