

## REPLACEMENT PARTS LIST

**CAUTION:** BEFORE REPLACING ANY OF THESE COMPONENTS,  
READ CAREFULLY THE **SAFETY PRECAUTIONS** IN THIS MANUAL.

\* NOTE : **S** SAFETY Mark   
**AL** ALTERNATIVE PARTS

MODEL: Flatron 795FT plus, 未来窗 795FT plus		DATE: 1999. 2. 5.			
*S	*AL	LOC. NO.	PART NO.	DESCRIPTION / SPECIFICATION	REMARK
<b>MAIN BOARD</b>					
<b>CAPACITORS</b>					
		C401	0CN1040K949	CAPACITOR, TUBULAR(HIGH DIELEC), 0.1M 50V Z F TA52	
		C402	181-288M	CAPACITOR, POLYESTER, MKT 63V 105KTR PHS15105	
		C407	181-304W	CAPACITOR, POLYPROPYLENE, 473J 20.0*16.0*10.0*10.0 400V	
		C411	0CE476ER618	CAPACITOR, AL.ELECTROLYTIC, 47UF KMG 250V M FL TP 5	
		C421	0CE6856K618	CAPACITOR, AL.ELECTROLYTIC, 6.8 UF SMS,SG 50V M FL	
		C424	181-288D	CAPACITOR, POLYESTER, MKT 100V 473JTR PHS26473	
		C427	0CE1076H618	CAPACITOR, AL.ELECTROLYTIC, 100M SMS 25V M FM5 TP(5)	
		C428	0CN1040K949	CAPACITOR, TUBULAR(HIGH DIELEC), 0.1M 50V Z F TA52	
		C429	0CN1020K519	CAPACITOR, TUBULAR(HIGH DIELEC), 1000P 50V K B TA52	
		C431	0CE3376H618	CAPACITOR, AL.ELECTROLYTIC, 330M SMS 25V M FL TP(5)	
		C432	0CN1040K949	CAPACITOR, TUBULAR(HIGH DIELEC), 0.1M 50V Z F TA52	
		C433	0CN1210K519	CAPACITOR, TUBULAR(HIGH DIELEC), 120P 50V K B TA52	
		C434	0CQ1021N419	CAPACITOR, POLYESTER, 1000P 100V J POLY NI TP	
		C435	181-475A	CAPACITOR, POLYPROPYLENE, 102J 11.5*10.0*6.0*5.0 100V	
		C436	0CN5610K519	CAPACITOR, TUBULAR(HIGH DIELEC), 560P 50V K B TA52	
		C437	0CE3376H618	CAPACITOR, AL.ELECTROLYTIC, 330M SMS 25V M FL TP(5)	
		C501	0CE1076H618	CAPACITOR, AL.ELECTROLYTIC, 100M SMS 25V M FM5 TP(5)	
		C502	0CN1020K519	CAPACITOR, TUBULAR(HIGH DIELEC), 1000P 50V K B TA52	
		C503	0CQ1021N419	CAPACITOR, POLYESTER, 1000P 100V J POLY NI TP	
		C504	0CE1056K618	CAPACITOR, AL.ELECTROLYTIC, 1.0U SMS 50V M FM5 TP5	
		C505	0CE4766H618	CAPACITOR, AL.ELECTROLYTIC, 47M SMS 25V M FL TP(5)	
		C506	0CN5610K519	CAPACITOR, TUBULAR(HIGH DIELEC), 560P 50V K B TA52	
		C507	0CC5600K415	CAPACITOR, CERAMIC (TEMP. COMPENSATE), 56P 50V	
		C508	0CN4710K519	CAPACITOR, TUBULAR(HIGH DIELEC), 470P 50V K B TA52	
		C511	181-288J	CAPACITOR, POLYESTER, MKT 100V 563JTR PHS26563	
		C512	0CE2266K618	CAPACITOR, AL.ELECTROLYTIC, 22M SMS 50V M FM5 TP(5)	
		C513	0CE4766H618	CAPACITOR, AL.ELECTROLYTIC, 47M SMS 25V M FL TP(5)	
		C514	0CK10302945	CAPACITOR, CERAMIC (HIGH DIELECTRIC), 0.01UF 2KV Z F	
		C516	181-477W	CAPACITOR, POLYPROPYLENE, 473J 19.5*15.0*8.5*7.5 250V	
		C518	0CN1030H949	CAPACITOR, TUBULAR(HIGH DIELEC), 0.0100UF 25V Z F TA52	
		C521	181-482F	CAPACITOR, POLYPROPYLENE, 274JF 18.0*17.0*10.0*7.5 250V	
		C522	0CE1076H618	CAPACITOR, AL.ELECTROLYTIC, 100M SMS 25V M FM5 TP(5)	
		C523	0CN2210K519	CAPACITOR, TUBULAR(HIGH DIELEC), 220P 50V K B TA52	
		C524	181-288D	CAPACITOR, POLYESTER, MKT 100V 473JTR PHS26473	
		C525	181-309D	CAPACITOR, POLYPROPYLENE, 182J 23.0*15.0*8.5*15.0 1.6KV	
		C526	0CK10302945	CAPACITOR, CERAMIC (HIGH DIELECTRIC), 0.01UF 2KV Z F	
		C527	0CE477CH618	CAPACITOR, AL.ELECTROLYTIC, 470UF SHL 25V M FL TP5	

*S	*AL	LOC. NO.	PART NO.	DESCRIPTION / SPECIFICATION	REMARK
		C528	0CE476ER618	CAPACITOR, AL.ELECTROLYTIC, 47UF KMG 250V M FL TP 5	
		C529	0CK56101515	CAPACITOR, CERAMIC (HIGH DIELECTRIC), 560P 1KV K B TS	
		C533	0CE476CP630	CAPACITOR, AL.ELECTROLYTIC, 47UF SHL 160V M FM5 BULK	
		C534	0CE3366N618	CAPACITOR, AL.ELECTROLYTIC, 33U SMS 100V M FM5 TP5	
		C535	0CE3356K618	CAPACITOR, AL.ELECTROLYTIC, 3.3U SMS 50V M FM5 TP5	
		C537	0CE6856K618	CAPACITOR, AL.ELECTROLYTIC, 6.8 UF SMS,SG 50V M FL	
		C538	0CE1066K618	CAPACITOR, AL.ELECTROLYTIC, 10M SMS 50V M FM5 TP(5)	
		C539	0CE6856K618	CAPACITOR, AL.ELECTROLYTIC, 6.8 UF SMS,SG 50V M FL	
		C540	0CE2266K618	CAPACITOR, AL.ELECTROLYTIC, 22M SMS 50V M FM5 TP(5)	
		C541	0CE2266K618	CAPACITOR, AL.ELECTROLYTIC, 22M SMS 50V M FM5 TP(5)	
		C543	0CX2200K409	CAPACITOR, TUBULAR(T.C), 22P 50V J SL TA52	
		C552	0CC1000W105	CAPACITOR, CERAMIC (TEMP. COMPENSATE), 10PF 500V D	
		C601	0CE3376H618	CAPACITOR, AL.ELECTROLYTIC, 330M SMS 25V M FL TP(5)	
		C602	0CN1040K949	CAPACITOR, TUBULAR(HIGH DIELEC), 0.1M 50V Z F TA52	
		C603	0CE227CK618	CAPACITOR, AL.ELECTROLYTIC, 220U SHL 50V M FL TP5	
		C604	0CE1066K618	CAPACITOR, AL.ELECTROLYTIC, 10M SMS 50V M FM5 TP(5)	
		C605	0CE1056K618	CAPACITOR, AL.ELECTROLYTIC, 1.0U SMS 50V M FM5 TP5	
		C606	0CQ2221N419	CAPACITOR, POLYESTER, 2200PF 100V J PE NI TP	
		C607	181-288N	CAPACITOR, POLYESTER, MKT 100V 103JTR PHS86103	
		C608	0CC2710K405	CAPACITOR, CERAMIC (TEMP. COMPENSATE), 270P 50V J SL	
		C609	181-288P	CAPACITOR, POLYESTER, MKT 100V 153JTR PHS86153	
		C611	0CE108CH618	CAPACITOR, AL.ELECTROLYTIC, 1000UF SHL 25V M FL TP5	
		C612	0CN1040K949	CAPACITOR, TUBULAR(HIGH DIELEC), 0.1M 50V Z F TA52	
		C613	181-288Q	CAPACITOR, POLYESTER, MKT 100V 154JTR PHS26154	
		C614	0CE2256K618	CAPACITOR, AL.ELECTROLYTIC, 2.2U SMS 50V M FM5 TP5	
		C615	0CQ2721N419	CAPACITOR, POLYESTER, 2700PF 100V J PE NI TP	
		C617	0CN1040K949	CAPACITOR, TUBULAR(HIGH DIELEC), 0.1M 50V Z F TA52	
		C631	181-288M	CAPACITOR, POLYESTER, MKT 63V 105KTR PHS15105	
		C633	0CN1040K949	CAPACITOR, TUBULAR(HIGH DIELEC), 0.1M 50V Z F TA52	
		C635	0CE1076K618	CAPACITOR, AL.ELECTROLYTIC, 100U SMS 50V M FM5 TP5	
		C642	0CN1040K949	CAPACITOR, TUBULAR(HIGH DIELEC), 0.1M 50V Z F TA52	
		C644	181-288E	CAPACITOR, POLYESTER, MKT 100V 474JTR PHS 26474	
		C701	0CE1076H618	CAPACITOR, AL.ELECTROLYTIC, 100M SMS 25V M FM5 TP(5)	
		C702	0CN1040K949	CAPACITOR, TUBULAR(HIGH DIELEC), 0.1M 50V Z F TA52	
		C703	181-288H	CAPACITOR, POLYESTER, MKT 100V 333JTR PHS 86333	
		C704	181-288X	CAPACITOR, POLYESTER, MKT 63V 684JTR PHS	
		C705	0CK1040K945	CAPACITOR, CERAMIC (HIGH DIELECTRIC), 0.1UF 50V Z F TR	
		C706	181-288B	CAPACITOR, POLYESTER, MKT 100V 104JTR PHS26104	
		C707	0CN3310K519	CAPACITOR, TUBULAR(HIGH DIELEC), 330P 50V K B TA52	
		C709	181-288H	CAPACITOR, POLYESTER, MKT 100V 333JTR PHS 86333	
		C711	0CC0400K115	CAPACITOR, CERAMIC (TEMP. COMPENSATE), 4P 50V D NP0	
		C712	0CQ2231N419	CAPACITOR, POLYESTER, 0.022UF 100V J PE NI TP	
		C713	0CE4776F618	CAPACITOR, AL.ELECTROLYTIC, 470U SMS 16V M FM5 TP5	
		C714	0CE2276F618	CAPACITOR, AL.ELECTROLYTIC, 220UF SMS 16V M FL TP5	
		C716	0CQ6821N419	CAPACITOR, POLYESTER, 6800PF 100V J PE NI TP	
		C717	0CE3366H618	CAPACITOR, AL.ELECTROLYTIC, 33M SMS 25V M FL TP(5)	

*S	*AL	LOC. NO.	PART NO.	DESCRIPTION / SPECIFICATION	REMARK
		C718	0CQ2231N419	CAPACITOR, POLYESTER, 0.022UF 100V J PE NI TP	
		C719	0CN1040K949	CAPACITOR, TUBULAR(HIGH DIELEC), 0.1M 50V Z F TA52	
		C720	181-304A	CAPACITOR, POLYPROPYLENE, 102J 19.5*12.0*7.0*10.0 400V	
		C721	0CE1066K618	CAPACITOR, AL.ELECTROLYTIC, 10M SMS 50V M FM5 TP(5)	
		C722	0CE4776F618	CAPACITOR, AL.ELECTROLYTIC, 470U SMS 16V M FM5 TP5	
		C724	0CE1066K618	CAPACITOR, AL.ELECTROLYTIC, 10M SMS 50V M FM5 TP(5)	
		C725	0CE2256K618	CAPACITOR, AL.ELECTROLYTIC, 2.2U SMS 50V M FM5 TP5	
		C726	0CQ1021N419	CAPACITOR, POLYESTER, 1000P 100V J POLY NI TP	
		C727	0CE2256K618	CAPACITOR, AL.ELECTROLYTIC, 2.2U SMS 50V M FM5 TP5	
		C732	0CE1076H618	CAPACITOR, AL.ELECTROLYTIC, 100M SMS 25V M FM5 TP(5)	
		C733	0CN1020K519	CAPACITOR, TUBULAR(HIGH DIELEC), 1000P 50V K B TA52	
		C734	0CN2210K519	CAPACITOR, TUBULAR(HIGH DIELEC), 220P 50V K B TA52	
		C741	0CE3366K618	CAPACITOR, AL.ELECTROLYTIC, 33M SMS 50V M FM(5) TP(5)	
		C742	0CE227CK618	CAPACITOR, AL.ELECTROLYTIC, 220U SHL 50V M FL TP5	
		C743	0CE1076K618	CAPACITOR, AL.ELECTROLYTIC, 100U SMS 50V M FM5 TP5	
		C744	0CE1066K618	CAPACITOR, AL.ELECTROLYTIC, 10M SMS 50V M FM5 TP(5)	
		C745	0CE4756K618	CAPACITOR, AL.ELECTROLYTIC, 4.7U SMS 50V M FM5 TP5	
		C746	0CN1040K949	CAPACITOR, TUBULAR(HIGH DIELEC), 0.1M 50V Z F TA52	
		C748	0CK1020K515	CAPACITOR, CERAMIC (HIGH DIELECTRIC), 1000PF 50V K B	
		C752	0CBZTTA002A	CAPACITOR, POLYPROPYLENE, 2000PF D 2.5KV J M/PP NI	
		C753	0CBZTTA002A	CAPACITOR, POLYPROPYLENE, 2000PF D 2.5KV J M/PP NI	
		C754	181-288D	CAPACITOR, POLYESTER, MKT 100V 473JTR PHS26473	
		C756	181-305J	CAPACITOR, POLYPROPYLENE, 474J 26.0*17.0*10.5*15.0 250V	
		C757	0CN1040K949	CAPACITOR, TUBULAR(HIGH DIELEC), 0.1M 50V Z F TA52	
		C760	181-478A	CAPACITOR, POLYPROPYLENE, 104J 20.0*18.5*10.5*7.5 250V	
		C761	0CN1040K949	CAPACITOR, TUBULAR(HIGH DIELEC), 0.1M 50V Z F TA52	
		C762	181-479X	CAPACITOR, POLYPROPYLENE, 563J 20.0*17.0*11.0*7.5 400V	
		C763	0CN1040K949	CAPACITOR, TUBULAR(HIGH DIELEC), 0.1M 50V Z F TA52	
		C764	181-305K	CAPACITOR, POLYPROPYLENE, 564J 26.0*18.0*11.0*15.0 250V	
		C765	0CN1040K949	CAPACITOR, TUBULAR(HIGH DIELEC), 0.1M 50V Z F TA52	
		C766	181-477X	CAPACITOR, POLYPROPYLENE, 563J 19.5*15.5*9.0*7.5 250V J	
		C767	181-288M	CAPACITOR, POLYESTER, MKT 63V 105KTR PHS15105	
		C768	181-477Z	CAPACITOR, POLYPROPYLENE, 823J 20.0*17.5*10.0*7.5 250V	
		C769	0CN1040K949	CAPACITOR, TUBULAR(HIGH DIELEC), 0.1M 50V Z F TA52	
		C771	0CN1040K949	CAPACITOR, TUBULAR(HIGH DIELEC), 0.1M 50V Z F TA52	
		C772	181-303D	CAPACITOR, POLYPROPYLENE, 184J 30.0*18.5*11.0*20.0 250V	
		C773	0CE475ER638	CAPACITOR, AL.ELECTROLYTIC, 4.7UF KMG 250V M FM5 TP 5	
		C774	181-479R	CAPACITOR, POLYPROPYLENE, 183J 19.5*12.0*17.0*7.5 400V	
		C775	0CE475ER638	CAPACITOR, AL.ELECTROLYTIC, 4.7UF KMG 250V M FM5 TP 5	
		C776	0CKZTTA002N	CAPACITOR, CERAMIC (HIGH DIELECTRIC), 100PF K 2KV R	
		C777	0CK1020W515	CAPACITOR, CERAMIC (HIGH DIELECTRIC), 1000P 500V	
		C779	0CN1040K949	CAPACITOR, TUBULAR(HIGH DIELEC), 0.1M 50V Z F TA52	
		C781	0CKZTTA002N	CAPACITOR, CERAMIC (HIGH DIELECTRIC), 100PF K 2KV	
		C790	0CK68101515	CAPACITOR, CERAMIC (HIGH DIELECTRIC), 680P 1KV	
		C901	0CBZTBU002C	CAPACITOR, POLYESTER, BULK PCX2 335 104M	
		C904	0CBZTBU002C	CAPACITOR, POLYESTER, BULK PCX2 335 104M	

*S	*AL	LOC. NO.	PART NO.	DESCRIPTION / SPECIFICATION	REMARK
		C905	181-304W	CAPACITOR, POLYPROPYLENE, 473J 20.0*16.0*10.0*10.0 400V	
		C906	0CE4756V630	CAPACITOR, AL.ELECTROLYTIC, 4.7UF SMS,SG 450V M FM5	
		C907	0CK68101515	CAPACITOR, CERAMIC (HIGH DIELECTRIC), 680P 1KV K B TS	
		C910	181-311C	CAPACITOR, CERAMIC (HIGH DIELECTRIC), DE7150-477F472M	
		C911	181-288D	CAPACITOR, POLYESTER, MKT 100V 473JTR PHS26473	
		C912	181-296R	CAPACITOR, AL.ELECTROLYTIC, 470UF SMH,HC 250V M VNSN	
		C913	181-296R	CAPACITOR, AL.ELECTROLYTIC, 470UF SMH,HC 250V M VNSN	
		C914	181-304N	CAPACITOR, POLYPROPYLENE, 103J 19.5*12.0*7.0*10.0 400V	
		C915	0CK10101515	CAPACITOR, CERAMIC (HIGH DIELECTRIC), 100PF 1KV K B TR	
		C916	0CE3366K618	CAPACITOR, AL.ELECTROLYTIC, 33M SMS 50V M FM(5) TP(5)	
		C918	0CE1056K618	CAPACITOR, AL.ELECTROLYTIC, 1.0U SMS 50V M FM5 TP5	
		C921	0CN1040K949	CAPACITOR, TUBULAR(HIGH DIELEC), 0.1M 50V Z F TA52	
		C922	0CE1066K618	CAPACITOR, AL.ELECTROLYTIC, 10M SMS 50V M FM5 TP(5)	
		C923	0CN1040K949	CAPACITOR, TUBULAR(HIGH DIELEC), 0.1M 50V Z F TA52	
		C924	0CQ8221N519	CAPACITOR, POLYESTER, 0.0082U 100V K POLY NI TP	
		C925	0CQ1021N419	CAPACITOR, POLYESTER, 1000P 100V J POLY NI TP	
		C926	181-288N	CAPACITOR, POLYESTER, MKT 100V 103JTR PHS86103	
		C927	0CE227CK618	CAPACITOR, AL.ELECTROLYTIC, 220U SHL 50V M FL TP5	
		C928	0CE3376H618	CAPACITOR, AL.ELECTROLYTIC, 330M SMS 25V M FL TP(5)	
		C929	0CE1066K618	CAPACITOR, AL.ELECTROLYTIC, 10M SMS 50V M FM5 TP(5)	
		C930	181-311C	CAPACITOR, CERAMIC (HIGH DIELECTRIC), DE7150-477F472M	
		C931	181-311C	CAPACITOR, CERAMIC (HIGH DIELECTRIC), DE7150-477F472M	
		C932	0CN1040K949	CAPACITOR, TUBULAR(HIGH DIELEC), 0.1M 50V Z F TA52	
		C933	0CE4766H618	CAPACITOR, AL.ELECTROLYTIC, 47M SMS 25V M FL TP(5)	
		C937	0CQ1021N419	CAPACITOR, POLYESTER, 1000P 100V J POLY NI TP	
		C941	0CE108CH618	CAPACITOR, AL.ELECTROLYTIC, 1000UF SHL 25V M FL TP5	
		C942	0CE3386H650	CAPACITOR, AL.ELECTROLYTIC, 3300M SMS 25V M FM7.5	
		C943	0CE3376F618	CAPACITOR, AL.ELECTROLYTIC, 330M SMS 16V M FM5 TP5	
		C944	0CE228CF618	CAPACITOR, AL.ELECTROLYTIC, 2200U SHL 16V M FL TP5	
		C945	0CE228EJ650	CAPACITOR, AL.ELECTROLYTIC, 2200UF 35V M KMG FM7.5	
		C947	181-288B	CAPACITOR, POLYESTER, MKT 100V 104JTR PHS26104	
		C950	0CE2276N618	CAPACITOR, AL.ELECTROLYTIC, 220UF SMS 100V M FL	
		C951	0CE227CR650	CAPACITOR, AL.ELECTROLYTIC, 220UF SHL 250V M FM7.5	
		C952	0CK4710K515	CAPACITOR, CERAMIC (HIGH DIELECTRIC), 470PF 50V K B TR	
		C953	0CE108BF618	CAPACITOR, AL.ELECTROLYTIC, 1000UF KME 16V M FL TP5	
		C954	0CE108CH618	CAPACITOR, AL.ELECTROLYTIC, 1000UF SHL 25V M FL TP5	
		C955	0CN1040K949	CAPACITOR, TUBULAR(HIGH DIELEC), 0.1M 50V Z F TA52	
		C956	0CE108BF618	CAPACITOR, AL.ELECTROLYTIC, 1000UF KME 16V M FL TP5	
		C957	181-288B	CAPACITOR, POLYESTER, MKT 100V 104JTR PHS26104	
		C958	0CK2220K515	CAPACITOR, CERAMIC (HIGH DIELECTRIC), 2200P 50V K B TS	
		C959	0CE4766H618	CAPACITOR, AL.ELECTROLYTIC, 47M SMS 25V M FL TP(5)	
		C963	0CE4766H618	CAPACITOR, AL.ELECTROLYTIC, 47M SMS 25V M FL TP(5)	
		C967	181-288B	CAPACITOR, POLYESTER, MKT 100V 104JTR PHS26104	
		C969	0CE1066K618	CAPACITOR, AL.ELECTROLYTIC, 10M SMS 50V M FM5 TP(5)	
		C973	0CE2256K618	CAPACITOR, AL.ELECTROLYTIC, 2.2U SMS 50V M FM5 TP5	
		C985	0CE2266N618	CAPACITOR, AL.ELECTROLYTIC, 22M SMS 100V M FM5 TP5	

MODEL: Flatron 795FT plus, 未来窗 795FT plus				DATE: 1999. 2. 5.	
*S	*AL	LOC. NO.	PART NO.	DESCRIPTION / SPECIFICATION	REMARK
		C1004	0CC2200K405	CAPACITOR, CERAMIC (TEMP. COMPENSATE), 22P 50V J SL	
		C1005	0CC2200K405	CAPACITOR, CERAMIC (TEMP. COMPENSATE), 22P 50V J SL	
		C1006	0CK1040K945	CAPACITOR, CERAMIC (HIGH DIELECTRIC), 0.1UF 50V Z F TR	
		C1008	0CE1066K618	CAPACITOR, AL.ELECTROLYTIC, 10M SMS 50V M FM5 TP(5)	
		C1009	0CN1040K949	CAPACITOR, TUBULAR(HIGH DIELEC), 0.1M 50V Z F TA52	
DIODEs					
		D401	0DS113309AA	DIODE, SWITCHING, 1SS133 TP ROHM KOREA DO34 90V 0.4A	
		D402	0DS113309AA	DIODE, SWITCHING, 1SS133 TP ROHM KOREA DO34 90V 0.4A	
		D404	0DZ180009AG	DIODE, ZENER, MTZJ18B TP ROHM-K DO34 500MW 18V 5MA	
		D405	0DR210009AB	DIODE, RECTIFIER, RL2AV(1) TP SANKEN A-TMD 600V 1.1A	
		D412	0DS113309AA	DIODE, SWITCHING, 1SS133 TP ROHM KOREA DO34 90V 0.4A	
		D414	0DZ910009AH	DIODE, ZENER, MTZJ9.1B TP ROHM-K DO34 500MW 9.1V 5MA	
		D415	0DZ510009AB	DIODE, ZENER, MTZ5.1B TP ROHM-K DO34 500MW 5.1V 20MA	
		D423	0DD860009AA	DIODE, RECTIFIER, BAT 86 TP PHILIPS DO34 50V 0.2A 0.25A	
		D501	0DS113309AA	DIODE, SWITCHING, 1SS133 TP ROHM KOREA DO34 90V 0.4A	
		D502	0DZ180009AG	DIODE, ZENER, MTZJ18B TP ROHM-K DO34 500MW 18V 5MA	
		D503	0DR210009AB	DIODE, RECTIFIER, RL2AV(1) TP SANKEN A-TMD 600V 1.1A	
		D504	0DS113309AA	DIODE, SWITCHING, 1SS133 TP ROHM KOREA DO34 90V 0.4A	
		D505	0DS113309AA	DIODE, SWITCHING, 1SS133 TP ROHM KOREA DO34 90V 0.4A	
		D506	0DD100009DK	DIODE, RECTIFIER, RU1P V(1) TP SANKEN R-TMD 1000V 0.4A	
		D507	0DD100009DK	DIODE, RECTIFIER, RU1P V(1) TP SANKEN R-TMD 1000V 0.4A	
		D513	0DD100009DD	DIODE, RECTIFIER, RGP10D TP G.I DO204AL 200V 1A 30A	
		D514	0DD100009DD	DIODE, RECTIFIER, RGP10D TP G.I DO204AL 200V 1A 30A	
		D515	0DZ270009AA	DIODE, ZENER, MTZ27D,TP(52MM),ROHM	
		D516	0DD100009DD	DIODE, RECTIFIER, RGP10D TP G.I DO204AL 200V 1A 30A	
		D521	0DS113309AA	DIODE, SWITCHING, 1SS133 TP ROHM KOREA DO34 90V 0.4A	
		D528	0DZ750009AG	DIODE, ZENER, MTZJ7.5B TP ROHM-K DO34 0.5W 7.5V 5MA	
		D531	0DS113309AA	DIODE, SWITCHING, 1SS133 TP ROHM KOREA DO34 90V 0.4A	
		D532	0DS113309AA	DIODE, SWITCHING, 1SS133 TP ROHM KOREA DO34 90V 0.4A	
		D602	0DS113309AA	DIODE, SWITCHING, 1SS133 TP ROHM KOREA DO34 90V 0.4A	
		D610	0DD100009DD	DIODE, RECTIFIER, RGP10D TP G.I DO204AL 200V 1A 30A	
		D617	0DS113309AA	DIODE, SWITCHING, 1SS133 TP ROHM KOREA DO34 90V 0.4A	
		D701	0DZ750009AG	DIODE, ZENER, MTZJ7.5B TP ROHM-K DO34 0.5W 7.5V 5MA	
		D702	0DS113309AA	DIODE, SWITCHING, 1SS133 TP ROHM KOREA DO34 90V 0.4A	
		D703	0DD140009AA	DIODE, RECTIFIER, EK14 V(1) TP SANKEN E/EO-TMD 40V 1.5A	
		D704	0DD140009AA	DIODE, RECTIFIER, EK14 V(1) TP SANKEN E/EO-TMD 40V 1.5A	
		D705	0DD140009AA	DIODE, RECTIFIER, EK14 V(1) TP SANKEN E/EO-TMD 40V 1.5A	
		D710	0DD140009AA	DIODE, RECTIFIER, EK14 V(1) TP SANKEN E/EO-TMD 40V 1.5A	
		D711	0DZ750009AG	DIODE, ZENER, MTZJ7.5B TP ROHM-K DO34 0.5W 7.5V 5MA	
		D712	0DD140009AA	DIODE, RECTIFIER, EK14 V(1) TP SANKEN E/EO-TMD 40V 1.5A	
		D713	0DD140009AA	DIODE, RECTIFIER, EK14 V(1) TP SANKEN E/EO-TMD 40V 1.5A	
		D714	0DD300000AC	DIODE, RECTIFIER, FMP-G3FS BK SANKEN TO220F 1500V 5A	
		D715	0DS113309AA	DIODE, SWITCHING, 1SS133 TP ROHM KOREA DO34 90V 0.4A	
		D716	0DS113309AA	DIODE, SWITCHING, 1SS133 TP ROHM KOREA DO34 90V 0.4A	
		D717	0DD220009AA	DIODE, RECTIFIER, RG2A2 TP SANKEN R-TMD 1300V 0.5A 5A	

MODEL: Flatron 795FT plus, 未来窗 795FT plus				DATE: 1999. 2. 5.	
*S	*AL	LOC. NO.	PART NO.	DESCRIPTION / SPECIFICATION	REMARK
		D718	0DD140009AA	DIODE, RECTIFIER, EK14 V(1) TP SANKEN E/EO-TMD 40V 1.5A	
		D719	0DD140009AA	DIODE, RECTIFIER, EK14 V(1) TP SANKEN E/EO-TMD 40V 1.5A	
		D720	0DD400509BB	DIODE, RECTIFIER, UF4005(52MM) TP G.I DO41 600V 1A 30A	
		D721	0DS113309AA	DIODE, SWITCHING, 1SS133 TP ROHM KOREA DO34 90V 0.4A	
		D722	0DS113309AA	DIODE, SWITCHING, 1SS133 TP ROHM KOREA DO34 90V 0.4A	
		D723	0DS113309AA	DIODE, SWITCHING, 1SS133 TP ROHM KOREA DO34 90V 0.4A	
		D731	0DD400109DB	DIODE, SWITCHING, 1N4001 TP ROHM-K DO41 50V 1A 30A	
		D737	0DD140009AA	DIODE, RECTIFIER, EK14 V(1) TP SANKEN E/EO-TMD 40V 1.5A	
△		D901	0DD406000AB	DIODE, BRIDGE, RBV406M FL-B BK SANKEN 600V 4A 120A	
		D902	0DD400709CB	DIODE, RECTIFIER, UF4007 TP G.I DO204AL 1000V 1A 30A	
		D906	0DD400709CB	DIODE, RECTIFIER, UF4007 TP G.I DO204AL 1000V 1A 30A	
		D910	0RD1200Q609	RESISTOR, FIXED CARBON FILM, 120 1/4W(3 5% TA52	
		D911	0DZ240009CG	DIODE, ZENER, MTZJ24B TP ROHM-K DO34 500MW 24V 5MA	
		D912	0DD400509BB	DIODE, RECTIFIER, UF4005(52MM) TP G.I DO41 600V 1A 30A	
		D913	0DD400509BB	DIODE, RECTIFIER, UF4005(52MM) TP G.I DO41 600V 1A 30A	
		D914	0DD400509BB	DIODE, RECTIFIER, UF4005(52MM) TP G.I DO41 600V 1A 30A	
		D915	0DS113309AA	DIODE, SWITCHING, 1SS133 TP ROHM KOREA DO34 90V 0.4A	
△		D916	0DS113309AA	DIODE, SWITCHING, 1SS133 TP ROHM KOREA DO34 90V 0.4A	
		D917	0DZ510009AB	DIODE, ZENER, MTZ5.1B TP ROHM-K DO34 500MW 5.1V 20MA	
		D918	0DZ620009AG	DIODE, ZENER, P6KE200 TP G.I D015 5W 200V 1MA 600W	
		D921	0DD400509BB	DIODE, RECTIFIER, UF4005(52MM) TP G.I DO41 600V 1A 30A	
		D922	0DD300900AA	DIODE, RECTIFIER, SB30-09J BK SANYO TO220ML 90V 3A 40A	
		D924	0DR210009AB	DIODE, RECTIFIER, RL2AV(1) TP SANKEN A-TMD 600V 1.1A	
		D925	0DR210000CA	DIODE, RECTIFIER, RL2A(LF-C1) BK SANKEN NON 600V 1.1A	
		D926	0DR210000CA	DIODE, RECTIFIER, RL2A(LF-C1) BK SANKEN NON 600V 1.1A	
		D927	0DR520000AA	DIODE, RECTIFIER, D5LC20U BK SHINDENGEN ITO220 200V	
		D931	0DD390009AA	DIODE, RECTIFIER, RK39V TP SANKEN R-TMD 90V 2A 50A	
		D932	0DD390009AA	DIODE, RECTIFIER, RK39V TP SANKEN R-TMD 90V 2A 50A	
ICs					
		IC401	0ISG082000B	IC, SGS-THOMSON, TL082ACN 8P,DIP BK DUAL J-FET OP-AMP	
		IC402	0ISS393000F	IC, SAMSUNG ELECTRONICS, KA393	
		IC501	0IMI625010A	IC, MITSUBISHI, M62501P 16P4 BK INTERFACE PWM IC	
		IC601	0ISG817200A	IC, SGS-THOMSON, TDA8172	
		IC603	0ISS455800H	IC, SAMSUNG ELECTRONICS, KA4558 8P DIP BK OP AMP	
		IC701	0INE188400B	IC, NEC, UPC1884ACT 30P,SDIP BK H/V PROCESSOR IC	
		IC702	0ISS358000C	IC, SAMSUNG ELECTRONICS, KA358 OP AMP	
		IC703	0IKE780500X	IC, KEC, KIA78L05BP T0-92L TP 5V REGULATOR	
△		IC901	0ISS384300A	IC, SAMSUNG ELECTRONICS, KA3843B 8P SDIP BK PWM	
△		IC902	0ISK831450B	IC, SANKEN, STR83145 5P(2GR) BK SWITCHING REGULATOR	
		IC903	0IPF223000A	IC, POWER INTEGRATION, TOP223Y-BE 3P,TO220 BK PWM SW	
		IC911	0IKE781200C	IC, KEC, KIA7812PI 3P(TO-220IS) 12V,1A	
△		IC912	0ITO721400A	IC, TOSHIBA, TLP721[D4-GR] 4D PHOTO(SEMKO)	
		IC913	0ISS431000A	IC, SAMSUNG ELECTRONICS, KA431AZ (LM431AZ)	
△		IC914	0ITO721400A	IC, TOSHIBA, TLP721[D4-GR] 4D PHOTO(SEMKO)	

MODEL: Flatron 795FT plus, 未来窗 795FT plus				DATE: 1999. 2. 5.	
*S	*AL	LOC. NO.	PART NO.	DESCRIPTION / SPECIFICATION	REMARK
		IC915	0ISS431000A	IC, SAMSUNG ELECTRONICS, KA431AZ (LM431AZ)	
⚠		IC916	0ITO721400A	IC, TOSHIBA, TLP721[D4-GR] 4D PHOTO(SEMKO)	
		IC960	0ISH608300A	IC, SHARP, PQ6RD083 4P BK 6.3V VOL. REGULATOR	
		IC1004	0IZZTSZ021A	IC[HYBRID ], 28PIN BK OTP(SUB-MICOM) FB795	
COILs & COREs					
		L411	150-A39A	COIL, CHOKE, SPT0508A-270K1R3 (TDK),TP	
		L412	125-155J	CORE (CIRC), BEAD, BFS2550A0FG SAMWHA 2.5*5.0MM	
		L431	125-155J	CORE (CIRC), BEAD, BFS2550A0FG SAMWHA 2.5*5.0MM	
		L501	150-A39A	COIL, CHOKE, SPT0508A-270K1R3 (TDK),TP	
		L502	150-985K	COIL, CHOKE, DR14*20 2.8MH 0.35MM 235.5T D/D CHOKE	
		L516	125-155J	CORE (CIRC), BEAD, BFS2550A0FG SAMWHA 2.5*5.0MM	
		L517	125-155J	CORE (CIRC), BEAD, BFS2550A0FG SAMWHA 2.5*5.0MM	
		L528	125-155J	CORE (CIRC), BEAD, BFS2550A0FG SAMWHA 2.5*5.0MM	
		L601	125-155J	CORE (CIRC), BEAD, BFS2550A0FG SAMWHA 2.5*5.0MM	
		L602	125-155J	CORE (CIRC), BEAD, BFS2550A0FG SAMWHA 2.5*5.0MM	
		L603	125-155J	CORE (CIRC), BEAD, BFS2550A0FG SAMWHA 2.5*5.0MM	
		L631	125-155J	CORE (CIRC), BEAD, BFS2550A0FG SAMWHA 2.5*5.0MM	
		L700	0LA1000K139	INDUCTOR, AXIAL LEAD, 100UH K 4*10.5 TP	
		L701	0LA1000K119	INDUCTOR, AXIAL LEAD, 100UH K 2.3*3.4 TP	
		L702	125-155J	CORE (CIRC), BEAD, BFS2550A0FG SAMWHA 2.5*5.0MM	
		L704	125-155J	CORE (CIRC), BEAD, BFS2550A0FG SAMWHA 2.5*5.0MM	
		L705	150-L05N	COIL, LINEARITY, DR14*15 14*6T 5.6UH 0.12*30MM 17.5T	
		L706	150-985R	COIL, CHOKE, DR10*12 50UH 0.12*15MM 35.5T SWITCHING	
		L707	150-985P	COIL, CHOKE, DR12*15 6MH 0.25MM 365.5T H-CENTERING	
		L708	150-985P	COIL, CHOKE, DR12*15 6MH 0.25MM 365.5T H-CENTERING	
		L709	125-155A	CORE (CIRC), BEAD, BFD3510R2FG SAMWHA 3.5*10MM	
		L711	150-985Q	COIL, CHOKE, DR8*11 3.3MH 0.15MM 319.5T	
		L753	125-155J	CORE (CIRC), BEAD, BFS2550A0FG SAMWHA 2.5*5.0MM	
		L771	125-155J	CORE (CIRC), BEAD, BFS2550A0FG SAMWHA 2.5*5.0MM	
		L772	125-155J	CORE (CIRC), BEAD, BFS2550A0FG SAMWHA 2.5*5.0MM	
⚠		L902	6140TBZ010A	COIL, CHOKE, RING 60UH 0.65MM 33.5T	
		L903	6140TBZ010A	COIL, CHOKE, RING 60UH 0.65MM 33.5T	
		L904	125-155J	CORE (CIRC), BEAD, BFS2550A0FG SAMWHA 2.5*5.0MM	
		L911	125-155J	CORE (CIRC), BEAD, BFS2550A0FG SAMWHA 2.5*5.0MM	
		L912	125-155J	CORE (CIRC), BEAD, BFS2550A0FG SAMWHA 2.5*5.0MM	
		L913	125-155J	CORE (CIRC), BEAD, BFS2550A0FG SAMWHA 2.5*5.0MM	
		L914	125-155J	CORE (CIRC), BEAD, BFS2550A0FG SAMWHA 2.5*5.0MM	
		L915	150-985F	COIL, CHOKE, DR10*10 10UH 0.5MM 14.5T	
		L916	125-155J	CORE (CIRC), BEAD, BFS2550A0FG SAMWHA 2.5*5.0MM	
		L921	125-155J	CORE (CIRC), BEAD, BFS2550A0FG SAMWHA 2.5*5.0MM	
		L1001	125-155J	CORE (CIRC), BEAD, BFS2550A0FG SAMWHA 2.5*5.0MM	
		L1002	125-155J	CORE (CIRC), BEAD, BFS2550A0FG SAMWHA 2.5*5.0MM	

MODEL: Flatron 795FT plus, 未来窗 795FT plus				DATE: 1999. 2. 5.	
*S	*AL	LOC. NO.	PART NO.	DESCRIPTION / SPECIFICATION	REMARK
TRANSISTORs					
		Q401	0TR126609AA	TRANSISTOR, KTA1266-Y(KTA1015) TP KEC TO92 PNP	
		Q402	0TR114009AB	TRANSISTOR, DTC114ES TP ROHM-K SPT NPN	
		Q404	0TF306000AA	FET, 2SJ306 BK SANYO -250V -3A TO220ML	
		Q411	0TR126609AA	TRANSISTOR, KTA1266-Y(KTA1015) TP KEC TO92 PNP	
		Q412	0TR390409CA	TRANSISTOR, 2N3904 TP SAMSUNG TO92 NPN	
		Q413	0TR320209AA	TRANSISTOR, KTC3202-TP-Y (KTC1959)KEC	
		Q414	0TR127009AA	TRANSISTOR, KTA1270-Y(KTA562TM) TP KEC TO92 PNP	
		Q503	0TF306000AA	FET, 2SJ306 BK SANYO -250V -3A TO220ML	
		Q504	0TR390409CA	TRANSISTOR, 2N3904 TP SAMSUNG TO92 NPN	
		Q505	0TR320209AA	TRANSISTOR, KTC3202-TP-Y (KTC1959)KEC	
		Q506	0TR127009AA	TRANSISTOR, KTA1270-Y(KTA562TM) TP KEC TO92 PNP	
⚠		Q507	0TF284700AA	FET, 2SK2847 BK TOSHIBA 900V 8A TO-3P(IS)	
		Q514	0TR390409CA	TRANSISTOR, 2N3904 TP SAMSUNG TO92 NPN	
		Q515	0TR463300AB	TRANSISTOR, 2SC4633(LS-CB11) BK SANYO LS-CB11 NPN	
		Q516	0TR463300AB	TRANSISTOR, 2SC4633(LS-CB11) BK SANYO LS-CB11 NPN	
		Q531	0TR390409CA	TRANSISTOR, 2N3904 TP SAMSUNG TO92 NPN	
		Q601	0TR319809AA	TRANSISTOR, KTC3198-Y(KTC1815) TP KEC TO92 NPN	
		Q602	0TR320509AB	TRANSISTOR, KTC3205-Y(KTC2236A) TP KEC TO92L NPN	
		Q603	0TR127309AA	TRANSISTOR, KTA1273-Y(KTA966A) TP KEC TO92L PNP	
		Q604	0TR437000AA	TRANSISTOR, KTC4370Y BK KEC TO220IS NPN	
		Q605	0TR165900AA	TRANSISTOR, KTA1659Y BK KEC TO220IS PNP	
		Q701	0TR390409CA	TRANSISTOR, 2N3904 TP SAMSUNG TO92 NPN	
		Q702	0TR320209AA	TRANSISTOR, KTC3202-TP-Y (KTC1959)KEC	
		Q703	0TR127009AA	TRANSISTOR, KTA1270-Y(KTA562TM) TP KEC TO92 PNP	
		Q704	0TR880000CA	TRANSISTOR, 2SD880-O BK TOSHIBA TO220AB NPN	
		Q705	0TF283509AA	FET, 2SK2835(TP) TP TOSHIBA 200V 5A NON	
		Q707	0TR504700AA	TRANSISTOR, 2SC5047 BK SANYO TO3PBL H-OUT TR	
		Q711	0TR320209AA	TRANSISTOR, KTC3202-TP-Y (KTC1959)KEC	
		Q712	0TF650000AA	FET, IRF650A BK SAMSUNG 200V 25A TO220	
		Q713	0TF640000CA	FET, IRFS640A BK SAMSUNG 200V 9A TO220F	
		Q714	0TF650000AA	FET, IRF650A BK SAMSUNG 200V 25A TO220	
		Q715	0TF640000CA	FET, IRFS640A BK SAMSUNG 200V 9A TO220F	
		Q716	0TR390409CA	TRANSISTOR, 2N3904 TP SAMSUNG TO92 NPN	
		Q717	0TF283509AA	FET, 2SK2835(TP) TP TOSHIBA 200V 5A NON	
		Q718	0TF640000CA	FET, IRFS640A BK SAMSUNG 200V 9A TO220F	
		Q721	0TR126609AA	TRANSISTOR, KTA1266-Y(KTA1015) TP KEC TO92 PNP	
		Q762	0TR114009AB	TRANSISTOR, DTC114ES TP ROHM-K SPT NPN	
		Q902	0TF284700AA	FET, 2SK2847 BK TOSHIBA 900V 8A TO-3P(IS)	
		Q903	0TR127509AC	TRANSISTOR, KTA1275-Y(KTA1013) TP KEC TO92L PNP	
		Q914	0TR390409CA	TRANSISTOR, 2N3904 TP SAMSUNG TO92 NPN	
		Q915	0TR319809AA	TRANSISTOR, KTC3198-Y(KTC1815) TP KEC TO92 NPN	
RESISTORs					
		R401	ORD1002Q609	RESISTOR, FIXED CARBON FILM, 10K 1/4W(3 5% TA52	
		R402	ORD1002Q609	RESISTOR, FIXED CARBON FILM, 10K 1/4W(3 5% TA52	

*S	*AL	LOC. NO.	PART NO.	DESCRIPTION / SPECIFICATION	REMARK
		R403	0RD3302Q609	RESISTOR, FIXED CARBON FILM, 33K 1/4W(3 5% TA52	
		R404	0RD2001Q609	RESISTOR, FIXED CARBON FILM, 2K 1/4W(3 5% TA52	
		R405	0RD1803A609	RESISTOR, FIXED CARBON FILM, 180K OHM 1/2 W (7.0) 5%	
		R411	0RN1502F409	RESISTOR, FIXED METAL FILM, 15K 1/6W 1% TA52	
		R412	0RD6802F509	RESISTOR, FIXED CARBON FILM, 68K 1/6W 2% TA52	
		R413	0RD3900Q609	RESISTOR, FIXED CARBON FILM, 390 1/4W(3 5% TA52	
		R417	0RD1302F509	RESISTOR, FIXED CARBON FILM, 13K 1/6W 2 TA52	
		R418	0RD2002Q609	RESISTOR, FIXED CARBON FILM, 20K 1/4W(3 5% TA52	
		R419	0RN4701F409	RESISTOR, FIXED METAL FILM, 4.70K 1/6W 1% TA52	
		R420	0RN1502F409	RESISTOR, FIXED METAL FILM, 15K 1/6W 1% TA52	
		R421	0RD1003Q609	RESISTOR, FIXED CARBON FILM, 100K 1/4W(3 5% TA52	
		R422	0RD1003Q609	RESISTOR, FIXED CARBON FILM, 100K 1/4W(3 5% TA52	
		R423	0RD8202Q609	RESISTOR, FIXED CARBON FILM, 82K 1/4W(3 5% TA52	
		R426	0RD5601F509	RESISTOR, FIXED CARBON FILM, 5.6K 1/6W 2 TA52	
		R428	0RD1000F609	RESISTOR, FIXED CARBON FILM, 100 1/6W 5 TA52	
		R430	0RN1502F409	RESISTOR, FIXED METAL FILM, 15K 1/6W 1% TA52	
		R431	0RN5101F409	RESISTOR, FIXED METAL FILM, 5.10K 1/6W 1% TA52	
		R432	0RD1001Q609	RESISTOR, FIXED CARBON FILM, 1K 1/4W(3 5% TA52	
		R433	0RD2201Q609	RESISTOR, FIXED CARBON FILM, 2.20K 1/4W(3 5% TA52	
		R434	0RD3901Q609	RESISTOR, FIXED CARBON FILM, 3.90K 1/4W(3 5% TA52	
		R435	0RN1502F409	RESISTOR, FIXED METAL FILM, 15K 1/6W 1% TA52	
		R436	0RD2001Q609	RESISTOR, FIXED CARBON FILM, 2K 1/4W(3 5% TA52	
		R437	0RD0102Q609	RESISTOR, FIXED CARBON FILM, 10 1/4W(3 5% TA52	
		R438	0RD0102Q609	RESISTOR, FIXED CARBON FILM, 10 1/4W(3 5% TA52	
		R439	0RD0222Q609	RESISTOR, FIXED CARBON FILM, 22 1/4W(3 5% TA52	
		R440	0RN1502F409	RESISTOR, FIXED METAL FILM, 15K 1/6W 1% TA52	
		R441	0RD2001Q609	RESISTOR, FIXED CARBON FILM, 2K 1/4W(3 5% TA52	
		R501	0RD1002F509	RESISTOR, FIXED CARBON FILM, 10K 1/6W 2 TA52	
		R502	0RD0332Q609	RESISTOR, FIXED CARBON FILM, 33 1/4W(3 5% TA52	
△		R503	0RN3601F409	RESISTOR, FIXED METAL FILM, 3.6K 1/6W 1 TA52	
△		R504	0RN1502F409	RESISTOR, FIXED METAL FILM, 15K 1/6W 1% TA52	
△		R505	0RD1001Q609	RESISTOR, FIXED CARBON FILM, 1K 1/4W(3 5% TA52	
△		R506	0RD1002F509	RESISTOR, FIXED CARBON FILM, 10K 1/6W 2 TA52	
△		R507	0RN1502F409	RESISTOR, FIXED METAL FILM, 15K 1/6W 1% TA52	
		R508	0RD1002F509	RESISTOR, FIXED CARBON FILM, 10K 1/6W 2 TA52	
		R509	0RD1000G609	RESISTOR, FIXED CARBON FILM, 100 1/4W 5 TA52	
		R510	971-0016	WIRE, JUMP, TIN HDC 0.60H	
△		R511	0RN9101F409	RESISTOR, FIXED METAL FILM, 9.10K 1/6W 1% TA52	
		R512	0RD2403Q609	RESISTOR, FIXED CARBON FILM, 240K 1/4W(3 5% TA52	
		R513	0RD3302Q609	RESISTOR, FIXED CARBON FILM, 33K 1/4W(3 5% TA52	
		R515	0RD1502A609	RESISTOR, FIXED CARBON FILM, 15K OHM 1/2 W (7.0) 5%	
		R516	0RD0222Q609	RESISTOR, FIXED CARBON FILM, 22 1/4W(3 5%	
		R517	0RD5601F509	RESISTOR, FIXED CARBON FILM, 5.6K 1/6W 2	
△		R519	0RN4700F409	RESISTOR, FIXED METAL FILM, 470 1/6W 1	
		R521	0RD0472Q609	RESISTOR, FIXED CARBON FILM, 47 1/4W(3 5%	
		R522	0RD1001Q609	RESISTOR, FIXED CARBON FILM, 1K 1/4W(3 5%	

MODEL: Flatron 795FT plus, 未来窗 795FT plus				DATE: 1999. 2. 5.	
*S	*AL	LOC. NO.	PART NO.	DESCRIPTION / SPECIFICATION	REMARK
		R523	0RD1002Q609	RESISTOR, FIXED CARBON FILM, 10K 1/4W(3 5%	
		R524	0RD3301F509	RESISTOR, FIXED CARBON FILM, 3.3K 1/6W 2	
		R525	0RD0222Q609	RESISTOR, FIXED CARBON FILM, 22 1/4W(3 5%	
		R526	0RD4701F509	RESISTOR, FIXED CARBON FILM, 4.7K 1/6W 2	
		R531	0RX0102J609	RESISTOR, SMALL FIX METAL FILM OXIDE, 10 OHM 1 W 5%	
		R534	0RX0332K607	RESISTOR, SMALL FIX METAL FILM OXIDE, 33 OHM 2 W 5%	
△		R541	0RN1303F409	RESISTOR, FIXED METAL FILM, 130K 1/6W 1%	
		R542	0RD1001Q609	RESISTOR, FIXED CARBON FILM, 1K 1/4W(3 5%	
		R543	0RD0621Q609	RESISTOR, FIXED CARBON FILM, 6.2 OHM 1/4 W (3.4) 5%	
		R546	0RD6201Q609	RESISTOR, FIXED CARBON FILM, 6.20K 1/4W(3 5%	
		R547	0RD0472Q609	RESISTOR, FIXED CARBON FILM, 47 1/4W(3 5%	
		R551	0RD2703A609	RESISTOR, FIXED CARBON FILM, 270K OHM 1/2 W (7.0) 5%	
		R552	0RD2703A609	RESISTOR, FIXED CARBON FILM, 270K OHM 1/2 W (7.0) 5%	
		R553	0RX1503L665	RESISTOR, SMALL FIX METAL FILM OXIDE, 150000 3 W 5% SF	
		R554	0RX1503L665	RESISTOR, SMALL FIX METAL FILM OXIDE, 150000 3 W 5% SF	
		R555	0RX1001H609	RESISTOR, SMALL FIX METAL FILM OXIDE, 1000 1/2 W 5%	
		R601	0RN1202F409	RESISTOR, FIXED METAL FILM, 12K 1/6W 1%	
		R602	0RN6201F409	RESISTOR, FIXED METAL FILM, 6.20K 1/6W 1%	
		R603	0RN3301F409	RESISTOR, FIXED METAL FILM, 3.30K 1/6W 1%	
		R604	0RN1001F409	RESISTOR, FIXED METAL FILM, 1K 1/6W 1%	
		R605	0RD1002Q609	RESISTOR, FIXED CARBON FILM, 10K 1/4W(3 5%	
		R606	0RN8201F409	RESISTOR, FIXED METAL FILM, 8.20K 1/6W 1%	
		R607	0RD1001Q609	RESISTOR, FIXED CARBON FILM, 1K 1/4W(3 5%	
		R611	0RD0151A609	RESISTOR, FIXED CARBON FILM, 1.5 OHM 1/2 W (7.0) 5%	
		R612	0RD4300A609	RESISTOR, FIXED CARBON FILM, 430 OHM 1/2 W (7.0) 5%	
		R613	0RD5602Q609	RESISTOR, FIXED CARBON FILM, 56K 1/4W(3 5%	
		R614	0RN0820H609	RESISTOR, FIXED METAL FILM, 0.82 1/2W 5	
		R615	0RN9101F409	RESISTOR, FIXED METAL FILM, 9.10K 1/6W 1%	
		R616	0RD1001Q609	RESISTOR, FIXED CARBON FILM, 1K 1/4W(3 5%	
		R617	0RN1001F409	RESISTOR, FIXED METAL FILM, 1K 1/6W 1%	
		R631	0RD0272Q609	RESISTOR, FIXED CARBON FILM, 27 OHM 1/4 W (3.4) 5%	
		R632	0RD1002F509	RESISTOR, FIXED CARBON FILM, 10K 1/6W 2	
		R633	0RD8201Q609	RESISTOR, FIXED CARBON FILM, 8.20K 1/4W(3 5%	
		R634	0RD7502Q609	RESISTOR, FIXED CARBON FILM, 75K 1/4W(3 5%	
		R635	0RD1002Q609	RESISTOR, FIXED CARBON FILM, 10K 1/4W(3 5%	
		R636	0RD0152Q609	RESISTOR, FIXED CARBON FILM, 15 1/4W(3 5%	
		R637	0CN1040K949	CAPACITOR, TUBULAR(HIGH DIELEC), 0.1M 50V Z F	
		R638	0RD0101Q609	RESISTOR, FIXED CARBON FILM, 1 1/4W(3 5%	
		R642	0RD1002F509	RESISTOR, FIXED CARBON FILM, 10K 1/6W 2	
		R643	0RN8201F409	RESISTOR, FIXED METAL FILM, 8.20K 1/6W 1%	
		R644	0RD8202Q609	RESISTOR, FIXED CARBON FILM, 82K 1/4W(3 5%	
		R645	0RD1002Q609	RESISTOR, FIXED CARBON FILM, 10K 1/4W(3 5%	
		R646	0RD0152Q609	RESISTOR, FIXED CARBON FILM, 15 1/4W(3 5%	
		R648	0RD0102Q609	RESISTOR, FIXED CARBON FILM, 10 1/4W(3 5%	
		R701	0RD3300A609	RESISTOR, FIXED CARBON FILM, 330 OHM 1/2 W (7.0) 5%	
		R702	0RD5101Q609	RESISTOR, FIXED CARBON FILM, 5.10K 1/4W(3 5%	

*S	*AL	LOC. NO.	PART NO.	DESCRIPTION / SPECIFICATION	REMARK
		R704	0RD1000F609	RESISTOR, FIXED CARBON FILM, 100 1/6W 5	
		R705	0RD1502Q609	RESISTOR, FIXED CARBON FILM, 15K 1/4W(3 5%	
		R706	0RD1000F609	RESISTOR, FIXED CARBON FILM, 100 1/6W 5	
		R707	0RD1000F609	RESISTOR, FIXED CARBON FILM, 100 1/6W 5	
		R708	0RD2000A609	RESISTOR, FIXED CARBON FILM, 200 OHM 1/2 W (7.0) 5%	
		R709	0RD2000A609	RESISTOR, FIXED CARBON FILM, 200 OHM 1/2 W (7.0) 5%	
		R710	125-155J	CORE (CIRC),BEAD, BFS2550A0FG SAMWHA 2.5*5.0MM	
		R711	0RD0102Q609	RESISTOR, FIXED CARBON FILM, 10 1/4W(3 5%	
		R712	0RD3901Q609	RESISTOR, FIXED CARBON FILM, 3.90K 1/4W(3 5%	
		R713	0RD5602Q609	RESISTOR, FIXED CARBON FILM, 56K 1/4W(3 5%	
		R714	0RD1201Q609	RESISTOR, FIXED CARBON FILM, 1.20K 1/4W(3 5%	
		R715	0RD1003Q609	RESISTOR, FIXED CARBON FILM, 100K 1/4W(3 5%	
		R716	0RX0472L607	RESISTOR, SMALL FIX METAL FILM OXIDE, 47.OHM 3 W 5%	
		R717	0RN0471H609	RESISTOR, FIXED METAL FILM, 4.7 OHM 1/2 W 5%	
		R719	0RD1001Q609	RESISTOR, FIXED CARBON FILM, 1K 1/4W(3 5%	
		R721	0RN2201F409	RESISTOR, FIXED METAL FILM, 2.20K 1/6W 1%	
		R722	0RD3301F509	RESISTOR, FIXED CARBON FILM, 3.3K 1/6W 2	
		R723	0RD2201Q609	RESISTOR, FIXED CARBON FILM, 2.20K 1/4W(3 5%	
		R724	0RD1200Q609	RESISTOR, FIXED CARBON FILM, 120 1/4W(3 5%	
		R725	0RD1000F609	RESISTOR, FIXED CARBON FILM, 100 1/6W 5	
		R727	0RD1002Q609	RESISTOR, FIXED CARBON FILM, 10K 1/4W(3 5%	
		R731	0RD1000F609	RESISTOR, FIXED CARBON FILM, 100 1/6W 5	
		R732	0RX2200K607	RESISTOR, SMALL FIX METAL FILM OXIDE, 220 OHM 2 W 5%	
		R733	0RD0471A609	RESISTOR, FIXED CARBON FILM, 4.7 OHM 1/2 W (7.0) 5%	
		R735	0RD1303Q609	RESISTOR, FIXED CARBON FILM, 130K 1/4W(3 5%	
		R737	0RD1000F609	RESISTOR, FIXED CARBON FILM, 100 1/6W 5	
		R738	0RD2701Q609	RESISTOR, FIXED CARBON FILM, 2.70K 1/4W(3 5%	
		R739	0RD4702Q609	RESISTOR, FIXED CARBON FILM, 47K 1/4W(3 5%	
		R741	0RD6802F509	RESISTOR, FIXED CARBON FILM, 68K 1/6W 2%	
		R743	0RN3602F409	RESISTOR, FIXED METAL FILM, 36K 1/6W 1	
		R744	0RN6202F409	RESISTOR, FIXED METAL FILM, 62KOHM 1/6 W 1%	
		R745	0RD5602Q609	RESISTOR, FIXED CARBON FILM, 56K 1/4W(3 5%	
		R747	0RD1000F609	RESISTOR, FIXED CARBON FILM, 100 1/6W 5	
		R748	0RD3000Q609	RESISTOR, FIXED CARBON FILM, 300 1/4W(3 5%	
		R751	0RX0511J609	RESISTOR, SMALL FIX METAL FILM OXIDE, 5.10 OHM 1 W 5%	
		R752	0RX0301K607	RESISTOR, SMALL FIX METAL FILM OXIDE, 3.0 OHM 2 W 5%	
		R753	0RX0301K607	RESISTOR, SMALL FIX METAL FILM OXIDE, 3.0 OHM 2 W 5%	
		R756	0RD0272A609	RESISTOR, FIXED CARBON FILM, 27 OHM 1/2 W (7.0) 5%	
		R761	0RX1500L607	RESISTOR, SMALL FIX METAL FILM OXIDE, 150 OHM 3 W 5%	
		R762	0RD4700A609	RESISTOR, FIXED CARBON FILM, 470 OHM 1/2 W (7.0) 5%	
		R763	0RD1200Q609	RESISTOR, FIXED CARBON FILM, 120 1/4W(3 5%	
		R764	0RD3001Q609	RESISTOR, FIXED CARBON FILM, 3K 1/4W(3 5%	
		R765	0RD1002Q609	RESISTOR, FIXED CARBON FILM, 10K 1/4W(3 5%	
		R767	0RD5601F509	RESISTOR, FIXED CARBON FILM, 5.6K 1/6W 2	
		R768	0RD1004Q609	RESISTOR, FIXED CARBON FILM, 1M OHM 1/4 W (3.4) 5%	
		R771	0RD1004Q609	RESISTOR, FIXED CARBON FILM, 1M OHM 1/4 W (3.4) 5%	

*S	*AL	LOC. NO.	PART NO.	DESCRIPTION / SPECIFICATION	REMARK
		R772	0RD1004Q609	RESISTOR, FIXED CARBON FILM, 1M OHM 1/4 W (3.4) 5%	
		R773	0RD1004Q609	RESISTOR, FIXED CARBON FILM, 1M OHM 1/4 W (3.4) 5%	
		R774	0RD1004Q609	RESISTOR, FIXED CARBON FILM, 1M OHM 1/4 W (3.4) 5%	
		R775	0RX1500L607	RESISTOR, SMALL FIX METAL FILM OXIDE, 150 OHM 3 W 5%	
		R776	0RD2202Q609	RESISTOR, FIXED CARBON FILM, 22K 1/4W(3 5%	
		R777	0RD5602Q609	RESISTOR, FIXED CARBON FILM, 56K 1/4W(3 5%	
		R778	0RX0102K607	RESISTOR, SMALL FIX METAL FILM OXIDE, 10 OHM 2 W 5%	
		R779	0RD2002Q609	RESISTOR, FIXED CARBON FILM, 20K 1/4W(3 5%	
		R781	0RD2401Q609	RESISTOR, FIXED CARBON FILM, 2.40K 1/4W(3 5%	
		R782	0RD4702Q609	RESISTOR, FIXED CARBON FILM, 47K 1/4W(3 5%	
		R783	0RD5600Q609	RESISTOR, FIXED CARBON FILM, 560 1/4W(3 5%	
		R788	0RD2700A609	RESISTOR, FIXED CARBON FILM, 270 OHM 1/2 W (7.0) 5%	
		R901	0RD3603A609	RESISTOR, FIXED CARBON FILM, 360K OHM 1/2 W (7.0) 5%	
		R902	0RB0390L607	RESISTOR, FIX WIRE-WOUND PRECISION, 0.39 OHM 3 W 5%	
		R903	0RD1004Q609	RESISTOR, FIXED CARBON FILM, 1M OHM 1/4 W (3.4) 5%	
		R904	0RD1004Q609	RESISTOR, FIXED CARBON FILM, 1M OHM 1/4 W (3.4) 5%	
		R906	0RD0471Q609	RESISTOR, FIXED CARBON FILM, 4.70 1/4W(3 5%	
		R908	180-465H	RESISTOR, CEMENT, 0.24 OHM 5W 5% B RWR	
		R915	0RD3001Q609	RESISTOR, FIXED CARBON FILM, 3K 1/4W(3 5%	
		R917	180-465Q	RESISTOR, CEMENT, 51K OHM 5W 5% B RSR	
		R920	0RN0270H609	RESISTOR, FIXED METAL FILM, 0.27 1/2W 5	
		R921	0RD0102Q609	RESISTOR, FIXED CARBON FILM, 10 1/4W(3 5%	
		R922	0RD1102Q609	RESISTOR, FIXED CARBON FILM, 11K 1/4W(3 5%	
		R923	0RD1001Q609	RESISTOR, FIXED CARBON FILM, 1K 1/4W(3 5%	
		R924	0RD1002Q609	RESISTOR, FIXED CARBON FILM, 10K 1/4W(3 5%	
		R925	0RD4702Q609	RESISTOR, FIXED CARBON FILM, 47K 1/4W(3 5%	
		R926	0RD4702Q609	RESISTOR, FIXED CARBON FILM, 47K 1/4W(3 5%	
		R927	0RD4701F509	RESISTOR, FIXED CARBON FILM, 4.7K 1/6W 2	
		R929	0RD1802Q609	RESISTOR, FIXED CARBON FILM, 18K 1/4W(3 5%	
		R931	0RD1004A609	RESISTOR, FIXED CARBON FILM, 1.0M OHM 1/2 W (7.0) 5%	
		R934	0RD0122Q609	RESISTOR, FIXED CARBON FILM, 12 1/4W(3 5%	
		R935	0RD0101A609	RESISTOR, FIXED CARBON FILM, 1 OHM 1/2 W (7.0) 5%	
		R936	0RD0332Q609	RESISTOR, FIXED CARBON FILM, 33 1/4W(3 5%	
		R937	0RD2201Q609	RESISTOR, FIXED CARBON FILM, 2.20K 1/4W(3 5%	
		R938	0RB0220K607	RESISTOR, FIX WIRE-WOUND PRECISION, 0.22 2 W 5%	
		R941	0RD2201Q609	RESISTOR, FIXED CARBON FILM, 2.20K 1/4W(3 5%	
		R947	0RD0122Q609	RESISTOR, FIXED CARBON FILM, 12 1/4W(3 5%	
		R950	0RN0270J607	RESISTOR, FIXED METAL FILM, 0.27 1W 5%	
⚠		R951	0RD3900Q609	RESISTOR, FIXED CARBON FILM, 390 1/4W(3 5%	
		R952	0RD1501F509	RESISTOR, FIXED CARBON FILM, 1.5K 1/6W 2	
		R953	0RD2003Q609	RESISTOR, FIXED CARBON FILM, 200K 1/4W(3 5%	
⚠		R954	0RN1801F409	RESISTOR, FIXED METAL FILM, 1.80K 1/6W 1%	
		R955	0RN1503H409	RESISTOR, FIXED METAL FILM, 150K OHM 1/2 W 1%	
		R956	0RD2201Q609	RESISTOR, FIXED CARBON FILM, 2.20K 1/4W(3 5%	
		R957	0RD6801Q609	RESISTOR, FIXED CARBON FILM, 6.80K 1/4W(3 5%	
		R958	0RX1003K607	RESISTOR, SMALL FIX METAL FILM OXIDE, 100KOHM 2 W 5%	

MODEL: Flatron 795FT plus, 未来窗 795FT plus				DATE: 1999. 2. 5.	
*S	*AL	LOC. NO.	PART NO.	DESCRIPTION / SPECIFICATION	REMARK
		R961	0RD1000F609	RESISTOR, FIXED CARBON FILM, 100 1/6W 5	
		R962	0RD1501F509	RESISTOR, FIXED CARBON FILM, 1.5K 1/6W 2	
		R963	0RN3601F409	RESISTOR, FIXED METAL FILM, 3.6K 1/6W 1	
		R964	0RN3601F409	RESISTOR, FIXED METAL FILM, 3.6K 1/6W 1	
		R965	0RD2200Q609	RESISTOR, FIXED CARBON FILM, 220 1/4W(3 5%	
		R966	0RN0270H609	RESISTOR, FIXED METAL FILM, 0.27 1/2W 5	
		R967	0RD4700Q609	RESISTOR, FIXED CARBON FILM, 470 OHM 1/4 W (3.4) 5%	
		R973	0RD1501F509	RESISTOR, FIXED CARBON FILM, 1.5K 1/6W 2	
		R974	0RD1001Q609	RESISTOR, FIXED CARBON FILM, 1K 1/4W(3 5%	
		R975	0RN1502F409	RESISTOR, FIXED METAL FILM, 15K 1/6W 1%	
		R976	0RD2401Q609	RESISTOR, FIXED CARBON FILM, 2.40K 1/4W(3 5%	
		R982	0RD1004A609	RESISTOR, FIXED CARBON FILM, 1.0M OHM 1/2 W (7.0) 5%	
		R1011	0RD1000F609	RESISTOR, FIXED CARBON FILM, 100 1/6W 5	
		R1012	0RD1000F609	RESISTOR, FIXED CARBON FILM, 100 1/6W 5	
		R1013	0RD4701F509	RESISTOR, FIXED CARBON FILM, 4.7K 1/6W 2	
		R1014	0RD4701F509	RESISTOR, FIXED CARBON FILM, 4.7K 1/6W 2	
		R1015	0RD4701F509	RESISTOR, FIXED CARBON FILM, 4.7K 1/6W 2	
		R1016	0RD4701F509	RESISTOR, FIXED CARBON FILM, 4.7K 1/6W 2	
		R1018	0RD4701F509	RESISTOR, FIXED CARBON FILM, 4.7K 1/6W 2	
		R1020	0RN4701F409	RESISTOR, FIXED METAL FILM, 4.70K 1/6W 1%	
		R1021	0RN4701F409	RESISTOR, FIXED METAL FILM, 4.70K 1/6W 1%	
		R1022	0RD2002Q609	RESISTOR, FIXED CARBON FILM, 20K 1/4W(3 5%	
OTHERs					
		F1	430-858C	FUSE HOLDER, AFC-520 BAE EUN TA	
		F901	430-858C	FUSE HOLDER, AFC-520 BAE EUN TA	
		F901	131-040E	FUSE, TIME LAG, 5A 250V HBC UL/CSA TRIAD	
		F951	131-041A	FUSE, TIME LAG, 5A 125V MICRO MICRO	
		J88	0RD1000F609	RESISTOR, FIXED CARBON FILM, 100 1/6W 5	
		LF901	150-A50F	FILTER(CIRC), LINE, SQ2930 6MH MIN 0.80MM 49T	
		RL701	141-014B	RELAY, UT205-12SC YUYU 250VAC 5A 12V 30MA 400 OHM 1C	
		RL902	141-040A	RELAY, JW2HN-DC5V MATSUSHITA 250VAC 5A 5V 106MA 47	
		SC701	140-079C	SWITCH,LEVER, SLS-1301 SW NON 30 0 HORIZONTAL 100	
		SG501	6918TAT005D	SPARK GAP, AXIAL, MTH-132M GIGA AXIAL TAPING	
		SG502	6918TAT001A	SPARK GAP, AXIAL, DSP-301N-A21F MMC AXIAL TAPPING	
		T701	151-515A	TRANSFORMER, HORIZONTAL DRIVER, EI 2519 4.5MH CF201	
		T702	6140TDZ004A	COIL, DUMMY, EER2834 2.0MH	
⚠		T703	6174T13003E	FBT (FLY BACK TRANSFORMER), Y265434 HITACHI 17"	
⚠		T901	6170TMZ062A	TRANSFORMER, SMPS, EER4045 0H / V-18PIN / FB792 / SC/NY	
⚠		T902	6170TMZ025A	TRANSFORMER, SMPS, CB790 SUB TRANS EER2834 12-PIN	
⚠		T903	151-414E	TRANSFORMER, PULSE, UU1116 8.8MH PLUSE	
		TH901	163-053D	THERMISTOR, PTC, J502P62C090Q290 JAHWA +/-20 220Vrms	
		VR501	180-035Q	VOLUME, EVN-DJAA03B24 (MEC),20KB	
		VR901	180-035D	VOLUME, EVN-DJAA03B32 (MEC),300B	
		WG3	387-T13C	CONNECTOR ASSY, R-T,101518,L120	

MODEL: Flatron 795FT plus, 未来窗 795FT plus				DATE: 1999. 2. 5.	
*S	*AL	LOC. NO.	PART NO.	DESCRIPTION / SPECIFICATION	REMARK
		X1001 X701	156-005B 6212TBU001A	CRYSTAL, 4.0MHZ(CL.15P) RESONATOR, CSB500E55 MURATA 500KHZ BK	
<b>VIDEO BOARD</b>					
<b>CAPACITORS</b>					
		C301	0CH6331K416	CAPACITOR, CHIP[CERAMIC LD-LESS TC], 330PF 50V J NP0	
		C302	0CH3103K516	CAPACITOR, CHIP[CERAMIC LD-LESS HD], 10000PF 50V K B	
		C303	0CH3104K946	CAPACITOR, CHIP[CERAMIC LD-LESS HD], 100000PF 50V Z F	
		C304	0CH6330K416	CAPACITOR, CHIP[CERAMIC LD-LESS TC], 33PF 50V J NP0	
		C305	0CH3104K946	CAPACITOR, CHIP[CERAMIC LD-LESS HD], 100000PF 50V Z F	
		C306	0CE1076F618	CAPACITOR, AL.ELECTROLYTIC, 100UF SMS 16V M TP(5)	
		C307	0CH6221K416	CAPACITOR, CHIP[CERAMIC LD-LESS TC], 220PF 50V J NP0	
		C309	0CH6121K416	CAPACITOR, CHIP[CERAMIC LD-LESS TC], 120PF 50V J NP0	
		C310	0CH3104K946	CAPACITOR, CHIP[CERAMIC LD-LESS HD], 100000PF 50V Z F	
		C311	0CH6470K416	CAPACITOR, CHIP[CERAMIC LD-LESS TC], 47PF 50V J NP0	
		C312	0CH6221K416	CAPACITOR, CHIP[CERAMIC LD-LESS TC], 220PF 50V J NP0	
		C313	0CH6102K406	CAPACITOR, CHIP[CERAMIC LD-LESS TC], 1000PF 50V J SL	
		C315	0CN1040K949	CAPACITOR, TUBULAR(HIGH DIELEC), 0.1M 50V Z F	
		C317	0CE1076F618	CAPACITOR, AL.ELECTROLYTIC, 100UF SMS 16V M TP(5)	
		C318	0CH3104K946	CAPACITOR, CHIP[CERAMIC LD-LESS HD], 100000PF 50V Z F	
		C321	0CH6100K116	CAPACITOR, CHIP[CERAMIC LD-LESS TC], 10PF 50V D NP0	
		C322	0CH6100K116	CAPACITOR, CHIP[CERAMIC LD-LESS TC], 10PF 50V D NP0	
		C323	0CH6100K116	CAPACITOR, CHIP[CERAMIC LD-LESS TC], 10PF 50V D NP0	
		C326	0CE1066H618	CAPACITOR, AL.ELECTROLYTIC, 10M SMS 25V M FM5 TP(5)	
		C330	0CH3104K946	CAPACITOR, CHIP[CERAMIC LD-LESS HD], 100000PF 50V Z F	
		C331	0CH3104K946	CAPACITOR, CHIP[CERAMIC LD-LESS HD], 100000PF 50V Z F	
		C332	0CH3104K946	CAPACITOR, CHIP[CERAMIC LD-LESS HD], 100000PF 50V Z F	
		C333	0CH6221K416	CAPACITOR, CHIP[CERAMIC LD-LESS TC], 220PF 50V J NP0	
		C334	0CH6221K416	CAPACITOR, CHIP[CERAMIC LD-LESS TC], 220PF 50V J NP0	
		C335	0CE1076F618	CAPACITOR, AL.ELECTROLYTIC, 100UF SMS 16V M TP(5)	
		C336	0CH3103K516	CAPACITOR, CHIP[CERAMIC LD-LESS HD], 10000PF 50V K B	
		C337	0CH3104K946	CAPACITOR, CHIP[CERAMIC LD-LESS HD], 100000PF 50V Z F	
		C338	0CH3104K946	CAPACITOR, CHIP[CERAMIC LD-LESS HD], 100000PF 50V Z F	
		C339	0CH3104K946	CAPACITOR, CHIP[CERAMIC LD-LESS HD], 100000PF 50V Z F	
		C340	0CE4766F618	CAPACITOR, AL.ELECTROLYTIC, 47U SMS 16V M FM5 TP5	
		C341	0CH3104K946	CAPACITOR, CHIP[CERAMIC LD-LESS HD], 100000PF 50V Z F	
		C342	0CH3104K946	CAPACITOR, CHIP[CERAMIC LD-LESS HD], 100000PF 50V Z F	
		C343	0CH3104K946	CAPACITOR, CHIP[CERAMIC LD-LESS HD], 100000PF 50V Z F	
		C344	0CH3104K946	CAPACITOR, CHIP[CERAMIC LD-LESS HD], 100000PF 50V Z F	
		C345	0CH3104K946	CAPACITOR, CHIP[CERAMIC LD-LESS HD], 100000PF 50V Z F	
		C346	0CE1076F618	CAPACITOR, AL.ELECTROLYTIC, 100UF SMS 16V M TP(5)	
		C347	0CE2276F618	CAPACITOR, AL.ELECTROLYTIC, 220UF SMS 16V M FL TP5	
		C348	0CE3356K618	CAPACITOR, AL.ELECTROLYTIC, 3.3U SMS 50V M FM5 TP5	
		C349	0CH3103K516	CAPACITOR, CHIP[CERAMIC LD-LESS HD], 10000PF 50V K B	
		C350	0CE1076F618	CAPACITOR, AL.ELECTROLYTIC, 100UF SMS 16V M TP(5)	

*S	*AL	LOC. NO.	PART NO.	DESCRIPTION / SPECIFICATION	REMARK
		C351	0CH3103K516	CAPACITOR, CHIP[CERAMIC LD-LESS HD], 10000PF 50V K B	
		C352	0CE3356K618	CAPACITOR, AL.ELECTROLYTIC, 3.3U SMS 50V M FM5 TP5	
		C354	0CE1056K618	CAPACITOR, AL.ELECTROLYTIC, 1.0U SMS 50V M FM5 TP5	
		C356	0CE3356K618	CAPACITOR, AL.ELECTROLYTIC, 3.3U SMS 50V M FM5 TP5	
		C357	0CE1076F618	CAPACITOR, AL.ELECTROLYTIC, 100UF SMS 16V M TP(5)	
		C358	0CH3104K946	CAPACITOR, CHIP[CERAMIC LD-LESS HD], 100000PF 50V Z F	
		C360	0CH3104K946	CAPACITOR, CHIP[CERAMIC LD-LESS HD], 100000PF 50V Z F	
		C361	0CH6120K416	CAPACITOR, CHIP[CERAMIC LD-LESS TC], 12PF 50V J NP0	
		C362	0CH6120K416	CAPACITOR, CHIP[CERAMIC LD-LESS TC], 12PF 50V J NP0	
		C363	0CH3104K946	CAPACITOR, CHIP[CERAMIC LD-LESS HD], 100000PF 50V Z F	
		C364	0CH3104K946	CAPACITOR, CHIP[CERAMIC LD-LESS HD], 100000PF 50V Z F	
		C365	0CH6120K416	CAPACITOR, CHIP[CERAMIC LD-LESS TC], 12PF 50V J NP0	
		C366	0CE4756Q638	CAPACITOR, AL.ELECTROLYTIC, 4.7000UF SMS 200V M FM5	
		C368	181-288E	CAPACITOR, POLYESTER, MKT 100V 474JTR PHS 26474	
		C369	181-288E	CAPACITOR, POLYESTER, MKT 100V 474JTR PHS 26474	
		C370	181-288E	CAPACITOR, POLYESTER, MKT 100V 474JTR PHS 26474	
		C371	0CH3104K946	CAPACITOR, CHIP[CERAMIC LD-LESS HD], 100000PF 50V Z F	
		C372	0CE1066H618	CAPACITOR, AL.ELECTROLYTIC, 10M SMS 25V M FM5 TP(5)	
		C373	0CK5610K515	CAPACITOR, CERAMIC (HIGH DIELECTRIC), 560P 50V K B TS	
		C374	0CK10301510	CAPACITOR, CERAMIC (HIGH DIELECTRIC), 0.01M 1KV K B S	
		C375	0CK2220W515	CAPACITOR, CERAMIC (HIGH DIELECTRIC), 2200P 500V K B	
		C377	0CH3104K946	CAPACITOR, CHIP[CERAMIC LD-LESS HD], 100000PF 50V Z F	
		C378	0CH3104K946	CAPACITOR, CHIP[CERAMIC LD-LESS HD], 100000PF 50V Z F	
		C379	0CH3104K946	CAPACITOR, CHIP[CERAMIC LD-LESS HD], 100000PF 50V Z F	
		C382	0CE2256P618	CAPACITOR, AL.ELECTROLYTIC, 2.2U SMS 160V M FM5 TP5	
		C383	0CE2256P618	CAPACITOR, AL.ELECTROLYTIC, 2.2U SMS 160V M FM5 TP5	
		C384	0CE2256P618	CAPACITOR, AL.ELECTROLYTIC, 2.2U SMS 160V M FM5 TP5	
		C385	0CE2266N618	CAPACITOR, AL.ELECTROLYTIC, 22M SMS 100V M FM5 TP5	
		C386	0CH3104K946	CAPACITOR, CHIP[CERAMIC LD-LESS HD], 100000PF 50V Z F	
		C387	0CH3104K946	CAPACITOR, CHIP[CERAMIC LD-LESS HD], 100000PF 50V Z F	
		C388	0CH3104K946	CAPACITOR, CHIP[CERAMIC LD-LESS HD], 100000PF 50V Z F	
		C389	0CH3104K946	CAPACITOR, CHIP[CERAMIC LD-LESS HD], 100000PF 50V Z F	
		C390	0CE1056Q638	CAPACITOR, AL.ELECTROLYTIC, 1UF SMS 200V M FM5 TP5	
		C391	0CE1076F618	CAPACITOR, AL.ELECTROLYTIC, 100UF SMS 16V M TP(5)	
		C392	0CH3104K946	CAPACITOR, CHIP[CERAMIC LD-LESS HD], 100000PF 50V Z F	
		C393	0CE1066H618	CAPACITOR, AL.ELECTROLYTIC, 10M SMS 25V M FM5 TP(5)	
		C394	0CH3104K946	CAPACITOR, CHIP[CERAMIC LD-LESS HD], 100000PF 50V Z F	
		C395	0CE1066H618	CAPACITOR, AL.ELECTROLYTIC, 10M SMS 25V M FM5 TP(5)	
DIODEs					
		D301	0DS113309AA	DIODE, SWITCHING, 1SS133 TP ROHM KOREA DO34 90V 0.4A	
		D302	0DS113309AA	DIODE, SWITCHING, 1SS133 TP ROHM KOREA DO34 90V 0.4A	
		D304	0DS113309AA	DIODE, SWITCHING, 1SS133 TP ROHM KOREA DO34 90V 0.4A	
		D305	0DS113309AA	DIODE, SWITCHING, 1SS133 TP ROHM KOREA DO34 90V 0.4A	
		D306	0DS113309AA	DIODE, SWITCHING, 1SS133 TP ROHM KOREA DO34 90V 0.4A	

MODEL: Flatron 795FT plus, 未来窗 795FT plus				DATE: 1999. 2. 5.	
*S	*AL	LOC. NO.	PART NO.	DESCRIPTION / SPECIFICATION	REMARK
		D307	0DS113309AA	DIODE, SWITCHING, 1SS133 TP ROHM KOREA DO34 90V 0.4A	
		D308	0DS113309AA	DIODE, SWITCHING, 1SS133 TP ROHM KOREA DO34 90V 0.4A	
		D309	0DS113309AA	DIODE, SWITCHING, 1SS133 TP ROHM KOREA DO34 90V 0.4A	
		D310	0DD860009AA	DIODE, RECTIFIER, BAT 86 TP PHILIPS DO34 50V 0.2A 0.25A	
		D311	0DS226009AA	DIODE, SWITCHING, KDS226 TP KEC SOT-23 80V 300MA 2A	
		D312	0DS226009AA	DIODE, SWITCHING, KDS226 TP KEC SOT-23 80V 300MA 2A	
		D313	0DS226009AA	DIODE, SWITCHING, KDS226 TP KEC SOT-23 80V 300MA 2A	
		D321	0DZ910009AH	DIODE, ZENER, MTZJ9.1B TP ROHM-K DO34 500MW 9.1V	
		D361	0DD830009AA	DIODE, SWITCHING, 1SS83 TP HITACHI DO35 250V 625MA	
		D362	0DD830009AA	DIODE, SWITCHING, 1SS83 TP HITACHI DO35 250V 625MA	
		D363	0DD830009AA	DIODE, SWITCHING, 1SS83 TP HITACHI DO35 250V 625MA	
		D364	0DD830009AA	DIODE, SWITCHING, 1SS83 TP HITACHI DO35 250V 625MA	
		D365	0DD830009AA	DIODE, SWITCHING, 1SS83 TP HITACHI DO35 250V 625MA	
		D366	0DD830009AA	DIODE, SWITCHING, 1SS83 TP HITACHI DO35 250V 625MA	
		D367	0DD830009AA	DIODE, SWITCHING, 1SS83 TP HITACHI DO35 250V 625MA	
		D368	0DD830009AA	DIODE, SWITCHING, 1SS83 TP HITACHI DO35 250V 625MA	
		D369	0DD830009AA	DIODE, SWITCHING, 1SS83 TP HITACHI DO35 250V 625MA	
		D376	0DD100009DE	DIODE, RECTIFIER, RGP10G TP G.I DO204AL 400V 1A 30A	
		D390	0DS113309AA	DIODE, SWITCHING, 1SS133 TP ROHM KOREA DO34 90V 0.4A	
ICs					
		IC301	0IMO455020A	IC, MOTOROLA, LSC4550P2 16,DIP BK OSD	
		IC302	0IMI527430B	IC, MITSUBISHI, M52743BSP 36P,SDIP BK 3CH VIDEO PREAMP	
		IC303	0ISA130000B	IC, SANYO, VPS13 SIP15 BK VIDEO OUTPUT	
		IC304	0IMA576900A	IC, MATSUSHITA, AN5769 SIL12P BK H/V CONV. CORRECTION	
		IC305	0ISS790500C	IC, SAMSUNG ELECTRONICS, KA7905 TO-220 BK REGULATOR	
		IC306	0IKE780800B	IC, KEC, KIA78L08BP(TA) TO-92 8V,150MA	
COILs & COREs					
		L301	0LA0390K119	INDUCTOR, AXIAL LEAD, 0.39UH K 2.3*3.4 TP	
		L302	0LA0272K119	INDUCTOR, AXIAL LEAD, 27UH K 2.3*3.4 TP	
		L303	125-155L	CORE (CIRC), BEAD, BFS3580A0FG SAMWHA 3.5*8.0MM	
		L331	0LR1000K5N5	INDUCTOR, RADIAL LEAD, EL0305RA TDK-K 100UH 10% M	
		L361	0LA0270K119	INDUCTOR, AXIAL LEAD, 0.27UH K 2.3*3.4 TP	
		L362	0LA0270K119	INDUCTOR, AXIAL LEAD, 0.27UH K 2.3*3.4 TP	
		L363	0LA0270K119	INDUCTOR, AXIAL LEAD, 0.27UH K 2.3*3.4 TP	
		L364	0LA1000K119	INDUCTOR, AXIAL LEAD, 100UH K 2.3*3.4 TP	
		L365	125-155A	CORE (CIRC), BEAD, BFD3510R2FG SAMWHA 3.5*10MM	
TRANSISTORs					
		Q301	0TR390409CA	TRANSISTOR, 2N3904 TP SAMSUNG TO92 NPN	
		Q302	0TR390409CA	TRANSISTOR, 2N3904 TP SAMSUNG TO92 NPN	
		Q303	0TR390409CA	TRANSISTOR, 2N3904 TP SAMSUNG TO92 NPN	
		Q304	0TR390409CA	TRANSISTOR, 2N3904 TP SAMSUNG TO92 NPN	
		Q305	0TR390409CA	TRANSISTOR, 2N3904 TP SAMSUNG TO92 NPN	
		Q309	0TR390409CA	TRANSISTOR, 2N3904 TP SAMSUNG TO92 NPN	

MODEL: Flatron 795FT plus, 未来窗 795FT plus				DATE: 1999. 2. 5.	
*S	*AL	LOC. NO.	PART NO.	DESCRIPTION / SPECIFICATION	REMARK
		Q330	0TR390609FA	TRANSISTOR, KST3906-MTF TP SAMSUNG SOT23 GEN.	
		Q331	0TR390609FA	TRANSISTOR, KST3906-MTF TP SAMSUNG SOT23 GEN.	
		Q332	0TR390609FA	TRANSISTOR, KST3906-MTF TP SAMSUNG SOT23 GEN.	
		Q361	0TR137009AA	TRANSISTOR, 2SA1370D/E TP SANYO MP PNP	
		Q362	0TR320609AB	TRANSISTOR, KTC3206-Y,TP(KTC2229),KEC	
		Q363	0TR137009AA	TRANSISTOR, 2SA1370D/E TP SANYO MP PNP	
		Q364	0TR320609AB	TRANSISTOR, KTC3206-Y,TP(KTC2229),KEC	
		Q365	0TR137009AA	TRANSISTOR, 2SA1370D/E TP SANYO MP PNP	
		Q366	0TR320609AB	TRANSISTOR, KTC3206-Y,TP(KTC2229),KEC	
		Q390	0TR320709AA	TRANSISTOR, KTC3207,TP(KTC2482),KEC	
<b>RESISTORs</b>					
		R301	0RH1000D622	RESISTOR, CHIP, 100 1/10W 5 D.R/TP	
		R302	0RH1000D622	RESISTOR, CHIP, 100 1/10W 5 D.R/TP	
		R303	0RH1000D622	RESISTOR, CHIP, 100 1/10W 5 D.R/TP	
		R304	0RH1001D622	RESISTOR, CHIP, 1.0K 1/10W 5 D.R/TP	
		R305	0RH1002D622	RESISTOR, CHIP, 10K 1/10W 5 D.R/TP	
		R306	0RH1000D622	RESISTOR, CHIP, 100 1/10W 5 D.R/TP	
		R307	0RH1000D622	RESISTOR, CHIP, 100 1/10W 5 D.R/TP	
		R308	0RH5601D622	RESISTOR, CHIP, 5.6K 1/10W 5 D.R/TP	
		R309	0RH2001D622	RESISTOR, CHIP, 2.0K 1/10W 5 D.R/TP	
		R310	0RH2001D622	RESISTOR, CHIP, 2.0K 1/10W 5 D.R/TP	
		R311	0RH2002D622	RESISTOR, CHIP, 20K 1/10W 5 D.R/TP	
		R312	0RH4700D622	RESISTOR, CHIP, 470 1/10W 5 D.R/TP	
		R313	0RH4700D622	RESISTOR, CHIP, 470 1/10W 5 D.R/TP	
		R314	0RH2203D622	RESISTOR, CHIP, 220K 1/10W 5 D.R/TP	
		R315	0RH3301D622	RESISTOR, CHIP, 3.3K 1/10W 5 D.R/TP	
		R316	0RH1001D622	RESISTOR, CHIP, 1.0K 1/10W 5 D.R/TP	
		R317	0RH4701D622	RESISTOR, CHIP, 4.7K 1/10W 5 D.R/TP	
		R318	0RH2201D622	RESISTOR, CHIP, 2.2K 1/10W P-TYPE TAPPING	
		R319	0RH2201D622	RESISTOR, CHIP, 2.2K 1/10W P-TYPE TAPPING	
		R320	0RH1001D622	RESISTOR, CHIP, 1.0K 1/10W 5 D.R/TP	
		R321	0RH1002D622	RESISTOR, CHIP, 10K 1/10W 5 D.R/TP	
		R327	0RD2200Q609	RESISTOR, FIXED CARBON FILM, 220 1/4W(3 5%	
		R328	0RH1002D622	RESISTOR, CHIP, 10K 1/10W 5 D.R/TP	
		R329	0RH1202D622	RESISTOR, CHIP, 12K 1/10W 5 D.R/TP	
		R330	0RH2201D622	RESISTOR, CHIP, 2.2K 1/10W P-TYPE TAPPING	
		R331	0RH0752D622	RESISTOR, CHIP, 75 1/10W 5 D.R/TP	
		R332	0RH0752D622	RESISTOR, CHIP, 75 1/10W 5 D.R/TP	
		R333	0RH0752D622	RESISTOR, CHIP, 75 1/10W 5 D.R/TP	
		R334	0RH1000D622	RESISTOR, CHIP, 100 1/10W 5 D.R/TP	
		R335	0RH1000D622	RESISTOR, CHIP, 100 1/10W 5 D.R/TP	
		R336	0RH1000D622	RESISTOR, CHIP, 100 1/10W 5 D.R/TP	
		R337	0RH1001D622	RESISTOR, CHIP, 1.0K 1/10W 5 D.R/TP	
		R338	0RH2001D622	RESISTOR, CHIP, 2.0K 1/10W 5 D.R/TP	

*S	*AL	LOC. NO.	PART NO.	DESCRIPTION / SPECIFICATION	REMARK
		R339	0RH0472D622	RESISTOR, CHIP, 47 1/10W 5 D.R/TP	
		R340	0RD4700Q609	RESISTOR, FIXED CARBON FILM, 470 OHM 1/4 W (3.4) 5%	
		R341	0RH2001D622	RESISTOR, CHIP, 2.0K 1/10W 5 D.R/TP	
		R342	0RH0472D622	RESISTOR, CHIP, 47 1/10W 5 D.R/TP	
		R343	0RD4700Q609	RESISTOR, FIXED CARBON FILM, 470 OHM 1/4 W (3.4) 5%	
		R344	0RH2001D622	RESISTOR, CHIP, 2.0K 1/10W 5 D.R/TP	
		R345	0RH0472D622	RESISTOR, CHIP, 47 1/10W 5 D.R/TP	
		R346	0RD4700Q609	RESISTOR, FIXED CARBON FILM, 470 OHM 1/4 W (3.4) 5%	
		R347	0RH1000D622	RESISTOR, CHIP, 100 1/10W 5 D.R/TP	
		R348	0RH2700D622	RESISTOR, CHIP, 270 1/10W 5 D.R/TP	
		R349	0RH1801D622	RESISTOR, CHIP, 1.8K 1/10W 5 D.R/TP	
		R350	0RD1803A609	RESISTOR, FIXED CARBON FILM, 180K OHM 1/2 W (7.0) 5%	
		R351	0RH0152D622	RESISTOR, CHIP, 15 1/10W 5 D.R/TP	
		R352	0RH0152D622	RESISTOR, CHIP, 15 1/10W 5 D.R/TP	
		R353	0RH0152D622	RESISTOR, CHIP, 15 1/10W 5 D.R/TP	
		R357	0RD5602Q609	RESISTOR, FIXED CARBON FILM, 56K 1/4W(3 5%	
		R358	0RH1000D622	RESISTOR, CHIP, 100 1/10W 5 D.R/TP	
		R359	0RD0472Q609	RESISTOR, FIXED CARBON FILM, 47 1/4W(3 5%	
		R360	0RH1000D622	RESISTOR, CHIP, 100 1/10W 5 D.R/TP	
		R361	0RH0682D622	RESISTOR, CHIP, 68 1/10W 5 D.R/TP	
		R362	0RH0682D622	RESISTOR, CHIP, 68 1/10W 5 D.R/TP	
		R363	0RD0472Q609	RESISTOR, FIXED CARBON FILM, 47 1/4W(3 5%	
		R364	0RH1000D622	RESISTOR, CHIP, 100 1/10W 5 D.R/TP	
		R365	0RD0472Q609	RESISTOR, FIXED CARBON FILM, 47 1/4W(3 5%	
		R366	0RH0682D622	RESISTOR, CHIP, 68 1/10W 5 D.R/TP	
		R367	0RH3300D622	RESISTOR, CHIP, 330 1/10W 5 D.R/TP	
		R368	0RD0222Q609	RESISTOR, FIXED CARBON FILM, 22 1/4W(3 5%	
		R369	0RH1004D622	RESISTOR, CHIP, 1.0M 1/10W 5 D.R/TP	
		R370	0RH3300D622	RESISTOR, CHIP, 330 1/10W 5 D.R/TP	
		R371	0RD0222Q609	RESISTOR, FIXED CARBON FILM, 22 1/4W(3 5%	
		R372	0RH1004D622	RESISTOR, CHIP, 1.0M 1/10W 5 D.R/TP	
		R373	0RH6800D622	RESISTOR, CHIP, 680 OHM 1 / 10 W 5% D R/TP	
		R374	0RD0222Q609	RESISTOR, FIXED CARBON FILM, 22 1/4W(3 5%	
		R375	0RH1004D622	RESISTOR, CHIP, 1.0M 1/10W 5 D.R/TP	
		R376	0RD1000Q609	RESISTOR, FIXED CARBON FILM, 100 1/4W(3 5%	
		R377	0RH4702D622	RESISTOR, CHIP, 47K 1/10W 5 D.R/TP	
		R378	0RH1502D622	RESISTOR, CHIP, 15K 1/10W 5 D.R/TP	
		R379	0RH5602D622	RESISTOR, CHIP, 56K 1/10W 5 D.R/TP	
		R380	0RH2201D622	RESISTOR, CHIP, 2.2K 1/10W P-TYPE TAPPING	
		R381	0RH4702D622	RESISTOR, CHIP, 47K 1/10W 5 D.R/TP	
		R382	0RH1502D622	RESISTOR, CHIP, 15K 1/10W 5 D.R/TP	
		R383	0RH2201D622	RESISTOR, CHIP, 2.2K 1/10W P-TYPE TAPPING	
		R384	0RH5602D622	RESISTOR, CHIP, 56K 1/10W 5 D.R/TP	
		R385	0RH4702D622	RESISTOR, CHIP, 47K 1/10W 5 D.R/TP	
		R386	0RH1502D622	RESISTOR, CHIP, 15K 1/10W 5 D.R/TP	
		R387	0RH2201D622	RESISTOR, CHIP, 2.2K 1/10W P-TYPE TAPPING	

MODEL: Flatron 795FT plus, 未来窗 795FT plus				DATE: 1999. 2. 5.	
*S	*AL	LOC. NO.	PART NO.	DESCRIPTION / SPECIFICATION	REMARK
		R388	0RH5602D622	RESISTOR, CHIP, 56K 1/10W 5 D.R/TP	
		R389	0RD0101Q609	RESISTOR, FIXED CARBON FILM, 1 1/4W(3 5%	
		R391	0RH1803D422	RESISTOR, CHIP, 180000 OHM 1 / 10 W 1% D R/TP	
		R392	0RH2703D622	RESISTOR, CHIP, 270K 1/10W 5 D.R/TP	
		R393	0RH1004D622	RESISTOR, CHIP, 1.0M 1/10W 5 D.R/TP	
		R396	0RH4700D622	RESISTOR, CHIP, 470 1/10W 5 D.R/TP	
		R397	0RH4701D622	RESISTOR, CHIP, 4.7K 1/10W 5 D.R/TP	
		R398	0RH1501D622	RESISTOR, CHIP, 1.5K 1/10W 5 D.R/TP	
		R3101	0RH5601D622	RESISTOR, CHIP, 5.6K 1/10W 5 D.R/TP	
		R3102	0RH5601D622	RESISTOR, CHIP, 5.6K 1/10W 5 D.R/TP	
		R3103	0RH5601D622	RESISTOR, CHIP, 5.6K 1/10W 5 D.R/TP	
		R3104	0RH5601D622	RESISTOR, CHIP, 5.6K 1/10W 5 D.R/TP	
		R3105	0RH0332D622	RESISTOR, CHIP, 33 1/10W 5 D.R/TP	
		R3106	0RH0332D622	RESISTOR, CHIP, 33 1/10W 5 D.R/TP	
<b>OTHERs</b>					
		SG301	6918TAT001B	SPARK GAP, AXIAL, DSP-201M-A21F MMC AXIAL TAPPING	
		SG302	6918TAT001B	SPARK GAP, AXIAL, DSP-201M-A21F MMC AXIAL TAPPING	
		SG303	6918TAT001B	SPARK GAP, AXIAL, DSP-201M-A21F MMC AXIAL TAPPING	
		SG304	6918TAT001B	SPARK GAP, AXIAL, DSP-201M-A21F MMC AXIAL TAPPING	
		SG305	165-004A	SPARK GAP, AG20PT 152F-L3N/S-23 HANDOK RADIAL BULK	
		SK301	381-094L	SOCKET (CIRC), CPT, 033-0-7700-41 METALLO 10PIN 14/360	
<b>INTERFACE BOARD</b>					
<b>CAPACITORS</b>					
		C101	0CE2264F638	CAPACITOR, AL.ELECTROLYTIC, 22UF SRA,SS 16V M FM5	
		C102	0CN1040K949	CAPACITOR, TUBULAR(HIGH DIELEC), 0.1M 50V Z F	
		C103	0CN1040K949	CAPACITOR, TUBULAR(HIGH DIELEC), 0.1M 50V Z F	
		C104	0CN1040K949	CAPACITOR, TUBULAR(HIGH DIELEC), 0.1M 50V Z F	
		C105	0CN1040K949	CAPACITOR, TUBULAR(HIGH DIELEC), 0.1M 50V Z F	
		C106	0CH3104K946	CAPACITOR, CHIP[CERAMIC LD-LESS HD], 100000PF 50V Z F	
		C131	0CN1040K949	CAPACITOR, TUBULAR(HIGH DIELEC), 0.1M 50V Z F	
		C132	0CE2264F638	CAPACITOR, AL.ELECTROLYTIC, 22UF SRA,SS 16V M FM5	
		C133	0CN1040K949	CAPACITOR, TUBULAR(HIGH DIELEC), 0.1M 50V Z F	
		C134	0CN1040K949	CAPACITOR, TUBULAR(HIGH DIELEC), 0.1M 50V Z F	
		C135	0CN1040K949	CAPACITOR, TUBULAR(HIGH DIELEC), 0.1M 50V Z F	
		C136	0CN1040K949	CAPACITOR, TUBULAR(HIGH DIELEC), 0.1M 50V Z F	
		C138	0CH6220K416	CAPACITOR, CHIP[CERAMIC LD-LESS TC], 22PF 50V J NP0	
		C141	0CH6220K416	CAPACITOR, CHIP[CERAMIC LD-LESS TC], 22PF 50V J NP0	
		C152	0CH6220K416	CAPACITOR, CHIP[CERAMIC LD-LESS TC], 22PF 50V J NP0	
		C154	0CH6220K416	CAPACITOR, CHIP[CERAMIC LD-LESS TC], 22PF 50V J NP0	
		C158	0CH6220K416	CAPACITOR, CHIP[CERAMIC LD-LESS TC], 22PF 50V J NP0	
		C160	0CE2264F638	CAPACITOR, AL.ELECTROLYTIC, 22UF SRA,SS 16V M FM5	
		C161	0CH6220K416	CAPACITOR, CHIP[CERAMIC LD-LESS TC], 22PF 50V J NP0	

MODEL: Flatron 795FT plus, 未来窗 795FT plus				DATE: 1999. 2. 5.	
*S	*AL	LOC. NO.	PART NO.	DESCRIPTION / SPECIFICATION	REMARK
DIODEs					
		D101	0DZ560009CE	DIODE, ZENER, MTZJ5.6B TP ROHM-K DO34 500MW 5.6V 5MA	
		D102	0DZ560009CE	DIODE, ZENER, MTZJ5.6B TP ROHM-K DO34 500MW 5.6V 5MA	
		D103	0DZ510009AB	DIODE, ZENER, MTZ5.1B TP ROHM-K DO34 500MW 5.1V 20MA	
		D104	0DZ510009AB	DIODE, ZENER, MTZ5.1B TP ROHM-K DO34 500MW 5.1V 20MA	
		D105	0DZ510009AB	DIODE, ZENER, MTZ5.1B TP ROHM-K DO34 500MW 5.1V 20MA	
		D107	0DZ510009AB	DIODE, ZENER, MTZ5.1B TP ROHM-K DO34 500MW 5.1V 20MA	
		D108	0DZ510009AB	DIODE, ZENER, MTZ5.1B TP ROHM-K DO34 500MW 5.1V 20MA	
		D109	0DZ510009AB	DIODE, ZENER, MTZ5.1B TP ROHM-K DO34 500MW 5.1V 20MA	
		D133	0DL571300AA	LED, SPR571MVW3 TP ROHM GREEN/RED 10,10MCD	
		D136	0DS113309AA	DIODE, SWITCHING, 1SS133 TP ROHM KOREA DO34 90V 0.4A	
		D137	0DS113309AA	DIODE, SWITCHING, 1SS133 TP ROHM KOREA DO34 90V 0.4A	
		D140	0DS113309AA	DIODE, SWITCHING, 1SS133 TP ROHM KOREA DO34 90V 0.4A	
		D141	0DS113309AA	DIODE, SWITCHING, 1SS133 TP ROHM KOREA DO34 90V 0.4A	
		D150	0DZ120009AF	DIODE, ZENER, MTZJ12B TP ROHM-K DO34 500MW 12V 5MA	
		D151	0DS226009AA	DIODE, SWITCHING, KDS226 TP KEC SOT-23 80V 300MA 2A	
		D155	0DS226009AA	DIODE, SWITCHING, KDS226 TP KEC SOT-23 80V 300MA 2A	
		D157	0DS226009AA	DIODE, SWITCHING, KDS226 TP KEC SOT-23 80V 300MA 2A	
		D159	0DS113309AA	DIODE, SWITCHING, 1SS133 TP ROHM KOREA DO34 90V 0.4A	
		D160	0DS113309AA	DIODE, SWITCHING, 1SS133 TP ROHM KOREA DO34 90V 0.4A	
		D161	0DZ120009AF	DIODE, ZENER, MTZJ12B TP ROHM-K DO34 500MW 12V 5MA	
ICs					
		IC101	0IPH401300A	IC, PHILIPS, HEF4013BP 14P DIP BK FLIP FLOP	
		IC102	0IPH401300A	IC, PHILIPS, HEF4013BP 14P DIP BK FLIP FLOP	
		IC103	0IPH401300A	IC, PHILIPS, HEF4013BP 14P DIP BK FLIP FLOP	
COILs & COREs					
		L101	125-155N	CORE (CIRC),BEAD, BFD3565R2FG SAMWHA 3.5*6.5MM	
		L131	971-0016	WIRE, JUMP, TIN HDC 0.60H	
TRANSISTORs					
		Q102	0TR114009AB	TRANSISTOR, DTC114ES TP ROHM-K SPT NPN	
		Q103	0TR114009AB	TRANSISTOR, DTC114ES TP ROHM-K SPT NPN	
		Q104	0TR114009AB	TRANSISTOR, DTC114ES TP ROHM-K SPT NPN	
		Q105	0TR114009AB	TRANSISTOR, DTC114ES TP ROHM-K SPT NPN	
		Q106	0TR114009AB	TRANSISTOR, DTC114ES TP ROHM-K SPT NPN	
		Q107	0TR114009AB	TRANSISTOR, DTC114ES TP ROHM-K SPT NPN	
		Q110	0TR114009AB	TRANSISTOR, DTC114ES TP ROHM-K SPT NPN	
		Q111	0TR114009AB	TRANSISTOR, DTC114ES TP ROHM-K SPT NPN	
		Q131	0TR114009AB	TRANSISTOR, DTC114ES TP ROHM-K SPT NPN	
		Q132	0TR114009AB	TRANSISTOR, DTC114ES TP ROHM-K SPT NPN	
		Q133	0TR114009AB	TRANSISTOR, DTC114ES TP ROHM-K SPT NPN	
		Q136	0TR390409AE	TRANSISTOR, KST3904-MTF TP SAMSUNG SOT23 GEN.	
		Q139	0TR390409AE	TRANSISTOR, KST3904-MTF TP SAMSUNG SOT23 GEN.	
		Q150	0TR390409AE	TRANSISTOR, KST3904-MTF TP SAMSUNG SOT23 GEN.	

MODEL: Flatron 795FT plus, 未来窗 795FT plus				DATE: 1999. 2. 5.	
*S	*AL	LOC. NO.	PART NO.	DESCRIPTION / SPECIFICATION	REMARK
		Q153	0TR390409AE	TRANSISTOR, KST3904-MTF TP SAMSUNG SOT23 GEN.	
		Q156	0TR390409AE	TRANSISTOR, KST3904-MTF TP SAMSUNG SOT23 GEN.	
		Q159	0TR390409AE	TRANSISTOR, KST3904-MTF TP SAMSUNG SOT23 GEN.	
<b>RESISTORS</b>					
		R101	0RN1001F409	RESISTOR, FIXED METAL FILM, 1K 1/6W 1%	
		R102	0RN3000F409	RESISTOR, FIXED METAL FILM, 300 1/6W 1%	
		R103	0RN3000F409	RESISTOR, FIXED METAL FILM, 300 1/6W 1%	
		R104	0RN4700F409	RESISTOR, FIXED METAL FILM, 470 1/6W 1	
		R105	0RD9100Q609	RESISTOR, FIXED CARBON FILM, 910 1/4W(3 5%	
		R106	0RD1801Q609	RESISTOR, FIXED CARBON FILM, 1.80K 1/4W(3 5%	
		R107	0RD6201Q609	RESISTOR, FIXED CARBON FILM, 6.20K 1/4W(3 5%	
		R108	0RH5100D622	RESISTOR, CHIP, 510 1/10W 5 D.R/TP	
		R110	0RD1002Q609	RESISTOR, FIXED CARBON FILM, 10K 1/4W(3 5%	
		R111	0RD1001Q609	RESISTOR, FIXED CARBON FILM, 1K 1/4W(3 5%	
		R112	0RD1001Q609	RESISTOR, FIXED CARBON FILM, 1K 1/4W(3 5%	
		R113	0RD1001Q609	RESISTOR, FIXED CARBON FILM, 1K 1/4W(3 5%	
		R114	0RD1001Q609	RESISTOR, FIXED CARBON FILM, 1K 1/4W(3 5%	
		R115	0RD1001Q609	RESISTOR, FIXED CARBON FILM, 1K 1/4W(3 5%	
		R116	0RD1001Q609	RESISTOR, FIXED CARBON FILM, 1K 1/4W(3 5%	
		R117	0RD1001Q609	RESISTOR, FIXED CARBON FILM, 1K 1/4W(3 5%	
		R118	0RD1001Q609	RESISTOR, FIXED CARBON FILM, 1K 1/4W(3 5%	
		R121	0RD4700Q609	RESISTOR, FIXED CARBON FILM, 470 OHM 1/4 W (3.4) 5%	
		R122	0RH4700D622	RESISTOR, CHIP, 470 1/10W 5 D.R/TP	
		R123	0RH4700D622	RESISTOR, CHIP, 470 1/10W 5 D.R/TP	
		R131	0RD1800Q609	RESISTOR, FIXED CARBON FILM, 180 1/4W(3 5%	
		R132	0RD2200Q609	RESISTOR, FIXED CARBON FILM, 220 1/4W(3 5%	
		R133	0RD2200Q609	RESISTOR, FIXED CARBON FILM, 220 1/4W(3 5%	
		R134	0RD1300Q609	RESISTOR, FIXED CARBON FILM, 130 1/4W(3 5%	
		R135	0RD1501Q609	RESISTOR, FIXED CARBON FILM, 1.50K 1/4W(3 5%	
		R136	0RD1002Q609	RESISTOR, FIXED CARBON FILM, 10K 1/4W(3 5%	
		R137	0RD2402A609	RESISTOR, FIXED CARBON FILM, 24K OHM 1/2 W (7.0) 5%	
		R138	0RH2202D622	RESISTOR, CHIP, 22K 1/10W 5 D.R/TP	
		R139	0RD1002Q609	RESISTOR, FIXED CARBON FILM, 10K 1/4W(3 5%	
		R140	0RD2402A609	RESISTOR, FIXED CARBON FILM, 24K OHM 1/2 W (7.0) 5%	
		R141	0RH2202D622	RESISTOR, CHIP, 22K 1/10W 5 D.R/TP	
		R150	0RD1002Q609	RESISTOR, FIXED CARBON FILM, 10K 1/4W(3 5%	
		R151	0RD2402A609	RESISTOR, FIXED CARBON FILM, 24K OHM 1/2 W (7.0) 5%	
		R152	0RH2202D622	RESISTOR, CHIP, 22K 1/10W 5 D.R/TP	
		R153	0RD1002Q609	RESISTOR, FIXED CARBON FILM, 10K 1/4W(3 5%	
		R154	0RD2202Q609	RESISTOR, FIXED CARBON FILM, 22K 1/4W(3 5%	
		R155	0RD2402A609	RESISTOR, FIXED CARBON FILM, 24K OHM 1/2 W (7.0) 5%	
		R156	0RD1002Q609	RESISTOR, FIXED CARBON FILM, 10K 1/4W(3 5%	
		R157	0RD2402A609	RESISTOR, FIXED CARBON FILM, 24K OHM 1/2 W (7.0) 5%	
		R158	0RD2202Q609	RESISTOR, FIXED CARBON FILM, 22K 1/4W(3 5%	

MODEL: Flatron 795FT plus, 未来窗 795FT plus				DATE: 1999. 2. 5.	
*S	*AL	LOC. NO.	PART NO.	DESCRIPTION / SPECIFICATION	REMARK
		R159	0RD1002Q609	RESISTOR, FIXED CARBON FILM, 10K 1/4W(3 5%	
		R160	0RD2402A609	RESISTOR, FIXED CARBON FILM, 24K OHM 1/2 W (7.0) 5%	
		R161	0RD2202Q609	RESISTOR, FIXED CARBON FILM, 22K 1/4W(3 5%	
		R170	0RD2200Q609	RESISTOR, FIXED CARBON FILM, 220 1/4W(3 5%	
<b>OTHERs</b>					
		BZ130	126-005A	BUZZER, PIEZO ELECTRIC, PKM13EPP-4002 (MURATA)	
		SW131	140-058D	SWITCH, TACT, SKHV10911A LGEC NON 12 20 HORIZONTAL	
<b>CONTROL BORAD</b>					
<b>CAPACITORS</b>					
		C202	0CH3104K946	CAPACITOR, CHIP[CERAMIC LD-LESS HD], 100000PF 50V Z F	
		C203	0CH6200K416	CAPACITOR, CHIP[CERAMIC LD-LESS TC], 20PF 50V J NP0	
		C205	0CH3104K946	CAPACITOR, CHIP[CERAMIC LD-LESS HD], 100000PF 50V Z F	
		C206	0CH6221K416	CAPACITOR, CHIP[CERAMIC LD-LESS TC], 220PF 50V J NP0	
		C207	0CH3104K946	CAPACITOR, CHIP[CERAMIC LD-LESS HD], 100000PF 50V Z F	
		C208	0CH6221K416	CAPACITOR, CHIP[CERAMIC LD-LESS TC], 220PF 50V J NP0	
		C209	0CH3104K946	CAPACITOR, CHIP[CERAMIC LD-LESS HD], 100000PF 50V Z F	
		C211	0CE1064H638	CAPACITOR, AL.ELECTROLYTIC, 10UF SRA 25V M FM5 TP5	
		C212	0CH6330K416	CAPACITOR, CHIP[CERAMIC LD-LESS TC], 33PF 50V J NP0	
		C213	0CH6330K416	CAPACITOR, CHIP[CERAMIC LD-LESS TC], 33PF 50V J NP0	
		C214	0CH3104K946	CAPACITOR, CHIP[CERAMIC LD-LESS HD], 100000PF 50V Z F	
		C215	0CH3104K946	CAPACITOR, CHIP[CERAMIC LD-LESS HD], 100000PF 50V Z F	
		C216	0RH1000D622	RESISTOR, CHIP, 100 1/10W 5 D.R/TP	
		C220	0CE1074F638	CAPACITOR, AL.ELECTROLYTIC, 100UF SRA,SS 16V M FM5	
		C221	0CH3104K946	CAPACITOR, CHIP[CERAMIC LD-LESS HD], 100000PF 50V Z F	
		C222	0CH3104K946	CAPACITOR, CHIP[CERAMIC LD-LESS HD], 100000PF 50V Z F	
		C241	0CE2264H638	CAPACITOR, AL.ELECTROLYTIC, 22UF SRA 25V M FM5 TP5	
		C242	0CH3104K946	CAPACITOR, CHIP[CERAMIC LD-LESS HD], 100000PF 50V Z F	
		C243	0CH3104K946	CAPACITOR, CHIP[CERAMIC LD-LESS HD], 100000PF 50V Z F	
		C244	0CH3104K946	CAPACITOR, CHIP[CERAMIC LD-LESS HD], 100000PF 50V Z F	
		C245	0CH3104K946	CAPACITOR, CHIP[CERAMIC LD-LESS HD], 100000PF 50V Z F	
		C246	0CH6221K416	CAPACITOR, CHIP[CERAMIC LD-LESS TC], 220PF 50V J NP0	
		C251	0CH3104K946	CAPACITOR, CHIP[CERAMIC LD-LESS HD], 100000PF 50V Z F	
		C252	0CE108CD618	CAPACITOR, AL.ELECTROLYTIC, 1000UF SHL 10V M FL TP5	
		C253	0CH3104K946	CAPACITOR, CHIP[CERAMIC LD-LESS HD], 100000PF 50V Z F	
		C254	0CE2264H638	CAPACITOR, AL.ELECTROLYTIC, 22UF SRA 25V M FM5 TP5	
		C255	0CE3354K638	CAPACITOR, AL.ELECTROLYTIC, 3.3U SRA 50V M FM5 TP(5)	
		C256	0CH3104K946	CAPACITOR, CHIP[CERAMIC LD-LESS HD], 100000PF 50V Z F	
		C257	0CK1020W515	CAPACITOR, CERAMIC (HIGH DIELECTRIC), 1000P 500V	
		C260	0CE1064H638	CAPACITOR, AL.ELECTROLYTIC, 10UF SRA 25V M FM5 TP5	
		C261	0CH3104K946	CAPACITOR, CHIP[CERAMIC LD-LESS HD], 100000PF 50V Z F	
		C262	0CE1074F638	CAPACITOR, AL.ELECTROLYTIC, 100UF SRA,SS 16V M FM5	
		C272	0CE4754K638	CAPACITOR, AL.ELECTROLYTIC, 4.7M SRA 50V M FM5 TP(5)	
		C274	0CE2264H638	CAPACITOR, AL.ELECTROLYTIC, 22UF SRA 25V M FM5 TP5	

MODEL: Flatron 795FT plus, 未来窗 795FT plus				DATE: 1999. 2. 5.	
*S	*AL	LOC. NO.	PART NO.	DESCRIPTION / SPECIFICATION	REMARK
		C275	0CE2264H638	CAPACITOR, AL.ELECTROLYTIC, 22UF SRA 25V M FM5 TP5	
		C278	0CE3354K638	CAPACITOR, AL.ELECTROLYTIC, 3.3U SRA 50V M FM5 TP(5)	
		C279	0CE3354K638	CAPACITOR, AL.ELECTROLYTIC, 3.3U SRA 50V M FM5 TP(5)	
		C280	0CE3354K638	CAPACITOR, AL.ELECTROLYTIC, 3.3U SRA 50V M FM5 TP(5)	
		C810	0CH6100K116	CAPACITOR, CHIP[CERAMIC LD-LESS TC], 10PF 50V D NP0	
		C811	0CH6100K116	CAPACITOR, CHIP[CERAMIC LD-LESS TC], 10PF 50V D NP0	
		C813	0CH3104K946	CAPACITOR, CHIP[CERAMIC LD-LESS HD], 100000PF 50V Z F	
		C815	0CE1074F638	CAPACITOR, AL.ELECTROLYTIC, 100UF SRA,SS 16V M FM5	
		C852	0CE1074F638	CAPACITOR, AL.ELECTROLYTIC, 100UF SRA,SS 16V M FM5	
		C853	0CE1074F638	CAPACITOR, AL.ELECTROLYTIC, 100UF SRA,SS 16V M FM5	
		C854	0CE1074F638	CAPACITOR, AL.ELECTROLYTIC, 100UF SRA,SS 16V M FM5	
		C855	0CE1074F638	CAPACITOR, AL.ELECTROLYTIC, 100UF SRA,SS 16V M FM5	
<b>DIODEs</b>					
		D202	0DZ510009EE	DIODE, ZENER, UDZ S 5.1B TP ROHM-K SOD323 200MW 5.1V	
		D203	0DS226009AA	DIODE, SWITCHING, KDS226 TP KEC SOT-23 80V 300MA 2A	
		D204	0DS226009AA	DIODE, SWITCHING, KDS226 TP KEC SOT-23 80V 300MA 2A	
		D205	0DS226009AA	DIODE, SWITCHING, KDS226 TP KEC SOT-23 80V 300MA 2A	
		D207	0DZ560009CE	DIODE, ZENER, MTZJ5.6B TP ROHM-K DO34 500MW 5.6V	
		D208	0DZ560009CE	DIODE, ZENER, MTZJ5.6B TP ROHM-K DO34 500MW 5.6V	
		D209	0DZ560009CE	DIODE, ZENER, MTZJ5.6B TP ROHM-K DO34 500MW 5.6V	
		D211	0DZ560009CE	DIODE, ZENER, MTZJ5.6B TP ROHM-K DO34 500MW 5.6V	
		D212	0DS226009AA	DIODE, SWITCHING, KDS226 TP KEC SOT-23 80V 300MA	
		D213	0DS113309AA	DIODE, SWITCHING, 1SS133 TP ROHM KOREA DO34 90V 0.4A	
		D214	0DS113309AA	DIODE, SWITCHING, 1SS133 TP ROHM KOREA DO34 90V 0.4A	
		D215	0DS113309AA	DIODE, SWITCHING, 1SS133 TP ROHM KOREA DO34 90V 0.4A	
		D217	0DR330009CA	DIODE, RECTIFIER, BYD33D TP PHILIPS SOD81 200V 1.3A 20A	
		D218	0DZ120009AF	DIODE, ZENER, MTZJ12B TP ROHM-K DO34 500MW 12V 5MA	
		D220	0DS113309AA	DIODE, SWITCHING, 1SS133 TP ROHM KOREA DO34 90V 0.4A	
		D221	0DZ510009EE	DIODE, ZENER, UDZ S 5.1B TP ROHM-K SOD323 200MW 5.1V	
		D222	0DS113309AA	DIODE, SWITCHING, 1SS133 TP ROHM KOREA DO34 90V 0.4A	
		D223	0DS226009AA	DIODE, SWITCHING, KDS226 TP KEC SOT-23 80V 300MA 2A	
		D224	0DS226009AA	DIODE, SWITCHING, KDS226 TP KEC SOT-23 80V 300MA 2A	
		D225	0DS113309AA	DIODE, SWITCHING, 1SS133 TP ROHM KOREA DO34 90V 0.4A	
		D226	0DD860009AA	DIODE, RECTIFIER, BAT 86 TP PHILIPS DO34 50V 0.2A 0.25A	
		D231	0DS226009AA	DIODE, SWITCHING, KDS226 TP KEC SOT-23 80V 300MA 2A 4	
		D240	0DZ470005AA	DIODE, ZENER, MTZ 4.7B TP ROHM-K DO34 500MW 4.7V 20MA	
		D284	0DZ150009AD	DIODE, ZENER, MTZJ15B TP ROHM-K DO34 500MW 15V 5MA	
		D801	0DZ510009EE	DIODE, ZENER, UDZ S 5.1B TP ROHM-K SOD323 200MW 5.1V	
		D802	0DZ510009EE	DIODE, ZENER, UDZ S 5.1B TP ROHM-K SOD323 200MW 5.1V	
		D803	0DZ510009EE	DIODE, ZENER, UDZ S 5.1B TP ROHM-K SOD323 200MW 5.1V	
		D804	0DZ510009EE	DIODE, ZENER, UDZ S 5.1B TP ROHM-K SOD323 200MW 5.1V	
		D805	0DZ510009EE	DIODE, ZENER, UDZ S 5.1B TP ROHM-K SOD323 200MW 5.1V	
		D806	0DZ510009EE	DIODE, ZENER, UDZ S 5.1B TP ROHM-K SOD323 200MW 5.1V	
		D807	0DZ510009EE	DIODE, ZENER, UDZ S 5.1B TP ROHM-K SOD323 200MW 5.1V	

MODEL: Flatron 795FT plus, 未来窗 795FT plus				DATE: 1999. 2. 5.	
*S	*AL	LOC. NO.	PART NO.	DESCRIPTION / SPECIFICATION	REMARK
		D808 D809 D810	0DZ510009EE 0DZ510009EE 0DZ510009EE	DIODE, ZENER, UDZ S 5.1B TP ROHM-K SOD323 200MW 5.1V DIODE, ZENER, UDZ S 5.1B TP ROHM-K SOD323 200MW 5.1V DIODE, ZENER, UDZ S 5.1B TP ROHM-K SOD323 200MW 5.1V	
ICs					
		IC202 IC207 IC209 IC801	0IZZTSZ020A 0IAL240800A 0INS353000A 0IMO141555A	IC[HYBRID ], 42PIN BK OTP(MICOM) FB795 IC, ATMEL, AT24C08 8D EEPROM(8K,IIC) IC, NATIONAL SEMICONDUCTOR, LF353N OP-AMP IC, MOTOROLA, MC141555 28DIP BK USB HUB CONTROLLER	
COILs & COREs					
		L201 L284	125-155B 125-155B	CORE (CIRC),BEAD, BFS3580R2FG SAMWHA 3.5*8.0MM R CORE (CIRC),BEAD, BFS3580R2FG SAMWHA 3.5*8.0MM	
TRANSISTORs					
		Q202 Q203 Q204 Q206 Q207 Q208 Q209 Q210 Q211 Q212 Q213 Q214 Q215 Q216 Q217 Q240 Q284 Q291 Q292 Q294 Q295	0TR319809AA 0TR319809AA 0TR102009AJ 0TR319809AA 0TR319809AA 0TR127009AA 0TR390409AE 0TR114009AB 0TR319809AA 0TR127509AC 0TR320709AA 0TR102409AB 0TR102409AB 0TR319809AA 0TR102409AB 0TR102009AM 0TR322809AB 0TR102009AM 0TR390409AE 0TR102009AJ 0TR390609FA	TRANSISTOR, KTC3198-Y(KTC1815) TP KEC TO92 NPN TRANSISTOR, KTC3198-Y(KTC1815) TP KEC TO92 NPN TRANSISTOR, KRC102S NPN SOT-23 TP KEC TRANSISTOR, KTC3198-Y(KTC1815) TP KEC TO92 NPN TRANSISTOR, KTC3198-Y(KTC1815) TP KEC TO92 NPN TRANSISTOR, KTA1270-Y(KTA562TM) TP KEC TO92 PNP TRANSISTOR, KST3904-MTF TP SAMSUNG SOT23 GEN. TRANSISTOR, DTC114ES TP ROHM-K SPT NPN TRANSISTOR, KTC3198-Y(KTC1815) TP KEC TO92 NPN TRANSISTOR, KTA1275-Y(KTA1013) TP KEC TO92L PNP TRANSISTOR, KTC3207,TP(KTC2482),KEC TRANSISTOR, KTA1024-Y(KTA949) TP KEC TO92L PNP TRANSISTOR, KTA1024-Y(KTA949) TP KEC TO92L PNP TRANSISTOR, KTC3198-Y(KTC1815) TP KEC TO92 NPN TRANSISTOR, KTA1024-Y(KTA949) TP KEC TO92L PNP TRANSISTOR, KRA102S TP KEC PNP SOT-23 TRANSISTOR, KTC3228-Y(KTC2383) TP KEC TO92L NPN TRANSISTOR, KRA102S TP KEC PNP SOT-23 TRANSISTOR, KST3904-MTF TP SAMSUNG SOT23 GEN. TRANSISTOR, KRC102S NPN SOT-23 TP KEC TRANSISTOR, KST3906-MTF TP SAMSUNG SOT23 GEN.	
RESISTORs					
		R202 R203 R204 R205 R206 R207 R208 R209	0RH4701D622 0RH5602D622 0RH4701D622 0RH1002D622 0RH3301D622 0RH5602D622 0RH1203D622 0RH1002D622	RESISTOR, CHIP, 4.7K 1/10W 5 D.R/TP RESISTOR, CHIP, 56K 1/10W 5 D.R/TP RESISTOR, CHIP, 4.7K 1/10W 5 D.R/TP RESISTOR, CHIP, 10K 1/10W 5 D.R/TP RESISTOR, CHIP, 3.3K 1/10W 5 D.R/TP RESISTOR, CHIP, 56K 1/10W 5 D.R/TP RESISTOR, CHIP, 120K OHM 1 / 10 W 5% D R/TP RESISTOR, CHIP, 10K 1/10W 5 D.R/TP	

*S	*AL	LOC. NO.	PART NO.	DESCRIPTION / SPECIFICATION	REMARK
		R210	0RH1001D622	RESISTOR, CHIP, 1.0K 1/10W 5 D.R/TP	
		R211	0RH1001D622	RESISTOR, CHIP, 1.0K 1/10W 5 D.R/TP	
		R212	0RH1002D622	RESISTOR, CHIP, 10K 1/10W 5 D.R/TP	
		R213	0RH1002D622	RESISTOR, CHIP, 10K 1/10W 5 D.R/TP	
		R214	0RH1002D622	RESISTOR, CHIP, 10K 1/10W 5 D.R/TP	
		R215	0RH1002D622	RESISTOR, CHIP, 10K 1/10W 5 D.R/TP	
		R216	0RH9102D622	RESISTOR, CHIP, 91K 1/10W P-TYPE TAPPING	
		R217	0RH1003D622	RESISTOR, CHIP, 100K 1/10W 5 D.R/TP	
		R218	0RH4701D622	RESISTOR, CHIP, 4.7K 1/10W 5 D.R/TP	
		R219	0RH1002D622	RESISTOR, CHIP, 10K 1/10W 5 D.R/TP	
		R220	0RH0472D622	RESISTOR, CHIP, 47 1/10W 5 D.R/TP	
		R221	0RH1002D622	RESISTOR, CHIP, 10K 1/10W 5 D.R/TP	
		R222	0RH1602D622	RESISTOR, CHIP, 16K 1/10W 5 TA	
		R223	0RH1001D622	RESISTOR, CHIP, 1.0K 1/10W 5 D.R/TP	
		R224	0RH1001D622	RESISTOR, CHIP, 1.0K 1/10W 5 D.R/TP	
		R225	0RH1001D622	RESISTOR, CHIP, 1.0K 1/10W 5 D.R/TP	
		R226	0RH1001D622	RESISTOR, CHIP, 1.0K 1/10W 5 D.R/TP	
		R227	0RH4701D622	RESISTOR, CHIP, 4.7K 1/10W 5 D.R/TP	
		R228	0RH4701D622	RESISTOR, CHIP, 4.7K 1/10W 5 D.R/TP	
		R229	0RH1001D622	RESISTOR, CHIP, 1.0K 1/10W 5 D.R/TP	
		R230	0RH1201D622	RESISTOR, CHIP, 1.2K 1/10W 5 D.R/TP	
		R231	0RH5601D622	RESISTOR, CHIP, 5.6K 1/10W 5 D.R/TP	
		R232	0RH1000D622	RESISTOR, CHIP, 100 1/10W 5 D.R/TP	
		R235	0RH1201D622	RESISTOR, CHIP, 1.2K 1/10W 5 D.R/TP	
		R236	0RH1201D622	RESISTOR, CHIP, 1.2K 1/10W 5 D.R/TP	
		R237	0RH1201D622	RESISTOR, CHIP, 1.2K 1/10W 5 D.R/TP	
		R238	0RH1201D622	RESISTOR, CHIP, 1.2K 1/10W 5 D.R/TP	
		R240	0RH1501D622	RESISTOR, CHIP, 1.5K 1/10W 5 D.R/TP	
		R241	0RH5601D622	RESISTOR, CHIP, 5.6K 1/10W 5 D.R/TP	
		R242	0RH0102D622	RESISTOR, CHIP, 10 1/10W 5 D.R/TP	
		R243	0RH0102D622	RESISTOR, CHIP, 10 1/10W 5 D.R/TP	
		R244	0RH1502D622	RESISTOR, CHIP, 15K 1/10W 5 D.R/TP	
		R245	0RH1502D622	RESISTOR, CHIP, 15K 1/10W 5 D.R/TP	
		R246	0RH1000D622	RESISTOR, CHIP, 100 1/10W 5 D.R/TP	
		R247	0RH1000D622	RESISTOR, CHIP, 100 1/10W 5 D.R/TP	
		R248	0RH1000D622	RESISTOR, CHIP, 100 1/10W 5 D.R/TP	
		R251	0RH1001D622	RESISTOR, CHIP, 1.0K 1/10W 5 D.R/TP	
		R252	0RH1502D622	RESISTOR, CHIP, 15K 1/10W 5 D.R/TP	
		R253	0RH1003D622	RESISTOR, CHIP, 100K 1/10W 5 D.R/TP	
		R254	0RH1002D622	RESISTOR, CHIP, 10K 1/10W 5 D.R/TP	
		R256	0RH1001D622	RESISTOR, CHIP, 1.0K 1/10W 5 D.R/TP	
		R257	0RH3903D622	RESISTOR, CHIP, 390K 1/10W 5 D.R/TP	
		R258	0RH2001D622	RESISTOR, CHIP, 2.0K 1/10W 5 D.R/TP	
		R259	0RH1501D622	RESISTOR, CHIP, 1.5K 1/10W 5 D.R/TP	
		R260	0RH1003D622	RESISTOR, CHIP, 100K 1/10W 5 D.R/TP	
		R261	0RH0102D622	RESISTOR, CHIP, 10 1/10W 5 D.R/TP	

*S	*AL	LOC. NO.	PART NO.	DESCRIPTION / SPECIFICATION	REMARK
		R262	0RH3001D622	RESISTOR, CHIP, 3.0K 1/10W 5 D.R/TP	
		R263	0RH1001D622	RESISTOR, CHIP, 1.0K 1/10W 5 D.R/TP	
		R264	0RH1601D622	RESISTOR, CHIP, 1.6K 1/10W 5 TA	
		R265	0RH1002D622	RESISTOR, CHIP, 10K 1/10W 5 D.R/TP	
		R266	0RH1002D622	RESISTOR, CHIP, 10K 1/10W 5 D.R/TP	
		R267	0RH5602D622	RESISTOR, CHIP, 56K 1/10W 5 D.R/TP	
		R268	0RD1102Q509	RESISTOR, FIXED CARBON FILM, 11K OHM 1/4 W (3.4) 2%	
		R269	0RH1002D622	RESISTOR, CHIP, 10K 1/10W 5 D.R/TP	
		R270	0RH2002D622	RESISTOR, CHIP, 20K 1/10W 5 D.R/TP	
		R271	0RH2202D622	RESISTOR, CHIP, 22K 1/10W 5 D.R/TP	
		R272	0RH1002D622	RESISTOR, CHIP, 10K 1/10W 5 D.R/TP	
		R273	0RH4700D622	RESISTOR, CHIP, 470 1/10W 5 D.R/TP	
		R274	0RH1003D622	RESISTOR, CHIP, 100K 1/10W 5 D.R/TP	
		R275	0RH3002D622	RESISTOR, CHIP, 30K 1/10W 5 D.R/TP	
		R276	0RH4700D622	RESISTOR, CHIP, 470 1/10W 5 D.R/TP	
		R277	0RH2002D622	RESISTOR, CHIP, 20K 1/10W 5 D.R/TP	
		R278	0RN6801F409	RESISTOR, FIXED METAL FILM, 6.80K 1/6W 1%	
		R279	0RH1602D622	RESISTOR, CHIP, 16K 1/10W 5 TA	
		R280	0RH3001D622	RESISTOR, CHIP, 3.0K 1/10W 5 D.R/TP	
		R281	0RD3001Q609	RESISTOR, FIXED CARBON FILM, 3K 1/4W(3 5%)	
		R282	0RH1002D622	RESISTOR, CHIP, 10K 1/10W 5 D.R/TP	
		R283	0RH3002D622	RESISTOR, CHIP, 30K 1/10W 5 D.R/TP	
		R284	0RH2001D622	RESISTOR, CHIP, 2.0K 1/10W 5 D.R/TP	
		R285	0RH0102D622	RESISTOR, CHIP, 10 1/10W 5 D.R/TP	
		R286	0RH1003D622	RESISTOR, CHIP, 100K 1/10W 5 D.R/TP	
		R287	0RH5103D622	RESISTOR, CHIP, 510K 1/10W 5 D.R/TP	
		R288	0RH1002D622	RESISTOR, CHIP, 10K 1/10W 5 D.R/TP	
		R289	0RN7501F409	RESISTOR, FIXED METAL FILM, 7.50K 1/6W 1%	
		R290	0RH3601D622	RESISTOR, CHIP, 3.6K 1/10W 5 D.R/TP	
		R291	0RD4703Q609	RESISTOR, FIXED CARBON FILM, 470K 1/4W(3 5%)	
		R292	0RH6802D622	RESISTOR, CHIP, 68K 1/10W 5 D.R/TP	
		R293	0RH1002D622	RESISTOR, CHIP, 10K 1/10W 5 D.R/TP	
		R294	0RD1000Q609	RESISTOR, FIXED CARBON FILM, 100 1/4W(3 5%)	
		R295	0RH8203D622	RESISTOR, CHIP, 820K 1/10W 5 D.R/TP	
		R296	0RH1002D622	RESISTOR, CHIP, 10K 1/10W 5 D.R/TP	
		R297	0RD0102Q609	RESISTOR, FIXED CARBON FILM, 10 1/4W(3 5%)	
		R298	0RN2402F409	RESISTOR, FIXED METAL FILM, 24K 1/6W 1%	
		R299	0RH1501D622	RESISTOR, CHIP, 1.5K 1/10W 5 D.R/TP	
		R803	0RH0102D622	RESISTOR, CHIP, 10 1/10W 5 D.R/TP	
		R804	0RH0102D622	RESISTOR, CHIP, 10 1/10W 5 D.R/TP	
		R807	0RH0102D622	RESISTOR, CHIP, 10 1/10W 5 D.R/TP	
		R808	0RH0102D622	RESISTOR, CHIP, 10 1/10W 5 D.R/TP	
		R811	0RH0102D622	RESISTOR, CHIP, 10 1/10W 5 D.R/TP	
		R812	0RH0102D622	RESISTOR, CHIP, 10 1/10W 5 D.R/TP	
		R815	0RH0102D622	RESISTOR, CHIP, 10 1/10W 5 D.R/TP	
		R816	0RH0102D622	RESISTOR, CHIP, 10 1/10W 5 D.R/TP	

MODEL: Flatron 795FT plus, 未来窗 795FT plus				DATE: 1999. 2. 5.	
*S	*AL	LOC. NO.	PART NO.	DESCRIPTION / SPECIFICATION	REMARK
		R817	0RH1502D622	RESISTOR, CHIP, 15K 1/10W 5 D.R/TP	
		R818	0RH1502D622	RESISTOR, CHIP, 15K 1/10W 5 D.R/TP	
		R819	0RH1005D622	RESISTOR, CHIP, 10M 1/10W 5 D.R/TP	
		R824	0RH0102D622	RESISTOR, CHIP, 10 1/10W 5 D.R/TP	
		R825	0RH0102D622	RESISTOR, CHIP, 10 1/10W 5 D.R/TP	
		R826	0RH1501D622	RESISTOR, CHIP, 1.5K 1/10W 5 D.R/TP	
		R827	0RH4701D622	RESISTOR, CHIP, 4.7K 1/10W 5 D.R/TP	
		R828	0RH4701D622	RESISTOR, CHIP, 4.7K 1/10W 5 D.R/TP	
		R829	0RH4701D622	RESISTOR, CHIP, 4.7K 1/10W 5 D.R/TP	
		R830	0RH4701D622	RESISTOR, CHIP, 4.7K 1/10W 5 D.R/TP	
		R831	0RH1502D622	RESISTOR, CHIP, 15K 1/10W 5 D.R/TP	
		R832	0RH1502D622	RESISTOR, CHIP, 15K 1/10W 5 D.R/TP	
		R833	0RH1502D622	RESISTOR, CHIP, 15K 1/10W 5 D.R/TP	
		R834	0RH1502D622	RESISTOR, CHIP, 15K 1/10W 5 D.R/TP	
		R835	0RH1502D622	RESISTOR, CHIP, 15K 1/10W 5 D.R/TP	
		R836	0RH1502D622	RESISTOR, CHIP, 15K 1/10W 5 D.R/TP	
		R837	0RH1502D622	RESISTOR, CHIP, 15K 1/10W 5 D.R/TP	
		R838	0RH1502D622	RESISTOR, CHIP, 15K 1/10W 5 D.R/TP	
		R850	0RH4701D622	RESISTOR, CHIP, 4.7K 1/10W 5 D.R/TP	
		R852	0RH6202D622	RESISTOR, CHIP, 62K 1/10W 5 TA	
<b>OTHERs</b>					
		X201	6202TTB002B	CRYSTAL, ATS-49/U SUNNY RADIAL 6MHZ 30PPM 16PF BK	
		X801	6202TTB004C	CRYSTAL, HC-49/U KONY RADIAL 24.0MHZ 30PPM 20PF BK	
<b>MISCELLANEOUS</b>					
△		CDT	2423GC3B41D	CDT SET, ITC, M41QBF423X 02N6LD	
		D/COIL	6140TC2005A	COIL, DEGAUSSING, 2320MM 18 OHM 0.55MM 110T 19" FB792	
		P/COIL	6140TC4001C	COIL, PURITY, 1360MM 88 OHM 0.22MM 140T 17" PURITY	
		EARTH	6868T17004B	CDT EARTH, FB792 TIN WIRE BRAID(128)	
		P/CORD	6410TEW003C	POWER CORD, SP023+IS14 I-SHENG VDE/SEMKO 1870MM	
	or	P/CORD	6410TWP001D	POWER CORD, ISO11+IS14 I-SHENG UNIVERSAL 1560MM	
	or	P/CORD	6410TBW001A	POWER CORD, SP60+IS14B I-SHENG ASTA 1870MM	
	or	P/CORD	6410TCP001A	POWER CORD, LAS-14+LAS-13 LENOI CCEE 1560MM PC	
		S/CABLE	387-874E	SIGNAL CABLE, UL 2990-9C DT 1870MM GRAY(85964)	
	or	S/CABLE	6866TDU002D	SIGNAL CABLE, UL20276SB10P+2C AWG30 DT 1870MM GRAY	